

### Alarm List for A06B-6044-Hxxx (PCB A20B-0009-053x or A20B-1000-069x)

| Alarm # | Led Display |   |   |   | Content of Alarms                         |
|---------|-------------|---|---|---|-------------------------------------------|
|         | 8           | 4 | 2 | 1 |                                           |
| 1       |             |   |   | o | Motor Overheat                            |
| 2       |             |   | o |   | Speed deviates from commanded speed       |
| 3       |             |   | o | o | Fuse F7in DC link is blown out.           |
| 4       |             | o |   |   | Fuses F1,F2,F3 for AC input blown out.    |
| 5       |             | o |   | o | Fuses AF2 or AF3 on PCB are blown out.    |
| 6       |             | o | o |   | Excess Motor Speed Analog                 |
| 7       |             | o | o | o | Excess Motor Speed Digital                |
| 8       | o           |   |   |   | Voltage higher than specified (24v)       |
| 9       | o           |   |   | o | Radiator for power semiconductor overheat |
| 10      | o           |   | o |   | +15Volt Supply is low                     |
| 11      | o           |   | o | o | DC Link voltage is high                   |
| 12      | o           | o |   |   | DC Link current is high                   |
| 13      | o           | o |   | o | CPU and peripheral parts are defective    |
| 14      | o           | o | o |   | ROM is defective                          |
| 15      | o           | o | o | o | Option circuit fault.                     |

### Alarm List for A06B-6055-Hxxx (PCB A20B-1001-0120)

| Alarm Display | Alarm Content                                               |
|---------------|-------------------------------------------------------------|
| AL-01         | Motor Overheated                                            |
| AL-02         | Speed deviates from commanded speed                         |
| AL-03         | Fuse F7in DC link is blown out.                             |
| AL-04         | Fuses F1,F2,F3 for AC input blown out.                      |
| AL-06         | Excess Motor Speed Analog                                   |
| AL-07         | Excess Motor Speed Digital                                  |
| AL-08         | Voltage higher than specified (24v)                         |
| AL-09         | Radiator for power semiconductor overheat                   |
| AL-10         | +15v power supply is abnormally low                         |
| AL-11         | DC Link voltage is high                                     |
| AL-12         | DC Link current is high                                     |
| AL-13         | Data memory for CPU abnormal                                |
| AL-16         | RAM in NVRAM is abnormal                                    |
| AL-17         | ROM in NVRAM is abnormal                                    |
| AL-18         | Check sum alarm of ROM                                      |
| AL-19         | Excessive alarm of U phase current detection circuit offset |
| AL-20         | Excessive alarm of V phase current detection circuit offset |
| AL-21         | Excessive alarm of velocity command circuit offset.         |
| AL-22         | Excessive alarm of velocity detection circuit offset.       |
| AL-23         | Excessive alarm of ER circuit offset.                       |
| AL-14         | ROM is abnormal                                             |
| AL-15         | Spindle selection control circuit is abnormal.              |

### Alarm List for A06B-6059-Hxxx

| Alarm #       | Meaning                                             |
|---------------|-----------------------------------------------------|
| AL-01         | Motor Overheat                                      |
| AL-02         | Speed deviates from commanded speed                 |
| AL-03         | 24v Fuse is blown. (before PCB edition 09A)         |
| AL-04         |                                                     |
| AL-05         |                                                     |
| AL-06         | Excess Motor Speed Analog                           |
| AL-07         | Excess Motor Speed Digital                          |
| AL-08         | Over voltage                                        |
| AL-09         | Overheat of radiator                                |
| AL-10         | Low voltage of input power.                         |
| AL-11         | Excessive high voltage of DC link                   |
| AL-12         | Abnormal current of DC link                         |
| AL-13-15      |                                                     |
| AL-16-23      | Defective arithmetic circuit and peripheral circuit |
| No indication | Defective ROM                                       |

### Alarm List for A06B-6059-Hxxx

| Alarm #       | Meaning                                             |
|---------------|-----------------------------------------------------|
| AL-01         | Motor Overheat                                      |
| AL-02         | Speed deviates from commanded speed                 |
| AL-03         | 24v Fuse is blown. (before PCB edition 09A)         |
| AL-04         | Open phase of input power.                          |
| AL-05         |                                                     |
| AL-06         | Excess Motor Speed Analog                           |
| AL-07         | Excess Motor Speed Digital                          |
| AL-08         | Over voltage                                        |
| AL-09         | Overheat of radiator                                |
| AL-10         | Low voltage of input power.                         |
| AL-11         | Excessive high voltage of DC link                   |
| AL-12         | Abnormal current of DC link                         |
| AL-13         | Defective arithmetic circuit                        |
| AL-14         | Defective ROM                                       |
| AL-15         | Defective optional circuit.                         |
| AL-16-23      | Defective arithmetic circuit and peripheral circuit |
| No indication | Defective ROM                                       |

