



- 8 (a) The following table shows part of the instruction set for a processor. The processor has two registers: the Accumulator (ACC) and an Index Register (IX).

Instruction		Explanation
Opcode	Operand	
LDM	#n	Immediate addressing. Load the number n to ACC
LDD	<address>	Direct addressing. Load the contents of the location at the given address to ACC
LDI	<address>	Indirect addressing. The address to be used is at the given address. Load the contents of this second address to ACC
INC	<register>	Add 1 to the contents of the register (ACC or IX)
STO	<address>	Store the contents of ACC at the given address
ADD	#n/Bn/&n	Add the number n to the ACC
DEC	<register>	Subtract 1 from the contents of the register (ACC or IX)
JMP	<address>	Jump to the given address
CMP	<address>	Compare the contents of ACC with the contents of <address>
JPE	<address>	Following a compare instruction, jump to <address> if the compare was True
END		Return control to the operating system
ACC denotes Accumulator <address> can be an absolute or a symbolic address # denotes a denary number, e.g. #123 B denotes a binary number, e.g. B01001010 & denotes a hexadecimal number, e.g. &4A		

