Contact ID Code Table for LS-30

ACCT	MT	Q	XYZ	GG	CZZ	S
Account	Message Type	Qualifier	Event Code	Group	Zone	Check Sum

Event	Q	XYZ				
Medical Alarm	1	100				
Fire Alarm	1	110				
Smoke Alarm	1	111				
Panic Alarm	1	120				
Duress	1	121				
Burglar Alarm	1	130				
Burglar Alarm Restore	3	130				
Burglar Sensor Tampered	1	137				
Keypad/Sensor Tampered	1	144				
Water Leakage	1	154				
High Temperature	1	158				
Restore High Temperature	3	158				
Low Temperature	1	159				
Restore Low Temperature	3	159				
High Humidity	1	168				
Restore High Humidity	3	168				
Low Humidity	1	169				
Restore Low Humidity	3	169				
AC Power Loss	1	301				
AC Power Restore	3	301				
Base Unit Low Battery	1	302				
Restore Base Unit Low Battery	3	302				
System Reset	1	305				
RF Jamming	1	344				
Tel. Line Fault	1	351				
Restore Tel. Line Fault	3	351				
Exit Error Alarm	1	374				
Loss Of Supervision-RF	1	381				
Restore Of Supervision-RF	3	381				
Sensor Low Battery	1	384				
Restore Sensor Low Battery	3	384				
Sensor Self-test Failure	1	389				
Arm State(AWAY)	**3**	**400**	Original	(1	408)	Note: from 1/24/08
Disarm State	**1**	**400**	Original	(1	573)	
Home State	**3**	**441**	Original	(1	574)	
Loop-Back Test Report	1	601				
Periodic Test Report	1	602				
Two Way Voice	1	606				
Trigger in Monitor Mode	1	618				
Monitor Mode	1	619				
Inactivity Alarm	1	641				