Serial Commands for Countdown Display

Joshua Bays (UAH ETLC)

Contents

setc

Ex: *setc 122520232015450000*

Set the clock to a given time in the MMDDYYYYhhmmss format.

(Example above sets the clock to 12.25.2023 at 8:15:45 PM)

sett

Ex: *sett 00:55:05*

Set the timer to a specific time in the hh:mm:ss format.

(Example above sets a timer for 55 minutes and 5 seconds)

swon

Ex: *swon*

Turn on the stopwatch. The stopwatch will display automatically.

swon

Ex: *swoff*

Turn off the stopwatch. The stopwatch will stop displaying automatically.

togc

Ex: *togc*

Toggle the clock from displaying.

togt

Ex: *togt*

Toggle the timer from displaying.

toga

Ex: *toga*

Toggle the alarm sound.

pzt

Ex: *pzt*

Pause/Resume the timer.

pzs

Ex: *pzs*

Pause/Resume the stopwatch

sec

Ex: *sec*

Toggle the seconds display on the clock