

Electronic equipments : cardiofrequency mesure, stop watch, compass, disposable cameras (with or without flash), fitness console, pedometer, altimeter, watches, and other equipments containing electronic parts

Produit : Electronic / Measuring devices

Legal manager : DLUBALA JULIEN

Updated at : 26/03/2025 10:23:00

Downloaded at : 27/03/2026 12:23:22

CHINA

Product's definition

Category

In which category the product is classified ?

Products covered: cardio frequency measure, stop watch, compass, disposable cameras(with and without flash), fitness console,

NB/T 42148.2-2020 Switches for battery-driven appliances and equipment Part 2-1: Particular requirements for power tool switchespedometer, altimeter, wathces.

GB/T 16895.21-2020 Low-voltage electrical installations-Part 4-41: Protection for safety-Protection against electric shock

Definition

What is the exact definition of the product ?

And if it exists, what is the interpretation of the authorities regarding it ?

Definition of measurement instrument

Measurement instrument refers to a device, an instrument, a meter or a measuring tool which can be used to determine the measurement values of the measured objects directly or indirectly, as well as a standard matter used to unify measurement values, which can be a datum measurement instrument, a standard measurement instrument and a working measurement apparatus. (Article 56 of Implementation Rules for Metrology Law of the P.R.C.) Different types of measuring instruments have different regulatory requirements. The specific product categories are specified in the following catalog.

1. "Catalogue of Measuring Instruments Subject to Compulsory Management". Some measuring instruments are subject to mandatory management by the state and require type approval and/or compulsory verification. Such measuring instruments are specifically listed in the "Catalogue of Measuring Instruments Subject to Mandatory Management", including pressure gauges, handheld laser rangefinders and other products.

2. "The Catalogue of Measuring Instruments Managed by Law of the People's Republic of China". This catalog was issued by the former National Bureau of Metrology, and it contains a wider range of products than the Catalog of Measuring Instruments Subject to Compulsory Management, including rangefinders, pressure gauges, stopwatches, etc. This catalog is cited in some regulatory provisions such as the "Administrative Measures for Supervision of Imported Instruments of Measurement" and the "Administrative Measures for New Products of Measurement Instruments".

3. "The Catalogue of Type Examination of Imported Measuring Instruments of the People's Republic of China". This catalog is stipulated in the "Administrative Measures for Supervision of Imported Instruments of Measurement", and the scope of its

products is different from the previous two catalogs, including sensors, pressure gauges, etc. This catalog is mainly applicable to the import field of measuring instruments.

Accordingly, among the products sold by your company, golf laser rangefinder, scuba diving double gauge-water pressure gauge & depth gauge, and stopwatch may belong to the measuring instruments managed according to law listed in the Catalogue of Measuring Instruments Managed by Law of the People's Republic of China; Among them, products such as golf laser rangefinder, scuba diving double gauge-water pressure gauge & depth gauge may belong to the measurement instruments subject to mandatory management listed in the "List of Measurement Instruments Subject to Mandatory Management". Products such as sensors, scuba diving double gauge-water pressure gauge & depth gauge may belong to the measuring instruments listed in the "Type Examination Catalogue of Imported Measuring Instruments of the People's Republic of China".

Definition of electrical and electronic products

Electrical and electronic products means the equipment and supporting products that work by relying on electric currents or electromagnetic fields or are manufactured for the purpose of generating, transmission and measuring electric currents and electromagnetic fields, with the rated working voltage of not more than 1,500 volts measured in direct current or not more than 1,000 volts measured in alternating current, excluding the equipment involving electrical energy production, transmission and distribution. (Administrative Measures for Restricted Use of the Hazardous Substances Contained in Electrical and Electronic Products)

Accordingly, most of the products involved in this section basically meet the definition of electrical and electronic products.

Definition of mechanical and electrical products

The term "mechanical and electrical products" refers to the mechanical equipment, electric equipment, transport tools, electronic products, electrical appliances, apparatus, instruments, metal products, and the parts and components and elements thereof. (Article 2 of Administrative Measures for Import of Mechanical and Electrical Products)

The specific scope of mechanical and electrical products is stipulated in the appendix of the "Administrative Measures for Import of Mechanical and Electrical Products", which covers a wide range, including electrical and electronic products, instruments and meters, various luminaries and lighting devices, clocks and watches and their parts.

Among them, the import of some mechanical and electrical products is subject to automatic licensing management. The specific product scope is stipulated in the "Automatic Import License Mechanical and Electrical Products Catalog", including other product categories such as other electronic watches directed mechanically.

Accordingly, among the products sold by your company, sports watches may belong to mechanical and electrical products subject to automatic import license.

Products that require 3C certification

Definition of low-power motors requiring compulsory certification

- Suitable for driving low-power motors with rated voltage greater than 36V (DC or AC rms) and less than 1500V DC and 1000V AC, including:
 - 1. When the speed is converted to 1500r/min, various AC asynchronous motors and AC synchronous motors whose maximum continuous rating does not exceed 1.1kW (rated power $\leq$ synchronous speed $\times$ 1.1kW/1500);
 2. AC commutator motors and DC motors whose maximum continuous rating does not exceed 1.1kW.
- Do not include:
 - 1. Motors for control purposes (such as servo motors, stepping motors, self-aligning machines, resolvers, tachogenerators, induction phase shifters, etc.)
 2. Multi-voltage and multi-speed motor whose one type of rating is beyond the above applicable range.

Definition of plug products requiring compulsory certification

- Plug and fixed, mobile socket suitable for indoor or outdoor use, household and similar purposes, only for alternating current, rated voltage above 50V but not more than 440V, rated current not more than 32A, with or without grounding angle;
- It is also applicable to plugs installed in wire assemblies and plugs and mobile sockets installed in wire extension assemblies, as well as plugs and sockets as a component of electrical appliances, unless otherwise stated in the relevant electrical standards;
- It is also applicable to sockets integrated with the appliance and installed in or fixed to the appliance;
- For fixed sockets equipped with screwless terminals, the maximum rated current is limited to 16A.

Definition of circuit breakers requiring compulsory certification

- A mechanical switching device that can connect, carry and break the current under normal circuit conditions, and could also connect and carry current for a certain period of time and breaking current under specified abnormal conditions (such as short-circuit conditions)

Definition of fuse links and low-voltage fuses requiring compulsory certification

Fuse link	When the current passing through the component exceeds the specified value and lasts for a sufficient time, the component fuses, disconnecting the circuit to which it is connected, thereby cutting off the current. And, a non-resettable device equipped with a thermal element would break the circuit when it is exposed to a temperature exceeding the designed temperature for a long enough time.
Low-voltage fuse	"gG" fuse for household and similar purposes, which is suitable for unskilled persons whose rated current does not exceed 100A and rated voltage does not exceed 500V AC.

Definition of switch products (belonging to low-voltage components) requiring compulsory certification:

- According to external signals and requirements, the circuit could be manually or automatically connected and disconnected to realize the switching, control, protection, detection, transformation and adjustment of the circuit or non-electric objects.

Products such as motors, circuit breakers, fuses, switches, plugs/power supplies, etc. sold by your company may belong to the above product categories, which need to be judged based on product parameters.

Comments

Comments

Labelling

Language

In which language must the information on the product or on the packaging be indicated? If English is sufficient please indicate NA.

Must use Chinese language .

Mandatory labelling on product

What are the mandatory labelling on the product ?

Regulatory requirements for
product labeling

- The producers and importers of electrical and electronic products shall, in accordance with the national or industrial standards for the marking of the restricted use of the hazardous substances contained in electrical and electronic products, mark the hazardous substances contained in the electrical and electronic products they put on markets, and indicate the names and contents of hazardous substances or whether the elements or products which contain such substances may be recycled, the fact that improper use or disposal thereof may affect the environment or human health and other information. Where the aforesaid information cannot be marked on the products due to the restrictions in product volume, shape, surface materials or functions, it shall be indicated in the product manuals.
- The producers and importers of electrical and electronic products shall, in accordance with the national or industrial standards for the marking of the restricted use of the hazardous substances contained in electrical and electronic products, indicate the EFUP on the electrical and electronic products they produce or import. Where the aforesaid information cannot be marked on the products due to the restrictions in product volume, shape, surface materials or functions, it shall be indicated in the product manuals.

General requirements

General Requirements of Labeling

1

All necessary information concerning the proper and safe use and (or) related service and maintenance of the products shall be included

2	Clear and easy to be identified, the smallest English letter shall not be less than 1.5 mm
3	Must use Chinese language
4	The contents shall be the same with that contained in other printed materials (such as advertisement and package)

Content of Labeling and Instruction for Use

1	Product summarizes (product name, variety, specifications, model, the main purpose and working conditions, etc.)
2	Precautions for safe use
3	Structural characteristics and working principle
4	Technical characteristics
5	Size, weight
6	Installation and adjustment
7	Use and operation
8	Malfunction analysis and exclusion
9	Safety protection device and incident handling
10	Maintenance and repair
11	Transport and storage
12	Unpacking and inspection
13	Environmental or other requirements
14	Graphs, charts, photographs (eg outline drawings, installation drawings, schematics, etc.)

Markings for Control of Pollution Caused by Electrical Equipment (Console):

- Please click [here](#) to see the detail info.

Labeling requirement of stop watch/watch

Labeling Requirement of Stop Watch/Watch

Item

Content

Dial /Back

1Trademark

2Name of manufacturer

3Place of production

Movement Year of manufacture code, markup or code number

Movement plywood Code of + and -

Labeling requirement for compass

1. size
2. Mark of factory
3. code

headset:

No. Requirements

Contents Requirements

Refer to the provisions specified in the standard of GB/T 14471-2013 General specification for headphones

Fished headsets should at least identify the manufacturer brand, model and impedance.

Product instructions

Refer to the provisions specified in the standard of GB/T 14471-2013 General specification for headphones

1. Matching of connectors
2. Control and its switches (if have)
3. Microphone (if have)
4. The connectivity map of headset (if more than one),
5. Classification code
6. The description of the type of headsets
7. The physical characteristics of headsets, such as size, weight, length of wire and categories and so on.

If the headset includes accessories, enterprise shall also provide the following information:

1. Preamplifier and/or passive network.
2. The receiver (for wireless systems)
3. Power type, constant rate of supply voltage and frequency, maximum power consumption etc.

4. Other components, such as a magnetic pickup device

Transportation

Refer to the provisions specified in the standard of GB/T 14471-2013 General specification for headphones

Packed headsets can be transported via normally available land, sea and air transportation

Transportation should be avoided of wetDB, shockproof, exposure, heavy pressure and so on.

Storage

Refer to the provisions specified in the standard of GB/T 14471-2013 General specification for headphones

Packaged headsets shall be stored in the warehouse, the temperature of which is from -10 degrees Celsius to 40 degrees Celsius and the relative humidity of which is less than 90% .There should no strong magnetic field, no sharp changes in temperature in the warehouse, and there shall be no acidic or other harmful gas around the warehouse.

Label requirements for pollution control regarding electronic information product

1. Electronic information product pollution control mark
2. harmful substances label
3. Environment use period label
4. Recycled usage label

Note: As to detailed information concerning label requirements for pollution control regarding electronic information product, please refer to the standard of SJ/T 11364-2014 Marking for the restriction of the use of hazardous substances in electrical and electronic product.

Labeling requirement of audio/video and similar electronic apparatus

Labeling Requirement of Audio/Video and Similar Electronic Apparatus

- 1 Name, trademark or identification mark of the manufacturer or the liability underwriter
- 2 Model or Code
- 3 Symbol of type II devices (if any)
- 4 Nature of power supply
- 5 Rated voltage/ Rated voltage range
- 6 Rated grid supply frequency if any

7	Rated consumed current or rated consumed power
8	Symbol of consumed power
9	Warning mark on the altitude / weather conditions / battery, etc.

Mandatory labelling on packaging

What are the mandatory labelling on the packaging ?

Mandatory labelling on the instructions manual

What are the mandatory labelling on the instructions manual (if one is required) ?
In which format, do we have to deliver the instruction manual to our customers ?

Certificate/Instruction for use of watches:

1. Name/Model/Trademark of product
2. Name and address of the manufacturer
3. Serial number for standard of implementation
4. Production time
5. Key performance indicators
6. Accuracy class (stopwatch)
7. Material of the shell, bands and glass; the thickness of the gold alloy overburden
8. Inspection signature
9. Maintenance instructions
10. Warranty period

Warnings - General ones

Are general warnings required ? If yes, which ones ?

Warnings - Specific ones

Are specific warnings required ? If yes which ones ?

Target Age

Is there any target age applicable? If so, does it have to be indicated and in which form?

Sanctions / Fines

What are the sanctions / fines in case of non conformity ?

Comments

Comments

Environment

Recycling - Eco taxes

Which regulations concerning ecodesign and recycling apply to this product? Are there any ecotaxes applicable to this category of product?

Regulatory requirements for electrical and electronic product

Regulatory requirements for
product design

The designers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules in the process of designing electrical and electronic products, and shall, on the premise of satisfying the technological requirements, adopt the schemes for making the said substances harmless, less harmful, easy to be degraded or convenient for being recycled, among others, in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products,

Product production supervision requirements

- The manufacturers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules in the process of manufacturing electrical and electronic products, and shall, in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products, adopt the materials, technologies and technological processes with higher resource utilization rates, easy to be recycled and disposed of and conducive to environmental protection, and restrict or eliminate the use of the hazardous substances in products.
- The manufacturers of electrical and electronic products may not allow the electrical and electronic products that fail to comply with the requirements of these Measures to leave factories or be sold.

regulatory requirements for packaging

The manufacturers and importers of electrical and electronic products may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules when making and using the packages of electrical and electronic products, and shall adopt the materials harmless, easy to be degraded and convenient for being recycled, and comply with the national or industrial standards for the use of packages.

Regulatory requirements stipulated in Administrative Measures for Prevention and Control of Environmental Pollution by Electronic Waste

Regulatory requirements for
product production

The producers of electrical and electronic products may in accordance with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products, restrict or eliminate the use of the hazardous substances in products.

Regulatory requirements for information disclosure

Producers, importers and sellers of electronic and electrical products shall disclose the lead, mercury, cadmium, hexavalent chromium, polybrominated biphenyls (PBB), polybrominated diphenyl ethers (PBDE) and other toxic and hazardous substances contained in their products in accordance with relevant national regulations. As well as information on the impact of improper use or disposal on the environment and human health, and tips on how to use or dispose of the product in an environmentally sound manner after it is discarded.

Recycling and disposal regulatory requirements

- Producers, importers and sellers of electronic and electrical products shall establish a recycling system in accordance with relevant national regulations, recycle waste products, and be responsible for storage, utilization or disposal in an environmentally sound manner;
- If the producers, sellers and importers of electronic products discard electronic and electrical products, they shall provide or entrust the electronic wastes to the dismantling, utilization and disposal units (including individual industrial and commercial households) with corresponding business scope listed in the directory (including the temporary directory) for dismantling, utilization or disposal.

Labelling

What are the mandatory labellings to put on the product or on the packaging regarding the environmental rules ?

Technical rules / Standards

General safety requirements

What are the general safety requirements ? Does a risk assessment have to be conducted ? If yes, does it concern specific risk ?

Mandatory or voluntary standards

Are there some mandatory or voluntary standards applicable ? If yes, which ones ?

Please indicate the reference of the applicable standards

Regard to your products, if you want to check what are the technical requirement /toxicology/design... shall respect, thanks to check the labelling of your product first and find code of standards in labelling.

Step 1:

Enter this link: https://docs.google.com/spreadsheets/d/1BDqhm609YySgDqs8cPOQUd-Dc_ZYPEEt7v-lv1sWB0CA/edit#gid=1640363751

Step 2:

Enter the code of product standard selected by you in PACE and open the link in red.

Enter the code of mandatory safety standard above.

Step3:

Open link and find documents of standard, your products shall respect all requirements in file.

PS: If you can't find the translation file in link above, please do not hesitate to contact with CHINA Conformity Leader by mail "chinadmilegal@decathlon.net".

Physical and mechanicals properties

What are the physical and mechanicals properties required ?

GB/T 10963.1-2020 Electrical accessories Overcurrent protective circuit breakers for household and similar places Part 1: Circuit breakers for AC

Rated voltage

Rated voltage

Rated working voltage: The rated working voltage of the circuit breaker (hereinafter referred to as the rated voltage) is the voltage value specified by the manufacturer, and this value is related to the performance of the circuit breaker (especially the short-circuit performance).

Note: The same circuit breaker can specify several rated voltages and corresponding rated short-circuit capabilities.

Rated insulation voltage: The rated insulation voltage of the circuit breaker is the voltage value specified by the manufacturer, which is related to the dielectric test voltage and creepage distance. Unless otherwise specified, the rated insulation voltage is the maximum rated voltage value of the circuit breaker. In any case, the maximum rated voltage should not exceed the rated insulation voltage.

Rated impulse withstand voltage: The rated impulse withstand voltage of the circuit breaker should be equal to or higher than the standard value of the impulse withstand voltage specified in Table 3.

Rated current: the current that the circuit breaker specified by the manufacturer can carry under the specified reference ambient air temperature and uninterrupted working system (see 3. 2. 14). The standard reference ambient air temperature is 30°C. If the circuit breaker adopts other reference ambient air temperature, the influence on the cable overload protection should be considered, because according to the installation regulations, the cable is also based on the 30°C reference ambient air temperature.

Note: According to IEC 60364, the reference ambient air temperature for cable overload protection is 25 .

Rated frequency: The rated frequency of the circuit breaker is specified for the design of the circuit breaker, and is the power frequency frequency corresponding to other characteristics. The same circuit breaker can specify several rated frequencies.

Rated short-circuit capacity: The rated short-circuit capacity of the circuit breaker is the limit short-circuit breaking capacity (see 3.5.5. 1) specified by the manufacturer for the circuit breaker.

Note: A circuit breaker with a given rated short-circuit capacity has a corresponding operating short-circuit capacity (I cs) (see Table 18).

Single-pole rated making and breaking capacity: the value of the limit short-circuit making and breaking capacity on each protection pole of a multi-pole circuit breaker.

Note: The corresponding rating of RCBO is the rated remaining making and breaking capacity. (See 5.2.7 of IEC 61009-1: 2010). For standard values, see 5. 3. 4. 1.

- Standard value and preferred value

ØStandard value and preferred value

Table 1 Preferred value of rated voltage

breaker	Power supply circuit of circuit breaker	Rated voltage of circuit breakers used in 230 V, 230/400 V, and 400 V systems	At 120/240 V, 240 V	Of the circuit breakers used in the system	Rated voltage
		V			
		230			
Unipolar	Single phase (phase wire to neutral wire or phase wire to phase wire)				
	230				
Three-phase four-wire					
			120		
Single phase (grounding conductor in the middle of the phase wire pair or phase wire to the neutral wire)			240		
Single-phase (phase wire to neutral wire) or three-phase, using three single-pole circuit breakers (three-wire or four-wire)					
		230			
Two poles	Single phase (phase wire to neutral wire or phase wire to phase wire)				

	400	240
Single phase (phase wire to phase wire)		
		120/240
Single phase (phase wire to phase wire, three wire)		
	230	
Three-phase (four-wire)		
	400	240
Three poles	Three-phase (three-wire or four-wire)	
		120/240
Single phase (three wire)		
	400	
Four-pole Three-phase (four-wire)		

Note 1: In IEC 60038, the grid voltage value 230/400 V has been standardized. These voltage values should gradually replace the 220/380 V and 240/415 V voltage values.

Note 2: In this section, where 230 V or 400 V is involved, it can be understood as 220 V or 240 V, 380 V or 415 V, respectively.

Note 3: In this section, where 120 V or 120/240 V is involved, it can be understood as 100 V or 100/200 V respectively.

- Preferred value of rated current

The preferred values of the rated current are: 6 A, 8 A, 10 A, 13 A, 16 A, 20 A, 25 A, 32 A, 40 A, 50 A, 63 A, 80 A, 100 A and 125 A.

Standard value of rated frequency: The standard value of rated frequency is 50 Hz or 60 Hz.

- Standard value of rated short-circuit capacity

Standard values of 10 000 A and below: The standard values of rated short-circuit capacity of 10 000 A and below are: 1 500 A, 3 000 A, 4 500 A, 6 000 A and 10 000 A.

Note: In some countries, 1 000 A, 2 000 A, 2 500 A, 5 000 A, 7 500 A and 9 000 A are also regarded as standard values.

The corresponding power factor range is specified in 9. 12. 5.

Values greater than 10 000 A to 25 000 A (including 25 000 A): For values greater than 10 000 A to 25,000 A (including 25 000 A), the preferred value is 20 000 A.

The corresponding power factor range is specified in 9. 12. 5.

Standard range of instantaneous trip: The standard range of instantaneous trip is specified in Table 2.

Table 2 Instantaneous trip range

Trip form	Trip range
B	$3I_n \sim 5 I_n$
C	$5I_n \sim 10 I_n$
D	$10I_n \sim 20 I_n$

For specific occasions, values up to 50 I_n can also be used.

Standard value of rated impulse withstand voltage: Table 3 shows the relationship between the standard value of rated impulse withstand voltage and the nominal voltage of the device.

Table 3 The relationship between rated impulse withstand voltage and device nominal voltage

Rated impulse withstand voltage		Nominal voltage of the device
Three-phase system		Single-phase system with grounded neutral point
2. 5		120/240
4	230/400 250/440	120/240 240

Note 1: See Table 14 for the test voltage for checking insulation.

Note 2: Refer to Table 15 for the test voltage to verify the isolation distance between the open contacts.

- Standard working conditions used

General requirements of the standard working conditions used: the circuit breaker conforming to this section should be able to be used under the following standard conditions.

Ambient air temperature range: the ambient air temperature does not exceed +40℃, and the average temperature within 24 h does not exceed +35℃. The lower limit of the ambient air temperature is -5℃. Circuit breakers used under conditions where

the ambient air temperature is higher than +40°C (especially in tropical countries) or lower than -5°C should be specially designed or used according to the data provided in the manufacturer's sample.

Altitude: The altitude of the installation site generally does not exceed 2 000 m (6 600 ft). For devices installed at higher altitudes, the reduction of dielectric strength and air cooling effect must be considered. The circuit breaker expected to be used under this condition should be specially designed or used in accordance with the agreement between the manufacturer and the user. The information given in the manufacturer's sample can replace this agreement.

Atmospheric conditions: The air is clean, and when the maximum temperature is +40°C, the relative humidity of the air does not exceed 50%.

Higher relative humidity is allowed at lower temperature, for example, at +20°C, the relative humidity is 90%. For moderate condensation that may occasionally occur due to temperature changes, care should be taken to take appropriate measures (such as drain holes).

Installation conditions: The circuit breaker should be installed according to the manufacturer's instructions.

Pollution degree: The circuit breaker in this section is suitable for the environment with pollution degree 2, that is, there is only non-conductive pollution under normal circumstances, but temporary conductive pollution caused by condensation can be expected.

- Structure and action requirements

Mechanical Design

General requirements: The design and structure of the circuit breaker should make it reliable under normal conditions of use, without danger to the operator or the surrounding environment. Generally, all relevant tests specified are used to check compliance.

Mechanism: The moving contacts of all poles of a multi-pole circuit breaker should be mechanically connected in such a way that, except for the openable and closable neutral pole (if any), all poles are basically connected at the same time regardless of manual operation or automatic operation. And simultaneous breaking, even when only one protection pole is overloaded. The opening and closing neutral pole of a four-pole circuit breaker should not be closed and opened before the protection pole. By using appropriate devices (for example, indicator lights, oscilloscopes, etc.) for visual inspection and manual testing to verify compliance. If one pole with proper short-circuit making and breaking capacity is used as the neutral pole and the circuit breaker is not operated manually. Then all poles, including the neutral pole, can act substantially simultaneously. The circuit breaker should have a free trip mechanism. Through visual inspection, manual test to check whether the above requirements are met and the test of 9. 10. 3 to check the free trip function. It should be possible to manually open and close the circuit breaker. For plug-in circuit breakers without operating parts, it cannot be considered that the circuit breaker can be unplugged from the base to meet this technical requirement.

The structure of the circuit breaker should be such that the movable contact can only be placed in the closed position or the open position, even when the operating member is released in an intermediate position. When the circuit breaker is in the off position, an isolation distance shall be provided according to the requirements necessary to satisfy the isolation function. Indicate the open and closed positions of the main contact in one or two of the following ways:-the position of the operating member (preferred);-separate mechanical indicators. If an independent mechanical indicator is used to indicate the position of the main contact, the indicator should display red for the closed position (ON) and green for the open position (OFF). The contact position indicating device should be reliable. Compliance is checked by inspection and 9. 10. 3 test.

The design of the circuit breaker should be such that the operating member, panel or cover can only be fixed in the correct position to ensure the correct indication of the contact position. Compliance is checked by inspection and tests of 9. 12. 12. 1 and 9. 12. 12. 2. If the operating element is used to indicate the position of the contact, the operating element should automatically be located at the position corresponding to the position of the moving contact when tripping. In this case, the operating element should have two distinct stopping positions corresponding to the contact position, but for automatic disconnection, the operating element can have a third distinctly different position. The action of the machine should not be affected by the position of the housing or cover, and has nothing to do with any movable parts. The cover sealed and positioned by the manufacturer is regarded as an immovable part. If the cover is used as a guide for the button, it should be impossible to remove the button from the outside of the circuit breaker.

The operating element should be reliably fixed on its shaft, and it should not be possible to remove the operating element without the aid of tools. It is allowed to fix the operating part directly on the cover. If the operating member is "up and down movement", when the circuit breaker is installed according to normal use, the upward movement should close the contact.

Note 1: So far, in some countries, downward movement is allowed to close the contacts.

Use visual inspection and manual operation test to verify compliance with the requirements. When the manufacturer provides or specifies a device to lock the operating element in the open position, it shall be possible to lock the operating element in the open position only when the main contact is in the open position.

Note 2: For specific applications, it is allowed to lock the operating element in the closed position.

Compliance is checked by visual inspection and referring to the manufacturer's instructions.

- Screws, current-carrying parts and connections

Either electrical connection or mechanical connection should be able to withstand the mechanical stress generated during normal use. During the installation process, the screws used to install the circuit breaker should not be thread-cutting self-tapping screws.

Note 1: The screws (or nuts) used to install the circuit breaker include screws to fix the cover or cover plate, but do not include the threaded conduit and the connection device for fixing the base of the circuit breaker. Compliance is checked by visual inspection and the test of 9.4.

Note 2: It can be considered that the tests of 9. 8, 9. 9, 9. 12, 9. 13, and 9. 14 have inspected threaded connections.

During the installation process, the screws used for the installation of the circuit breaker that engage with the threads of the insulating material should be inserted correctly into the screw hole or nut. Compliance is checked by visual inspection and manual test. If the screw can be prevented from being introduced obliquely, for example, a part fixed with a groove in the internal thread or a screw with a leading thread removed from the front end is used for guiding, then the requirements for the correct introduction of the screw are met. The electrical connection should be designed so that contact pressure is not transmitted through insulating materials other than ceramic, pure mica or other materials with equivalent properties, unless the metal parts have sufficient elasticity to compensate for any possible shrinkage or deformation of the insulating material. Compliance is checked by visual inspection.

Note: The suitability of materials is considered in terms of the dimensional stability of the materials.

Current-carrying parts, including parts used as protective conductors (if any), should be made of metal, which has sufficient mechanical strength, conductivity and corrosion resistance for the intended use under the conditions encountered by the equipment performance.

Examples:-Copper;-For cold-worked parts, an alloy containing at least 58% copper. For other parts, it is an alloy with at least 50% copper content;-other metals with appropriate mechanical properties or with appropriate coatings with corrosion resistance not lower than copper. When ferroalloys or ferroalloys with appropriate coatings are used, the anti-corrosion test (see 9.16) is used to check whether they meet the corrosion protection requirements. The requirements of this clause do not apply to the components of contacts, magnetic circuits, heating elements, bimetals, shunts, and electronic devices, nor do they apply to screws, nuts, washers, clamping plates, similar parts of terminals, and test circuits. part.

- Terminals for connecting external wires

Terminals connected to external wires should ensure that the wires connected to them can maintain the necessary contact pressure for a long time. As long as the wiring device is not used to connect cables, the device is allowed to connect to busbars. The device can be a plug-in type or a bolt-on type. The terminal should be easily accessible under the expected usage conditions. Through visual inspection, pass the test of 9.5 for threaded terminal blocks, use special tests for plug-in or bolt-on circuit breakers in this section, or use Appendix J or Appendix K for related connection methods to verify compliance Claim.

The circuit breaker shall have a terminal allowing the connection of copper conductors with the nominal cross-sectional area shown in Table 5.

Note 1: See Appendix F for the structural design example of the possible terminal blocks. —Or the threaded terminals for connecting external untreated aluminum wires and the aluminum threaded terminals for connecting copper or aluminum wires as specified in Appendix L.

Through visual inspection, measurement and successively connecting a specified minimum cross-sectional area and a maximum cross-sectional area conductor to verify compliance with the requirements.

Table 5 The cross-sectional area of the copper wire that can be connected to the screw terminal

Rated current A		Nominal cross-sectional area of clamped mm2	
more than the	To (inclusive)	Rigid (solid or stranded) conductor	Soft conductor
	13	1 ² . 5	1 ² . 5
13	16	1 ⁴	1 ⁴
16	25	1. 5 ⁶	1. 5 ⁶
25	32	2. 5 ¹⁰	2. 5 ⁶
32	50	4 ¹⁶	4 ¹⁰
50	80	10 ²⁵	10 ¹⁶
80	100	16 ³⁵	16 ²⁵
100	125	25 ⁵⁰	25 ³⁵

a For terminals with a rated current less than or equal to 50 A, the structure is required to clamp solid conductors and rigid stranded conductors. However, for conductors with a cross-sectional area of 1 mm 2 to 6 mm 2, the structure allows only solid conductors to be clamped.

b For a series of circuit breakers with the same basic design and the same terminal design and structure, the terminal should be connected to the copper conductor with the smallest cross section corresponding to the minimum rated current and the largest cross section corresponding to the maximum rated current. Copper wires, copper wires are solid and stranded wires (if applicable).

c For conductors with a cross-sectional area of 1.5 mm2 to 50 mm 2, rigid stranded conductors should be used, and should meet the requirements of the second type of conductor of single-core stranded conductors in GB/T 3956-2008.

The parts used to fasten the wires in the terminal should not be used to fix any other components, although they can be used to position the terminal or prevent it from rotating. Compliance is checked by visual inspection and 9.5 test.

Terminals with a rated current less than or equal to 32 A shall allow the connection of wires without special processing. By visually checking whether it meets the requirements.

Note: The term "special processing" includes welding wires, using cable glands, bending into small rings, etc., but does not include reshaping the wires before inserting them into the terminals or tightening the wires to increase the strength of the flexible wire head .

The terminal should have sufficient mechanical strength. The screws and nuts used to fasten the wires should have metric threads or threads with equivalent pitch and mechanical strength specified by ISO. Check whether it meets the requirements by visual inspection and the tests of 9.4 and 9.5.2.

Note: Currently, SI, BA and UN threads can be used because these threads are actually equivalent to metric ISO threads in terms of pitch and mechanical strength.

The design of the terminal should be such that it will not excessively damage the wire when tightening the wire. Check whether it meets the requirements through visual inspection and 9.5.3 test.

The design of the terminal should be able to reliably fasten the loquat wire between the metal surfaces. Check whether it meets the requirements by visual inspection and the tests of 9.4 and 9.5.2.

The design or arrangement of the terminal should be such that the wire of the rigid solid wire or stranded wire cannot slide out of the terminal when tightening the fastening screw or nut. This requirement does not apply to lug type terminals.

The terminal block should be fixed or positioned so that the terminal block will not loosen from the fixing place of the circuit breaker when tightening or loosening the fastening screw or nut.

The fastening screw or nut of the terminal connecting the protective conductor should have sufficient reliability to prevent accidental loosening.

Manually test to check whether it meets the requirements.

The post terminal should allow the wire to be fully inserted and reliably clamped: fully insert the solid wire with the largest cross-sectional area specified in Table 5 for the corresponding rated current into the terminal, and apply the torque specified in Table 11 to fully tighten it. Visually check whether it meets the requirements.

Non-interchangeability: After the circuit breaker (plug-in type or screw type) installed on the base that constitutes a unit with it is installed and wired according to normal use, it should not be possible to use another of the same model without tools. Replace the circuit breaker with a larger rated current. Check whether it meets the requirements by visual inspection.

- Mechanical installation of plug-in circuit breakers

General requirements: the mechanical installation of plug-in circuit breakers whose positioning is not only related to its plug-in connection should be reliable and have sufficient stability. The plug-in circuit breaker whose positioning is not only related to its plug-in connection shall be checked for compliance with the mechanical installation requirements through the relevant test of 9.13.

The plug-in circuit breaker whose positioning is only related to its plug-in connection is checked for compliance with the mechanical installation requirements through the relevant test of 9.13.

Electric shock protection: The structure of the circuit breaker should be such that after installation and wiring according to normal use (see 8.1.6 notes), the electrical components are not easily accessible. If the part can be touched by the test finger (see 9.6), the part is considered to be easily touchable.

For circuit breakers other than plug-in type, when they are installed and wired according to normal use conditions, the external parts that are easy to touch, excluding the screws or other devices that fix the cover and the nameplate, should be made of insulating materials or all gasket insulating materials. Unless the live parts are located in an inner shell of insulating material.

The gaskets should be fixed in such a way that they cannot be lost during the installation of the circuit breaker. The liner should have sufficient thickness and mechanical strength and provide adequate protection at sharp edges. The entrance of the cable or conduit should be made of insulating material or have insulating material sleeves or similar devices. These devices should be reliably fixed and have sufficient mechanical strength. For plug-in circuit breakers, the external parts that are easily accessible during normal use, excluding screws or other devices for fixing the cover, should be made of insulating materials. Metal operating parts should be insulated from live parts, and their exposed conductive parts should be covered with insulating materials. This requirement does not apply to components that connect several insulated operating parts. It shall be possible to easily replace the plug-in circuit breaker without touching live parts. For the purposes of this clause, it is considered that varnish and enamel cannot provide adequate insulation. Compliance is checked by visual inspection and the test of 9.6.

- Dielectric performance and isolation ability

General requirements: The circuit breaker should have sufficient dielectric performance and ensure isolation.

The power frequency dielectric strength circuit breaker should have sufficient dielectric strength under the power frequency voltage. Check whether it meets the requirements by performing the tests of 9.7.1, 9.7.2 and 9.7.3 on the new circuit breaker. In addition, after the life test of 9.11 and the short-circuit test of 9.12, the circuit breaker shall be able to withstand the test of 9.7.3, which is reduced as specified in 9. 11. 3 and 9. 12. 12. 2 respectively. Test under voltage, and do not carry out the wet treatment of 9.7.1 before the test.

Isolation capability: The circuit breaker should be suitable for isolation. Compliance is checked by verifying compliance with the minimum electrical clearance and creepage distance of item 1 in Table 4 and the tests of 9.7.1.1 and 9.7.3.

The dielectric strength circuit breaker under the rated impulse withstand voltage should be sufficient to withstand the impulse voltage. Compliance with the requirements is checked by the test of 9.7.5.2.

- Temperature rise

Temperature rise limit: Under the conditions specified in 9.8.2, the temperature rise of each component of the circuit breaker specified in the measurement table 6 shall not exceed the limit value specified in the table. The circuit breaker should not be damaged that affects its function and use safety.

Table 6 Temperature rise value

a b	
Parts	Temperature rise
	60
Terminal c for connecting external wires	40
In the process of manually operating the circuit breaker, the accessible external parts include the operating parts of insulating material and the metal parts connecting the insulating operating parts of each pole	25
	60
The external metal parts of the operating parts and other external parts, including the surface of the circuit breaker in direct contact with the installation plane	

The temperature rise value of the contact is not specified, because the structure of most circuit breakers such as unchanging parts or moving parts cannot directly measure the temperature of these parts, and these changes often affect the repeatability of the test. The 28-day test (see 9.9) is considered to have indirectly tested the excessive heating of the contacts during use.

b Except for the parts listed in the table, the temperature rise values of other parts are not specified, but they should not cause damage to adjacent insulating material parts or hinder the operation of the circuit breaker.

c pair plug-in circuit breaker refers to the terminal block of the base where the circuit breaker is installed.

Ambient air temperature: The temperature rise limit values shown in Table 6 are only applicable when the ambient air temperature is kept within the limit range specified in 7.2.

Uninterrupted working system: The circuit breaker should work reliably even after long-term operation. The test of 9.9 is used to verify whether it meets the requirements.

- Automatic action

Standard time-current band: The tripping characteristics of circuit breakers should enable them to adequately protect the circuit without premature action.

The time-current characteristic band (trip characteristic) of the circuit breaker is determined by the conditions and values specified in Table 7.

Table 7 means that the circuit breaker is installed under the reference conditions (see 9.2) and works at the reference calibration temperature of 30 °C, with a temperature error of +50 °C.

Compliance is checked by the test specified in 9.10.

The test can be carried out at any suitable temperature, and the test results are based on 30 °C according to the information given by the manufacturer.

In any case, for every 1 K change in the calibration temperature, the change in the test current in Table 7 should not exceed 1.2%. If the calibration temperature of the circuit breaker mark is not 30 °C, they should be tested at this different temperature. When the calibration temperature is different from the reference value, the manufacturer shall provide information on the change of the tripping characteristics.

- Approximate quantitative

Agreed time: For a circuit breaker with a rated current less than or equal to 63 A, the agreed time is 1 h; for a circuit breaker with a rated current greater than 63 A, the agreed time is 2 h.

Conventional non-trip current: The agreed non-trip current of the circuit breaker is 1.13 times its rated current.

Conventional trip current: The agreed trip current of the circuit breaker is 1.45 times its rated current.

- Tripping characteristics

General requirements: The tripping characteristics of the circuit breaker should be included in the standard time-current band specified in 8.6.1.

Note: When the temperature and installation conditions are different from those specified in 9.2 (for example, installing in a specific enclosure, assembling several circuit breakers in the same enclosure, etc.), the tripping characteristics of the circuit breaker may be affected. When the ambient temperature is different from the reference value, but within the limit specified in 7.2, the manufacturer shall provide information on the changes in the tripping characteristics.

The effect of single-pole load of multi-pole circuit breaker on the tripping characteristics: When the circuit breaker with multiple protection poles starts from the cold state, and only one protection pole is connected to the following current load:

——For a two-pole circuit breaker with two protected poles, it is 1.1 times the agreed tripping current;

——For three-pole and four-pole circuit breakers, it is 1.2 times the conventional trip current.

The circuit breaker shall trip within the agreed time specified in 8. 6.2.1. The 9. 10. 4 test is used to check whether it meets the requirements.

Mechanical and electrical life: The circuit breaker should be able to carry out sufficient operating cycles under the rated current.

The 9.11 test is used to check whether it meets the requirements.

Performance under short-circuit current: The circuit breaker should be able to perform the specified number of short-circuit operations, and should not endanger the operator during short-circuit operation, nor should it cause flashover between live conductive parts or between live conductive parts and the ground. The 9.12 test is used to check whether it meets the requirements. This requires that the circuit breaker can be turned on under the conditions of rated frequency, a power frequency recovery voltage equal to 105% ($\pm 5\%$) of the rated voltage, and a power factor not lower than the lower limit of the appropriate range specified in 9.12. 5 And breaking corresponds to any current value below the rated short-circuit capacity; at the same time, the corresponding I_{2t} value is required to be less than the I_{2t} characteristic (see 3. 5. 13).

Resistance to mechanical shock and impact: The circuit breaker should have sufficient mechanical properties to withstand the mechanical stress suffered during installation and use. The 9.13 test is used to check whether it meets the requirements.

Heat resistance: The circuit breaker should have sufficient heat resistance. The 9.14 test is used to check whether it meets the requirements.

Abnormal heat resistance and flame resistance: If the adjacent current-carrying parts reach a high temperature under fault or overload conditions, the external parts made of insulating materials in the circuit breaker should not easily ignite and spread flame. Through visual inspection and 9.15 test to verify whether it meets the requirements.

Anti-rust: Iron parts should have adequate anti-rust protection. The 9.16 test is used to check whether it meets the requirements.

Power consumption: The power consumption of the circuit breaker should not be too large. The maximum allowable value for each pole is specified in Table 8. The 9.8.5 test is used to check whether it meets the requirements.

Table 8 Maximum power consumption per pole

Rated current range	Maximum power loss per pole
I_d10	3
$10 I_n d16$	3. 5
$16 I_n d25$	4. 5

25 I n d32	6
32 I n d40	7.5
40 I n d50	9
50 I n d63	13
63 I n d100	15
100 I n d125	20

GB/T 10963.2-2020 Electrical accessories-Overcurrent protective circuit breakers for household and similar places-Part 2: Circuit breakers for AC and DC

- Preferred value of rated voltage

Replace with the following clause: See Table 1 for the preferred value of rated voltage. Figure 18 shows an example of circuit breaker wiring in a DC system.

Table 1 Preferred value of rated voltage

		AC	DC	
breaker				
AC circuit that supplies power to the circuit breaker	AC rated voltage	DC circuit powering the circuit breaker	DC rated voltage	DC wiring example
Unipolar	230 V		125 V or 220 V	18a
	Single phase (relative to neutral)	Two wires (un-grounded system)		
	120 V	-	-	
Single phase (intermediate conductor relative to ground, or relative neutral)				
	230/400 V	-	-	
Single-phase (relative to neutral) or three-phase (three single-pole circuit breakers) (three-wire or four-wire)				
Two poles	400 V		220/440 V	18b 18c
	Single phase (relative phase)	Two wires (grounding system)		18d

120/240 V

125/250 V

Single phase (phase to phase,
three wire)

Two wires (grounding system)

Suitable for AC voltage:

Note 1: In IEC 60038, the 230/400 V grid voltage has been standardized. This value will gradually replace the 220/380 V and 240/415 V voltage values.

Note 2: In this section, where 230 V or 400 V is mentioned, it can be regarded as 220 V or 240 V and 380 V or 415 V respectively.

Note 3: Circuit breakers meeting the technical requirements of this section can be used in IT systems.

The manufacturer shall specify the minimum voltage of the circuit breaker design in its technical file. Related trials are under consideration. Standard range of instantaneous trip

Table 2 Instantaneous trip range

Trip form	Communication range	DC range
B	$3 I_n < I_d \leq 5 I_n$	$4 I_n < I_d \leq 7 I_n$
C	$5 I_n < I_d \leq 10 I_n$	$7 I_n < I_d \leq 15 I_n$

- Logo and other product information

The rated AC voltage is represented by the symbol ~ (IEC 60417-5032: 2002-10), and the rated DC voltage is represented by the symbol (IEC60417-5031: 2002-10);

d) Rated current, without the symbol "A", preceded by the symbol of instantaneous trip (B or C), such as B 16;

f) If the rated short-circuit capacity of AC and DC are the same, it is represented by amperage without the symbol A in a rectangular box (see example 1 below). If the rated short-circuit capacity of AC and DC are different, it is represented by the amperage without the symbol A in two adjacent rectangular boxes, and the symbol beside the rectangular box containing the AC value ~ (IEC 60417-5032: 2002-10), including The symbol next to the rectangular box of the DC value (IEC60417-5031:2002-10) (see example 2 below).

The time constant T 15 is marked in a rectangular box (when applicable), combined with the short-circuit capability mark at a time constant of 15 ms (see example 3 below).

l) The first paragraph below is replaced with the following:

For small circuit breakers, if the available space is not enough to mark all the above data, at least the data of items c) and d) should be marked and visible after the circuit breaker is installed.

The information of items a), b), e), f), g), h), i), l) and m) can be marked on the side or back of the circuit breaker, and it can only be seen before the circuit breaker is installed.

In addition, the data in g) can be marked inside any cover that must be removed when connecting the power cord. Any other unmarked data should be given in the manufacturer's technical documents.

Example 1:

Example 2:

Example 3:

If necessary, the terminal should be marked with + or -. In addition, arrows are allowed to indicate the direction of current. The applicable wiring diagram according to Figure 18 shall be indicated in the manufacturer's instructions.

Standard time-current band

Table 7 Time-current operating characteristics

test	Type	AC test current	DC test current	Starting state	Trip or non-trip time limit	expected outcome	Note
a	B, C	1. 13 I		Cold state	te1 h(I nd63 A) t e2 h(I n 63 A)	No tripping	
b	B, C	1. 45 I		Followed by a Test	t 1 h(I n d63 A) t 2 h(I n 63 A)	tripping	The current rises steadily within 5s
c	B, C	2. 55 I		Cold state	1 st 60 s (I n d32 A) 1 st 120 s (I n 32 A)	tripping	
d	B, C	3 I 5 I	4 I 7 I	Cold state	1. 1 st 45 s(I n d32 A) 2. 0.1 st 90 s(I n 32 A) 1. 1 st 15 s(I nd32 A) 2. 0.1 st 30 s(I n 32 A)	tripping	Close the auxiliary switch and turn on the power

e	B, C	5 I	7 I	t < 0.1 s		
		10 I	15 I	Cold state	tripping	Close the auxiliary switch and turn on the power

The term "cold" refers to no load before the test, and at the reference calibration temperature.

- Performance under short-circuit current

This requires the circuit breaker to be able to make and break any current value corresponding to the rated short-circuit capacity and below at a power-frequency recovery voltage equal to 105% (5%) of the rated working voltage at the rated frequency. The power factor is not less than or the time constant is not more than the limit range specified in 9.12.5. In addition, it is also required that the corresponding I_{2t} value should be lower than the I_{2t} characteristic (3.5.13).

Electrical aspects

What are requirements regarding electrical aspects ?

Inflammability

Are there any specific requirements to ensure inflammability?

Hygiene

What are the rules regarding hygiene ?

Radioactivity

What are the rules regarding radioactivity ?

Radiofrequency (2G,3G,4G,5G, Bluetooth, Ant+, GPS, Wifi...)

What are the rules regarding the radiofrequency?

Products making noise

What are the requirements regarding products making noise ?

Chemicals substances

What are the requirements regarding chemicals substances ? Which ones are forbidden ? Limited ? Do we have to clearly indicate all substances that are in the product, or is the indication of major substances enough?"

The electronic information products shall meet the relevant provisions stipulated by Measures for the Administration of the Restricted Use of the Hazardous Substances Contained in Electrical and Electronic Products.

Measures for the Administration of the Restricted Use of the Hazardous Substances Contained in Electrical and Electronic Products was issued on 6th January, 2016 and came into force on 1st July, 2016. Regulation on the Pollution Control Caused of Electronic Information Products (PCCEP) issued on 28th February, 2006 was repealed concurrently. The matched standards, Requirements of concentration limits for certain restricted substances in electrical and electronic products (GB/T 26572-2011) and Marking for the restriction of the use of hazardous substances in electrical and electronic product (SJ/T 11364-2014), required by the Measures, therefore, shall be mandatorily implemented.

The phthalates disabled in the plastic components

The Phthalates Disabled in the Plastic Components

Chinese Name	English Name	Abbreviation	CA Login Number
邻苯二甲酸二异壬酯	Di-iso-nonylphthalate	DINP	28553-12-0
邻苯二甲酸二辛酯	Di-n-octylphthalate	DNOP	117-84-0
邻苯二甲酸二(2-乙基己)酯	Di-(2-ethylhexy)- phthalate	DEHP	117-81-7
邻苯二甲酸二异癸酯	Di-isodecylphthalate	DIDP	26761-40-0
邻苯二甲酸二(2-乙基己)酯	Di-isodecylphthalate	DIDP	26761-40-0
邻苯二甲酸二丁酯	Di-butylphthalate	DBP	84-74-2

According to the provisions stipulated in the standard of GB/T 26572-2011 Requirements of concentration limits for certain restricted substances in electrical and electronic products, each homogeneous material of electrical and electronic products, the content of lead, mercury, hexavalent chromium, polybrominated biphenyls and polybrominated diphenyl ethers shall not exceed 0.1% (mass fraction), cadmium shall not exceed 0.01% (mass fraction).

Have a look on [Toxiline](#) to check our toxicological specifications.

Packaging requirements

Can you please indicate if there are some requirements regarding the packaging of our products (mainly they are in paper, carton, plastic, textile) ? If yes, please explain them.

Laboratory

In which laboratory can we perform the testing of the product according to the standard?

Sanctions / Fines

What are the sanctions / fines in case of non conformity ?

Certifications / Registrations

Certifications or registrations

Are there some certifications or registrations applicable to the product ?

Compulsory product certification regulatory requirements

- Switches (belonging to low-voltage components), circuit breakers, low-power motors, fuses, low-voltage fuses and plugs have compulsory certification requirements.
- According to CNCA-C02-01: 2014 Implementation Rules for Compulsory Product Certification Circuit Switches and Electrical Devices for Protection or Connection (Electrical Accessories), the following certification rules apply to plugs:

The principle of dividing certification units for plugs and sockets for household or similar use is: dividing certification units according to product grades, detachable and non-detachable wires, terminal types, etc.

The basic certification mode of certification is: type test + post-certification supervision.

- The certification institution shall formulate a type test plan after the data review, and inform the certification client. The type test plan includes all the sample requirements and quantities for the type test, test standard items, laboratory information, etc.;
- In principle, the type test items shall include all applicable items specified in the product safety standards;
- In principle, the type test shall be completed in the laboratory designated by CNCA.

Post-certification supervision refers to one of the three methods: follow-up inspection after certification, sample testing or inspection at the production site, and market (and/or user) sample testing or inspection.

- According to CNCA-00C-008: 2019 Self-declaration of Implementation Rules for Compulsory Product Certification, the following rules apply to compulsory certification of switches (which belong to low-voltage components), low-power motors, fuses, low-voltage fuses and circuit breakers:

Basic requirements of self-declaration procedure

- Producers (manufacturers) aim at ensuring that their self-declared products continuously meet the applicable standards of compulsory product certification, and implement internal quality control and establish factory quality assurance system according to product characteristics and production and processing characteristics.
- The producer (manufacturer) selects an appropriate type of conformity assessment method to evaluate the conformity of the product, and proves that the product continuously meets the requirements of applicable standards for compulsory product certification.
- The producer establishes technical documents and keeps them properly; since the date of completing the submission of product compliance information, they shall be kept for at least 10 years for future reference.
- The authorized representative of the producer (manufacturer) signs the "Compulsory Certification Product Conformity Self-Declaration" for the qualified products and completes the submission of product conformity information.
- Producers (manufacturers) add CCC marks to their self-declared products.
- When the product design, technical characteristics, relevant compulsory product certification requirements or self-declaration related information are changed, the producer (manufacturer) and authorized representative (if applicable) shall supplement and evaluate the product compliance and update the self-declaration and product compliance information according to the changed content.

Conformity assessment methods applicable to self-declaration procedures

The applicable conformity assessment methods of self-declaration procedure B are as follows: (All products such as low-power motors involved in this part are subject to self-declaration procedure B)

- The type test shall be conducted by the laboratory designated by the corresponding business scope of compulsory product certification (i.e. designated laboratory) and a type test report shall be issued, and the manufacturer (manufacturer) shall organize self-inspection of its factory quality assurance ability and issue a self-inspection report.
- Or, the producer (manufacturer) independently chooses the certification institution to voluntarily certify its products. Among them, the certification institution shall meet the requirements of the following certification institution: the certification process shall at least include type testing and factory inspection; the laboratory conducting the type test shall be a designated laboratory.

Certification institution requirements

- The certification institution shall be established in accordance with the law, comply with the “Requirements for the Management Measures of Certification Institution”, and possess certification qualifications in the corresponding fields.
- Certification institutions shall meet the requirements of GB/T 27065 (or ISO/IEC 17065) standards, and CNAS (or ILAC member institutions) accreditation is encouraged to be obtained.

Submitting compliance information

Producers (manufacturers), laboratories and certification institutions involved in self-declaration shall register in the “Self-declaration Information Submission System for Compulsory Certification of Product Compliance” (hereinafter referred to as the system), and submit relevant organization information and qualification documents.

If the producer (manufacturer) entrusts the design and production of the product in the ODM mode, it shall submit the following compliance information:

a Self-declared product information;

b Standard information that the product complies with;

c Initial self-declaration information;

d ODM agreement among the producer (manufacturer), the ODM initial self-declaration producer (manufacturer) and the production enterprise;

e The manufacturer (manufacturer) and the ODM initial self-declaration agreement between the producer (manufacturer) and the manufacturer on self-declaration and product quality and safety responsibilities;

f ODM product nameplate (external mark);

g Other documents related to product compliance.

After the compliance information above is submitted, the system would automatically generate the “Compulsory Certification Product Compliance Self-Declaration” based on the submitted information. The signer designated by the producer (manufacturer) and authorized representative (if applicable) signs and uploads the system to complete the self-declaration submission.

Regulatory requirements for new product development of measuring instruments

The regulatory requirements for the development of new products of measuring instruments are mainly stipulated in the “Measurement Law”, the “Implementation Rules for Metrology Law of the P.R.C.”, and the “Administrative Measures for New Products of Measurement Instruments”.

Main range	The new products of measurement instruments refer to those measurement instruments that an entity has never produced, including those whose performance and technical characters have been altered upon significant improvements in the aspects of structure and quality of material of original products.
Main supervision methods	Type approval/prototype testing (including design appraisal/type evaluation)
Applicant	Manufacturers of new products for measuring instruments. Note: With regard to the identification of the manufacturer in the mode of entrusted production, Article 14 of the "Implementation Rules for Metrology Law of the P.R.C." stipulates: An enterprise, public institution, or individual industrial and commercial household manufacturing or repairing measuring instruments must operate on fixed premises, have production facilities, inspection conditions, and technicians, among others, as specified by the state, and satisfy safety requirements. Since the manufacturer needs to have production facilities, it generally refers to the actual entrusted producer. At the same time, the answer to the frequently asked questions (https://zwdt.sh.gov.cn/govportal/bsfw/item/be4d31ff-e85b-4f7d-bc3e-d975a3aba8b5) of the type approval of domestic measuring instruments also clearly states: "The products applying for the type approval of measuring instruments must be manufactured by such enterprise. If such enterprise does not produce and entrusts other enterprises to produce, the entrusted production enterprise shall apply for the type approval of measuring instruments." Accordingly, if your company is the entrusting party in the entrusted production mode, it is usually not necessary to apply by yourself, but your company shall ask the entrusted production enterprise to apply.

Laboratory

In case of mandatory certification/ registration that we must follow please precise the name and address of any laboratories where we can conduct them

Comments

Comments

Conformity documents

Documents

What are the conformity documents ? Can you please list them ?

Format

Does it exist a specific format for the conformity documents ? If yes, can you please provide us an example in english ?

Comments

Comments

Importation rules

General rules

What are the general rules in order to import the product ?

Regulatory requirements for import of measuring instruments

The regulatory requirements for the import of measuring instruments are mainly stipulated in Measurement Law, Detailed Rules for the Implementation of Metrology Law, Administrative Measures for Supervision of Imported Instruments of Measurement, Implementation Rules of Administrative Measures for Supervision of Imported Instruments of Measurement of the P.R.C., etc.

General regulatory requirements

Anyone who intends to import or sell in China those measuring instruments included in the Catalogue of the People's Republic of China for Imported Measuring Instruments Subject to Type Approval shall apply to the competent authority for type approval.

Applicant

- The applications for the type approval of measuring instruments to be imported shall be filed by foreign traders.
- The applications for the type approval of products to be sold by foreign traders in China shall be filed by the foreign traders or its agents.

Competent authority

State Administration for Market Regulation (-
<http://zwfw.samr.gov.cn/wsbs/jl/jkjlqj/>)

Application process

- When applying to the metrological administrative department of the State Council for type approval, a foreign trader or the agent thereof shall submit the following application materials: A written application for type approval; Photos of the prototypes of measuring instruments; A description of technical features of measuring instruments (including a Chinese description).
- The metrological administrative department of the State Council shall complete the legal metrological examination on the application materials for type approval within 15 days upon receipt of such materials, primarily examining: (1) whether China's legal units of measurement are used; (2) whether the instruments are those measuring instruments which have been expressly prohibited by the State Council; (3) and whether the instruments fulfill the other requirements of metrology laws and regulations.
- After the legal metrological examination is passed, the metrological administrative department of the State Council shall determine the size and number of prototypes for appraisal, and authorize a technical institution to conduct design appraisal, and notify the foreign trader or the agent thereof to provide the technical institution with experimental prototypes and the technical materials.
- The main content of a design appraisal includes appearance inspection, metrological performance test, safety, adaptability to environment, reliability or endurance test, and other items. The design appraisal shall be completed within three months after receipt of the prototypes, and where it is necessary to extend the period due to special circumstances, such extension shall be reported to the metrological administrative department of the State Council for approval.
- Where the design appraisal passes the examination, the metrological administrative department of the State Council shall issue a Type Approval Certificate of the People's Republic of China for Imported Measuring Instruments to the foreign trader or the agent thereof who applies for type approval, and allowed it to use the mark and serial number of the type approval certificate for imported measuring instruments on the corresponding instruments and their packages.

Approval requirements for imported measuring instruments

- Applications to import instruments of measurement must be examined and approved according to the procedures stipulated by the state concerning imported commodities.
- The relevant competent administrative department for examination and approval and the special departments in charge of examination shall conduct examination of official measures for instruments of measurement to be imported, which are listed in the [Catalogue of the People's Republic of China Concerning Instruments of Measurement Controlled by Law](#) and must ensure that the instruments of measurement to be imported which are listed in the Catalogue of the People's Republic of China for Imported Measuring Instruments Subject to Type Approval pass model approval. If the relevant instruments fail to pass the examination, the department responsible for examination and approval may not approve of import of them and foreign trade department may not order the goods.
- Application, as required by special needs, to import instruments of non-official measures or those instruments which have been prohibited by the State Council must be subject to approval of metrological administrative departments of the people's governments of provinces, autonomous regions, and municipalities directly under the Central Government.

Regulatory requirements for electrical and electronic product

Regulatory requirements for product import

- The electrical and electronic products imported may not violate the compulsory standards or the standards that must be implemented as prescribed by laws, administrative regulations and rules, and shall comply with the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products.
- The entry-exit inspection and quarantine institutions shall conduct port verification and statutory inspection of the electrical and electronic products imported. The Customs shall verify the Customs Clearance Form for Goods Entering China issued by entry-exit inspection and quarantine institutions and undergo the customs clearance formalities under the relevant provisions.

Regulatory requirements for import of mechanical and electrical products

The regulatory requirements for the import of mechanical and electrical products are mainly stipulated in Administrative Measures for Import of Mechanical and Electrical Products and Implementation Measures of Automatic Import License for Mechanical and Electrical Products and other regulations. Since it has not been retrieved that your company sells products listed in the Catalog of Restricted Imports of Mechanical and Electrical Products and Electrical Products or the Catalog of Mechanical and Electrical Products Prohibited from Importing, this section is mainly aimed at the mechanical and electrical products listed in Automatic Import License Mechanical and Electrical Products Catalog, which are classified as product with automatic import license.

General regulatory requirements

- To import mechanical and electrical products with automatic import license, the import entity shall file an application with the Ministry of Commerce or its authorized institution for an Automatic Import License before it goes through the customs formalities.

Application requirements

- The import of a mechanical and electrical product in Automatic Import License Mechanical and Electrical Products Catalog shall conform to the provisions of the following laws and administrative regulations:

(1) The provisions of Standardization Law of the P.R.C. regarding the standards and enforcement standards on ensuring the human health, personal safety and property safety;

(2) The provisions of [the Environmental Protection Law of the People's Republic of China](#) and other laws and administrative regulations on environmental protection;

- (3) The provisions [the Law of the People's Republic of China on the Prevention and Control of Air Pollution](#) and other laws and administrative regulations;

(4) The relevant provisions of [the Regulation of the People's Republic of China on Certification and Accreditation](#);

(5) The import of measurement instruments shall conform to the relevant provisions of [Measurement Law of the P.R.C.](#) and Administrative Measures for Supervision of Imported Instruments of Measurement;

(6) The import of radio transmission equipment shall conform to Administrative Regulations for Radio of the P.R.C.;

(7) Conforming to relevant provisions of other laws and administrative regulations.

Application process

The applicant may submit a written application or an on-line application.

1.
 1. Written application procedure: The import applicant can obtain the "Mechanical and Electrical Products Import Application Form" from the issuing agency or download (copy) from the website authorized by the Ministry of Commerce, and submit it to the corresponding competent authority together with other relevant written materials.
 2. Online application procedure: The applicant for import logs on the website authorized by the Ministry of Commerce, enters the national mechanical and electrical product import document management system, and truthfully fills in the "Mechanical and Electrical Product Import Application Form" online as required and submits it to the corresponding competent authority

The procedure for issuing "Automatic Import License" for mechanical and electrical products is as follows:

1.
 1. For the import of an mechanical and electrical product that shall be handled by the local or departmental mechanical and electrical office, as soon as the local or departmental mechanical and electrical office receives a Form of Application for Import of mechanical and electrical Products and relevant materials, whose contents are correct and which meet the formal requirements, it shall issue an Automatic Import License. In a special case, it may issue an Automatic Import License within 10 working days.
 2. For the import of a mechanical and electrical product that shall be handled by the Ministry of Commerce, the local or departmental mechanical and electrical office shall, within 3 working days after it receives a complete set of application materials, submit to the Ministry of Commerce the electronic data thereof upon verification. As soon as the Ministry of Commerce receives the corresponding data, it shall issue an Automatic Import License. In special cases, it may issue an Automatic Import License within 10 working days.

Documents

What are the required documents ?

Time period

In which time period may we obtain the right to import ?

Administration

What is the administration in charge of importations ? Name and address ?

Comments

Comments

Inspection of the product

Inspection method

Does it exist an inspection procedure applicable to the product ? If yes, which administration is in charge of ? Can you please describe the procedure ?

Commercialization rules

Notification / Declaration

What are the general rules in order to comercialize a product ?
Is there a notification / declaration to do ?

Regulatory requirements for the sales of measuring instruments

The regulatory requirements for the sales of measuring instruments are mainly stipulated in Measurement Law, Implementation Rules for Metrology Law of the P.R.C..

Those who sales the new measurement products which have not passed model approval or prototype testing shall be ordered to stop selling such products and seal them up for safekeeping. Their total amount of illegal gains shall be confiscated and a fine of 3,000 yuan or less may be imposed simultaneously.

Whoever sells unqualified measuring instruments shall be confiscated of the illegal income, and may be imposed on a fine.

Where metrological instruments not adopting legal units of measurement are sold in violation of [Article 14](#) of Measurement Law of the P.R.C. , the violator shall be ordered to cease the sale, with the metrological instruments and all illegal income confiscated, and may be fined 10% to 50% of the illegal income.

Those who sell damaged and substandard spare parts and components of measurement instruments shall be ordered to stop their business. The instruments and total amount of illegal gains shall be confiscated and a fine of 2,000 yuan or less may be imposed simultaneously; in more serious cases, the business licence shall be revoked by administrative departments for industry and commerce.

Regulatory requirements for electrical and electronic product

regulatory requirements for

product sales

The sellers of electrical and electronic products may not sell the electrical and electronic products that violate the national or industrial standards for the restricted use of the hazardous substances contained in electrical and electronic products.

Documents

What are the required documents ?

Delay

What is the delay to obtain the right to commercialize ?

Display in store

Is there some specific rules on the way to display the product in store ?

Display on internet

Is there some specific mentions to display the product on internet ?

Information to consumers

Do some specific information to have be given to consumers when the product is placed on the market ?

“Three Guarantees” regulatory requirements

The regulatory requirements of “Three Guarantees” are mainly stipulated in Regulations on Responsibility for Repair, Replacement and Return of Certain Commodities, which put forward regulatory requirements for producers and sellers.

Regulatory requirements of “Three Guarantees” for producers

“Three Guarantees” obligations that shall be performed by producers

- (1) Clarifying the methods for “three guarantees”: where a producer determines or designates the repairer by itself, it shall provide the vouchers for “three guarantees”, the name, addresses and phone number of the repairers to the consumers together with the products;
- (2) Providing technical materials and qualified fittings for repair to the seller and the repairer responsible for the repair, taking charge of the training, providing the expenses for repair; and guaranteeing to continuously provide the accessories and fittings consistent with technical requirements for five years after production of the products stops; and
- (3) Properly handling the direct or indirect inquiries of consumers, and providing relevant services.

Article 9

Bearing of repair cost

- The expenses for repair shall be provided by the producers, and which refers to the expenses to be paid for ensuring the normal repair within the valid term for “three guarantees”.
- With respect to the products for which the liability of repair shall be borne by the seller, the producer shall allot the expenses once and for all according to the contract or agreement, and the specific measures shall be determined upon negotiations of both parties. If the producer chooses other methods or sets up repair outlets by itself, the producer shall directly provide the repair costs.

Regulatory requirements of “Three Guarantees” for sellers

“Three Guarantees” obligations that shall be performed by sellers

- (1) not selling any products listed in the Catalogue if it could not guarantee the implementation of the provisions on “three guarantees”;
- (2) keeping the quality of products as sold;
- (3) implementing the system for check and acceptance of commodities as procured, and not selling those commodities that do not comply with the requirements of mandatory marks;
- (4) When selling products, opening the box for inspection, conducting correct debugging, introducing how to use and maintain the products, the methods for “three guarantees”, as well as the entities for repair, and providing valid invoices and vouchers for “three guarantees”; and
- (5) properly handling the inquiries and complaints of consumers, and providing relevant services.

Requirements for

return and repair

- In case a product fails to function within 7 days after it is sold, the consumer may choose the return, replacement or repair of the product. In the case of return of the product, the seller shall return the payments once and for all according to the price on the invoice, and then recover the losses against the producer or supplier, or handle it according to the purchase-and-sale contract.
- In case a product fails to function within 15 days after it is sold, the consumer may choose the replacement or repair of the product. In the case of replacement of the product, the seller shall replace it with a product of the same model and specification for the consumer free of charge, and then recover losses against the producer or supplier, or handle it according to the purchase-and-sale contract.
- In case a product has been repaired for two times but still could not be normally used within the valid term for “three guarantees”, the seller shall be responsible for replacing it with a product of the same model and specification or returning the product according to Article 13 of these Provisions for the consumer free of charge and upon the strength of the repair records or certificates as provided by the repairer, and then recover losses from the producer or supplier, or handle it according to the purchase-and-sale contract.
- In case a product has not been repaired within 90 after the product was sent to the repairer within the valid term for “three guarantees” due to the fact that the producer fails to provide accessories or fittings, the repairer shall indicate it in the repair conditions, and the seller shall replace it with a product of the same model and specification for the consumer free of charge based thereon, and then recover losses against the producer or supplier, or handle it according to the purchase-and-sale contract.
- In case the requirements for replacement of the product are met within the valid term for “three guarantees”, and the consumer requires the return of the product due to the fact that the seller could not provide an qualified product of the same model and specification, and the consumer is unwilling to exchange other models and specifications, the seller shall return the product. And if there is an qualified product of the same model and specification, and the consumer is unwilling to replace the product but requires to return the product, the seller shall return the product, and may collect the fees for depreciation according to these Provisions if the product has been used.
- At the time of replacing products, the products that are incomplete, inferior, unqualified, or have been repaired shall not be provided to consumers. The valid term for “three guarantees” after the replacement of a product shall be calculated anew as of the date of replacement of the product. The seller shall affix a seal for replacement on the inverse side of the invoice, and provide a new voucher for “three guarantees” or affix a seal for replacement on the inverse side of the voucher for “three guarantees”.

Bearing of repair cost

- In case the seller entrusts or designates the repairer, the method for paying the expenses for repair shall be stipulated in the contract between the seller and the repairer.

Comments

Comments

Administration

What is the administration in charge of commercialization ? Name and address ?

Documents