

SoC → caminhos de boot (logo + animation)

Referência para customização de boot por família de chip. Validar no modelo exato antes de flash em produção.

Bootanimation Android (todas as famílias)

Item	Valor
Arquivo	bootanimation.zip
Local runtime	/system/media/bootanimation.zip
Formato ZIP	ZIP_STORED (sem compressão)
Conteúdo	desc.txt + part0/000000.png (ou sequência)
Gerador projeto	Player-AD/scripts/build-bootanimation.py
Instalador	Player-AD/scripts/install-bootanimation.ps1 -Portrait

desc.txt portrait (1080×1920)

```
1080 1920 1
p 1 0 part0
```

Bootlogo (splash antes / durante boot Android)

Allwinner (H313, H616, H618, H728, sun8iw7...)

Item	Valor
Formato	BMP 24-bit RGB
Resolução TV_BOX_3	1280×720
Partição TV_BOX_3	/dev/block/mmcblk0p2 (vfat)
Arquivo	bootlogo.bmp
Mount	/mnt/bootlogo
Gerador	Player-AD/scripts/build-bootlogo.py
Instalador	Player-AD/scripts/install-bootlogo.ps1

SDK / firmware path (H618, KICKPI doc):

```
longan/device/config/chips/h618/boot-resource/boot-resource/bootlogo.bmp
```

Outros Allwinner (exemplos KICKPI wiki):

Board	SoC	Path bootlogo
K2B / K2C	H618	.../chips/h618/boot-resource/ boot-resource/bootlogo.bmp
K5 / K5C	A133	.../chips/a133/configs/c3/an droid/bootlogo.bmp

Board	SoC	Path bootlogo
K9	T527	.../chips/t527/boot-resource /boot-resource/bootlogo.bmp

Fonte: KICKPI boot logo wiki

Rockchip (RK3566, RK3568, RK3588...)

Item	Valor
Formato	BMP (logo.bmp, logo_kernel.bmp)
SDK path (ex.)	kernel-5.10/logo.bmp, kernel-5.10/logo_kernel.bmp
RK3576	kernel-6.1/logo.bmp
Bootanimation	/system/media/bootanimation.zip (igual Android padrão)

Duas fases: U-Boot logo + Kernel logo.

Amlogic (S905X4, S905Y5, S905W2...)

Item	Valor
Bootanimation	/system/media/bootanimation.zip
Bootlogo	Varia por BSP — solicitar path ao OEM (partição Logo ou resource pack)
Nota	Tanix/Amlogic signage costuma oferecer ODM boot image de fábrica

Matriz rápida

SoC	bootanimation	bootlogo	Script projeto
Allwinner sun8iw7 (TV_BOX_3)	/system/media/	mmcblk0p2 bootlogo.bmp	bootanimation + bootlogo
Allwinner H618	/system/media/	boot-resource bootlogo.bmp	bootanimation + bootlogo (confirmar partição)
Rockchip RK3566/68	/system/media/	logo.bmp no kernel	bootanimation (+ OEM logo)
Amlogic S905Y5	/system/media/	ODM / perguntar fábrica	bootanimation (+ OEM logo)

Portrait no SO

Config Player-AD	displayRotation	user_rotation (TV landscape nativa)
Portrait	0	1
Landscape	1	0
Reverse portrait	2	3
Reverse landscape	3	2

Script: Player-AD/scripts/set-android-display-rotation.ps1 -Rotation 1

Links

- [MANUAL-OPERACIONAL-TVBOX.md](#)
- [TOTEM-ODM-SPEC-v1.md](#)
- [TV_BOX_3-SPEC.md](#)