

# Vibe Time Keeper — Setup

Enable, sign in, and configure Vibe Time Keeper on your Vibe Appliance.

Vibe Appliance setup guide · built 2026-08-31 · generated from the app's manifest · KisaesDevLab/Vibe-Appliance

---

## 1. What this app is

Time tracking and payroll runs for small accounting practices.

|                      |                                                                                                                                                |
|----------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>App id (slug)</b> | vibe-payroll                                                                                                                                   |
| <b>Uses</b>          | the appliance's shared postgres, redis — nothing separate to install                                                                           |
| <b>Data lives in</b> | database <code>vibe_payroll_db</code> inside the appliance's Postgres — covered by your Duplicati backups and by the automatic pre-update dump |

## 2. Before you enable it

- The appliance itself must be installed and healthy — see the **Vibe Appliance setup guide** first if you haven't done that yet.
- Each running app uses memory. Two or three apps fit a 2 GB server; for all of them plan on 4 GB or more.
- If the card shows an image not published badge, the app's build isn't available yet — the Enable button stays off until it is.

## 3. Enable the app

1. Open the admin console and scroll to **Apps**.
2. On the **Vibe Time Keeper** card, click **Enable**.
3. Watch the badge: `not-installed` → `enabling...` → `running`. This usually takes a minute or two (first enable pulls the app's images).

Behind the button, the appliance creates the app's database and a restricted database user, writes the app's configuration file from a template, starts its containers, and only reports **running** once the app's own health check answers that it is fully ready. If enabling fails, the card shows the error with a recovery hint — fix the cause and click Enable again; re-running is always safe.

## 4. Open it and sign in

|                    |                                                                                                                              |
|--------------------|------------------------------------------------------------------------------------------------------------------------------|
| <b>Domain mode</b> | <code>https://vibe.&lt;your-domain&gt;/time/</code> (replace <code>vibe</code> with your tunnel subdomain if you changed it) |
|--------------------|------------------------------------------------------------------------------------------------------------------------------|

---

|                       |                                              |
|-----------------------|----------------------------------------------|
| <b>LAN mode</b>       | <code>http://&lt;host&gt;.local/time/</code> |
| <b>Tailscale mode</b> | <code>http://&lt;tailnet-ip&gt;/time/</code> |

The exact live URL for your install is always shown on this app's card in the admin console — use that if in doubt.

Open the app URL. The first-login credentials are shown in the admin console under **First-login info**.

## 5. Setup on Windows

There is nothing to install on Windows for this app — it runs on the appliance server, and you use it from a browser (Microsoft Edge or Chrome, as your firm prefers). What follows is the Windows side of reaching it in each mode.

- **Domain mode:** just open the URL from the previous section. The certificate is real, so there is nothing to click through.
- **LAN mode:** recent Windows 10 and 11 resolve `<host>.local` addresses out of the box, but some office networks and VPN clients block that discovery traffic. If the `.local` address doesn't load, use the server's IP address instead: `http://<server-ip>/time/`. The exact working URL is always shown on this app's card in the admin console.
- **Tailscale mode:** install the Tailscale app for Windows from `tailscale.com/download`, sign in to the firm's tailnet, and the tailnet URL from the section above works. The Tailscale icon in the system tray shows whether you're connected.
- **Bookmark it:** once the right URL loads, save it as a browser favorite (Ctrl+D) — or let your IT person pin it via a browser shortcut on each staff desktop.

## 6. Settings

Everything required (database, cache, secrets, URLs) is generated automatically when you enable the app. The settings below are the ones you may need to fill in yourself. Find them in the admin console under **Settings**, on the tab named in the left column.

### Network tab

| SETTING          | WHAT TO ENTER                                                                                                                                                                                                                                                                                                                                           |
|------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Subdomain</b> | The <code>&lt;subdomain&gt;</code> in <code>&lt;subdomain&gt;.&lt;your-domain&gt;</code> for this app when routing is 'subdomain per app' (see Network settings). Leave blank to use the built-in default. Lowercase letters, digits, and dashes; no dots. Saving re-renders routing and re-provisions the Cloudflare Tunnel; the app briefly restarts. |

## Application tab

| SETTING                        | WHAT TO ENTER                                                                            |
|--------------------------------|------------------------------------------------------------------------------------------|
| <b>Firm name</b>               | e.g. "Acme Tax LLC". Shown to staff at the time-tracking kiosk.                          |
| <b>Enabled states</b>          | Multi-select. Each state activates its own withholding tables and overtime rules.        |
| <b>FLSA workweek start day</b> | FLSA requires a fixed 7-day workweek; this sets the start day for overtime calculations. |
| <b>Kiosk auto-logout (ms)</b>  | 3000-60000. Shorter is more secure but rushes slow staff. Default 5000 (5s).             |

## Time & Logging tab

| SETTING                     | WHAT TO ENTER                                                                                    |
|-----------------------------|--------------------------------------------------------------------------------------------------|
| <b>Time zone (override)</b> | Inherited from appliance. Override only if this firm operates in a different zone than the host. |

## 7. Updates and rollback

- When a newer build is available, the card shows an **update available** badge. Click **Update**.
- Before updating, the appliance takes a database backup automatically. If the updated app fails its health check, it is rolled back to the previous version — and the **Roll back** button lets you do the same by hand.
- Updates are never automatic; nothing changes until you click.

## 8. If something goes wrong

- **Run the doctor first.** Admin console → **Doctor** → Run (or `sudo vibe doctor` on the server). It names the failing check and the fix.
- **Read the card.** Errors on the app card include a recovery hint; the output panel under the buttons shows the last action's log.
- **Emergency access.** If the normal URL is down but the app itself is running, `http://<server-ip>:5192/` reaches it directly, bypassing the web front end. Plain HTTP — use it from the LAN or Tailscale only, for getting back on your feet, not for daily work.
- **Disable / Enable** from the card restarts the app cleanly. Disabling never deletes data.
- Still stuck? `docs/TROUBLESHOOTING.md` in the appliance repository is keyed by symptom.