

Aim:

Write a C Program to count the number of 0's and 1's in a **binary** representation of a given number.

Sample Input and Output:

```
Enter a decimal number : 25
Binary number : 11001
Number of zero's : 2
Number of one's : 3
```

Source Code:

zerosOnesCount.c

```
#include<stdio.h>
#include<math.h>
int main()
{
    int num,b_num=0,once_count=0,zero_count=0,count=0;
    printf("Enter a decimal number : ");
    scanf("%d",&num);
    while(num!=0)
    {
        int rem=num%2;
        if(rem==0)
            zero_count++;
        else
            once_count++;
        int c=pow(10,count);
        b_num=b_num+rem*c;
        num=num/2;
        count++;
    }
    printf("Binary number : %d\n",b_num);
    printf("Number of zero's : %d\n",zero_count);
    printf("Number of one's : %d\n",once_count);
}
```

Execution Results - All test cases have succeeded!

Test Case - 1
User Output
Enter a decimal number : 10
Binary number : 1010
Number of zero's : 2
Number of one's : 2

Test Case - 2

User Output
Enter a decimal number : 7
Binary number : 111
Number of zero's : 0
Number of one's : 3

Test Case - 3
User Output
Enter a decimal number : 4
Binary number : 100
Number of zero's : 2
Number of one's : 1

Test Case - 4
User Output
Enter a decimal number : 25
Binary number : 11001
Number of zero's : 2
Number of one's : 3

Test Case - 5
User Output
Enter a decimal number : 255
Binary number : 11111111
Number of zero's : 0
Number of one's : 8

Test Case - 6
User Output
Enter a decimal number : 201
Binary number : 11001001
Number of zero's : 4
Number of one's : 4

Test Case - 7
User Output
Enter a decimal number : 111
Binary number : 1101111
Number of zero's : 1
Number of one's : 6

Test Case - 8
User Output
Enter a decimal number : 99
Binary number : 1100011
Number of zero's : 3
Number of one's : 4