Kuuube's Wacom Tablet Mastersheet

Tablets

Consumer Tablets

Category	Model Identifier	Aspect Ratio	Pen LPI/LPMM	Active Area Size	Physical Size	Physical - Active [W] [H]	Weight	Tablet Buttons	Default Pen Model Identifier	Max Hover Height with Default Pen (Detection Range)	Pen/Mouse Report Rate	Touch LPI/LPMM	Touch Report Rate	Wireless Report Rate	Max TIS Levels	Hardware Filtering	Cable (Device > Host)	Compatible Pens	Compatible Mice
Consumer Tablets	CTC-4110WL [1]	16 : 10	2540/100	152 x 95 mm	188 x 141 x 8 mm	1.8:0.1:0.3[0.1:1.48:0]	250g	0	CP-923 [2]	20mm (22.5mm)	240	N/A	N/A	120	128	Slight Hover Anti-chatter + Hover/Drag Smoothing + Glitchy Pressure Filtering	Detachable USB-C to USB-A	CP-923, CP-913, CP-203, LGT-1-2, 180 22-1, 1812 22-1	N/A
	CTC-6110WL [4]	16 : 10	2540/100	216 x 135 mm	252 x 185 x 8 mm	1.9:0.1:0.3[0.1:1.48:0]	350g	0	CP-923 [4]	???	240	N/A	N/A	120	128	Slight Hover Anti-chatter + Hover/Drag Smoothing + Glitchy Pressure Filtering	Detachable USB-C to USB-A	CP-923, CP-913, CP-203, LGT-1-2, 180 22-1, 1812 22-1	N/A
	CTL-4100 [5]	16 : 10	2540/100	152 x 95 mm	200 x 140 x 8.8 mm	2.2:2:1.5[1.48:0]	230g	4	LP-1100K [6]	20mm (18.5mm)	133	N/A	N/A	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	CP-1100K	N/A	N/A
	CTL-6100WL [7]	16 : 10	2540/100	216 x 135 mm	260 x 160 x 8.8 mm	2.2:2:1.5[1.48:0]	230g	4	LP-1100K [8]	20mm (18.5mm)	133	N/A	N/A	???	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	CP-1100K	N/A
	CTL-6100 [9]	16 : 10	2540/100	216 x 135 mm	260 x 200 x 8.8 mm	1.8:1.5:2.2[1.48:0]	450g	4	LP-1100K [10]	???	133	N/A	N/A	N/A	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	CP-1100K	N/A
	CTL-6100WL [11]	16 : 10	2540/100	216 x 135 mm	264 x 200 x 8.8 mm	1.8:1.5:2.2[1.48:0]	450g	4	LP-1100K [12]	???	133	N/A	N/A	???	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	CP-1100K	N/A
	CTL-490 [13]	16 : 10	2540/100	152 x 95 mm	230 x 160 x 7 mm	2.4:2:0.3[1.48:0.1]	290g	4	LP-1100K [14]	13mm (15mm)	133	N/A	N/A	N/A	N/A	Anti-chatter + Hover Smoothing + Glitchy Hover/Drag Transition	Detachable Micro USB B to USB-A	LP-190, LP-1900	N/A
	CTH-690 [15]	16 : 10	2540/100	152 x 95 mm	250 x 169 x 7 mm	2.6:2:0.3[1.48:0.1]	290g	4	LP-1900 [16]	13mm (15mm)	133	254/10?	100	???[17]	N/A	Anti-chatter + Hover Smoothing + Glitchy Hover/Drag Transition	Detachable Micro USB B to USB-A	LP-190, LP-1900	N/A
	CTL-690 [18]	16 : 10	2540/100	216 x 135 mm	275 x 217.2 x 7.10.7 mm	2.0:1.5:0.2[1.48:0.3]	480g	4	LP-1900 [19]	???	133	N/A	N/A	N/A	N/A	Anti-chatter + Hover Smoothing + Glitchy Hover/Drag Transition	Detachable Micro USB B to USB-A	LP-190, LP-1900	N/A
	CTH-690 [20]	16 : 10	2540/100	216 x 135 mm	275 x 217.2 x 7.10.7 mm	2.0:1.5:0.2[1.48:0.3]	480g	4	LP-1900 [21]	???	133	254/10?	100	???[22]	N/A	Anti-chatter + Hover Smoothing + Glitchy Hover/Drag Transition	Detachable Micro USB B to USB-A	LP-190, LP-1900	N/A
	CTL-480 [23]	16 : 10	2540/100	152 x 95 mm	209.9 x 177.5 x 7.10 mm	2.5:2:1.5[1.48:0.1]	450g	4	LP-180	15mm (18mm)	133	N/A	N/A	N/A	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTH-480 [24]	16 : 10	2540/100	152 x 95 mm	209.9 x 177.5 x 7.10 mm	2.5:2:1.5[1.48:0.1]	450g	4	LP-180 [25]	15mm (18mm)	133	254/10?	100	???[26]	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTL-680 [27]	16 : 10	2540/100	216 x 135 mm	275 x 217.2 x 7.10.1 mm	2.0:1.5:2.2[1.48:0.3]	500g	4	LP-1800	???	133	N/A	N/A	N/A	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTH-680 [28]	16 : 10	2540/100	216 x 135 mm	275 x 217.2 x 7.10.1 mm	2.0:1.5:2.2[1.48:0.3]	520g	4	LP-1800	???	133	254/10?	100	???[29]	N/A	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTL-470 [30]	16 : 10	2540/100	152 x 95 mm	277 x 189 x 8.7 mm	1.8:1:0.2[0.1:1.48:0.1]	337g	0	LP-1908 [31]	17mm (17mm)	133	N/A	N/A	N/A	None	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-190, LP-1900	N/A
	CTL-471 [32]	16 : 10	2540/100	216 x 135 mm	277 x 189 x 8.7 mm	1.8:1:0.2[0.1:1.48:0.1]	337g	0	LP-1908 [33]	???	133	N/A	N/A	N/A	None	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-190, LP-1900	N/A
	CTL-671 [34]	16 : 10	2540/100	216 x 135 mm	277 x 189 x 7.9 mm	1.7:1:0.2[0.1:1.48:0.1]	422g?	0	LP-171	21mm (18.5mm)	133	N/A	N/A	N/A	None	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTL-671 [35]	16 : 10	2540/100	216 x 135 mm	277 x 189 x 7.9 mm	1.7:1:0.2[0.1:1.48:0.1]	422g?	0	LP-171	???	133	N/A	N/A	N/A	None	Anti-chatter + Hover Smoothing	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTH-670 [36]	16 : 10	2540/100	147.2 x 92 mm	278 x 176 x 9.8 mm	3.6:1:1.8[0.1:1.48:0.1]	480g	4	LP-1700	11.5mm (11.5mm)	133	254/10	100	???[37]	N/A	Anti-chatter + Hover Smoothing + Glitchy Hover/Drag Transition	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTH-670 [38]	16 : 10	2540/100	147.2 x 92 mm	278 x 176 x 9.8 mm	3.6:1:1.8[0.1:1.48:0.1]	480g	4	LP-1700 or LP-170	11.5mm (11.5mm)	133	254/10	100	???[39]	N/A	Anti-chatter + Hover Smoothing + Glitchy Hover/Drag Transition	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTH-470 [40]	16 : 10	2540/100	216.08 x 137 mm	251.75 x 209 x 8.8 mm	2.8:2:1.5[1.48:0.1]	350g	4	LP-1700	???	133	254/10	100	???[41]	N/A	Anti-chatter + Hover Smoothing + Glitchy Hover/Drag Transition	Detachable Micro USB B to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTE-460 [42]	16 : 10	2540/100	147.2 x 92.3 mm	195 x 197 x 10.7 mm	2.8:1:1.5[1.52:1.2:0.1]	400g	0	EP-550 [43]	???	133	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	EP-550	N/A
	CTE-640 [44]	16 : 10	2540/100	216 x 135.1 mm	260.9 x 208 x 10.7 mm67	2.1:1:1.2[1.52:1.2:0.1]	600g?	0	EP-550 [45]	???	133	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	EP-550	N/A
	CTH-461 [46]	16 : 10	2540/100	147.2 x 92 mm	268.2 x 176.1 x 8.5 mm	3.2:1:1.6[0.1:1.48:0.1]	420g	4	LP-1610 [47]	15mm (15mm)	133	101.6/8	50	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTL-461 [48]	16 : 10.1	2540/100	216.08 x 137 mm	268.8 x 223 x 8.5 mm	2.5:2:1.5[1.48:0.1]	470g	4	LP-1610 [49]	???	133	101.6/8	50	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTL-661 [50]	16 : 10	2540/100	147.2 x 92 mm	268.2 x 176.1 x 8.5 mm	3.2:1:1.6[0.1:1.48:0.1]	560g	0	LP-1661 [51]	15mm (12mm)	133	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTH-661 [52]	16 : 10	2540/100	147.2 x 92 mm	268.2 x 176.1 x 8.5 mm	3.2:1:1.6[0.1:1.48:0.1]	560g	0	LP-1600 [53]	15mm (12mm)	133	101.6/8	50	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTL-460 [54]	16 : 10.1	2540/100	216.08 x 137 mm	268.8 x 223 x 8.5 mm	2.5:2:1.5[1.48:0.1]	470g	4	LP-1610	???	133	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTL-860 [55]	16 : 10	2540/100	147.2 x 92 mm	268.2 x 176.1 x 8.5 mm	3.2:1:1.6[0.1:1.48:0.1]	560g	0	LP-1661 [56]	15mm (12mm)	133	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTH-860 [57]	16 : 10	2540/100	147.2 x 92 mm	268.2 x 176.1 x 8.5 mm	3.2:1:1.6[0.1:1.48:0.1]	560g	0	LP-1600 [58]	15mm (12mm)	133	101.6/8	50	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	CTT-460 [59.5]	16 : 10.88	N/A	120 x 85 mm	208.6 x 137.6 x 7.5 mm	2.7:1:0.4[1.5:1:0.2:0.1]	250g	4	N/A	N/A	N/A	101.6/8	50	N/A	None	Anti-chatter	N/A to USB-A	N/A	N/A
	CTL-480 [59.5]	16 : 10.1	2540/100	216 x 137 mm	268.8 x 223 x 8.5 mm	2.5:2:1.5[1.48:0.1]	470g	4	LP-1610	???	133	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	LP-171, LP-173, LP-1700, LP-1601, LP-1603, LP-180, LP-1800, LP-1809	N/A
	MTE-450 [60]	16 : 10	2540/100	147.2 x 92.3 mm	200 x 186 x 10.7 mm	2.7:1:1.3[0.1:1.52:0.1]	370g	4 + Wheel	EP-1500 [59]	15mm (15mm)	133	N/A	N/A	N/A	None	Anti-chatter	Detachable Micro USB B to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	N/A
	CTE-450 [61]	16 : 10	2540/100	147.2 x 92.3 mm	210 x 156.1 x 11.2 mm	2.9:1:1.3[0.1:1.52:0.1]	370g	4 + Wheel	EP-1500 [57]	???	133	N/A	N/A	N/A	None	Anti-chatter	Detachable Micro USB B to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-155
	CTE-450 [62]	16 : 10	2540/100	216.5 x 135.5 mm	280 x 235.1 x 11 mm	2.2:1:1.3[0.1:1.52:0.1]	550g	4 + Wheel	EP-1500 [59]	???	133	N/A	N/A	N/A	None	Anti-chatter	Detachable Micro USB B to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-155
	PTK-450 [63]	16 : 12	2540/100	152 x 95 mm	216 x 178.8 mm	2.8:1:1.5[0.1:1.52:0.1]	350g	0 + Wheel	EP-B10	???	100	N/A	N/A	???	None	Anti-chatter	N/A to USB-A	UP-B10	N/A
	CTH-640 [64]	16 : 11.6	2032/80	216 x 92.8 mm	208 x 203.8 x 17.8 mm	3.9:0.1:1.6[0.1:2:1]	550g	2 + Wheel	EP-1600 [65]	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-160
	CTH-630 [66]	16 : 11.95	2032/80	208.8 x 130.8 mm	279 x 230.8 x 18 mm	2.9:0.1:1.6[0.1:2:1]	900g	2 + Wheel	EP-1600 [64]	???	100	N/A	N/A	N/A	None	Anti-chatter	Detachable Micro USB B to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-160
	CTH-305 [67]	16 : 10	508/20	107 x 67 mm	161.4 x 166.5 x 6.9 10.7 mm	3.2:1:1.5[0.2:1.48:0]	130g	2	???	???	???	???	???	???	N/A	Anti-chatter	Detachable Micro USB B to USB-A	???	N/A
	CTH-309 [68]	16 : 10	508/20	107 x 67 mm	161.4 x 166.5 x 6.9 10.7 mm	3.2:1:1.5[0.2:1.48:0]	137g	2	???	???	???	???	???	???	N/A	Anti-chatter	N/A to USB-A	???	N/A
	PTH-870 [69]	16 : 11.6	2032/80	217.6 x 92.8 mm	210 x 208 x 17.5 mm	3.6:0.1:1.6[0.1:2:1.1]	???	0	EP-1102 [67]	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	???
	CTH-980 [70.5]	16 : 11.95	2032/80	208.8 x 130.8 mm	279 x 230.8 x 18 mm	2.9:0.1:1.6[0.1:2:1.1]	900g	0	EP-1100 [71]	???	100	N/A	N/A	N/A	None	Anti-chatter	Detachable Micro USB B to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-160
	CTH-970 [72]	16 : 11.95	2032/80	208.8 x 130.8 mm	277 x 230 x 20.3 mm	2.9:0.1:1.6[0.1:2:1.1]	???	0	EP-1100 [73]	???	100	N/A	N/A	???	None	Anti-chatter	Detachable Micro USB B to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-160
	CTH-670 [74]	16 : 11.6	2032/80	216 x 92.8 mm	195 x 197 x 20.7 mm	3.6:0.1:1.6[0.1:2:1.1]	450g	0	EP-1102 [75]	???	100	N/A	N/A	???	None	Anti-chatter	N/A to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	???
	CTP-231 [76]	16 : 11.42	1016/40	81.2 x 58 mm	146 x 150.6 x 8.5 mm	4.6:1:1.8[0.1:2:0.1]	160g	0	PP-410	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	PP-501, PP-610, PP-510	???
	CTP-420 [76]	16 : 11.6	1016/40	127 x 92.8 mm	203 x 209.2 x 12.8 mm	3.6:1:1.7[0.1:2:0.1]	300g	0	PP-410	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	PP-501, PP-610, PP-510	???
	PTD-2310 U [77]	16 : 11.42	1016/40	65 x 36.6 mm	???	??? : ??? : ???	???	0	???	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	PP-501, PP-610, PP-510	???
	PTH-851 U [78]	16 : 11.6	1016/40	127 x 92.8 mm	216.1 x 221 x 22.2 mm	4.1:0.1:1.7[0.1:2:0.38:0]	565g	0	PP-1002 [79]	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	PP-100	EC-100
	ET-0870A-U [80]	16 : 11.6	1016/40	127 x 92.8 mm	216.1 x 218 x 9.3 mm	3.9:0.1:1.6[0.1:2:0.1]	420g	0	PP-1100 [81]	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-100
	ET-0870A-U [82]	16 : 11.7	1016/40	170 x 127.8 mm	284 x 245 x 9.4 mm	3.7:1:1.6[0.1:2:0.1]	500g	0	PP-1100	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-100
	ET-0691-U [83]	16 : 11.6	1016/40	127 x 92.8 mm	209 x 216 x 9.3 mm	3.7:0.1:1.6[0.1:2:0.1]	341g	0	EP-1000 [84]	12mm (11mm)	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-100
	ET-0691-K [85]	16 : 11.6	1016/40	127 x 92.8 mm	209 x 216 x 9.3 mm	3.7:0.1:1.6[0.1:2:0.1]	341g	0	EP-1000 [86]	12mm (11mm)	100	N/A	N/A	N/A	None	Anti-chatter	N/A to Pro 21CC Serial: 9-pin D-sub female	EP-1000, EP-1200, EP-1300, EP-200, EP-1400, EP1500, EP1550	EC-100
	CT-0691-U [87]	16 : 12	1016/40	128 x 96 mm	196 x 181 x 7 mm	2.8:0.1:1.5[0.1:1.89:0]	430g	0	LP-1100 [88]	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to USB-A	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	CT-0691-K [88]	16 : 12	1016/40	128 x 96 mm	196 x 181 x 7 mm	2.8:0.1:1.5[0.1:1.89:0]	430g	0	LP-1100 [86]	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to Pro 21CC Serial: 9-pin D-sub female	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	CT-0405-A [91]	16 : 12	1016/40	128 x 96 mm	196 x 181 x 7 mm	2.8:0.1:1.5[0.1:1.89:0]	430g	0	LP-1100 [92]	???	100	N/A	N/A	N/A	None	Anti-chatter	N/A to Pro 21CC Serial: 9-pin D-sub female	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	PTH-660 A [94]	16 : 12	2540/100	128 x 96 mm	191 x 175 x 8.98 mm	2.7:1:1.5[0.1:1.82:0]	350g	0	LP-B310 [95]	10mm (9.5mm)	205	N/A	N/A	N/A	None	Anti-chatter	N/A to Pro 21CC Serial: 9-pin D-sub female	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	ET-0660A-R [95]	16 : 12	2540/100	216 x 96 mm	191 x 175 x 8.98 mm	2.7:1:1.5[0.1:1.82:0]	350g	0	LP-B310 [96]	???	205	N/A	N/A	N/A	None	Anti-chatter	N/A to Pro 21CC Serial: 9-pin D-sub female	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	ET-0660A-W [97]	16 : 12	2540/100	216 x 96 mm	191 x 175 x 8.98 mm	2.7:1:1.5[0.1:1.82:0]	350g	0	LP-B310 [100]	???	205	N/A	N/A	N/A	None	Anti-chatter	N/A to Pro 21CC Serial: 9-pin D-sub female	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	ET-0405-WB [98]	16 : 12	2540/100	128 x 96 mm	191 x 175 x 8.98 mm	2.7:1:1.5[0.1:1.82:0]	350g	0	LP-B310 [99]	???	140	N/A	N/A	N/A	None	Anti-chatter	N/A to ADB: 6-pin mini-circular DIN	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	ET-0405-S [101]	16 : 12	1270/50	128 x 96 mm	191 x 175 x 8.98 mm	2.7:1:1.5[0.1:1.82:0]	350g	0	LP-B310 [102]	???	205	N/A	N/A	N/A	None	Anti-chatter	N/A to Pro 21CC Serial: 9-pin D-sub female	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A
	ET-0405-G [103]	16 : 12	1270/50	128 x 96 mm	191 x 175 x 8.98 mm	2.7:1:1.5[0.1:1.82:0]	350g	0	LP-B310 [104]	???	140	N/A	N/A	N/A	None	Anti-chatter	N/A to ADB: 6-pin mini-circular DIN	UP-801, UP-810, UP-811, UP-241, UP-421, UP-501, UP-201, UP-911N, UP-917N, UP-810E, UP-710W, UP-211, UP-401	N/A

Professional Tablets

Category	Model Identifier	Aspect Ratio	Pen LPI/LPMM	Active Area Size	Physical Size	Physical - Active [W] [H]	Weight	Tablet Buttons	Default Pen Model Identifier	Max Hover Height with Default Pen (Detection Range)	Pen/Mouse Report Rate	Touch LPI/LPMM	Touch Report Rate	Wireless Report Rate	Max TIS Levels	Hardware Filtering	Cable (Device > Host)	Compatible Pens	Compatible Mice
Professional Tablets	PTK-870 [105]	16 : 8.98	5080/200	187 x 105 mm	235 x 165 x 8.7 mm	1.9:0.1:0.3[0.1:0.9:0]	215g	5 + Wheel	ACP-920	15mm (19mm)	360 [100]	N/A	N/A	260	128	Slight Hover Anti-chatter	Detachable USB-C to USB-A	ACP-920, ACP-921A, KP-504E, KP-501E, KP-505, KP-501E, KP-501A, KP-501E, KP-505E, KP-505E, KP-130, CP-921, CP-911, CP-202, LGT-1-2, 180 22-1, 1812 22-1	N/A
	PTK-470 [107]	16 : 9	5080/200	260 x 158 mm	291 x 200 x 7.7 mm	1.5:1:1.1[0.1:1.39:0]	411g	10 + 2 Wheels	ACP-920	15mm (19mm)	360 [100]	N/A	N/A	260	128	Slight Hover Anti-chatter	Detachable USB-C to USB-A	ACP-920, ACP-921A, KP-504E, KP-501E, KP-505, KP-501E, KP-501A, KP-501E, KP-505E, KP-505E, KP-130, CP-921, CP-911, CP-202, LGT-1-2, 180 22-1, 1812 22-1	N/A
	PTH-660 [108]	16 : 10	5080/200	216 x 135 mm	251 x 175 x 8.98 mm	2.3:1:1.5[0.1:1.82:0]	350g	0 + Wheel	ACP-920	15mm (19mm)	360 [100]	N/A	N/A	260	128	Slight Hover Anti-chatter	Detachable USB-C to USB-A	ACP-920, ACP-921A, KP-504E, KP-501E, KP-505, KP-501E, KP-501A, KP-501E, KP-505E, KP-505E, KP-130, CP-921, CP-911, CP-202, LGT-1-2, 180 22-1, 1812 22-1	N/A
	PTH-451 [109]	16 : 10	5080/200	159.5 x 99.75 mm	200 x 175.5 x 8 mm	2.8:0.1:0.8[0.1:1.5:1]	300g	7 + Wheel	EP-501E [110]	8mm (10mm)	200	???	100	200	128	Slight Hover Anti-chatter	Detachable USB-C to USB-A	KP-501E, KP-501E, KP-505, KP-501E, KP-501E, KP-505E, KP-505E, KP-130, EP-131	N/A
	PTH-660 [111]	16 : 10.97	5080/200	216 x 138 mm	336 x 219 x 8 mm	2.2:1:1.5[1.1:1.68:0]	750g	9 + Wheel	EP-501E [114]	???	200	???	100	100	128	Slight Hover Anti-chatter	Detachable USB-C to USB-A	KP-501E, KP-501E, KP-505, KP-501E, KP-501E, KP-505E, KP-505E, KP-130, EP-131	N/A
	PTH-860 [112]	16 : 11.1	5080/200	216 x 136 mm	350 x 230 x 9 mm	2.2:1:1.5[1.1:1.68:0]	1100g	9 + Wheel	EP-501E [116]	???	200	???	100	100	128	Slight Hover Anti-chatter	Detachable USB-C to USB-A	KP-501E, KP-501E, KP-505, KP-501E, KP-501E, KP-505E, KP-505E, KP-130, EP-131	N/A
	PTH-851 [117]	16 : 10	5080/200	157.48 x 98.43 mm	325.1 x 207.9 x 9 mm	2.9:1:1.5[0.1:1.56:1]	1100g	7 + Wheel	EP-501A [118]	???	200	???	100	???[119]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTH-651 [120]	16 : 10	5080/200	215.52 x 134.7 mm	379.9 x 251.4 x 11.5 mm	3.6:1:1.7[0.1:1.8:1]	990g	9 + Wheel	EP-501A [121]	???	200	???	100	???[122]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTH-851 [123]	16 : 10	5080/200	325.12 x 203.2 mm	487 x 317.7 x 12 mm	2.3:1:1.5:1:1[1.56:1]	1890g	9 + Wheel	EP-501A [124]	???	200	???	100	???[125]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTH-851 [126]	16 : 10	5080/200	157.48 x 98.43 mm	325 x 208.2 x 12.7 mm	4.1:1:2[0.9:1:2:1.5]	1890g	7 + Wheel	EP-501A [127]	???	200	???	100	???[128]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTK-650 [129]	16 : 10	5080/200	157.48 x 98.43 mm	320 x 208.2 x 12.7 mm	4.1:1:2[0.9:1:2:1.5]	1890g	7 + Wheel	EP-501A [130]	???	200	N/A	N/A	???[131]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTH-651 [132]	16 : 10	5080/200	215.52 x 134.7 mm	381 x 251.46 x 12.7 mm	3.7:1:1.7[0.1:1.8:1]	990g	9 + Wheel	EP-501A [133]	???	200	???	100	???[134]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTH-651 [135]	16 : 10	5080/200	215.52 x 134.7 mm	381 x 251.46 x 12.7 mm	3.7:1:1.7[0.1:1.8:1]	990g	9 + Wheel	EP-501A [136]	???	200	N/A	N/A	???[137]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTH-851 [138]	16 : 10	5080/200	325.12 x 203.2 mm	487.68 x 317.5 x 12.7 mm	2.3:1:1.5:1:1[1.56:1]	1840g	9 + Wheel	EP-501A [139]	???	200	???	100	???[140]	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	N/A
	PTK-640 [141]	16 : 10	5080/200	157.48 x 98.43 mm	339 x 208.2 x 16 mm	4.1:1:2[0.9:1:2:1.5]	750g	7 + Wheel	EP-501A [142]	19mm (19mm)	200	N/A	N/A	N/A	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	KC-100
	PTK-540WL [143]	16 : 10	5080/200	203.2 x 127 mm	364 x 230 x 16 mm	3.9:1:1.7[0.9:1:1.5]	900g	9 + Wheel	EP-501A [144]	???	200	N/A	N/A	200	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	KC-100
	PTK-540 [145]	16 : 10	5080/200	215.52 x 134.7 mm	370 x 216 x 12 mm	3.2:1:1.6[0.1:1.82:1]	1020g	9 + Wheel	EP-501A [146]	???	200	N/A	N/A	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	KC-100	N/A
	PTK-840 [147]	16 : 10	5080/200	325.12 x 203.2 mm	475 x 320 x 16 mm	2.3:1:1.6[0.1:1.57:1]	1600g	9 + Wheel	EP-501A [148]	???	200	N/A	N/A	128	None	Detachable Micro USB B to USB-A	KP-501E, KP-501E, KP-701E, KP-501E, KP-501E	KC-100, KC-210	N/A
	PTK-1160 [149]	16 : 10	5080/200	697.7 x 304.8 mm	623 x 662 x 28 mm	1.9:0.1:1.2[0.1:1.5:0.5]	1500g	9 + Wheel	EP-501A [150]	17mm (17mm)	200	N/A	N/A	128	None	Detachable Micro USB B to USB-A	KP-501E,

Pens

Consumer

Category	Model Identifier	Weight	Size	Max Pressure Levels (Approximate Physical Pressure Range ≈0.001-0.01%, 1%, 25%, 50%, 75%, 100%)	Pen Buttons	Pen Tip Travel (Eraser Travel)	Compatible Nibs (Old Versions)	Compatible Tablets
	CP-923 [258]	9.9g	149.9 x 9.8 mm	4096 (≈6gf, 18gf, 34gf, 56gf, 115gf, 291gf)	2	0.1mm	ACK2491IZ, ACK2491BZ, ACK2491SZ, ACK2450ZZ	PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	CP-913 [259]	11.1g	148.2 x 11.5 mm	4096 (≈6gf, 28gf, 45gf, 85gf, 151gf, 358gf)	1	0.1mm	ACK2491IZ, ACK2491BZ, ACK2491SZ, ACK2450ZZ	PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	CP-2020682 [260]	4.8g	140 x 7.73 mm	4096	0	???		PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	CP-2020ADA [261]	15g	143 x 14.2 mm	4096	0	???	ACK2460ZZ	PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	CP-2020ASUA [262]	15g	143 x 14.2 mm	4096	0	???	ACK2460ZZ	PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	L-ATI-2 [263]	15g	139 x 13 mm	4096	1	???	2101	PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	180 22-1 [264]	8.7g	175 x 7.5 mm	4096	0	???	18022 SN	PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	1802 22-1 [265]	30g	140 x 9.1 mm	4096	0	???	18022 SN	PTK-470, PTK-670, PTK-870, CTC-4110WL, CTC-6110WL
	LP-1300K [266]	11g	139 x 12 mm	4096 (≈≈1gf, <1gf, 18gf, 54gf, 108gf, 226gf)	2	1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [267]	CTL-4100L, CTL-4100WL, CTL-6100, CTL-6100WL
	LP-190K [268]	9g	138.8 x 11.5 mm	2048 (≈1gf, <1gf, 15gf, 61gf, 134gf, 320gf)	2	1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [268]	CTL-490, CTH-890, CTL-690, CTH-690, CTL-472, CTL-672
	LP-190 [270]	10g	138.8 x 11.5 mm	2048 (≈1gf, 8gf, 45gf, 118gf, 227gf, 485gf)	2	1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [270]	CTL-490, CTH-890, CTL-690, CTH-690, CTL-472, CTL-672
	LP-180	10.8 g	146.4 x 11.2 mm	1024 (≈1gf, <1gf, 14gf, 65gf, 134gf, 340gf)	2	1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [272]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-180E	12.1 g	151.2 x 11.2 mm	1024 (≈1gf, <1gf, 14gf, 65gf, 134gf, 340gf)	2 + Eraser	1mm (1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [273]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-171	13g	150 x 11.5 mm	1024 (≈1gf, <1gf, 16gf, 68gf, 206gf, 350gf)	2	1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [274]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-170	12g	150 x 11.5 mm	1024 (≈1gf, <1gf, 25gf, 113gf, 270gf, 525gf)	2	1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [275]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-170E	14g	151.6 x 11.5 mm	1024 (≈1gf, <1gf, 25gf, 113gf, 270gf, 525gf)	2 + Eraser	1mm (1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [276]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-161E [277]	15g	154 x 11.8 mm	1024 (≈1gf, <1gf, 26gf, 87gf, 175gf, 353gf)	2 + Eraser	1mm (1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [278]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-160 [279]	11g	149 x 11.8 mm	1024 (≈≈1gf, 10gf, 46gf, 110gf, 185gf, 396gf)	2	1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [280]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-160E [281]	15g	154 x 11.8 mm	1024 (≈≈1gf, 10gf, 46gf, 110gf, 185gf, 396gf)	2 + Eraser	1mm (1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [282]	CTL-480, CTH-880, CTL-680, CTH-680, CTL-471, CTL-671, CTL470, CTH-870, CTH-670, CTL-460, CTH-860, CTT-460, CTL-660, CTH-861, CTH-661
	LP-150 [283]	10g	148 x 12 mm	1024	2	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [284]	MTE-450, CTE-450, CTE-650, CTE-440, CTE-640, CTE-430, FB-630, CTE-630, CTE-630BT, ET-0570-U, ET-0465-U
	LP-150E [285]	12g	142.5 x 11.4 mm	512 (≈≈1gf, 5gf, 17gf, 69gf, 172gf, 341gf)	2 + Eraser	0.1mm (1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [286]	MTE-450, CTE-450, CTE-650, CTE-440, CTE-640, CTE-430, FB-630, CTE-630, CTE-630BT, ET-0465x-U, ET-0570-U, ET-0465-U
	LP-155E [287]	15g	152.5 x 12 mm	512	2 + Eraser	0.1mm (0.1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [288]	MTE-450, CTE-450, CTE-650, CTE-440, CTE-640, FB-630, CTE-630, CTE-630, CTE-630BT, ET-0465x-U, ET-0570-U, ET-0465-U
	LP-145E [289]	17g	157.8 x 12 mm	512	2 + Eraser	0.1mm (0.1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [290]	MTE-450, CTE-450, CTE-650, CTE-440, CTE-640, CTE-430, FB-630, CTE-630, CTE-630BT, ET-0465x-U, ET-0570-U, ET-0465-U
	FP-500 [291]	10g	142.5 x 11.4 mm	512	2	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [292]	CTF-430, CTF-221, CTF-420, FT-0320-U
	FP-410	12g	148 x 12.5 mm	512	2	2mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [293]	CTF-430, CTF-221, CTF-420, FT-0320-U
	EP-200 [294]	12g	151 x 12.5 mm	512	N/A	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [295]	FB-630, CTE-630, CTE-630, CTE-630BT, ET-0465A-U, ET-0570T-A-U, ET-0465-U
	EP-130E [296]	11g	145 x 12.5 mm	512	2 + Eraser	0.1mm (0.1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [297]	FB-630, CTE-430, CTE-630, CTE-630BT, ET-0465A-U, ET-0570T-A-U, ET-0465-U
	EP-130 [298]	11g	145 x 12.5 mm	512	2 + Eraser	0.1mm (0.1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [299]	FB-630, CTE-430, CTE-630, CTE-630BT, ET-0465A-U, ET-0570T-A-U, ET-0465-U
	FP-110	???	???	512	1	???	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [300]	CTF-430, CTF-221, CTF-420, FT-0320-U
	EP-100 [301]	10g	149 x 12.3 mm	512	2	2mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [302]	FT0405U
	EP-120E [303]	11g	145 x 12.5 mm	512	2 + Eraser	0.1mm (0.1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [304]	MTE-450, CTE-450, CTE-650, CTE-440, CTE-640, CTE-430, FB-630, CTE-630, CTE-630BT, ET-0465A-U, ET-0570-U, ET-0465-U
	EP-100E [305]	11g	145 x 12.5 mm	512	2 + Eraser	0.1mm (0.1mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [306]	MTE-450, CTE-450, CTE-650, CTE-440, CTE-640, CTE-430, FB-630, CTE-630, CTE-630BT, ET-0465A-U, ET-0570-U, ET-0465-U
	EP-812E	???	???	512	2 + Eraser	???	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [307]	FW-300
	LP-701K [308]	11.2g	140.5 x 11.4 mm	256	2 + Eraser	0.1mm (2mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [309]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A

Professional

Category	Model Identifier	Weight	Size	Max Pressure Levels (Approximate Physical Pressure Range ≈0.001-0.01%, 1%, 25%, 50%, 75%, 100%)	Pen Buttons	Pen Tip Travel (Eraser Travel)	Compatible Nibs (Old Versions)	Compatible Tablets
	ACP-501K	9.8g	160 x 8.6mm	8192	2 + Eraser	0.1mm? (???)	ACK-22211, ACK-22212, ACK-24831Z, ACK-24833Z, ACK2510102	PTK-470, PTK-670, PTK-870
	ACP-500 [w/ weight] [w/ grip]	[9.9g] [12.6g] [14.4g]	160 x 8.6mm	8192	3	0.1mm	ACK-22211, ACK-22212, ACK-24831Z, ACK-24833Z, ACK2510102	PTK-470, PTK-670, PTK-870
	KP-504E [311]	15g	157 x 15 mm	8192 (≈≈1gf, <1gf, 26gf, 85gf, 261gf, 794gf)	2 + Eraser	1mm? (1.5mm?)	ACK-22211, ACK-22212, ACK-24831Z, ACK-24833Z, ACK2510102	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860
	KP-501E [312]	12g	157 x 9.5 x10 mm	8192 (≈≈1gf, <1gf, 26gf, 79gf, 234gf, 751gf)	2 + Eraser	1mm? (1.5mm?)	ACK-22211, ACK-22212, ACK-24831Z, ACK-24833Z, ACK2510102	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860
	KP-505 [313]	15g	157 x 15 mm	8192	3	1mm?	ACK-22211, ACK-22212, ACK-24831Z, ACK-24833Z, ACK2510102	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860
	KP-132 [w/o cap] [314]	18g [15g]	145 x 11 mm [132.6 x 11mm]	8192	N/A	1mm?	ACK-22207, ACK-22208 [315]	PTH-660, PTH-860
	KP-137 [w/o cap] [316]	18g [15g]	145 x 11 mm [132.6 x 11mm]	8192	N/A	1mm?	ACK-22207, ACK-22208 [317]	PTH-660, PTH-860
	KP-501E [318]	17g	156.5 x 14.9 mm	2048 (≈≈1gf, <1gf, 5-20gf, 55-75gf, 114-210gf, 275-510gf)	2 + Eraser	1mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [319]	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860, PTH-660, PTH-860, PTH-651, PTH-651, PTH-851, PTH-651, PTH-650, PTK-650, PTK-650, PTH-850, PTK-660, PTK-640L, PTK-640, PTK-840, PTK-1260
	KP-501E [320]	17g	156.5 x 14.9 mm	2048 (≈≈1gf, <1gf, 5-20gf, 55-75gf, 114-210gf, 275-510gf)	2 + Eraser	0.2mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [321]	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860, PTH-660, PTH-860, PTH-651, PTH-651, PTH-851, PTH-651, PTH-650, PTK-650, PTK-650, PTH-850, PTK-660, PTK-640L, PTK-640, PTK-840, PTK-1260
	KP-501E [322]	16g	157 x 14.9 mm	2048 (≈≈1gf, <1gf, 5-18gf, 51-68gf, 114-208gf, 275-510gf)	2 + Eraser	1mm? (1.5mm?)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [323]	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860, PTH-660, PTH-860, PTH-651, PTH-651, PTH-851, PTH-651, PTH-650, PTK-650, PTK-650, PTH-850, PTK-660, PTK-640L, PTK-640, PTK-840, PTK-1260
	KP-400E [324]	23g	162.5 x 17.5 x 32.5 mm	2048	1 + Eraser + Wheel	0.2mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [325]	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860, PTH-660, PTH-860, PTH-651, PTH-651, PTH-851, PTH-651, PTH-650, PTK-650, PTK-650, PTH-850, PTK-660, PTK-640L, PTK-640, PTK-840, PTK-1260
	KP-130 [326]	12g	151 x 12.5 mm	2048	N/A	0.2mm	ACK-22207, ACK-22208 [327]	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860, PTH-660, PTH-860, PTH-651, PTH-651, PTH-851, PTH-651, PTH-650, PTK-650, PTK-650, PTH-850, PTK-660, PTK-640L, PTK-640, PTK-840, PTK-1260
	KP-701E [328]	20g	156.3 x 15.8 mm	2048	2 + Eraser + Rotation	1mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [329]	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860, PTH-660, PTH-860, PTH-651, PTH-651, PTH-851, PTH-651, PTH-650, PTK-650, PTK-650, PTH-850, PTK-660, PTK-640L, PTK-640, PTK-840, PTK-1260
	KP-300E [330]	12g	150.7 x 12.2 mm	2048	2 + Eraser	1mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W [331]	PTK-470, PTK-670, PTK-870, PTH-860, PTH-660, PTH-860, PTH-660, PTH-860, PTH-651, PTH-651, PTH-851, PTH-651, PTH-650, PTK-650, PTK-650, PTH-850, PTK-660, PTK-640L, PTK-640, PTK-840, PTK-1260
	ZP-501E [332]	17g	174.8 x 14.8 mm	1024 (≈≈1gf, <1gf, 30gf, 69gf, 160gf, 508gf)	2 + Eraser	0.2mm? (1.3mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W [333]	PT2-430, PT2-431W, PT2-630, PT2-631W, PT2-930, PT2-1230, PT2-1230W
	ZP-400E [334]	23.3g	162.5 x 17.5 x 32.5 mm	1024	2 + Eraser	0.2mm? (1.3mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W [335]	PT2-430, PT2-431W, PT2-630, PT2-631W, PT2-930, PT2-1230, PT2-1230W
	ZP-600 [336]	14g	146.7 x 15.5 x 12.5 mm	1024 (≈≈1gf, 10gf, 36gf, 103gf, 191gf, 383gf)	Rotation	0.2mm	(PS)-A051, PSI-A052]	PT2-430, PT2-431W, PT2-630, PT2-631W, PT2-930, PT2-1230, PT2-1230W
	ZP-130 [337]	12g	151.5 x 12.5 mm	1024	N/A	0.2mm	ACK-22207, ACK-22208 [338]	PT2-430, PT2-431W, PT2-630, PT2-631W, PT2-930, PT2-1230, PT2-1230W
	ZP-300E [339]	12g	150.7 x 12.2 mm	1024	2 + Eraser	0.1mm (1.3mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [340]	PT2-430, PT2-431W, PT2-630, PT2-631W, PT2-930, PT2-1230, PT2-1230W
	XP-501E [341]	17g	160 x 14 mm	1024 (≈≈1gf, <1gf, 28gf, 81gf, 215gf, 419gf)	2 + Eraser	0.1mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [342]	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0812-U, XD-0812-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	XP-501A [343]	19g	160 x 14 mm	1024	2	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [344]	
	XP-400E [345]	24g	162.5 x 32.6 mm	1024	1 + Eraser + Wheel	0.1mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [346]	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0812-U, XD-0812-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	XP-300E [347]	17g	151 x 12.2 mm	1024	2 + Eraser	0.1mm (1.5mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [348]	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0812-U, XD-0812-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	XP-110 [349]	12g	151 x 12.5 mm	1024	N/A	0.1mm	ACK-22207, ACK-22208 [350]	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0812-U, XD-0812-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	XP-120 [351]	12g	151 x 12.5 mm	1024	N/A	0.1mm	ACK-22207, ACK-22208 [352]	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0812-U, XD-0812-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	GP-300E [353]	13g	151 x 12.2 mm	1024 (≈≈1gf, <1gf, 6gf, 10gf, 20gf, 362gf)	2 + Eraser	0.1mm (1.3mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [354]	GD-0405-U, GD-0405-R, GD-0405-A, GD-0608-U, GD-0608-R, GD-0608-A, GD-0812-U, GD-0812-R, GD-0812-A, GD-1212-U, GD-1212-R, GD-1218-U, GD-1218-R
	GP-400E [355]	24g	162.5 x 17.5 x 32.6 mm	1024	1 + Eraser + Wheel	0.1mm (1.3mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [356]	GD-0405-U, GD-0405-R, GD-0405-A, GD-0608-U, GD-0608-R, GD-0608-A, GD-0812-U, GD-0812-R, GD-0812-A, GD-1212-U, GD-1212-R, GD-1218-U, GD-1218-R
	GP-110 [357]	12g	151 x 12.5 mm	1024	N/A	0.1mm	ACK-22207, ACK-22208 [358]	GD-0405-U, GD-0405-R, GD-0405-A, GD-0608-U, GD-0608-R, GD-0608-A, GD-0812-U, GD-0812-R, GD-0812-A, GD-1212-U, GD-1212-R, GD-1218-U, GD-1218-R
	GP-120 [359]	12g	151 x 12.5 mm	1024	N/A	0.1mm	ACK-22207, ACK-22208 [360]	GD-0405-U, GD-0405-R, GD-0405-A, GD-0608-U, GD-0608-R, GD-0608-A, GD-0812-U, GD-0812-R, GD-0812-A, GD-1212-U, GD-1212-R, GD-1218-U, GD-1218-R
	LP-801	8g	140 x 9 mm	256	2	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [361]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-801E [362]	9g	140.5 x 9 mm	256 (≈≈3gf, 20gf, 68gf, 114gf, 208gf, 414gf)	2 + Eraser	0.1mm (2mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [363]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-811E	9g	140.5 x 9 mm	256	2 + Eraser	0.1mm (2mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [364]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-241 [365]	8g	140 x 9 mm	256	1	???	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [366]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-421 [367]	11g	148 x 11.4 mm	256	1	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [368]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-501 [369]	11g	148 x 11.4 mm	256	1	0.1mm	0.5mm Pencil Lead	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-201	8g	140 x 9 mm	256	2	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [370]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-911E [371]	16g	159 x 14 mm	512 (≈≈20-36gf, 20-36gf, 31-51gf, 54-88gf, 90-150gf, 191-318gf)	2 + Eraser	0.1mm (2mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [372]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-817E [373]	12g	147.5 x 12.5 mm	512	2	0.2mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [374]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-813E [375]	12g	140.5 x 11.4 mm	512	2 + Eraser	0.1mm (2mm)	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [376]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-714W [377]	8g	140.5 x 9 mm	512	1	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [378]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-211 [379]	8g	140.5 x 9 mm	256	1	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [380]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	LP-401 [381]	11g	148 x 11.4 mm	256	1	0.1mm	ACK-20001, ACK-20003, ACK-20004, ACK-20002, ACK-20401W, ACK-2006L, ACK-20005 [382]	KT-0405-R, KT-0608-R, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, KT-0405-R, KT-0405-A, KT-0405-R, KT-0405-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R, CT-0405-U, CT-0405-R, CT-0405-A
	SP-200 [383]	11g	148 x 11 mm	2	1	0.2mm	(PLD-1, PLD-2R, PLD-28L, PLD-28K, PLD-3)	SD-510C, SD-420E, SD-421L, SD-422L, SD-320L, SD-321L, SD-322L, SD-310L, SD-311L, SD-312L, SD-210L, SD-013A
	SP-210 [384]	11g	148 x 11 mm	2	1	0.9mm	(PLD-1, PLD-2R, PLD-28L, PLD-28K, PLD-3]	SD-510C, SD-420E, SD-421L, SD-422L, SD-320L, SD-321L, SD-322L, SD-310L, SD-311L, SD-312L, SD-210L, SD-013A
	SP-350A [385]	8.4g	142.5 x 11 mm	2	1	1.2mm	(PLD-4)	SD-510C, SD-420E, SD-421L, SD-422L, SD-320L, SD-321L, SD-322L, SD-310L, SD-311L, SD-312L, SD-210L, SD-013A
	SP-250A [386]	8.4g	142.5 x 11 mm	2	1	1.2mm	(PLD-4)	SD-510C, SD-420E, SD-421L, SD-422L, SD-320L, SD-321L, SD-322L, SD-310L, SD-311L, SD-312L, SD-210L, SD-013A
	SP-300 [387]	11g or 18g	148 x 11 mm	64	0	0.2mm	(PLD-4)	SD-510C, SD-420E, SD-421L, SD-422L, SD-320L, SD-321L, SD-322L, SD-310L, SD-311L, SD-312L, SD-210L, SD-013A
	SP-310 [388]	11g or 18g	148 x 11 mm	64	0	0.9mm	(PLD-4)	SD-510C, SD-420E, SD-421L, SD-422L, SD-320L, SD-321L, SD-322L, SD-310L, SD-311L, SD-312L, SD-210L, SD-013A

Mice

Category	Model Identifier	Weight	Size	Mouse Buttons	Button Travel	Scroll Wheel Type	Compatible Tablets
Mice	EC-155 [389]	90g	105 x 66.7 x 37.6 mm	3	???	Rotation, 24 steps per revolution	CTE-450, CTE-650
	EC-140 [390]	90g	106.2 x 62.3 x 37.4 mm	3	???	Rotation, 24 steps per revolution	CTE-440, CTE-640
	EC-130 [391]	90g	115 x 60 x 38 mm	3	???	Rotation, 24 steps per revolution	CTE-430, CTE-630BT, CTE-630
	EC-120 [392]	90g	116 x 58 x 37 mm	3	???	Rotation, 24 steps per revolution	ET-0405A-U, ET-0507A-U
	EC-100 [w/o weight] [	90g [65g]	125 x 65 x 39 mm	3	???	Rotation, 24 steps per revolution	ET-0405-U, ET-0405-R
	KC-100 [w/o weight] [	83g [58g]	102.9 x 61.8 x 38.6 mm	5	1.3mm	Rotation, 24 steps per revolution	PTK-440, PTK-540WL, PTK-640, PTK-840, PTK-1240
	KC-210 [395]	75g	159 x 66 x 33.8 mm	5	1.3mm	N/A	PTK-840, PTK-1240
	ZC-100 [w/o weight] [	105g [70g]	112.0 x 58.0 x 38.0 mm	5	1mm	Rotation, 24 steps per revolution	PTZ-430, PTZ-431W, PTZ-630, PTZ-631W, PTZ-930, PTZ-1230, PTZ-1231W
	ZC-210 [397]	75g	159 x 66 x 33 mm	5	1mm	N/A	PTZ-1230, PTZ-1231W
	XC-100 [398]	100g	117.2 x 68.2 x 40.3 mm	3	1mm?	Rotation, 24 steps per revolution	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0912-U, XD-0912-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	XC-400 [w/o weight] [	105g [88g]	120.0 x 71.0 x 35.4 mm	5	1mm	Rotation, ???	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0912-U, XD-0912-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	XC-210 [400]	75g	159 x 66 x 33 mm	5	1mm	N/A	XD-0405-U, XD-0405-R, XD-0608-U, XD-0608-R, XD-0912-U, XD-0912-R, XD-1212-U, XD-1212-R, XD-1218-U, XD-1218-R
	GC-500 [401]	75g	113 x 72.6 x 38.5 mm	5 + Thumbwheel	1mm	N/A	GD-0405-U, GD-0405-R, GD-0405-A, GD-0608-U, GD-0608-R, GD-0608-A, GD-0912-U, GD-0912-R, GD-0912-A, GD-1212-U, GD-1212-R, GD-1218-U, GD-1218-R
	GC-210 [402]	72g	158.9 x 66.1 x 33 mm	5	1mm	N/A	GD-0405-U, GD-0405-R, GD-0405-A, GD-0608-U, GD-0608-R, GD-0608-A, GD-0912-U, GD-0912-R, GD-0912-A, GD-1212-U, GD-1212-R, GD-1218-U, GD-1218-R
	UC-520 [403]	???	???	4	???	???	UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R,UD-1218-A, UD-0608-R, UD-0608-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R
	UC-620 [404]	???	???	16	???	???	UD-1212-R, UD-1212-A, UD-1218-R, UD-1218-A, UD-1212-R, UD-1212-A, UD-1218-R, UD-1825-R
	SC-100 [405]	45g	55 x 118 x 21 mm	4	???	N/A	SD-420E, SD-421E, SD-422E, SD-320E, SD-321E, SD-322E, SD-310E, SD-311E, SD-312E, SD-210L
	SC-510 [406]	45g	55 x 118 x 21 mm	4	???	N/A	SD-510C
	SC-410 [407]	55g	62 x 130 x 24 mm	4	???	N/A	SD-013A, SD-013L
	SC-610 [408]	85g	62 x 130 x 24 mm	16	???	N/A	SD-013A, SD-013L

Kuuube's Info

Tablet Sheets and Guides

Kuuube's Tablet Buying Guide

Kuuube's Wacom Tablet Mastersheet

Kuuube's Wacom Tablet Pen Compatibility Mastersheet

Kuuube's Wacom Pen Nib Guide

Kuuube's Wacom Pen Nib Compatibility Mastersheet

Info

The quickest way to contact me is to join my discord. I may take awhile to reply elsewhere.

osu! Profile

Discord Server

Github

Youtube

Ko-fi

Business Inquiries Email (**DO NOT send me tablet sponsorship offers**)

Sources

Not all sources are directly listed. Some information may be found in links or media contained in the pages below.

https://support.wacom.com/hc/ja/articles/5444635267479-Hi-uni-DIGITAL-for-Wacom%E3%81%A8Wacom-One-Pen%E3%81%AE%E9%81%95%E3%81%84%E3%81%AB%E3%81%A4%E3%81%84%E3%81%A6
https://estore.wacom.jp/ja-JP/products/accessories/acp501e00dz.html
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq21ux-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq-software-users-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq20wsx-user-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq18sx-user-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq15x-user-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq12wx-usermanual-final.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-capture-users-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/intuos5-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-pen-bamboo-touch-bamboo-fun.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-user-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-fun-users-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/intuos3-users-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire4-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire3-users-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/intuos2-users-manual-win.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire2-users-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/intuos-users-manual-mac.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/intuos-users-manual-win.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphiremanual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphireusersmanual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire-bluetooth-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/penpartner-usb-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/penpartner.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/dth2242-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/dtk2241-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/dtu710-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/dtf720-manual.pdf
https://wcm-cdn.wacom.com/events/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/dtf521-manual.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-tablets/intuosprosml-2021updated/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/intuos3-users-manual.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-tablets/wacomintuos-2021/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-tablets/wacom-intuos-2015-ipi/ipi-en.pdf
https://cdn.wacom.com/f/ipi/0x0302/IPI-EN.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-tablets/onebywacom-2021/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-capture-users-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-warranties/bamboo-warranty.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-pen-bamboo-touch-bamboo-fun.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-user-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/bamboo-fun-users-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire4-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire3-users-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire-bluetooth-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphire2-users-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/graphiremanual.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-tablets/wacomintuospro-2021/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-warranties/intuos-pro-2017/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-warranties/intuos5-warranty.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/intuos5-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-warranties/intuos4-warranty.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/intuos4-wireless-users-manualkr.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/intuos4-users-manualkr.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-displays/wcp27/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-displays/wacomone-ipi-2021/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-displays/cintiq22-ipi-2021latest/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-displays/wacom-cintiq-pro-24-32ipi-2021/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-warranties/cintiq-pro/ipi-en.pdf
https://wcm-cdn.wacom.com/-/media/files/downloads/product-support/ipis/pen-computers/mobile-studio-pro/2020/ipi-en.pdf
https://cdn.wacom.com/f/ipi/0x0325/IPI-EN.pdf
https://cdn.wacom.com/f/ipi/0x032B/IPI-EN.pdf
https://cdn.wacom.com/f/ipi/0x032A/IPI-EN.pdf
https://cdn.wacom.com/f/ipi/0x0304/IPI-EN.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-warranties/cintiq-companion-warranty.pdf
https://cdn.wacom.com/f/ipi/0x005B/IPI-EN.pdf
https://cdn.wacom.com/f/ipi/0x00F8/IPI-EN.pdf
https://cdn.wacom.com/f/ipi/0x00FA/IPI-EN.pdf
https://cdn.wacom.com/f/ipi/0x00F4/IPI-EN.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-warranties/pen-display-tablet-warranty.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq-software-users-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq12wx-usermanual-final.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq21ux-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq15x-user-manual.pdf
https://wcm-cdn.wacom.com/-/media/graveyard/wacomdotcom/files/store-manuals/legacy-models/cintiq18sx-user-manual.pdf
https://www.manualslib.com/manual/378157/Wacom-Sd-013a.html
https://www.manualslib.com/products/Wacom-Sd-210l-719853.html

https://www.manualslib.com/products/Wacom-Sd-310e-719843.html			
https://www.manualslib.com/products/Wacom-Sd-311e-719844.html			
https://www.manualslib.com/products/Wacom-Sd-312e-719851.html			
https://www.manualslib.com/products/Wacom-Sd-320e-719845.html			
https://www.manualslib.com/products/Wacom-Sd-321e-719846.html			
https://www.manualslib.com/products/Wacom-Sd-322e-719847.html			
https://www.manualslib.com/products/Wacom-Sd-420e-719848.html			
https://www.manualslib.com/products/Wacom-Sd-421e-719849.html			
https://www.manualslib.com/products/Wacom-Sd-422e-719850.html			
https://www.manualslib.com/products/Wacom-Ctf-221-K-9366610.html			
https://www.manualslib.com/products/Wacom-Cte-660-8828808.html			
https://www.manualslib.com/products/Wacom-Cte-460-8828807.html			
https://www.manualslib.com/products/Wacom-Ct-0405-U-9366374.html			
https://www.manualslib.com/products/Wacom-Bamboo-Fun-Cth-461-12708124.html			
https://www.manualslib.com/products/Wacom-Bamboo-Fun-Cth-661-12708125.html			
https://fccid.io/HV4CTL4100WLA			
https://fccid.io/HV4CTL6100WLA			
https://fccid.io/HV4CTL6100WL			
https://fccid.io/HV4CTL4100WL			
https://fccid.io/HV4CTL6100			
https://fccid.io/HV4CTL4100			
https://fccid.io/HV4CTL672			
https://fccid.io/HV4CTL472			
https://fccid.io/HV4CTL671			
https://fccid.io/HV4CTL471			
https://fccid.io/HV4CTH690			
https://fccid.io/HV4CTH490			
https://fccid.io/HV4CTH301			
https://fccid.io/HV4CTH300			
https://fccid.io/HV4CTH680			
https://fccid.io/HV4CTH480			
https://fccid.io/HV4CTH670			
https://fccid.io/HV4CTE660			
https://fccid.io/HV4CTL-660			
https://fccid.io/HV4CT0405U			
https://fccid.io/HV4DTU1141BA			
https://fccid.io/HV4DTC121			
https://fccid.io/HV4DTH271			
https://fccid.io/HV4DTH134			
https://fccid.io/HV4DTH167			
https://fccid.io/HV4DTC133			
https://fccid.io/HV4DTHW1321			
https://fccid.io/HV4DTU1031AX			
https://fccid.io/HV4DTK2260			
https://fccid.io/HV4DTHW1621			
https://fccid.io/HV4DTK1660			
https://fccid.io/HV4DTH2420			
https://fccid.io/HV4DTH3220			
https://fccid.io/HV4DTK2451			
https://fccid.io/HV4DTH2452			
https://fccid.io/HV4DTH1152			
https://fccid.io/HV4DTU1141B			
https://fccid.io/HV4DTH1620			
https://fccid.io/HV4DTH1320			
https://fccid.io/HV4DTHW1620			
https://fccid.io/HV4DTHW1320			
https://fccid.io/HV4DTK1651			
https://fccid.io/HV4DTU1141			
https://fccid.io/HV4DTK1301			
https://fccid.io/HV4DTH1300			
https://fccid.io/HV4DTK2700			
https://fccid.io/HV4DTH2700			
https://fccid.io/HV4DTHW1310			
https://fccid.io/HV4DTU1031X			
https://fccid.io/HV4DTU1031			
https://fccid.io/HV4DTHW1300			
https://fccid.io/HV4DTHA1300			
https://fccid.io/HV4DTK2241			
https://fccid.io/HV4DTH2242			
https://fccid.io/HV4DTH2200			
https://fccid.io/HV4DTK1300			
https://fccid.io/HV4DTK2200			
https://fccid.io/HV4DTH2400			
https://fccid.io/HV4DTK2400			
https://fccid.io/HV4DTU2235B			
https://fccid.io/HV4DTF720C			
https://fccid.io/HV4DTU1631			
https://fccid.io/HV4DTK2100			
https://fccid.io/HV4DTU2231A			
https://fccid.io/HV4DTU2231			
https://fccid.io/HV4DTF720A			
https://fccid.io/HV4DTU1931			
https://fccid.io/HV4DTZ2000W			

https://fccid.io/HV4DTF521			
https://fccid.io/HV4DTF720			
https://fccid.io/HV4DTI520			
https://fccid.io/HV4DTU710			
https://fccid.io/HV4PTH460			
https://fccid.io/HV4PTH860			
https://fccid.io/HV4PTH660			
https://fccid.io/HV4PTH851			
https://fccid.io/HV4PTH651			
https://fccid.io/HV4PTH451			
https://fccid.io/HV4PTH850			
https://fccid.io/HV4PTH650			
https://fccid.io/HV4PTH450			
https://fccid.io/HV4PTKW			
https://fccid.io/HV4PTKL			
https://fccid.io/HV4PTK			
https://fccid.io/HV4PTZ			
https://fccid.io/HV4PTZL			
https://fccid.io/HV4PTU600			
https://fccid.io/HV4PL700			
https://fccid.io/HV4PL800			
https://fccid.io/HV4PL550			
https://fccid.io/HV4PL-500			
https://fccid.io/HV4PL500			
https://fccid.io/HV4PL400			
https://fccid.io/HV4PL300			
https://fccid.io/HV4PL100V1			
https://fccid.io/HV4PL100V			
https://fccid.io/HV4GD1212U			
https://fccid.io/HV4GD0608U			
https://fccid.io/HV4GD1218U			
https://fccid.io/HV4GD0912U			
https://fccid.io/HV4GD0405U			
https://fccid.io/HV4GD0912A			
https://fccid.io/HV4GD0405A			
https://fccid.io/HV4GD0608A			
https://fccid.io/HV4GD1212R			
https://fccid.io/HV4GD1218R			
https://fccid.io/HV4GD0912R			
https://fccid.io/HV4GD0608R			
https://fccid.io/HV4GD0405R			
https://fccid.io/HV4FT0405U			
https://fccid.io/HV4XD			
https://fccid.io/HV4SD210L			
https://fccid.io/HV4SD311E			
https://fccid.io/HV4SD322E			
https://fccid.io/HV4SD321E			
https://fccid.io/HV4SD312E			
https://fccid.io/HV4SD421E			
https://fccid.io/HV4SD422E			
https://fccid.io/HV4SD510C			
https://fccid.io/HV4SD113L			
https://fccid.io/HV4SD013L			
https://fccid.io/HV4SD312L			
https://fccid.io/HV4SD311L			
https://fccid.io/HV4SD510B			
https://fccid.io/HV4SD422A			
https://fccid.io/HV4SD321A			
https://fccid.io/HV4SD421A			
https://fccid.io/HV4SD322A			
https://fccid.io/HV4UD1825R			
https://fccid.io/HV4UD1218RE			
https://fccid.io/HV4UD1218R			
https://fccid.io/HV4UD1212R			
https://fccid.io/HV4UD0608R			
https://fccid.io/HV4UD0608A			
https://fccid.io/HV4UD1515R			
https://fccid.io/HV4WKT400			
https://fccid.io/HV4KT0405RNB23			
https://fccid.io/HV4KT0405R			
https://fccid.io/HV4KT0405A			
http://lowtech-city.org/blog/index.php?e=189			
http://lowtech-city.org/blog/index.php?e=188			
http://lowtech-city.org/blog/index.php?e=187			
http://lowtech-city.org/blog/index.php?e=186			
http://lowtech-city.org/blog/index.php?e=185			
https://web.archive.org/web/19970710015016/http://www.wacom.co.jp/tablet/ArtPad2.html			
https://web.archive.org/web/19970710015016/http://www.wacom.co.jp/tablet/ArtPad2pro.html			
https://web.archive.org/web/19970710015016/http://www.wacom.co.jp/tablet/UD2.html			
https://web.archive.org/web/19970710015016/http://www.wacom.co.jp/tablet/prepio.html			
https://web.archive.org/web/19970710015016/http://www.wacom.co.jp/tablet/pl250.html			
https://web.archive.org/web/19970710015016/http://www.wacom.co.jp/tablet/pl300.html			
https://web.archive.org/web/19970710015016/http://www.wacom.co.jp/tablet/pens.html			

https://web.archive.org/web/20010205040300/http://tablet.wacom.co.jp/products/ud/top.html			
https://web.archive.org/web/20010205021100/http://tablet.wacom.co.jp/products/artpadfun/top.html			
https://web.archive.org/web/20001215051200/http://tablet.wacom.co.jp/products/pl/pl_index.html			
https://web.archive.org/web/20010409192903/http://tablet.wacom.co.jp/products/favo/open.html			
https://web.archive.org/web/20010204061900/http://tablet.wacom.co.jp/products/intuos/intuos_index.html			
https://web.archive.org/web/20031003002009/http://tablet.wacom.co.jp/products/intuos2/hardware_top.html			
https://web.archive.org/web/20031001235545/http://tablet.wacom.co.jp/products/cintiq/index.html			
https://web.archive.org/web/20030807113820/http://tablet.wacom.co.jp/products/favo2/index.html			

[1] (Wacom One S)

[2] Wacom One Standard Pen

[3] (Wacom One M)

[4] Wacom One Standard Pen

[5] (Intuos S) (Wacom Intuos, Pen Only Small)

[6] (Wacom Pen 4K)

[7] (Intuos BT S) (Wacom Intuos, Pen & Bluetooth Small)

[8] (Wacom Pen 4K)

[9] (Intuos M) (Wacom Intuos, Pen Only Medium)

[10] (Wacom Pen 4K)

[11] (Intuos BT M) (Wacom Intuos, Pen & Bluetooth Medium)

[12] (Wacom Pen 4K)

[13] (Intuos Draw Small) (Intuos Small)

[14] (Wacom Pen 2K)

[15] (Intuos Art Small) (Intuos Photo Small) (Intuos Comic Small) (Intuos Touch Small)

[16] (Wacom Pen 2K)

[17] Wireless kit required

[18] (Intuos Draw Medium) (Intuos Medium)

[19] (Wacom Pen 2K)

[20] (Intuos Art Medium) (Intuos Touch Medium)

[21] (Wacom Pen 2K)

[22] Wireless kit required

[23] (Intuos Pen (S)) (Intuos Small) (Intuos Creative Pen Tablet - Small)

[24] (Intuos Pen & Touch (S)) (Intuos Touch Small) (Intuos Creative Pen & Touch Tablet - Small)

[25] Wireless kit required

[26] (Intuos Pen & Touch (M)) (Intuos Medium)

[27] (Intuos Pen (M)) (Intuos Touch Medium) (Intuos Creative Pen & Touch Tablet - Medium)

[28] Wireless kit required

[29] (One by Wacom (S)) (One by Wacom small) (One by Wacom pen tablet)

[30] (Wacom Pen 2K)

[31] (One by Wacom (M)) (One by Wacom medium) (One by Wacom pen tablet)

[32] (Wacom Pen 2K)

[33] (Bamboo Splash) (One by Wacom (S))

[34] (One by Wacom (M))

[35] (Bamboo Connect) (Bamboo Pen Tablet)

[36] (Bamboo Capture) (Bamboo Manga) (Bamboo Comic)

[37] Wireless kit required

[38] (Bamboo Create) (Bamboo Fun) (Bamboo Comic)

[39] Wireless kit required

[40] (Bamboo One Pen (S)) (Bamboo One, Small Tablet)

[41] (Bamboo One Pen)

[42] (Bamboo One Pen (M)) (Bamboo One, Medium Tablet)

[43] (Bamboo One Pen)

[44] (Bamboo Fun (S)) (Bamboo Craft (S)) (Bamboo Comic Pen & Touch (S)) (Bamboo Pen & Touch Special Edition (S)) (Bamboo Fun Small Tablet) (Bamboo Fun Pen & Touch) (Bamboo Comic Pen & Touch) (Bamboo Tablet)

[45] (Bamboo Fun CTH Pen)

[46] (Bamboo Fun (M)) (Bamboo Comic Pen & Touch (M)) (Bamboo Pen & Touch Special Edition (M)) (Bamboo Fun Medium Tablet) (Bamboo Tablet)

[47] (Bamboo Fun CTH Pen)

[48] (Bamboo Pen (S)) (Bamboo Pen Tablet)

[49] (Bamboo CTL Pen)

[50] (Bamboo Pen & Touch) (Bamboo Pen & Touch) (Bamboo Tablet)

[51] (Bamboo CTH Pen)

[52] (Bamboo Touch) (Bamboo Touch Tablet) [no emr digitizer]

[53] (Bamboo Pen (M)) (Bamboo Pen Tablet)

[54] (Bamboo) (Bamboo Tablet)

[55] (Bamboo Pen)

[56] (Bamboo Fun (4x5)) (Small Bamboo Fun Tablet)

[57] (Bamboo Fun Pen)

[58] (Bamboo Fun (6x8)) (Medium Bamboo Fun Tablet)

[59] (Bamboo Fun Pen)

[60] (Wacom FAVO Wireless FW-300USB)

[61] (Graphire4 (4x5))

[62] (Graphire4 Pen)

[63] (Graphire4 (6x8))

[64] (Graphire4 Pen)

[65] (Bamboo Pad USB model, Bamboo Pad Light)

[66] (Bamboo Pad wireless model)

[67] (Graphire3 Pen)

[68] (Graphire3 (4x5)) (Graphire3 4x5 / A6 Tablet) (F-430)

[69] (Graphire3 Pen)

[70] (Graphire Bluetooth Pen Tablet)

[71] (Graphire Pen)

[72] (Graphire3 (6x8)) (Graphire3 6x8 / A5 Tablet) (F-630)

[73] (Graphire3 Pen)

[74] (Bamboo One) (Bamboo One Tablet)

[75] (PenPartner2)

[76] (Volito 2 A6)

[77] (Volito) (PenPartner) (PenStation (2x3))

[78] (Volito) (PenPartner) (PenStation (4x5)) (LLC Tablet)

[79] (LLC Pen)

[80] (Graphire2 (4x5)) (Graphire2 Tablet) (Graphire2 USB Tablet) (F-410)

[81] (Graphire2 Pen)

[82] (Graphire2 (5x7)) (F-510)

[83] (Graphire) (Graphire Tablet) (F-401U) (Wacom FAVO USB)

[84] (Graphire Pen)

[85] (Graphire) (Graphire Tablet)

[86] (Graphire Pen)

[87] (ARTPAD FAN) (PenParter Tablet)

[88] (PenPartner Pen) (UltraPen)

[89] (ARTPAD FAN) (PenParter Tablet)

[90] (PenPartner Pen) (UltraPen)

[91] (ARTPAD FAN) (PenParter Tablet)

[92] (PenPartner Pen) (UltraPen)

[93] (ART Z)

[94] (UltraPen Eraser) (Erasing UltraPen)

[95] (ART Z II)

[96] (UltraPen Eraser) (Erasing UltraPen)

[97] (ARTPAD II Serial) (ArtPad II A6 Serial)

[98] (UltraPen Eraser) (Erasing UltraPen)

[99] (ARTPAD II ADB) (ArtPad II A6 ADB)

[100] (UltraPen Eraser) (Erasing UltraPen)

[101] (ARTPAD)

[102] (UltraPen Eraser) (Erasing UltraPen)

[103] (ARTPAD)

[104] (UltraPen Eraser) (Erasing UltraPen)

[105] (Intuos Pro 2025 Small)

[106] Some pens lower report rate to around 200-240hz

[107] (Intuos Pro 2025 Medium)

[108] Some pens lower report rate to around 200-240hz

[109] (Intuos Pro 2025 Large)

[110] Some pens lower report rate to around 200-240hz

[111] (Intuos Pro Small) (Wacom Intuos Pro)

[112] (Wacom Pro Pen 2)

[113] (Intuos Pro Medium) (Wacom Intuos Pro)

[114] (Wacom Pro Pen 2)

[115] (Intuos Pro Large) (Wacom Intuos Pro)

[116] (Wacom Pro Pen 2)

[117] (Intuos pro (S)) (Intuos Pro Professional Pen & Touch Tablet - Small) (Intuos Pro Touch S Tablet) (Intuos Pro Small)

[118] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[119] Wireless kit required

[120] (Intuos pro (M)) (Intuos Pro Professional Pen & Touch Tablet - Medium) (Intuos Pro Touch M Tablet) (Intuos Pro Medium) (Intuos Pro Medium Special Edition)

[121] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[122] Wireless kit required

[123] (Intuos pro (L)) (Intuos Pro Professional Pen & Touch Tablet - Large) (Intuos Pro Touch L Tablet) (Intuos Pro Large)

[124] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[125] Wireless kit required

[126] (Intuos5 touch (S)) (Wacom Intuos5 Touch (Small))

[127] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[128] Wireless kit required

[129] (Intuos5 (S)) (Wacom Intuos5 (Small))

[130] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[131] Wireless kit required

[132] (Intuos5 touch (M)) (Wacom Intuos5 Touch (Medium))

[133] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[134] Wireless kit required

[135] (Intuos5 (M)) (Wacom Intuos5 (Medium))

[136] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[137] Wireless kit required

[138] (Intuos5 touch (L)) (Wacom Intuos5 Touch (Large))

[139] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[140] Wireless kit required

[141] (Intuos4 (4x6)) (Intuos4 S Tablet) (Intuos4 Small) (Intuos4 Special Edition) (Intuos 4 Comic Edition)

[142] (Intuos4 Grip Pen)

[143] (Intuos4 Wireless) (Intuos4 Wireless Tablet)

[144] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[145] (Intuos4 (6x9)) (Intuos4 M Tablet) (Intuos4 Medium) (Intuos4 Special Edition) (Intuos 4 Comic Edition)

[146] (Intuos4 Grip Pen)

[147] (Intuos4 (8x13)) (Intuos4 L Tablet) (Intuos4 Large)

[148] (Intuos4 Grip Pen)

[149] (Intuos4 (12x19)) (Intuos4 XL Tablet) (Intuos4 Extra Large)

[150] (Intuos4 Grip Pen)

[151] (Intuos3 (4x5)) (Intuos3 4x5 / A6 Tablet)

[152] (Intuos3 Grip Pen)

[153] (Intuos3 (4x6)) (Intuos3 4x6 / A6 Wide Tablet)

[154] (Intuos3 Grip Pen)

[155] (Intuos3 (6x8)) (Intuos3 6x8 / A5 Tablet)

[156] (Intuos3 Grip Pen)

[157] (Intuos3 (6x11)) (Intuos3 6x11 / A5 Wide Tablet)

[158] (Intuos3 Grip Pen)

[159] (Intuos3 (9x12)) (Intuos3 9x12 / A4-Regular Tablet)

[160] (Intuos3 Grip Pen)

[161] (Intuos3 (12x12)) (Intuos3 12x12 / A4 Oversize Tablet)

[162] (Intuos3 Grip Pen)

[163] (Intuos3 (12x19)) (Intuos3 12x19 / A3 Wide Tablet)

[164] (Intuos3 Grip Pen)

[165] Cintiq Partner

[166] (Intuos2 (4x5)) (Intuos2 4x5 / A6 Tablet) (I-420USB)

[167] (Intuos2 Grip Pen)

[168] (Intuos2 (4x5)) (Intuos2 4x5 / A6 Tablet) (I-420Serial)

[169] (Intuos2 Grip Pen)

[170] (Intuos2 (6x8)) (Intuos2 6x8 / A5 Tablet) (I-620USB)

[171] (Intuos2 Grip Pen)

[172] (Intuos2 (6x8)) (Intuos2 6x8 / A5 Tablet) (I-620Serial)

[173] (Intuos2 Grip Pen)

[174] (Intuos2 (9x12)) (Intuos2 9x12 / A4-Regular Tablet) (I-920USB)

[175] (Intuos2 Grip Pen)

[176] (Intuos2 (9x12)) (Intuos2 9x12 / A4-Regular Tablet) (I-920Serial)

[177] (Intuos2 Grip Pen)

[178] (Intuos2 (12x12)) (Intuos2 12x12 / A4-Oversize Tablet) (I-1220USB)

[179] (Intuos2 Grip Pen)

[180] (Intuos2 (12x12)) (Intuos2 12x12 / A4-Oversize Tablet) (I-1220Serial)

[181] (Intuos2 Grip Pen)

[182] (Intuos2 (12x18)) (Intuos2 12x18 / A3 Tablet) (I-1820USB)

[183] (Intuos2 Grip Pen)

[184] (Intuos2 (12x18)) (Intuos2 12x18 / A3 Tablet) (I-1820Serial)

[185] (Intuos2 Grip Pen)

[186] (Intuos (4x5)) (Intuos 4x5 Tablet) (I-400USB)

[187] (Intuos Pen)

[188] (Intuos (4x5)) (Intuos 4x5 Tablet) (I-400Serial)

[189] (Intuos Pen)

[190] (Intuos (4x5)) (Intuos 4x5 Tablet) (I-400ADB)

[191] (Intuos Pen)

[192] (Intuos (6x8)) (Intuos 6x8 Tablet) (I-600USB)

[193] (Intuos Pen)

[194] (Intuos (6x8)) (Intuos 6x8 Tablet) (I-600Serial)

[195] (Intuos Pen)

[196] (Intuos (6x8)) (Intuos 6x8 Tablet) (I-600ADB)

[197] (Intuos Pen)

[198] (Intuos (9x12)) (Intuos 9x12 Tablet) (I-900USB)

[199] (Intuos Pen)

[200] (Intuos (9x12)) (Intuos 9x12 Tablet) (I-900Serial)

[201] (Intuos Pen)

[202] (Intuos (9x12)) (Intuos 9x12 Tablet) (I-900ADB)

[203] (Intuos Pen)

[204] (Intuos (12x12)) (Intuos 12x12 Tablet) (I-1200USB)

[205] (Intuos Pen)

[206] (Intuos (12x12)) (Intuos 12x12 Tablet) (I-1200Serial)

[207] (Intuos Pen)

[208] (Intuos (12x18)) (Intuos 12x18 Tablet) (I-1800USB)

[209] (Intuos Pen)

[210] (Intuos (12x18)) (Intuos 12x18 Tablet) (I-1800Serial)

[211] (Intuos Pen)

[212] (ART Z II)

[213] (UltraPen Eraser) (Erasing UltraPen)

[214] (ART Z II)

[215] (UltraPen Eraser) (Erasing UltraPen)

[216] (ART Z II)

[217] (UltraPen Eraser) (Erasing UltraPen)

[218] (ART Z II)

[219] (UltraPen Eraser) (Erasing UltraPen)

[220] (ART Z II)

[221] (UltraPen Eraser) (Erasing UltraPen)

[222] (ART Z II)

[223] (UltraPen Eraser) (Erasing UltraPen)

[224] (Artpad II Pro Serial) (UltraPad A5 Serial)

[225] (UltraPen Eraser) (Erasing UltraPen)

[226] (Artpad II Pro ADB) (UltraPad A5 ADB)

[227] (UltraPen Eraser) (Erasing UltraPen)

[228] (UD-1212 II) (ULTRAPAD II) (UltraPad A4) (UD-1212-RSR) (UD-1212-RSB)

[229] (UltraPen Eraser) (Erasing UltraPen)

[230] (UD-1218 II / E) (UD-1218 II / S) (ULTRAPAD II) (UltraPad A3) (UD-1218-RER) (UD-1218-RSR)

[231] (UltraPen Eraser) (Erasing UltraPen)

[232] (UD-1825 II) (ULTRAPAD II) (UltraPad A2) (UD-1825-RSR)

[233] (UltraPen Eraser) (Erasing UltraPen)

[234] (Standard 6 x 9)

[235] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[236] (Standard 12 x 12)

[237] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[238] (Electrostatic 12 x 12)

[239] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[240] (Menu Panel 12 x 12)

[241] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[242] (Standard 15 x 15)

[243] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[244] (Electrostatic 15 x 15)

[245] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[246] (Menu Panel 15 x 15)

[247] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[248] (Standard 12 x 18)

[249] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[250] (Electrostatic 12 x 18)

[251] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[252] (Menu Panel 12 x 18)

[253] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[254] (Standard 18 x 25)

[255] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[256] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[257] (Standard Stylus), (Standard Stylus), (Slim Stylus), (Slim Stylus), (Pressure Stylus), (Pressure Stylus)

[258] (Wacom One Standard Pen)

[259] (Wacom One Pen)

[260] (Hi-Uni Digital Mitsubishi Pencil)

[261] (Dr. Grip Digital for Wacom ブラック)
(Dr. Grip Digital for Wacom Black)

[262] (Dr. Grip Digital for Wacom アクアブルー)
(Dr. Grip Digital for Wacom Blue)

[263] (LAMY AL-Star black EMR Pen)

[264] (STAEDTLER Noris digital classic Stylus)

[265] (STAEDTLER Noris digital jumbo Stylus)

[266] (Wacom Pen 4K)

[267] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[268] (Wacom Pen 2K)

[269] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[270] (Wacom Pen 2K)

[271] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[272] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[273] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[274] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[275] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[276] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[277] (Bamboo Fun CTH Pen)

[278] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[279] (Bamboo CTL Pen)

[280] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[281] (Bamboo CTH Pen)

[282] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[283] (Bamboo One Pen)

[284] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[285] (Bamboo Pen)

[286] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[287] (Bamboo Fun Pen)

[288] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[289] (Graphire4 Pen)

[290] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[291] (Bamboo One Pen)

[292] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[293] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[294] (Graphire3 Inking Pen) (Graphire2 Inking Pen) (Graphire Inking Pen)

[295] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[296] (Graphire Pen)

[297] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[298] (Graphire3 Pen)

[299] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[300] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[301] (LLC Pen)

[302] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[303] (Graphire2 Pen)

[304] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[305] (Graphire Pen)

[306] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[307] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[308] (PenPartner Pen) (UltraPen)

[309] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[310] (Wacom Pro Pen 3)

[311] (Wacom Pro Pen 2)

[312] (Wacom Pro Pen Slim)

[313] (Wacom Pro Pen 3d)

[314] (Wacom Finetip Pen)

[315] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[316] (Wacom Ballpoint Pen)

[317] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[318] (Intuos4 Grip Pen) (Intuos5 Grip Pen) (Wacom Grip Pen)

[319] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[320] (Intuos4 Grip Pen)

[321] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[322] (Wacom Pro Pen)

[323] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[324] (Intuos4 Airbrush) (Intuos5 Airbrush) (Wacom Airbrush)

[325] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[326] (Intuos4 Inking Pen) (Intuos5 Inking Pen) (Wacom Inking Pen)

[327] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[328] (Intuos4 Art Pen) (Intuos5 Art Pen) (Wacom Art Pen)

[329] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[330] (Intuos4 Classic Pen) (Intuos5 Classic Pen) (Wacom Classic Pen)

[331] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A010-03, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A011, PSI-A021)

[332] (Intuos3 Grip Pen)

[333] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A010-03, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A011, PSI-A021)

[334] (Intuos3 Airbrush)

[335] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A010-03, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A011, PSI-A021)

[336] (Intuos3 Art Pen)

[337] (Intuos3 Ink Pen)

[338] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[339] (Intuos3 Classic Pen)

[340] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[341] (Intuos2 Grip Pen)

[342] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[343] (Intuos2 Designer Pen) (Design Pen)

[344] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[345] (Intuos2 Airbrush)

[346] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[347] (Intuos2 Classic Pen)

[348] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[349] (Intuos2 Ink Pen)

[350] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[351] (Intuos2 Stroke Pen)

[352] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[353] (Intuos Pen)

[354] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[355] (Intuos Airbrush)

[356] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[357] (Intuos Inking Pen)

[358] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[359] (Intuos Stroke Pen)

[360] (PSI-A024-BK, PSI-A025-R, PSI-A026-BL, PSI-A024-BK-01, PSI-A011, PSI-A023, FUZ-A010-03)

[361] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[362] (UltraPen Eraser) (Erasing UltraPen)

[363] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[364] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[365] Click pen

[366] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[367] (UltraPen Brush)

[368] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[369] (UltraPen Pencil)

[370] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[371] (Grip Pen)

[372] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[373] (Grip Pen)

[374] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[375] (UltraPen 813E)

[376] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120,

PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[377] (UltraPen Write)

[378] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[379] (UltraPen Write)

[380] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[381] (UltraPen Ink)

[382] (ACK-20401K, ACK-20101W, ACK-20014, FUZ-A141, FUZ-A010, FUZ-A121, FUZ-A154, FUZ-A120, PSI-A034, PSI-A007, PSI-A043, PSI-A042, PSI-A066, PSI-A021)

[383] (Standard Stylus Gray)

[384] (Standard Stylus Red)

[385] (Slim Stylus Gray)

[386] (Slim Stylus Magenta)

[387] (Pressure Stylus Blue)

[388] (Pressure Stylus Red)

[389] BAMBOO FUN CORDLESS MOUSE

[390] Graphire4 cordless mouse

[391] GRAPHIRE3 CORDLESS MOUSE

[392] GRAPHIRE2 CORDLESS MOUSE

[393] GRAPHIRE CORDLESS MOUSE

[394] INTUOS4 MOUSE

[395] INTUOS4 LENS CURSOR

[396] Intuos3 mouse

[397] Intuos3 lens cursor

[398] INTUOS2 2D MOUSE

[399] INTUOS2 4D MOUSE

[400] INTUOS2 LENS CURSOR

[401] INTUOS 4D MOUSE

[402] INTUOS LENS CURSOR

[403] 4-button cursor

[404] 16 button cursor

[405] Four-Button Cursor

[406] Four-Button Cursor

[407] Four-Button Cursor

[408] Sixteen-Button Cursor