

NOP (00)		Cycles: 2	Size: 1
Implied			
Cycle	R/W		Desc.
-X.2	Read PC		Store as OpCode.
1.1			Inc. PC .
1.2			
2.1			
2.2	Read PC		Store as OpCode.
+X.1			

TCALL (01)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFDE	Store as PC .L.
7.1		
7.2	Read \$FFDF	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (02)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$01) \$01.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (03)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 0)) == (1 << 0).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

OR (04)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

OR (05)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

OR (06)	Cycles: 3	Size: 1
Indirect X (X) (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2	Read (X ((PSW & \$20) << 3))	Store as Operand.
3.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

OR (07)	Cycles: 6	Size: 2
X-Indexed Indirect [d+X] (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Store as Operand.
6.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
6.2	Read PC	Store as OpCode.
+X.1		

OR (08)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . A = Operand. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

OR (09)	Cycles: 6	Size: 3
Direct Page to Direct Page dd, ds (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand0.
3.1		
3.2	Read PC	Store as Operand.
4.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
4.2	Read Address	Store as Operand1.
5.1		Operand0 = Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
5.2	Write to Address	Write Operand0.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

OR1 (0A)	Cycles: 5	Size: 3
Absolute Boolean Bit m.b		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		
4.2		
5.1		Bit = Address >> 13. C flag = ((Operand & (1 << Bit)) != 0).
5.2	Read PC	Store as OpCode.
+X.1		

ASL (0B)	Cycles: 4	Size: 2
Direct Page d (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		C flag = (Operand & \$80). Operand <= 1. N flag = (Operand & \$80), Z flag = !Operand.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

ASL (0C)	Cycles: 5	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		C flag = (Operand & \$80). Operand <= 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

PUSH (0D)		Cycles: 4	Size: 1
Implied			
Cycle	R/W		Desc.
-X.2	Read PC		Store as OpCode.
1.1			Inc. PC .
1.2	Read PC		Discard.
2.1			
2.2	Write to u8(SP +0) \$0100		Push PSW onto stack.
3.1			Dec. SP by 1.
3.2			
4.1			
4.2	Read PC		Store as OpCode.
+X.1			

TSET1 (0E)	Cycles: 6	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Tmp = (A - Operand). Operand = A . Z flag = (Tmp == 0), N flag = (Tmp & \$80).
4.2	Read Address	Discard.
5.1		
5.2	Write to Address	Write Operand.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

BRK (0F)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
3.1		
3.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
4.1		
4.2	Write to u8(SP -2) \$0100	Push PSW onto stack.
5.1		Dec. SP by 3. I flag = 0, X flag = 1.
5.2		
6.1		
6.2	Read \$FFDE	Store as PC .L.
7.1		
7.2	Read \$FFDF	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

BPL (10)	Cycles: 2-4	Size: 2
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$80) == \$00.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (11)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFDC	Store as PC .L.
7.1		
7.2	Read \$FFDD	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (12)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$01) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (13)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 0)) == (0 << 0).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

OR (14)	Cycles: 4	Size: 2
X-Indexed Direct Page d+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

OR (15)	Cycles: 5	Size: 3
X-Indexed Absolute !a+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Store as Operand.
5.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

OR (16)	Cycles: 5	Size: 3
Y-Indexed Absolute !a+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2	Read Pointer	Store as Operand.
5.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

OR (17)	Cycles: 6	Size: 2
Indirect Y-Indexed [d]+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		Address = (Y + Pointer).
5.2	Read Address	Store as Operand.
6.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
6.2	Read PC	Store as OpCode.
+X.1		

OR (18)	Cycles: 5	Size: 3
Immediate Data to Direct Page d, #i (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand0.
2.1		Inc. PC .
2.2	Read PC	Store as Operand.
3.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Operand1.
4.1		Operand0 = Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
4.2	Write to Address	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

OR (19)	Cycles: 5	Size: 1
Indirect Page to Indirect Page		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2	Read (Y ((PSW & \$20) << 3))	Store as Operand0.
3.1		
3.2	Read (X ((PSW & \$20) << 3))	Store as Operand1.
4.1		Operand0 = Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
4.2	Write to (X ((PSW & \$20) << 3))	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

DECW (1A)	Cycles: 6	Size: 2
Direct Page d (Read/Modify/Write 16)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Underflow = (Operand == 0). Operand -= 1. LowZero = (Operand == 0).
3.2	Write to Address	Write Operand.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Operand.
5.1		Operand -= Underflow. N flag = (Operand & \$80), Z flag = (LowZero && !Operand).
5.2	Write to ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Write Operand.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

ASL (1B)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		C flag = (Operand & \$80). Operand <= 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

ASL (1C)	Cycles: 2	Size: 1
Accumulator A		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		C flag = (A & \$80). A <<= 1. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

DEC (1D)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		X -= 1. N flag = (X & \$80), Z flag = ! X .
2.2		Store as OpCode.
+X.1		

CMP (1E)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Tmp = X - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
4.2	Read PC	Store as OpCode.
+X.1		

JMP (1F)	Cycles: 6	Size: 3
Absolute X-Indexed Indirect [!a+X]		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Store as PC .L.
5.1		
5.2	Read Pointer + 1	Store as PC .H.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

CLRP (20)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		PSW = (PSW & ~\$20).
2.2		Store as OpCode.
+X.1		

TCALL (21)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFDA	Store as PC .L.
7.1		
7.2	Read \$FFDB	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (22)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$02) \$02.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (23)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 1)) == (1 << 1).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

AND (24)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		A &= Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

AND (25)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		A &= Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

AND (26)	Cycles: 3	Size: 1
Indirect X (X) (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2	Read (X ((PSW & \$20) << 3))	Store as Operand.
3.1		A &= Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

AND (27)	Cycles: 6	Size: 2
X-Indexed Indirect [d+X] (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Store as Operand.
6.1		A &= Operand. N flag = (A & \$80), Z flag = ! A .
6.2	Read PC	Store as OpCode.
+X.1		

AND (28)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . A &= Operand. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

AND (29)	Cycles: 6	Size: 3
Direct Page to Direct Page dd, ds (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand0.
3.1		
3.2	Read PC	Store as Operand.
4.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
4.2	Read Address	Store as Operand1.
5.1		Operand0 &= Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
5.2	Write to Address	Write Operand0.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

OR1 (2A)	Cycles: 5	Size: 3
Absolute Boolean Bit /m.b		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		
4.2		
5.1		Bit = Address >> 13. C flag = ((Operand & (1 << Bit)) == 0).
5.2	Read PC	Store as OpCode.
+X.1		

ROL (2B)	Cycles: 4	Size: 2
Direct Page d (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Tmp = C flag. C flag = (Operand & \$80). Operand = (Operand << 1) Tmp. N flag = (Operand & \$80), Z flag = !Operand.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

ROL (2C)	Cycles: 5	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Tmp = C flag. C flag = (Operand & \$80). Operand = (Operand << 1) Tmp. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

PUSH (2D)	Cycles: 4	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC Write to u8(SP +0) \$0100	Inc. PC .
1.2		Discard.
2.1		
2.2		Push A onto stack.
3.1		Dec. SP by 1.
3.2		
4.1		
4.2		Store as OpCode.
+X.1		

CBNE (2E)	Cycles: 5-7	Size: 3
Direct Page Relative d, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (A != Operand).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

BRA (2F)	Cycles: 4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to true.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

BMI (30)	Cycles: 2-4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$80) == \$80.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (31)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFD8	Store as PC .L.
7.1		
7.2	Read \$FFD9	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (32)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$02) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (33)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 1)) == (0 << 1).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

AND (34) Cycles: 4 Size: 2		
X-Indexed Direct Page d+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		A &= Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

AND (35)	Cycles: 5	Size: 3
X-Indexed Absolute !a+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Store as Operand.
5.1		A &= Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

AND (36)	Cycles: 5	Size: 3
Y-Indexed Absolute !a+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2	Read Pointer	Store as Operand.
5.1		A &= Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

AND (37)	Cycles: 6	Size: 2
Indirect Y-Indexed [d]+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		Address = (Y + Pointer).
5.2	Read Address	Store as Operand.
6.1		A &= Operand. N flag = (A & \$80), Z flag = !A.
6.2	Read PC	Store as OpCode.
+X.1		

AND (38)	Cycles: 5	Size: 3
Immediate Data to Direct Page d, #i (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand0.
2.1		Inc. PC .
2.2	Read PC	Store as Operand.
3.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Operand1.
4.1		Operand0 &= Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
4.2	Write to Address	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

AND (39)	Cycles: 5	Size: 1
Indirect Page to Indirect Page (X), (Y) (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2	Read (Y ((PSW & \$20) << 3))	Store as Operand0.
3.1		
3.2	Read (X ((PSW & \$20) << 3))	Store as Operand1.
4.1		Operand0 &= Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
4.2	Write to (X ((PSW & \$20) << 3))	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

INCW (3A)		Cycles: 6	Size: 2
Direct Page d (Read/Modify/Write 16)			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1		Inc. PC .	
1.2	Read PC	Store as Operand.	
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).	
2.2	Read Address	Store as Operand.	
3.1		Overflow = (Operand == \$FF).	
		Operand += 1.	
		LowZero = (Operand == 0).	
3.2	Write to Address	Write Operand.	
4.1			
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Operand.	
5.1		Operand += Overflow. N flag = (Operand & \$80), Z flag = (LowZero && !Operand).	
5.2	Write to ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Write Operand.	
6.1			
6.2	Read PC	Store as OpCode.	
+X.1			

ROL (3B)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Tmp = C flag. C flag = (Operand & \$80). Operand = (Operand << 1) Tmp. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

ROL (3C)	Cycles: 2	Size: 1
Accumulator A		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		Tmp = C flag. C flag = (A & \$80). A = (A << 1) Tmp. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

INC (3D)		Cycles: 2	Size: 1
Implied			
Cycle	R/W		Desc.
-X.2	Read PC		Store as OpCode.
1.1			Inc. PC .
1.2			
2.1			X += 1. N flag = (X & \$80), Z flag = ! X .
2.2			Store as OpCode.
+X.1			

CMP (3E)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Tmp = X - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
3.2	Read PC	Store as OpCode.
+X.1		

CALL (3F)	Cycles: 8	Size: 3
Absolute Call !a		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		
4.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
5.1		
5.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
6.1		Dec. SP by 2.
6.2		
7.1		PC .L = Address.L.
7.2		
8.1		PC .H = Address.H.
8.2	Read PC	Store as OpCode.
+X.1		

SETP (40)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		PSW = (PSW \$20).
2.2		Store as OpCode.
+X.1		

TCALL (41)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFD6	Store as PC .L.
7.1		
7.2	Read \$FFD7	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (42)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$04) \$04.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (43)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 2)) == (1 << 2).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

EOR (44)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

EOR (45)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

EOR (46)	Cycles: 3	Size: 1
Indirect X (X) (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2	Read (X ((PSW & \$20) << 3))	Store as Operand.
3.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

EOR (47)	Cycles: 6	Size: 2
X-Indexed Indirect [d+X] (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Store as Operand.
6.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
6.2	Read PC	Store as OpCode.
+X.1		

EOR (48)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . A ^= Operand. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

EOR (49)	Cycles: 6	Size: 3
Direct Page to Direct Page dd, ds (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand0.
3.1		
3.2	Read PC	Store as Operand.
4.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
4.2	Read Address	Store as Operand1.
5.1		Operand0 ^= Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
5.2	Write to Address	Write Operand0.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

AND1 (4A)	Cycles: 4	Size: 3
Absolute Boolean Bit m.b		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		Bit = Address >> 13. C flag &= ((Operand & (1 << Bit)) != 0).
4.2	Read PC	Store as OpCode.
+X.1		

LSR (4B)	Cycles: 4	Size: 2
Direct Page d (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		C flag = (Operand & 01). Operand >>= 1. N flag = (Operand & \$80), Z flag = !Operand.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

LSR (4C)	Cycles: 5	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		C flag = (Operand & 01). Operand >>= 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

PUSH (4D)		Cycles: 4	Size: 1
Implied			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1	Write to u8(SP +0) \$0100	Inc. PC .	
1.2		Discard.	
2.1			
2.2		Push X onto stack.	
3.1		Dec. SP by 1.	
3.2			
4.1			
4.2		Store as OpCode.	
+X.1			

TCLR1 (4E)	Cycles: 6	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Tmp = (A - Operand). Operand = (Operand & ~ A). Z flag = (Tmp == 0), N flag = (Tmp & \$80).
4.2	Read Address	Discard.
5.1		
5.2	Write to Address	Write Operand.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

PCALL (4F)	Cycles: 6	Size: 2
Absolute Call !a		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		PC .L = Address.L, PC .H = \$FF.
6.2	Read PC	Store as OpCode.
+X.1		

BVC (50)	Cycles: 2-4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$40) == \$00.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (51)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFD4	Store as PC .L.
7.1		
7.2	Read \$FFD5	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (52)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$04) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (53)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 2)) == (0 << 2).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

EOR (54)	Cycles: 4	Size: 2
X-Indexed Direct Page d+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

EOR (55)	Cycles: 5	Size: 3
X-Indexed Absolute !a+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Store as Operand.
5.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

EOR (56)	Cycles: 5	Size: 3
Y-Indexed Absolute !a+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2	Read Pointer	Store as Operand.
5.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

EOR (57)	Cycles: 6	Size: 2
Indirect Y-Indexed [d]+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		Address = (Y + Pointer).
5.2	Read Address	Store as Operand.
6.1		A ^= Operand. N flag = (A & \$80), Z flag = ! A .
6.2	Read PC	Store as OpCode.
+X.1		

EOR (58)	Cycles: 5	Size: 3
Immediate Data to Direct Page d, #i (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand0.
2.1		Inc. PC .
2.2	Read PC	Store as Operand.
3.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Operand1.
4.1		Operand0 ^= Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
4.2	Write to Address	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

EOR (59)	Cycles: 5	Size: 1
Indirect Page to Indirect Page (X), (Y) (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2	Read (Y ((PSW & \$20) << 3))	Store as Operand0.
3.1		
3.2	Read (X ((PSW & \$20) << 3))	Store as Operand1.
4.1		Operand0 ^= Operand1. N flag = (Operand0 & \$80), Z flag = !Operand0.
4.2	Write to (X ((PSW & \$20) << 3))	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

CMPW (5A)	Cycles: 4	Size: 2
Direct Page d (Read 16)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand16.L.
3.1		
3.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Operand16.H.
4.1		Tmp = YA - Operand16. C flag = (Tmp >= 0), N flag = (Tmp & \$8000), Z flag = !Tmp.
4.2	Read PC	Store as OpCode.
+X.1		

LSR (5B)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		C flag = (Operand & 01). Operand >>= 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

LSR (5C)	Cycles: 2	Size: 1
Accumulator A		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		C flag = (A & 01). A >>= 1. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

MOV (5D)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		X = A . N flag = (X & \$80), Z flag = ! X .
2.2		Store as OpCode.
+X.1		

CMP (5E)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Tmp = Y - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
4.2	Read PC	Store as OpCode.
+X.1		

JMP (5F)	Cycles: 3	Size: 3
Absolute !a		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		PC = Address.
3.2	Read PC	Store as OpCode.
+X.1		

CLRC (60)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		PSW = (PSW & ~\$01).
2.2		Store as OpCode.
+X.1		

TCALL (61)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFD2	Store as PC .L.
7.1		
7.2	Read \$FFD3	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (62)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$08) \$08.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (63)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 3)) == (1 << 3).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

CMP (64)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
3.2	Read PC	Store as OpCode.
+X.1		

CMP (65)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
4.2	Read PC	Store as OpCode.
+X.1		

CMP (66)	Cycles: 3	Size: 1
Indirect X (X) (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2	Read (X ((PSW & \$20) << 3))	Store as Operand.
3.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
3.2	Read PC	Store as OpCode.
+X.1		

CMP (67)	Cycles: 6	Size: 2
X-Indexed Indirect [d+X] (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Store as Operand.
6.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
6.2	Read PC	Store as OpCode.
+X.1		

CMP (68)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
2.2	Read PC	Store as OpCode.
+X.1		

CMP (69)	Cycles: 6	Size: 3
Direct Page to Direct Page dd, ds (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand0.
3.1		
3.2	Read PC	Store as Operand.
4.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
4.2	Read Address	Store as Operand1.
5.1		Tmp = Operand1 - Operand0. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
5.2	Write to Address	Write Operand0.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

AND1 (6A)	Cycles: 4	Size: 3
Absolute Boolean Bit m.b		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		Bit = Address >> 13. C flag &= ((Operand & (1 << Bit)) == 0).
4.2	Read PC	Store as OpCode.
+X.1		

ROR (6B)	Cycles: 4	Size: 2
Direct Page d (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Tmp = (C flag << 7). C flag = (Operand & \$01). Operand = (Operand << 1) Tmp. N flag = (Operand & \$80), Z flag = !Operand.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

ROR (6C)	Cycles: 5	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Tmp = (C flag << 7). C flag = (Operand & \$01). Operand = (Operand << 1) Tmp. N flag = (Operand & \$80), Z flag =
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

PUSH (6D)		Cycles: 4	Size: 1
Implied			
Cycle	R/W		Desc.
-X.2	Read PC		Store as OpCode.
1.1			Inc. PC .
1.2	Read PC		Discard.
2.1			
2.2	Write to u8(SP +0) \$0100		Push Y onto stack.
3.1			Dec. SP by 1.
3.2			
4.1			
4.2	Read PC		Store as OpCode.
+X.1			

DBNZ (6E)	Cycles: 5-7	Size: 3
Direct Page Relative d, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		--Operand. Set Jump to (Operand != 0).
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

RET (6F)	Cycles: 5	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2		
3.1		Inc. SP by 1.
3.2	Read u8(SP +0) \$0100	Pull to PC .L.
4.1		
4.2	Read u8(SP +1) \$0100	Pull to PC .H.
5.1	Inc. SP by 1.	
5.2	Read PC	Store as OpCode.
+X.1		

BVS (70)	Cycles: 2-4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$40) == \$40.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (71)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFD0	Store as PC .L.
7.1		
7.2	Read \$FFD1	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (72)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$08) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (73)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 3)) == (0 << 3).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

CMP (74) Cycles: 4 Size: 2		
X-Indexed Direct Page d+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
4.2	Read PC	Store as OpCode.
+X.1		

CMP (75)	Cycles: 5	Size: 3
X-Indexed Absolute !a+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Store as Operand.
5.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
5.2	Read PC	Store as OpCode.
+X.1		

CMP (76)	Cycles: 5	Size: 3
Y-Indexed Absolute !a+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2	Read Pointer	Store as Operand.
5.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
5.2	Read PC	Store as OpCode.
+X.1		

CMP (77)	Cycles: 6	Size: 2
Indirect Y-Indexed [d]+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		Address = (Y + Pointer).
5.2	Read Address	Store as Operand.
6.1		Tmp = A - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
6.2	Read PC	Store as OpCode.
+X.1		

CMP (78)	Cycles: 5	Size: 3
Immediate Data to Direct Page d, #i (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand0.
2.1		Inc. PC .
2.2	Read PC	Store as Operand.
3.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Operand1.
4.1		Tmp = Operand1 - Operand0. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
4.2	Write to Address	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

CMP (79)	Cycles: 5	Size: 1
Indirect Page to Indirect Page (X), (Y) (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2	Read (Y ((PSW & \$20) << 3))	Store as Operand0.
3.1		
3.2	Read (X ((PSW & \$20) << 3))	Store as Operand1.
4.1		Tmp = Operand1 - Operand0. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
4.2	Write to (X ((PSW & \$20) << 3))	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

ADDW (7A)	Cycles: 5	Size: 2
Direct Page d (Read 16)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand16.L.
3.1		
3.2		
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Operand16.H.
5.1		Tmp = u32(A) + u32(Operand16.L). C flag = (Tmp > \$FF). A = u8(Tmp). Tmp = u32(Y) + u32(Operand16.H) + u32(C flag). C flag = (Tmp > \$FF). H flag = ((Y ^ Operand16.H ^ u8(Tmp)) & \$10). V flag = ~(Y ^ Operand16.H) & (Y ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Y = u8(Tmp). Z flag = (YA == \$0000).
5.2	Read PC	Store as OpCode.
+X.1		

ROR (7B)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Tmp = (C flag << 7). C flag = (Operand & \$01). Operand = (Operand << 1) Tmp. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

ROR (7C)	Cycles: 2	Size: 1
Accumulator A		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		Tmp = (C flag << 7). C flag = (A & \$01). A = (A >> 1) Tmp. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

MOV (7D) Cycles: 2 Size: 1		
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		A = X . N flag = (A & \$80), Z flag = ! A .
2.2		Store as OpCode.
+X.1		

CMP (7E)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Tmp = Y - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
3.2	Read PC	Store as OpCode.
+X.1		

RETI (7F)	Cycles: 6	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2		
3.1		Inc. SP by 1.
3.2	Read u8(SP +0) \$0100	Pull to PSW .
4.1		
4.2	Read u8(SP +1) \$0100	Pull to PC .L.
5.1		
5.2	Read u8(SP +2) \$0100	Pull to PC .H.
6.1	Inc. SP by 2.	
6.2	Read PC	Store as OpCode.
+X.1		

SETC (80)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		PSW = (PSW \$01).
2.2		Store as OpCode.
+X.1		

TCALL (81)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFCE	Store as PC .L.
7.1		
7.2	Read \$FFCF	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (82)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$10) \$10.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (83)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 4)) == (1 << 4).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

ADC (84)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
3.2	Read PC	Store as OpCode.
+X.1		

ADC (85)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC Read PC Read PC Read Address	Inc. PC .
1.2		Store as Address.L.
2.1		Inc. PC .
2.2		Store as Address.H.
3.1		Inc. PC .
3.2		Store as Operand.
4.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
4.2		Store as OpCode.
+X.1		

ADC (86)	Cycles: 3	Size: 1
Indirect X (X) (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read (X ((PSW & \$20) << 3))	Inc. PC .
1.2		
2.1		
2.2		Store as Operand.
3.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
3.2	Read PC	Store as OpCode.
+X.1		

ADC (87)	Cycles: 6	Size: 2
X-Indexed Indirect [d+X] (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Store as Operand.
6.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
6.2	Read PC	Store as OpCode.
+X.1		

ADC (88)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Store as Operand.
2.1		Inc. PC . Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
2.2	Read PC	Store as OpCode.
+X.1		

ADC (89)	Cycles: 6	Size: 3
Direct Page to Direct Page dd, ds (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand0.
3.1		
3.2	Read PC	Store as Operand.
4.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
4.2	Read Address	Store as Operand1.
5.1		Tmp = u32(Operand0) + u32(Operand1) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((Operand0 ^ Operand1 ^ u8(Tmp)) & \$10). V flag = ~(Operand0 ^ Operand1) & (Operand0 ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Operand0 = u8(Tmp).
5.2	Write to Address	Write Operand0.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

EOR1 (8A)	Cycles: 5	Size: 3
Absolute Boolean Bit m.b		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		
4.2		
5.1		Bit = Address >> 13. C flag ^= ((Operand & (1 << Bit)) != 0).
5.2	Read PC	Store as OpCode.
+X.1		

DEC (8B)	Cycles: 4	Size: 2
Direct Page d (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand -= 1. N flag = (Operand & \$80), Z flag = !Operand.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

DEC (8C)	Cycles: 5	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Operand -= 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOV (8D) Cycles: 2 Size: 2		
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Y = Operand. N flag = (Operand & \$80), Z flag = !Operand.
2.2	Read PC	Store as OpCode.
+X.1		

POP (8E)	Cycles: 4	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Discard.
2.1		
2.2		
3.1		Inc. SP by 1.
3.2		Pull to PSW .
4.1		
4.2		Store as OpCode.
+X.1		

MOV (8F)		Cycles: 5	Size: 3
Immediate Data to Direct Page d, #i (Read/Modify/Write)			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1		Inc. PC .	
1.2	Read PC	Store as Operand0.	
2.1		Inc. PC .	
2.2	Read PC	Store as Operand.	
3.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).	
3.2	Read Address	Store as Operand1.	
4.1		Operand = A . N flag = (Operand & \$80), Z flag = !Operand.	
4.2	Write to Address	Write Operand0.	
5.1			
5.2	Read PC	Store as OpCode.	
+X.1			

BCC (90)	Cycles: 2-4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$01) == \$00.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (91)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFCC	Store as PC .L.
7.1		
7.2	Read \$FFCD	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (92)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$10) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (93)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 4)) == (0 << 4).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

ADC (94)	Cycles: 4	Size: 2
X-Indexed Direct Page d+X		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
4.2	Read PC	Store as OpCode.
+X.1		

ADC (95)	Cycles: 5	Size: 3
X-Indexed Absolute !a+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Store as Operand.
5.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
5.2	Read PC	Store as OpCode.
+X.1		

ADC (96)	Cycles: 5	Size: 3
Y-Indexed Absolute !a+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2	Read Pointer	Store as Operand.
5.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = (~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
5.2	Read PC	Store as OpCode.
+X.1		

ADC (97)	Cycles: 6	Size: 2
Indirect Y-Indexed [d]+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		Address = (Y + Pointer).
5.2	Read Address	Store as Operand.
6.1		Tmp = u32(A) + u32(Operand) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ Operand ^ u8(Tmp)) & \$10). V flag = ~(A ^ Operand) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
6.2	Read PC	Store as OpCode.
+X.1		

ADC (98)	Cycles: 5	Size: 3
Immediate Data to Direct Page d, #i (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand0.
2.1		Inc. PC .
2.2	Read PC	Store as Operand.
3.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Operand1.
4.1		Tmp = u32(Operand0) + u32(Operand1) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((Operand0 ^ Operand1 ^ u8(Tmp)) & \$10). V flag = ~(Operand0 ^ Operand1) & (Operand0 ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Operand0 = u8(Tmp).
4.2	Write to Address	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

ADC (99)	Cycles: 5	Size: 1
Indirect Page to Indirect Page (X), (Y) (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2	Read (Y ((PSW & \$20) << 3))	Store as Operand0.
3.1		
3.2	Read (X ((PSW & \$20) << 3))	Store as Operand1.
4.1		Tmp = u32(Operand0) + u32(Operand1) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((Operand0 ^ Operand1 ^ u8(Tmp)) & \$10). V flag = ~(Operand0 ^ Operand1) & (Operand0 ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Operand0 = u8(Tmp).
4.2	Write to (X ((PSW & \$20) << 3))	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

SUBW (9A)		Cycles: 5	Size: 2
Direct Page d (Read 16)			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1		Inc. PC .	
1.2	Read PC	Store as Operand.	
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).	
2.2	Read Address	Store as Operand16.L.	
3.1			
3.2			
4.1			
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Operand16.H.	
5.1		TmpR = ~Operand16.L. Tmp = u32(A) + u32(TmpR) + 1. C flag = (Tmp > \$FF). A = u8(Tmp). TmpR = ~Operand16.H. Tmp = u32(Y) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). H flag = ((Y ^ TmpR ^ u8(Tmp)) & \$10). V flag = ~(Y ^ TmpR) & (Y ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Y = u8(Tmp). Z flag = (YA == \$0000).	
5.2	Read PC	Store as OpCode.	
+X.1			

DEC (9B)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Operand -= 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

DEC (9C)	Cycles: 2	Size: 1
Accumulator A		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		A -= 1. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

MOV (9D) Cycles: 2 Size: 1		
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		X = SP . N flag = (X & \$80), Z flag = ! X .
2.2		Store as OpCode.
+X.1		

DIV (9E)		Cycles: 12	Size: 1
Implied			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1		Inc. PC .	
1.2			
2.1		H flag = ((Y & 15) >= (X & 15)), V flag = (Y >= X). DivYa = u32(YA), ShiftedX = u32(X) << 9.	
2.2			
3.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
3.2			
4.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
4.2			
5.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
5.2			
6.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
6.2			
7.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
7.2			
8.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
8.2			
9.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
9.2			
10.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
10.2			
11.1		DivYa <= 1. If DivYa & \$20000: DivYa ^= \$20001. If DivYa >= ShiftedX: DivYa ^= 1. If DivYa & 1: DivYa = (DivYa - ShiftedX) & \$1FFFF.	
11.2			
12.1		Y = u8(DivYa >> 9), A = u8(DivYa). N flag = (A & \$80), Z flag = ! A .	
12.2	Read PC	Store as OpCode.	
+X.1			

XCN (9F)	Cycles: 5	Size: 1
Accumulator A		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		A = (A >> 7) (A << 1).
2.2		
3.1		A = (A >> 7) (A << 1).
3.2		
4.1		A = (A >> 7) (A << 1).
4.2		
5.1		A = (A >> 7) (A << 1). N flag = (A & \$80), Z flag = ! A .
5.2		Read PC
		Store as OpCode.
+X.1		

El (A0)	Cycles: 3	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2		
3.1		PSW = (PSW \$04).
3.2		Store as OpCode.
+X.1		

TCALL (A1)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFCA	Store as PC .L.
7.1		
7.2	Read \$FFCB	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (A2)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$20) \$20.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (A3)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 5)) == (1 << 5).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

SBC (A4)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		TmpR = ~Operand. Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = ~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
3.2	Read PC	Store as OpCode.
+X.1		

SBC (A6)	Cycles: 3	Size: 1
Indirect X (X) (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read (X ((PSW & \$20) << 3))	Inc. PC .
1.2		
2.1		
2.2		Store as Operand.
3.1		TmpR = ~Operand. Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = ~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
3.2	Read PC	Store as OpCode.
+X.1		

SBC (A7)	Cycles: 6	Size: 2
X-Indexed Indirect [d+X] (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Store as Operand.
6.1		TmpR = ~Operand. Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = (~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
6.2	Read PC	Store as OpCode.
+X.1		

SBC (A8)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Store as Operand.
2.1		Inc. PC . TmpR = ~Operand.
		Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = (~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
2.2	Read PC	Store as OpCode.
+X.1		

SBC (A9)	Cycles: 6	Size: 3
Direct Page to Direct Page dd, ds (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand0.
3.1		
3.2	Read PC	Store as Operand.
4.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
4.2	Read Address	Store as Operand1.
5.1		TmpR = ~Operand0. Tmp = u32(Operand1) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((Operand1 ^ TmpR ^ u8(Tmp)) & \$10). V flag = (~ (Operand1 ^ TmpR) & (Operand1 ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Operand0 = u8(Tmp).
5.2	Write to Address	Write Operand0.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

MOV1 (AA)	Cycles: 4	Size: 3
Absolute Boolean Bit m.b		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		Bit = Address >> 13. C flag = ((Operand & (1 << Bit)) != 0).
4.2	Read PC	Store as OpCode.
+X.1		

INC (AB)	Cycles: 4	Size: 2
Direct Page d (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand += 1. N flag = (Operand & \$80), Z flag = !Operand.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

INC (AC)	Cycles: 5	Size: 3
Absolute !a (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Operand += 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

CMP (AD)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Tmp = Y - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
2.2	Read PC	Store as OpCode.
+X.1		

POP (AE)	Cycles: 4	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Discard.
2.1		
2.2		
3.1		Inc. SP by 1.
3.2		Pull to A .
4.1		
4.2		Store as OpCode.
+X.1		

MOV (AF)	Cycles: 4	Size: 1
Indirect Auto-Increment (X)+ (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		Address = (X ((PSW & \$20) << 3)).
2.2		
3.1		
3.2	Write to Address	Write A .
4.1		X += 1.
4.2	Read PC	Store as OpCode.
+X.1		

BCS (B0)	Cycles: 2-4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$01) == \$01.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (B1)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFC8	Store as PC .L.
7.1		
7.2	Read \$FFC9	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (B2)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$20) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (B3)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 5)) == (0 << 5).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

SBC (B4)	Cycles: 4	Size: 2
X-Indexed Direct Page d+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2		Store as Operand.
4.1		TmpR = ~Operand. Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = (~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
4.2		Read PC
		Store as OpCode.
+X.1		

SBC (B5)	Cycles: 5	Size: 3
X-Indexed Absolute !a+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Store as Address.L.
2.1		Inc. PC .
2.2		Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2		Store as Operand.
5.1		TmpR = ~Operand. Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = ~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
5.2		Read PC
		Store as OpCode.
+X.1		

SBC (B6)	Cycles: 5	Size: 3
Y-Indexed Absolute !a+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Store as Address.L.
2.1		Inc. PC .
2.2		Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2		Store as Operand.
5.1		TmpR = ~Operand. Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = ~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
5.2		Read PC
		Store as OpCode.
+X.1		

SBC (B7)	Cycles: 6	Size: 2
Indirect Y-Indexed [d]+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		Address = (Y + Pointer).
5.2	Read Address	Store as Operand.
6.1		TmpR = ~Operand. Tmp = u32(A) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((A ^ TmpR ^ u8(Tmp)) & \$10). V flag = (~(A ^ TmpR) & (A ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). A = u8(Tmp).
6.2	Read PC	Store as OpCode.
+X.1		

SBC (B8)	Cycles: 5	Size: 3
Immediate Data to Direct Page d, #i (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand0.
2.1		Inc. PC .
2.2	Read PC	Store as Operand.
3.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Operand1.
4.1		TmpR = ~Operand0. Tmp = u32(Operand1) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((Operand1 ^ TmpR ^ u8(Tmp)) & \$10). V flag = ~(Operand1 ^ TmpR) & (Operand1 ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Operand0 = u8(Tmp).
4.2	Write to Address	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

SBC (B9)	Cycles: 5	Size: 1
Indirect Page to Indirect Page (X), (Y) (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		
2.2	Read (Y ((PSW & \$20) << 3))	Store as Operand0.
3.1		
3.2	Read (X ((PSW & \$20) << 3))	Store as Operand1.
4.1		TmpR = ~Operand0. Tmp = u32(Operand1) + u32(TmpR) + u32(C flag). C flag = (Tmp > \$FF). Z flag = (u8(Tmp) == \$00). H flag = ((Operand1 ^ TmpR ^ u8(Tmp)) & \$10). V flag = ~(Operand1 ^ TmpR) & (Operand1 ^ u8(Tmp)) & \$80). N flag = (u8(Tmp) & \$80). Operand0 = u8(Tmp).
4.2	Write to (X ((PSW & \$20) << 3))	Write Operand0.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOVW (BA)		Cycles: 5	Size: 2
Direct Page d (Read 16)			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1		Inc. PC .	
1.2	Read PC	Store as Operand.	
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).	
2.2	Read Address	Store as A .	
3.1			
3.2			
4.1			
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Y .	
5.1		N flag = (YA & \$8000), Z flag = ! YA .	
5.2	Read PC	Store as OpCode.	
+X.1			

INC (BB)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Operand += 1. N flag = (Operand & \$80), Z flag = !Operand.
4.2	Write to Address	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

INC (BC)	Cycles: 2	Size: 1
Accumulator A		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		A += 1. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

MOV (BD)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		SP = X.
2.2		Store as OpCode.
+X.1		

DAS (BE)	Cycles: 3	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		If (! C flag A > \$99): A -= \$60, C flag = 0.
2.2		
3.1		If (! H flag (A & \$0F) > \$09): A -= \$06. N flag = (A & \$80), Z flag = ! A .
3.2		N flag = (A & \$80), Z flag = ! A . Store as OpCode.
+X.1	Read PC	

MOV (BF)	Cycles: 4	Size: 1
Indirect Auto-Increment (X)+ (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Discard.
2.1		Address = (X ((PSW & \$20) << 3)).
2.2	Read Address	Store as A .
3.1		N flag = (A & \$80), Z flag = ! A .
3.2		
4.1		X += 1.
4.2	Read PC	Store as OpCode.
+X.1		

DI (C0)	Cycles: 3	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2		
3.1		PSW = (PSW & ~\$04).
3.2		Store as OpCode.
+X.1		

TCALL (C1)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFC6	Store as PC .L.
7.1		
7.2	Read \$FFC7	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (C2)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$40) \$40.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (C3)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 6)) == (1 << 6).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

MOV (C4)	Cycles: 4	Size: 2
Direct Page d (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		
3.2	Write to Address	Write A .
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

MOV (C5)	Cycles: 5	Size: 3
Absolute !a (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Discard.
4.1		
4.2	Write to Address	Write A .
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOV (C6)	Cycles: 4	Size: 1
Indirect X (X) (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2	Read (X ((PSW & \$20) << 3))	Store as Discard.
3.1		
3.2	Write to (X ((PSW & \$20) << 3))	Write A .
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

MOV (C7)	Cycles: 7	Size: 2
X-Indexed Indirect [d+X] (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Discard.
6.1		
6.2	Write to Pointer	Write A .
7.1		
7.2	Read PC	Store as OpCode.
+X.1		

CMP (C8)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Tmp = X - Operand. C flag = (Tmp >= 0), N flag = (Tmp & \$80), Z flag = !Tmp.
2.2	Read PC	Store as OpCode.
+X.1		

MOV (C9)	Cycles: 5	Size: 3
Absolute !a (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Discard.
4.1		
4.2	Write to Address	Write X .
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOV1 (CA)	Cycles: 6	Size: 3
Absolute Boolean Bit m.b, C		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		
4.2		
5.1		Bit = Address >> 13. Operand &= ~(1 << Bit).
		Operand = (C flag << Bit).
5.2	Write to (Address & \$1FFF)	Write Operand.
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

MOV (CB)	Cycles: 4	Size: 2
Direct Page d (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		
3.2	Write to Address	Write Y .
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

MOV (CC)	Cycles: 5	Size: 3
Absolute !a (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Discard.
4.1		
4.2	Write to Address	Write Y .
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOV (CD)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . X = Operand. N flag = (X & \$80), Z flag = ! X .
2.2	Read PC	Store as OpCode.
+X.1		

POP (CE)	Cycles: 4	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Discard.
2.1		
2.2		
3.1		Inc. SP by 1.
3.2		Pull to X .
4.1		
4.2		Store as OpCode.
+X.1		

MUL (CF)	Cycles: 9	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . MulYa = u32(A), ShiftedY = (u32(Y) << 8).
1.2		
2.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1.
2.2		
3.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1.
3.2		
4.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1.
4.2		
5.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1.
5.2		
6.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1.
6.2		
7.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1.
7.2		
8.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1.
8.2		
9.1		If MulYa & \$1: MulYa += ShiftedY. MulYa >>= 1. Y = u8(MulYa >> 8), A = u8(MulYa). N flag = (Y & \$80), Z flag = ! Y .
9.2	Read PC	Store as OpCode.
+X.1		

BNE (D0)	Cycles: 2-4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$02) == \$00.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (D1)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFC4	Store as PC .L.
7.1		
7.2	Read \$FFC5	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (D2)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$40) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (D3)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 6)) == (0 << 6).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

MOV (D4)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Discard.
4.1		
4.2	Write to Address	Write A .
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOV (D5)	Cycles: 6	Size: 3
X-Indexed Absolute !a+X (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Discard.
5.1		
5.2	Write to Pointer	Write A .
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

MOV (D6)	Cycles: 6	Size: 3
Y-Indexed Absolute !a+Y (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2	Read Pointer	Discard.
5.1		
5.2	Write to Pointer	Write A .
6.1		
6.2	Read PC	Store as OpCode.
+X.1		

MOV (D7)		Cycles: 7	Size: 2
Indirect Y-Indexed [d]+Y (Write)			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1		Inc. PC .	
1.2	Read PC	Store as Operand.	
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).	
2.2	Read Address	Store as Pointer.L.	
3.1			
3.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.	
4.1			
4.2			
5.1		Address = (Y + Pointer).	
5.2	Read Address	Discard.	
6.1			
6.2	Write to Address	Write A .	
7.1			
7.2	Read PC	Store as OpCode.	
+X.1			

MOV (D8)	Cycles: 4	Size: 2
Direct Page d (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		
3.2	Write to Address	Write X .
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

MOV (D9)	Cycles: 5	Size: 2
Y-Indexed Direct Page d+Y (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((Y + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Discard.
4.1		
4.2	Write to Address	Write X .
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOVW (DA)		Cycles: 5	Size: 2
Direct Page d (Write 16)			
Cycle	R/W	Desc.	
-X.2	Read PC	Store as OpCode.	
1.1		Inc. PC .	
1.2	Read PC	Store as Operand.	
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).	
2.2	Read Address	Discard.	
3.1			
3.2	Write to Address	Write A .	
4.1			
4.2	Write to ((Address + 1) & \$00FF)	Write Y .	
5.1	((PSW & \$20) << 3)		
5.2	Read PC	Store as OpCode.	
+X.1			

MOV (DB)	Cycles: 5	Size: 2
X-Indexed Direct Page d+X (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Discard.
4.1		
4.2	Write to Address	Write Y .
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

DEC (DC)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		Y -= 1. N flag = (Y & \$80), Z flag = ! Y .
2.2		Store as OpCode.
+X.1		

DEC (DC)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		Y -= 1. N flag = (Y & \$80), Z flag = ! Y .
2.2		Store as OpCode.
+X.1		

MOV (DD)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		A = Y . N flag = (A & \$80), Z flag = ! A .
2.2		Store as OpCode.
+X.1		

CBNE (DE)	Cycles: 6-8	Size: 3
X-Indexed Direct Page Relative d+X, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Set Jump to (A != Operand).
4.2		
5.1		
5.2	Read PC	Store as Operand.
6.1		Inc. PC . If !Jump, end instruction (next half-cycle is 8.2).
6.2		
7.1		Address = PC + i8(Operand). PC .L = Address.L.
7.2		
8.1		PC .H = Address.H.
8.2	Read PC	Store as OpCode.
+X.1		

DAA (DF)	Cycles: 3	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		If (C flag A > \$99): A += \$60, C flag = 1.
2.2		
3.1		If (H flag (A & \$0F) > \$09): A += \$06. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

CLRV (E0)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		PSW = (PSW & ~\$40).
2.2		Store as OpCode.
+X.1		

TCALL (E1)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFC2	Store as PC .L.
7.1		
7.2	Read \$FFC3	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

SET1 (E2)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$80) \$80.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBS (E3)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 7)) == (1 << 7).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

MOV (E4)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

MOV (E5)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

MOV (E6)	Cycles: 3	Size: 1
Indirect X (X) (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2	Read (X ((PSW & \$20) << 3))	Store as Operand.
3.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
3.2	Read PC	Store as OpCode.
+X.1		

MOV (E7)	Cycles: 6	Size: 2
X-Indexed Indirect [d+X] (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		
5.2	Read Pointer	Store as Operand.
6.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
6.2	Read PC	Store as OpCode.
+X.1		

MOV (E8)	Cycles: 2	Size: 2
Immediate		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . A = Operand. N flag = (A & \$80), Z flag = ! A .
2.2	Read PC	Store as OpCode.
+X.1		

MOV (E9)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		X = Operand. N flag = (X & \$80), Z flag = ! X .
4.2	Read PC	Store as OpCode.
+X.1		

NOT1 (EA)	Cycles: 5	Size: 3
Absolute Boolean Bit m.b		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read (Address & \$1FFF)	Store as Operand.
4.1		Bit = Address >> 13. Operand ^= (1 << Bit).
4.2	Write to (Address & \$1FFF)	Write Operand.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOV (EB)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Y = Operand. N flag = (Y & \$80), Z flag = ! Y .
3.2	Read PC	Store as OpCode.
+X.1		

MOV (EC)	Cycles: 4	Size: 3
Absolute !a (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2	Read Address	Store as Operand.
4.1		Y = Operand. N flag = (Y & \$80), Z flag = ! Y .
4.2	Read PC	Store as OpCode.
+X.1		

NOTC (ED)	Cycles: 3	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		
2.2		
3.1		PSW ^= \$01.
3.2		Store as OpCode.
+X.1		

POP (EE)	Cycles: 4	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1	Read PC	Inc. PC .
1.2		Discard.
2.1		
2.2		
3.1		Inc. SP by 1.
3.2		Pull to Y .
4.1		
4.2		Store as OpCode.
+X.1		

SLEEP (EF)	Cycles: 3	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		Discard.
2.1		
2.2		
3.1		Return to cycle 1 (next half-cycle is 1.2).

BEQ (F0)	Cycles: 2-4	Size: 2
Relative r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC . Set Jump to (PSW & \$02) == \$02.
1.2		Store as Operand.
2.1		Inc. PC . If !Jump, end instruction (next half-cycle is 4.2).
2.2		
3.1		Address = PC + i8(Operand).
		PC .L = Address.L.
3.2		
4.1		PC .H = Address.H.
4.2	Read PC	Store as OpCode.
+X.1		

TCALL (F1)	Cycles: 8	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		
2.2		
3.1		
3.2	Write to u8(SP +0) \$0100	Push PC .H onto stack.
4.1		
4.2	Write to u8(SP -1) \$0100	Push PC .L onto stack.
5.1		Dec. SP by 2.
5.2		
6.1		
6.2	Read \$FFC0	Store as PC .L.
7.1		
7.2	Read \$FFC1	Store as PC .H.
8.1		
8.2	Read PC	Store as OpCode.
+X.1		

CLR1 (F2)	Cycles: 4	Size: 2
Direct Page Bit d.b (Read/Modify/Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Operand = (Operand & ~\$80) \$00.
3.2	Write to Address	Write Operand.
4.1		
4.2	Read PC	Store as OpCode.
+X.1		

BBC (F3)	Cycles: 5-7	Size: 3
Direct Page Bit Relative d.b, r		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		Set Jump to (Operand & (1 << 7)) == (0 << 7).
3.2		
4.1		
4.2	Read PC	Store as Operand.
5.1		Inc. PC . If !Jump, end instruction (next half-cycle is 7.2).
5.2		
6.1		Address = PC + i8(Operand). PC .L = Address.L.
6.2		
7.1		PC .H = Address.H.
7.2	Read PC	Store as OpCode.
+X.1		

MOV (F4)	Cycles: 4	Size: 2
X-Indexed Direct Page d+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
4.2	Read PC	Store as OpCode.
+X.1		

MOV (F5)	Cycles: 5	Size: 3
X-Indexed Absolute !a+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (X + Address).
4.2	Read Pointer	Store as Operand.
5.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

MOV (F6)	Cycles: 5	Size: 3
Y-Indexed Absolute !a+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Address.L.
2.1		Inc. PC .
2.2	Read PC	Store as Address.H.
3.1		Inc. PC .
3.2		
4.1		Pointer = (Y + Address).
4.2	Read Pointer	Store as Operand.
5.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
5.2	Read PC	Store as OpCode.
+X.1		

MOV (F7)	Cycles: 6	Size: 2
Indirect Y-Indexed [d]+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = (Operand ((PSW & \$20) << 3)).
3.2	Read Address	Store as Pointer.L.
4.1		
4.2	Read ((Address + 1) & \$FF) ((PSW & \$20) << 3)	Store as Pointer.H.
5.1		Address = (Y + Pointer).
5.2	Read Address	Store as Operand.
6.1		A = Operand. N flag = (A & \$80), Z flag = ! A .
6.2	Read PC	Store as OpCode.
+X.1		

MOV (F8)	Cycles: 3	Size: 2
Direct Page d (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand.
3.1		X = Operand. N flag = (X & \$80), Z flag = ! X .
3.2	Read PC	Store as OpCode.
+X.1		

MOV (F9)	Cycles: 4	Size: 2
Y-Indexed Direct Page d+Y (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((Y + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		X = Operand. N flag = (X & \$80), Z flag = ! X .
4.2	Read PC	Store as OpCode.
+X.1		

MOV (FA)	Cycles: 5	Size: 3
Direct Page to Direct Page dd, ds (Write)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
2.2	Read Address	Store as Operand1.
3.1		
3.2	Read PC	Store as Operand.
4.1		Inc. PC . Address = (Operand ((PSW & \$20) << 3)).
4.2	Write to Address	Write Operand1.
5.1		
5.2	Read PC	Store as OpCode.
+X.1		

MOV (FB)	Cycles: 4	Size: 2
X-Indexed Direct Page d+X (Read)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2	Read PC	Store as Operand.
2.1		Inc. PC .
2.2		
3.1		Address = ((X + Operand) & \$FF) ((PSW & \$20) << 3).
3.2	Read Address	Store as Operand.
4.1		Y = Operand. N flag = (Y & \$80), Z flag = ! Y .
4.2	Read PC	Store as OpCode.
+X.1		

INC (FC)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		Y += 1. N flag = (Y & \$80), Z flag = ! Y .
2.2		Store as OpCode.
+X.1		

MOV (FD)	Cycles: 2	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		
2.1		Y = A. N flag = (Y & \$80), Z flag = !Y.
2.2		Store as OpCode.
+X.1		

DBNZ (FE)	Cycles: 4-6	Size: 2
Relative r (Y)		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		Discard.
2.1		Address = (Operand ((PSW & \$20) << 3)).
2.2		
3.1		-- Y . Set Jump to (Y != 0).
3.2		Store as Operand.
4.1		Inc. PC . If !Jump, end instruction (next half-cycle is 6.2).
4.2		
5.1		Address = PC + i8(Operand). PC .L = Address.L.
5.2		
6.1		PC .H = Address.H.
6.2		Store as OpCode.
+X.1		

STOP (FF)	Cycles: 3	Size: 1
Implied		
Cycle	R/W	Desc.
-X.2	Read PC	Store as OpCode.
1.1		Inc. PC .
1.2		Discard.
2.1		
2.2		
3.1		Return to cycle 1 (next half-cycle is 1.2).