

4. No corresponding screen displayed when "Audio" or "Information" switch pressed.

INSPECTION PROCEDURE

1	Service check mode (Panel switch check mode screen)
---	---

NG

Troubleshoot for each diagnosis.

OK

2	Check AVC-LAN communication circuit (See page DI-275).
---	--

NG

Repair or replace AVC –LAN circuit.

OK

Replace the multi display.