Microarchitectural, Forensic, and Workload Memory Sampling on the Lenovo IdeaPad 5i (32 GiB)

The term memory sampling encompasses several distinct technical operations across computer architecture, systems programming, real-time media engineering, and digital forensics. When applied to the Lenovo IdeaPad 5i configured with 32 GiB of system memory, the operation refers to four technical disciplines: microarchitectural performance event sampling to identify cache-hierarchy stalls and memory-bus bottlenecks; real-time sample preload buffering within digital audio workstations; forensic volatile memory acquisition for incident response; and diagnostic bit-error stress testing and physical fault sampling. Executing these procedures effectively requires accounting for the physical topology of the device's memory subsystem, its Intel hybrid CPU architecture, platform power frameworks, and operating system virtualization layers.

Hardware Architecture and Memory Subsystem Topologies

The Lenovo IdeaPad 5i platform spans multiple hardware generations, primarily featuring Intel 13th Generation Raptor Lake-H processors (such as the Core i7-13620H) and Intel Core Ultra Series 1 Meteor Lake architectures (such as the Core Ultra 5 125H, Core Ultra 7 155H, and Core Ultra 9 185H)[1]. The 32 GiB memory configuration is implemented across two distinct physical topologies that dictate memory throughput, signaling latency, and hardware serviceability.

In mainstream revisions such as the IdeaPad Slim 5i 16IRH10 and 16IPH11, the 32 GiB configuration consists of two discrete 262-pin DDR5 Small Outline Dual In-Line Memory Module (SO-DIMM) slots populated in a symmetrical, dual-channel architecture[1]. Operating at a native signaling rate of DDR5-5600, each physical module implements two independent 32-bit wide memory sub-channels, yielding four 32-bit sub-channels across the platform[1]. This discrete configuration supports field replacement and hardware upgrades, while introducing moderate trace lengths and standard JEDEC CAS timing profiles[1].

Performance-oriented configurations—most notably the IdeaPad Slim 5i 14IMH9, Slim 5i 16IMH9, and IdeaPad Pro 5i 16IMH9—utilize soldered Low Power Double Data Rate 5X (LPDDR5x) memory[2]. Surface-mounted directly to the systemboard in a Ball Grid Array (BGA) topology, this 32 GiB layout operates at signaling rates up to LPDDR5x-7467 over a 128-bit aggregated wide bus (four 32-bit sub-channels)[2]. The soldered arrangement minimizes trace impedance and package power consumption, which benefits high-frequency transfers and graphics throughput[2]. However, the design is non-upgradable; a permanent hardware failure in any DRAM die requires replacing the entire systemboard[2].

Storage across both configurations interfaces over Peripheral Component Interconnect Express (PCIe) 4.0 x4 M.2 Non-Volatile Memory Express (NVMe) solid-state drives, maintaining

theoretical storage transfer ceilings of approximately $8\ \mathrm{GB/s}$ [1].

Platform Metric	IdeaPad Slim 5i (16IRH10 / DDR5)	IdeaPad Slim 5i / Pro 5i (16IMH9 / LPDDR5x)
Processor Family	Intel Raptor Lake-H (Core i7-13620H)[1]	Intel Core Ultra / Meteor Lake (Core Ultra 7 155H)[2]
Physical Topology	2x 262-pin DDR5 SO-DIMM slots[1]	Soldered systemboard BGA (Non-upgradable)[2]
Memory Bus Type	Dual-channel DDR5-5600[1]	Quad 32-bit sub-channel LPDDR5x-7467[2]
Peak Theoretical Bandwidth	$89.6\ \mathrm{GB/s}$	$119.5\ \mathrm{GB/s}$
Interconnect Latency Profile	Standard CAS latency; modular bus trace delay	Higher CAS latency; lower trace impedance
Storage Architecture	Dual M.2 PCIe 4.0 x4 (2242 + 2280)[1]	Dual M.2 PCIe 4.0 x4 (2242 + 2280)[2]
Firmware Power Management	Intel Dynamic Tuning / IPF[9]	Intel Innovation Platform Framework (IPF)[9]

Microarchitectural Memory Access Sampling and Hardware Event Profiling

Microarchitectural sampling uses hardware counters to analyze memory-access latencies, cache-miss penalties, and bus-saturation events across the memory hierarchy[10]. On an IdeaPad 5i, this analysis is governed by Intel's Performance Hybrid Architecture, which pairs high-throughput Performance Cores (P-cores) with area-efficient Efficient Cores (E-cores), supplemented on Meteor Lake architectures by Low Power Island E-cores[2].

Because the hardware Performance Monitoring Unit (PMU) implementation differs between core types, memory access profiling cannot rely on uniform hardware counters[13].

Hardware PMU Architecture on Hybrid Cores
- Performance Cores (P-Cores): Provide full Processor Event-Based Sampling (PEBS), precise load-latency capture (ldlat), and Data Linear Address (DLA) recording.
- Efficient Cores (E-Cores): Provide standard architectural counters with coarse event counting, lacking load-latency slicing and precise address attribution.

Hardware Event-Based Sampling Mechanisms

Intel Processor Event-Based Sampling (PEBS) provides the foundation for low-overhead memory profiling[10]. Traditional interrupt-driven performance counters incur interrupt skid: when a hardware counter overflows, the CPU triggers an Interrupt Service Routine (ISR), by which point the instruction pointer has moved past the instruction that caused the cache miss[10].

PEBS eliminates this skid by configuring internal hardware execution units to write the machine state, including the Data Linear Address (DLA) and execution metrics, directly into a dedicated virtual memory buffer upon counter overflow[10].

On the IdeaPad 5i, full PEBS memory profiling is supported exclusively on the P-cores[10]. P-cores support the MEM_TRANS_RETIRED event cluster, which isolates whether an access resolved in the L1 Data Cache, L2 unified cache, shared Last Level Cache (LLC), or system DRAM[13].

The P-core PMU also provides load-latency filtering, which records samples only when memory access latency exceeds a programmer-defined clock-cycle threshold[10]. Conversely, E-cores provide standard architectural counters that record uncore stalls and generic load counts without precise address attribution, meaning memory profiling frameworks must handle core topologies separately[10].

Implementation Frameworks

Software execution profiling across the IdeaPad 5i relies on three primary tooling ecosystems:

Intel VTune Profiler

Intel VTune Profiler uses its kernel-level Sampling Enabling Product (SEP) driver to configure the processor's Model-Specific Registers (MSRs) for Memory Access Analysis[14]. On hybrid platforms, VTune isolates thread migrations between core types, mapping memory transactions against uncore memory controller counters[14].

The tool generates bandwidth saturation curves, measures Last Level Cache hit rates, flags Data Translation Lookaside Buffer (dTLB) misses, and highlights NUMA-like access penalties caused by ring-bus or fabric contention between the compute and SoC tiles[18].

Linux Perf (perf mem)

Within Linux environments, the kernel exposes the hybrid architecture via separate PMU devices: cpu_core for P-cores and cpu_atom for E-cores[10]. Executing a precise memory profile requires configuring the sampling facility across these individual event sources:

```bash
# Capture memory loads and stores with load-latency filtering on P-cores
perf mem record -e cpu_core/mem-loads,ldlat=30/P,cpu_core/mem-stores/P -a -- sleep 10

# Inspect the resulting memory profile and cache-tier resolutions
perf mem report --stdio
```

The precise execution modifier /P configures the underlying hardware to invoke PEBS at maximum precision to eliminate instruction skid[10]. Setting ldlat=30 instructs the hardware to discard all load operations that resolve in fewer than 30 cycles, filtering out low-latency L1 and L2 cache hits so that the trace captures only Last Level Cache misses, DRAM access times, and interconnect stalls[15].

Windows Performance Analyzer (WPA)

On Windows installations, Event Tracing for Windows (ETW) provides low-overhead, kernel-level memory monitoring without requiring direct PMU access[13].

WPA evaluates memory sampling by logging hard and soft page faults, working set expansion, and thread context switches orchestrated by the Intel Thread Director[13]. This identifies memory starvation or paging bottlenecks within high-level user applications[21].

Profiling Tool	Kernel Interface	Hybrid Architecture Support	Profiling Capabilities
Intel VTune	Proprietary SEP Driver[14]	Fully unified across P-core and E-core topologies[17]	Bandwidth histograms, memory hierarchy diagrams, and latency attribution[18]
Linux perf mem	Kernel perf_events subsystem[20]	Separate cpu_core and cpu_atom PMU contexts[10]	Data Linear Address capture, precise latency slicing, and cache-tier breakdown[10]
Windows WPA	Event Tracing for Windows (ETW)[21]	Abstracted via Windows NT scheduler and	Working set analysis, virtual memory allocation

		Thread Director[13]	tracking, and hard page-fault rates[21]

Real-Time Audio Production: Virtual Instrument Sample Hosting and Buffer Constraints

In digital audio production, memory sampling refers to caching large multi-gigabyte sample-based virtual instruments—such as orchestral libraries in Native Instruments Kontakt, Steinberg HALion, or Spitfire Audio—directly within host memory[22]. On an IdeaPad 5i, a 32 GiB memory footprint serves as a dedicated sample-preload cache that balances real-time polyphony against storage subsystem overhead[22].



Direct-From-Disk (DFD) Memory Management

Because modern sample libraries often span hundreds of gigabytes, loading complete acoustic instrument profiles entirely into physical RAM is impractical[22]. Digital audio workstations address this through Direct-From-Disk (DFD) streaming engines[22].

When an instrument patch loads, the sampler places only the initial attack transient—the first 6 KB to 60 KB of each audio wave—into the physical RAM preload buffer[23]. When a MIDI note-on message triggers, the audio engine plays this in-memory transient immediately, giving the storage subsystem time to stream the sustained portion of the sample from disk into circular memory buffers[22].

On a 32 GiB IdeaPad 5i, configuring the DFD preload buffer size requires balancing memory capacity against the throughput of the internal PCIe 4.0 NVMe drive[1]:

- Setting a small preload buffer (6 KB to 12 KB) minimizes the RAM footprint per instrument[23]. This allows large templates to load within 6 GiB to 10 GiB of RAM, leaving headroom for host DAW operations and audio processing buffers. However, it places higher demand on the storage drive, requiring high random-read performance to prevent buffer underruns during dense polyphony[22].
- Setting a large preload buffer (48 KB to 60 KB) caches larger sample segments in memory, reducing storage transfer demands[23]. In dense arrangements, this approach

can consume 20 GiB to 26 GiB of RAM, increasing the risk of OS-level memory paging if the working set exceeds physical capacity[23].

Real-Time Interrupt Stalls: DPC Latency and ACPI.sys

Real-time audio processing operates under strict deterministic timing guarantees. Audio buffers (typically 64 to 256 samples at 48 kHz or 96 kHz) require processing windows between 0.66 ms and 5.33 ms. If a kernel-level hardware driver monopolizes a CPU core during this interval, the DAW misses its audio processing deadline, producing audible pops, clicks, or dropouts[21].

Consumer laptops like the Lenovo IdeaPad 5i often exhibit elevated Deferred Procedure Call (DPC) and Interrupt Service Routine (ISR) execution times[26]. Profiling real-time systems using diagnostic tools such as LatencyMon consistently exposes ACPI.sys as the primary contributor to latency spikes[26].



This elevated DPC latency stems from dynamic thermal throttling managed by Intel's Dynamic Tuning Technology / Innovation Platform Framework (DPTF / IPF) interacting with the Lenovo embedded controller[9]. As the processor transitions between C-states or alters Package Power Limits (PL_1/PL_2) to regulate surface temperatures, ACPI.sys halts the thread scheduler for periods exceeding $1000\,\mu s$, inducing audio dropouts[9].

Mitigating these dropouts requires setting the Windows Power Scheme to **Best Performance**, disabling PCI Express Link State Power Management, and using vendor-provided ASIO drivers rather than generic Windows audio endpoints[25].

DFD Preload Allocation	Preloaded Voice Capacity	NVMe Storage Read Demand	Primary Operational Bottleneck
6 KB (Aggressive Low-RAM)	$>$	High continuous random read load	Storage controller queue depth saturation

18 KB (Balanced Profile)	≈	Moderate sequential & random streaming	System DPC latency spikes (ACPI.sys)[26]
60 KB (Conservative Cache)	≈	Minimal storage streaming overhead	Physical memory capacity exhaustion and paging

Forensic Volatile Memory Acquisition and Cryptographic Artifact Extraction

In digital forensics and incident response (DFIR), memory sampling refers to capturing an exact, uncorrupted bit-stream image of physical RAM from an active system to preserve volatile evidence[31]. Capturing the 32 GiB physical address space of an IdeaPad 5i requires navigating modern OS security controls, hypervisor memory partitions, and disk encryption boundaries[32].

[redacted]

Windows Security Subsystems (VBS, HVCI, and BitLocker)

Modern IdeaPad 5i devices ship with Windows 11, where Virtualization-Based Security (VBS) and Hypervisor-Protected Code Integrity (HVCI) are enabled by default[34]. Operating through Intel VT-x hardware virtualization, Microsoft's Hyper-V hypervisor partitions physical execution into Virtual Trust Levels[34]:

- Virtual Trust Level 0 (VTL 0) hosts the standard Windows operating system, user applications, and standard device drivers, including the core NT executive kernel (ntoskrnl.exe)[34].
- Virtual Trust Level 1 (VTL 1) hosts the isolated Secure World, containing the Secure Kernel (securekernel.exe), isolated security authorities, and Local Security Authority Subsystem Service (LSASS) credentials protected by Credential Guard[34].

Legacy acquisition tools that attempt to capture physical memory by mapping \Device\PhysicalMemory fail or cause system crashes under HVCI[36]. Modern acquisition suites—such as DumpIt, Magnet RAM Capture, and FTK Imager—use signed, hypervisor-aware

kernel drivers to capture volatile memory[31].
However, because the hypervisor protects VTL 1 memory, standard memory dumps capture only VTL 0 physical addresses. The memory pages assigned to VTL 1 remain hardware-isolated by Hyper-V and appear as zero-filled pages or unmapped blocks[34].

Linux Kernel Lockdown and Module Restrictions

When investigating an IdeaPad 5i running Linux with UEFI Secure Boot enabled, the kernel automatically engages Kernel Lockdown Mode, enforcing either the integrity or confidentiality security policy[32]. This security layer restricts direct access to /dev/mem, /dev/kmem, and /dev/crash[32].
Loadable Kernel Modules (LKMs) such as LiME (Linux Memory Extractor) cannot load into kernel space unless they are cryptographically signed with a private key whose corresponding public certificate is enrolled in the system's Machine Owner Key (MOK) database[32]. Attempting to load an unsigned lime.ko via insmod returns an immediate permission error[32].
To bypass this restriction without modifying the system's Secure Boot state, examiners use user-space acquisition tools such as AVML (Acquire Volatile Memory for Linux)[32]. AVML reads from the /proc/kcore interface via a statically linked binary, allowing volatile memory acquisition on modern kernels without requiring custom driver compilation or MOK enrollment[32]:

```bash
# Execute volatile memory acquisition on a Secure Boot Linux platform
sudo ./avml --compress /mnt/external_usb/ideapad_live_ram.lime.compressed
```

Decryption Key Sampling with Volatility 3

Because modern IdeaPad systems enable BitLocker encryption tied to the hardware TPM 2.0 by default, capturing volatile memory is essential for recovering mounted volume keys[6]. When a BitLocker-protected partition is mounted, the operating system holds the Full Volume Encryption Key (FVEK) in non-paged kernel memory pools to service active file reads and writes[33].
Extracting these keys from a 32 GiB memory dump bypasses the TPM and eliminates the need to brute-force the user passphrase[33].
Using the Volatility 3 framework, examiners scan non-paged pool memory allocations for signatures used by the BitLocker driver (fvevol.sys)[39]. The extraction plugin scans pool tags (including FVEc, Cngb, and dFVE) to isolate the Full Volume Encryption Key and its accompanying AES-XTS tweak keys[41]:

```
Bash
# Extract the BitLocker FVEK and export it for filesystem mounting
vol -f ideapad_live_ram.raw windows.bitlocker.BitlockerFVEKScan --dislocker

# Mount the encrypted storage volume on an analysis workstation using the recovered FVEK
sudo dislocker -V /dev/nvme0n1p3 -k 0x8087865bead0-Dislocker.fvek -- /mnt/dislocker
sudo mount -t ntfs-3g -o loop /mnt/dislocker/dislocker-file /mnt/decrypted
```

Operating System Context	Security Boundary	Recommended Acquisition Tool	Extractable Cryptographic Artifacts
Windows 11 (VBS / HVCI)	Hypervisor memory isolation[34]	Magnet RAM Capture / DumpIt / FTK Imager[31]	BitLocker FVEK, VMK, and cleartext credentials[33]
Linux (UEFI Secure Boot)	Kernel Lockdown enforcement[32]	Microsoft AVML (via /proc/kcore)[32]	dm-crypt / LUKS master keys[39]
Firmware TPM Binding	Platform Configuration Registers[34]	Live driver-based memory acquisition[31]	AES volume master keys stored in RAM pools[33]

Diagnostic Bit-Error Sampling and DRAM Physical Integrity

Diagnostic memory sampling evaluates physical DRAM reliability, timing margins, and resilience against electromagnetic crosstalk[42]. Testing modern memory subsystems requires accounting for the structural differences between traditional error-correcting memory and the standard protections deployed in modern DDR5 platforms[44].

```
Comparison of Memory Error-Correction Architectures
- On-Die ECC (DDR5 / LPDDR5x): Correction occurs inside the DRAM die to repair silicon cell leakage. Corrected errors are not reported to the CPU memory controller or operating system.
- Side-Band ECC (Server / Workstation): Correction occurs at the CPU memory controller using dedicated bus lines. Single-bit and multi-bit faults are logged to system firmware.
```

and OS event logs

On-Die ECC (ODECC) Mechanics and Limitations

The JEDEC specifications for both DDR5 and LPDDR5x mandate the integration of On-Die ECC (ODECC)[44]. Because modern high-density memory is manufactured using advanced sub-20nm fabrication nodes, individual DRAM storage cells suffer from higher charge leakage and internal defect rates[44].

ODECC implements error-correction circuitry directly within the memory chips, computing internal parity bits for each access[44].

However, On-Die ECC differs fundamentally from traditional Side-Band ECC found in server hardware[44]:

- ODECC detects and corrects single-bit errors *only* within the internal DRAM storage die[44].
- It provides zero protection against transmission errors across the physical memory bus between the DRAM chips and the processor's memory controller[44].
- Memory errors corrected by ODECC are resolved silently inside the chip without signaling the processor or logging events to the operating system[42].

Diagnostic tools such as MemTest86 or Memtest86+ running on an IdeaPad 5i will register zero errors when single-bit faults occur, as the physical DRAM die quietly corrects them before the data crosses the bus[42]. Only double-bit or multi-bit errors that exceed the correction capability of the on-die Hamming/parity codes surface as visible test failures[42].

Rowhammer Vulnerability and Pattern Stress Testing

Diagnostic memory testing also maps vulnerability to disturbance errors caused by high-frequency cell activations, known as Rowhammer[42]. By executing rapid, repeated read operations against adjacent memory rows ("aggressors"), charge can leak into unaddressed neighboring cells ("victims"), causing bit-flips[42].

Advanced diagnostic passes evaluate row disturbance thresholds across several test patterns[42]:

- Moving Inversions alternates blocks of zeros and ones across physical memory boundaries to surface simple stuck-at faults and address-line decoding defects[42].
- Hammering Sweeps uses aggressive dual-sided address-pair hammering to test whether Target Row Refresh (TRR) mitigations built into the DDR5 memory modules and memory controller successfully refresh vulnerable victim rows before bit-flips occur[42].

On 32 GiB DDR5 configurations, the high activation frequencies achieved during these sweeps evaluate whether the memory controller's refresh intervals prevent disturbance errors without degrading overall bus performance[43].

Fault Mechanism	Detection Tools	ODECC Masking Behavior	Remediation Path on IdeaPad 5i

DRAM Cell Stuck Bit	MemTest86 (Tests 4–9)[42]	Silently corrects single-bit defects; fails on multi-bit faults[42]	Replace module (Slim 5i)[1] or systemboard (soldered)[2]
Bus Signaling Fault	MemTest86 (Test 3)[42]	Visible; ODECC does not protect the data bus[44]	Reseat SO-DIMM (Slim 5i) or downclock memory bus
Rowhammer Bit-Flip	MemTest86 (Test 11 / Rowhammer)[42]	Single-bit flips often masked; multi-bit flips trigger exceptions[42]	Update UEFI firmware to adjust Target Row Refresh (TRR) timings

System Optimization and Operational Guidelines

Optimizing memory sampling across the Lenovo IdeaPad 5i requires tailoring system settings to the physical topology, CPU architecture, and target operating system. The following guidelines address hardware stability, real-time performance, and evidence integrity across deployment environments.

Performance Profiling Configurations

When collecting hardware performance events with tools like Linux perf or Intel VTune Profiler, target memory counters to P-core affinities[10]. Because Intel hybrid processors feature asymmetric PMU architectures, uniform system-wide collection risks dropping events or skewing metrics across core types[14].

Setting sampling thresholds to ignore low-latency access (e.g., ldlat=30) ensures collection captures true Last Level Cache misses and main memory traffic rather than redundant L1 and L2 cache hits[15].

Real-Time Audio Tuning

To prevent audio dropouts during heavy sample playback, reduce real-time DPC latency bottlenecks:

- Set the Windows power plan to **Best Performance** to prevent frequent, latency-inducing processor C-state transitions[25].
- Disable PCIe Link State Power Management to maintain consistent bus access for audio peripherals and internal storage[25].
- Tune Direct-From-Disk (DFD) preload caches according to the physical drive's read characteristics[22]. A balanced preload buffer between 18 KB and 24 KB maximizes polyphony across a 32 GiB memory budget without saturating the internal PCIe 4.0 NVMe storage bus[1].

Digital Forensics Procedures

During live incident response, account for active platform security boundaries:

- On Windows 11 systems running Virtualization-Based Security (VBS) and Hypervisor-Protected Code Integrity (HVCI), deploy modern hypervisor-aware acquisition tools rather than legacy physical-memory dump utilities[34].
- On Linux installations protected by UEFI Secure Boot and Kernel Lockdown, capture memory through user-space mechanisms like AVML (/proc/kcore) to avoid module signature rejections[32].
- For BitLocker-encrypted systems, extract the active Full Volume Encryption Keys (FVEK) from volatile memory pools before shutting down or disconnecting the device to simplify volume recovery[33].

Diagnostic Verification

When troubleshooting memory stability with utilities such as MemTest86, recognize that clean test results do not completely rule out hardware degradation on DDR5 or LPDDR5x platforms[42]. Because On-Die ECC silently corrects single-bit faults inside the memory chips, routine tests only report errors when degradation exceeds internal correction limits[42].

On models utilizing discrete SO-DIMM slots (such as the IdeaPad Slim 5i 16IRH10), failing test runs can be resolved by replacing individual modules[1]. On variants with soldered LPDDR5x memory (such as the Pro 5i 16IMH9), uncorrectable hardware errors require servicing or replacing the systemboard[2].

Works cited

1. IdeaPad Slim 5 16IRH10 - Product - Lenovo PSREF, https://psref.lenovo.com/Product/IdeaPad/IdeaPad_Slim_5_16IRH10
2. IdeaPad Pro 5 16IMH9 - Product - Lenovo PSREF, https://psref.lenovo.com/product/IdeaPad/IdeaPad_Pro_5_16IMH9
3. IdeaPad Slim 5 16IMH9 - Specifications - Lenovo PSREF, https://psref.lenovo.com/Detail/ideapad_slim_5_16imh9?M=83DC00A1TW
4. IdeaPad Slim 5 16IPH11 - Product - Lenovo PSREF, https://psref.lenovo.com/Product/IdeaPad/IdeaPad_Slim_5_16IPH11?MT=83S6
5. IdeaPad Slim 5 14IMH10 - Product - Lenovo PSREF, https://psref.lenovo.com/Product/IdeaPad/IdeaPad_Slim_5_14IMH10
6. IdeaPad Slim 5 14IMH9 - Lenovo PSREF, https://psref.lenovo.com/syspool/Sys/PDF/IdeaPad/IdeaPad_Slim_5_14IMH9/IdeaPad_Slim_5_14IMH9_Spec.PDF
7. IdeaPad Slim 5 16IMH9 - Specifications - Lenovo PSREF, https://psref.lenovo.com/Detail/ideapad_slim_5_16imh9?M=83DC00ADAU
8. IdeaPad Slim 5 14AKP10 - Lenovo PSREF, https://psref.lenovo.com/syspool/Sys/PDF/IdeaPad/IdeaPad_Slim_5_14AKP10/IdeaPad_Slim_5_14AKP10_Spec.PDF
9. Easily Disable Intel DPTF / IPF (Power Throttling) for Good, https://bradshacks.com/disable-dptf/
10. perf-record(1) - Arch manual pages,

https://man.archlinux.org/man/perf-record.1.en
11. PerformanceAnalysisAndTuning, https://www.scribd.com/document/812432827/PerformanceAnalysisAndTuningOnModernCPUs-SecondEdition
12. x86 - Wikipedia, https://en.wikipedia.org/wiki/X86
13. Intel® 64 and IA-32 Architectures Optimization Reference Manual, https://cdrdv2-public.intel.com/821613/355308-Software-Optimization-Manual-048-Changes-Doc-2.pdf
14. Intel® VTune™ Profiler Release Notes and New Features, https://www.intel.com/content/www/us/en/developer/articles/release-notes/vtune-profiler/legacy.html
15. [PATCH V2 0/5] Clean up perf mem - Mailing Lists, https://lists.infradead.org/pipermail/linux-arm-kernel/2023-December/887739.html
16. Cookbook - Intel, https://cdrdv2-public.intel.com/817273/vtune-profiler_cookbook_2024.1-766316-817273.pdf
17. Hybrid CPU Analysis - Intel, https://www.intel.com/content/www/us/en/docs/vtune-profiler/user-guide/2026-0/hybrid-cpu-analysis.html
18. Enhance GenAI LLMs performance using Intel VTune Profiler, https://www.intel.com/content/www/us/en/developer/articles/technical/enhance-genai-llm-performance-using-vtune-profiler.html
19. CPU Hardware Architecture and Performance Optimization - Indico, https://indico.cern.ch/event/1377435/contributions/5788940/attachments/2874689/5033970/tcsc24-cpu.pdf
20. perf-record(1) - Linux manual page - man7.org, https://man7.org/linux/man-pages/man1/perf-record.1.html
21. DPC latency issues while gaming : r/Amd - Reddit, https://www.reddit.com/r/Amd/comments/qe79f2/dpc_latency_issues_while_gaming/
22. Questions about Gigfile size and RAM management, https://community.gigperformer.com/t/questions-about-gigfile-size-and-ram-management/16746
23. Where is my bottleneck? - Cockos Incorporated Forums, https://forums.cockos.com/showthread.php?p=1844412
24. Hi Folks, is that normal? I'm running a project with a dozen Kontakt 5, https://www.facebook.com/groups/543628065696081/posts/889381451120739/
25. P16-gen-3-high-latency-device-disconnections-and-crackling-sound, https://forums.lenovo.com/t5/ThinkPad-P-and-W-Series-Mobile-Workstations/P16-gen-3-high-latency-device-disconnections-and-crackling-sound-from-USB-audio-interface/m-p/10042692
26. Help need with Laptop - PianoClack Forum, https://pianoclack.com/forum/d/1564-help-need-with-laptop
27. Lenovo IdeaPad Slim 9i Laptop Review: Luxurious Looks, Terrible,

https://www.notebookcheck.net/Lenovo-IdeaPad-Slim-9i-Laptop-Review-Luxurious-Looks-Terrible-Touchpad.514191.0.html
28. Gaming laptop for Traktor : r/traktorpro - Reddit, https://www.reddit.com/r/traktorpro/comments/1lpdesx/gaming_laptop_for_traktor/
29. USB-Audio-Pops-Clicks-During-CPU-Idle-High-ACPI-DPC-Latency, https://forums.lenovo.com/t5/ThinkPad-P-and-W-Series-Mobile-Workstations/ThinkPad-P14s-Gen-4-Intel-%E2%80%93-USB-Audio-Pops-Clicks-During-CPU-Idle-High-ACPI-DPC-Latency/m-p/10046460
30. TS5Plus+ USB latency/stutter with ThinkPad P14s Gen 6 (Intel Core, https://www.reddit.com/r/CalDigit/comments/1pt4yrr/ts5plus_usb_latencystutter_with_thinkpad_p14s_gen/
31. Analyzing Tor Browser Artifacts for Enhanced Web Forensics ... - MDPI, https://www.mdpi.com/2078-2489/15/8/495
32. Linux Baseline & Forensic Triage Tool (LBFTT) - GitHub, https://github.com/jgasmussen/Linux-Baseline-and-Forensic-Triage-Tool
33. CH8: Windows Memory Forensics - Professor Busch's CFS Resources, https://cfs.fyi/eBooks/CFS137/CH08_Memory_Forensics/
34. (PDF) Analyzing Tor Browser Artifacts for Enhanced Web Forensics, https://www.researchgate.net/publication/383258888_Analyzing_Tor_Browser_Artifacts_for_Enhanced_Web_Forensics_Anonymity_Cybersecurity_and_Privacy_in_Windows-Based_Systems
35. EDR Tradecraft: Internals, Detection, Evasion & Advanced Researchg, https://0xdbgman.github.io/posts/edr-internals-research-and-bypass/
36. Windows Acquisition with WinPmem | Ridgeline Cyber Defence, https://ridgelinecyber.com/training/modules/free/mf01-memory-acquisition/02-winpmem-windows-capture/
37. intel-codex/Security/Analysis/sop-forensics-investigation.md at main, https://github.com/gl0bal01/intel-codex/blob/main/Security/Analysis/sop-forensics-investigation.md
38. Linux Forensics | PDF | Network Socket | File System - Scribd, https://www.scribd.com/document/507077872/Linux-Forensics
39. Memory Forensics - Trackr.Live, https://www.trackr.live/digital-forensics/memory-forensics/
40. picoCTF 2025 — Forensics Track: A Complete Walkthrough | Medium, https://medium.com/@akumar54/picoctf-2025-forensics-track-a-complete-walkthrough-15f998b88f3d
41. lorelyai/volatility3-bitlocker: Volatility 3 plugin for extracting ... - GitHub, https://github.com/lorelyai/volatility3-bitlocker
42. The Open-Source Memory Testing Tool - Memtest86+, https://memtest.org/readme
43. A Fault Injection Platform for Rowhammer Research on DDR5 Memory, https://uasc.cc/proceedings25/uasc25-gloor.pdf
44. ECC memory - Wikipedia, https://en.wikipedia.org/wiki/ECC_memory
45. Error-Correcting RAM On The Desktop - Hackaday,

https://hackaday.com/2023/10/12/error-correcting-ram-on-the-desktop/
46. Rethinking the Producer-Consumer Relationship in Modern DRAM, https://arxiv.org/html/2401.16279v1
47. ECC Technical Details - MemTest86, https://www.memtest86.com/ecc.htm
48. Phoenix root privilege escalation attack proves that Rowhammer still, https://www.tomshardware.com/tech-industry/cyber-security/modern-memory-is-still-vulnerable-to-rowhammer-vulnerabilities-phoenix-root-privilege-escalation-attack-proves-that-rowhammer-still-smashes-ddr5-security-to-bits
49. Helmut Neukirchen » iKOOLCORE R2 with In-Band ECC support, https://uni.hi.is/helmut/2024/07/02/ikoolcore-r2-with-in-band-ecc-support/