

LOT SYSTEMS

COSMO[®] Cube

Quick Start Guide

A hardware node connected to the LOT Systems platform.

40mm × 40mm × 5mm · 316L stainless steel · Made for lot-systems.com

What is COSMO® Cube?

COSMO® Cube is an ambient intelligence device that sits on your desk. It receives autonomous notifications from the AI at lot-systems.com (e.g. “Coffee time!”), reads the room with weather and motion sensors, and logs a moment back to your LOT Log tab whenever you press the single Copy button on its face.

It is not a phone and it is not a screen you scroll. One display, one button, one camera — a quiet companion, not another feed.

In the Box

Item	Qty
COSMO® Cube device	1
Qi wireless charging pad	1
USB-C to USB-A cable (for charging pad)	1
Microfiber cloth	1
Quick Start Guide (this document)	1

Setup

1. Charge

Place COSMO® Cube face-up on the charging pad, mirror-polished side down. The status LED pulses white while charging, solid green at full charge (~2.5 hours from empty).

2. Pair

Open lot-systems.com on your phone or laptop, sign in, and go to Settings → My Devices → Add COSMO® Cube. Hold the Copy button for 3 seconds until the LED blinks blue to enter pairing mode.

3. Connect to Wi-Fi

Select your 2.4GHz network from the list shown on the LOT web app and enter your password. The Cube confirms with a single green blink.

4. Place it

Set the Cube on your desk, satin side up, where you can see it without looking for it. Weather and motion sensors need open air on the right edge — avoid boxing it in.

5. First notification

Once connected, the LOT AI will send its first message to the OLED display within a few minutes based on your current Index of Systems state.

The Copy Button

Press once to log the current moment — timestamp, temperature, humidity, light level, and orientation — to your LOT Log tab, tagged **[COSMO® Cube]**. There is no undo and no edit: it is a deliberate gesture, not a draft. Double-press to dismiss the notification currently on screen. Hold 3 seconds to re-enter pairing mode.

Care

Wipe the mirror-polished back with the included microfiber cloth only. IP54 splash resistant — do not submerge. Operating range 0°C to 45°C. Avoid the weather-mesh vent on the right edge when cleaning.

Specifications

Dimensions	40 × 40 × 5 mm
Weight	~28 g
Body	316L stainless steel, 2-part CNC
Display	1.0" SSD1327 OLED, 128×128, grayscale
Connectivity	Wi-Fi 802.11n 2.4GHz, BLE 5.0
Charging	Qi wireless, 5W
Sensors	BME280 weather, ICM-42688-P IMU, APDS-9960 light/gesture

Full manual, firmware developer guide, and API integration guide: [docs/hardware/](#) at [github.com/LOT-Systems/LOT-Computer](#) · Support: [lot-systems.com/about](#)
COSMO® CIA · LOT Systems, Inc. · Made in the USA.