

API-CONNECTOR-SPEC

LOT Computer — API Connector Spec (draft v0.1)

Not implemented. Proposed additions to `src/server/routes/` (new `device-api.ts`).

Auth

Today `/api` is session-cookie only. Add per-device bearer tokens: Authorization: Bearer `lotdev_<32 bytes>`; store SHA-256 hash in a new `devices` table (`id`, `userId`, `name`, `tokenHash`, `serial`, `lastSeenAt`, `revokedAt`). Pairing: user taps “Add device” in site settings -> 6-digit code (5 min TTL) -> device calls `POST /api/device/pair {code, serial}` -> receives token once. Rate-limit and TLS only.

Endpoints

Method	Path	Purpose
POST	<code>/api/device/pair</code>	Exchange code for token
GET	<code>/api/device/notifications?since=<iso></code>	Poll (30 s default; Retry-After honored). Optional SSE upgrade later using existing sync layer
POST	<code>/api/device/ack {id}</code>	Notification displayed/dismissed
POST	<code>/api/device/event {type:"copy", ts, battery, rssi}</code>	Button press -> creates Log row event='device_copy', text='Copy', metadata={deviceId,...}
POST	<code>/api/device/telemetry {temp,rh,pressure,gas_iaq,uv,lux}</code>	Batched every 5–15 min; optional Log device_telemetry
GET	<code>/api/device/config</code>	Poll interval, quiet hours, brightness

Notification payload: `{id, text (<=64 chars), level: "info|alert", haptic: "short|double|long", expiresAt}`. Text is produced by an AI job on the site (e.g. “Coffee time!”) and must be plain text, length-capped server-side.

Log tab

`displayableEvents` in GET `/api/logs` is a whitelist: **add `device_copy`** (and optionally `device_telemetry`) or presses won’t show.

Security

Tokens revocable; devices cannot read user data other than their own notification queue; no inbound ports on device; camera frames are NOT uploaded unless a future explicit user action (separate endpoint, out of scope v1).

Companion software (req 10)

v1: browser WebSerial/WebUSB flasher + config page (Wi-Fi creds, pairing code) served from the site; fallback: esptool + CLI lotdev provision.