

```

#include _____ //头文件

unsigned char code discoedDot []={0xbf,0x86,0xdb,0xcf,0xe6,0xed,0xfd,0x87,0xff,0xef}; //带小数点
unsigned char code discodeNormal[]={0x3f,0x06,0x5b,0x4f,0x66,0x6d,0x7d,0x07,0x7f,0x6f}; //不带小数点
unsigned char timer=0; //记录中断次数
unsigned int second; //储存秒
unsigned char key=0; //记录按键次数
Main() //主函数
{
    TMOD=_____ ;
    ET0=_____ ;
    EA=_____ ;
    second=300;
    P0=discodeNormal[_____];
    P2=discoedDot[_____];
    P1=discodeNormal[_____];
    while(1) //按键次数循环
    {
        if((P3&0x80)==_____) //判断是否按P3.7键按下
        {
            key++;
            switch(key)
            {
                case 1:
                    TH0=_____ ;
                    TL0=_____ ;
                    TR0=1;
                    break;
                case 2:
                    TR0=0;
                    break;
                case 3:
                    key=0;
                    second=300;
                    P0=discodeNormal[_____];
                    P2=discoedDot[_____];
                    P1=discodeNormal[_____];
                    break;
            }
            while((P3&0x80)==0x00);
        }
    }
}

void int_T0() _____ //定时器中断函数
{
    TR0=0;
    TH0=_____ ;
    TL0=_____ ;
    timer++;
    if(timer==_____)
    {
        timer=0;
        second--;
        P0=discodeNormal[_____];
        P2=discoedDot[_____];
        P1=discodeNormal[_____];
    }

    if(second==0)
    {
        TR0=0;
    }
}

```

```
    second=300;  
    key=2;  
}  
else  
{  
    TR0=1;  
}  
}
```