

```
/****** writer:shopping.w ******/
#include <reg52.h>
#define uint unsigned int
#define uchar unsigned char
sbit LED1 = P1^0;
sbit LED2 = P1^3;
sbit K1 = P1^7;
uchar Operation_N0 = 0;
uchar code DSY_CODE[]=
{
    0x3f,0x06,0x5b,0x4f,0x66,0x6d,0x7d,0x07,0x7f,0x6f
};

void Delay(uint x)
{
    uchar i;
    while(x--)
    {
        for(i=0;i<120;i++);
    }
}

void putc_to_SerialPort(uchar c)
{
    SBUF = c;
    while(TI == 0);
    TI = 0;
}

void main()
{
    LED1=LED2=1;
    P0 = 0x00;
    SCON = _____; //补充完整
    TMOD = _____; //补充完整
    PCON = 0x00;
    TH1 = 0xfd;
    TL1 = 0xfd;
    TI = 0;
    RI = 0;
    TR1 = _____; //补充完整
    IE = 0x90;
    while(1)
    {
        Delay(100);
        if(K1 == 0)
        {
            while(K1==0);

            switch(Operation_N0)
            {
                case 0:
                    putc_to_SerialPort(0);
                    LED1=LED2=1; break;
                case 1:
                    putc_to_SerialPort(1);
                    LED1=0;LED2=1;break;
                case 2:
                    putc_to_SerialPort(2);
                    LED2=0;LED1=1;break;
                case 3:
                    putc_to_SerialPort(3);
                    LED1=0;LED2=0;break;
                case 4:
            }
```

```
        putc_to_SerialPort(4);
        LED1=0;LED2=0;break;
    }
    Operation_N0=(Operation_N0+1)%5;
}
}
}

void Serial_INT() _____ //补充完整
{
    if(RI)
    {
        RI = _____; //补充完整
        if(SBUF>=0&&SBUF<=9)
            P0 = DSY_CODE[ _____]; //补充完整
        else
            P0 = 0x00;
    }
}
```