32.6.154 SW_PAD_CTL_PAD_GPIO1_IO01 SW PAD Control Register (IOMUXC_SW_PAD_CTL_PAD_GPIO1_IO01)

SW_PAD_CTL Register

Address: 20E_0000h base + 2ECh offset = 20E_02ECh

Bit	31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16
R W	Reserved															HYS
Reset	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0

Bit	15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
R W	PUS		PUE	PKE	ODE	Reserved			SPEED		DSE			Reserved		SRE
Reset	0	0	0	1	0	0	0	0	1	0	1	1	0	0	0	0

IOMUXC_SW_PAD_CTL_PAD_GPIO1_IO01 field descriptions

Field	Description
31–17 -	This field is reserved. Reserved
16 HYS	Hyst. Enable Field Select one out of next values for pad: GPIO1_IO01 0 **HYS_0_Hysteresis_Disabled** — Hysteresis Disabled 1 **HYS_1_Hysteresis_Enabled** — Hysteresis Enabled
15–14 PUS	Pull Up / Down Config. Field Select one out of next values for pad: GPIO1_IO01 00 **PUS_0_100K_Ohm_Pull_Down** — 100K Ohm Pull Down 01 **PUS_1_47K_Ohm_Pull_Up** — 47K Ohm Pull Up 10 **PUS_2_100K_Ohm_Pull_Up** — 100K Ohm Pull Up 11 **PUS_3_22K_Ohm_Pull_Up** — 22K Ohm Pull Up
13 PUE	Pull / Keep Select Field Select one out of next values for pad: GPIO1_IO01 0 **PUE_0_Keeper** — Keeper 1 **PUE_1_Pull** — Pull
12 PKE	Pull / Keep Enable Field Select one out of next values for pad: GPIO1_IO01 0 **PKE_0_Pull_Keeper_Disabled** — Pull/Keeper Disabled 1 **PKE_1_Pull_Keeper_Enabled** — Pull/Keeper Enabled
11 ODE	Open Drain Enable Field Select one out of next values for pad: GPIO1_IO01

Table continues on the next page...

IOMUXC_SW_PAD_CTL_PAD_GPIO1_IO01 field descriptions (continued)

Field	Description
	0 **ODE_0_Open_Drain_Disabled** — Open Drain Disabled 1 **ODE_1_Open_Drain_Enabled** — Open Drain Enabled
10–8 -	This field is reserved. Reserved
7–6 SPEED	Speed Field Select one out of next values for pad: GPIO1_IO01 00 **SPEED_0_low_50MHz_** — low(50MHz) 01 **SPEED_1_medium_100MHz_** — medium(100MHz) 10 **SPEED_2_medium_100MHz_** — medium(100MHz) 11 **SPEED_3_max_200MHz_** — max(200MHz)
5–3 DSE	Drive Strength Field Select one out of next values for pad: GPIO1_IO01 000 **DSE_0_output_driver_disabled_** — output driver disabled; 001 **DSE_1_R0_260_Ohm___3_3V__150_Ohm_1_8V__240_Ohm_for_DDR_** — R0(260 Ohm @ 3.3V, 150 Ohm@1.8V, 240 Ohm for DDR) 010 **DSE_2_R0_2** — R0/2 011 **DSE_3_R0_3** — R0/3 100 **DSE_4_R0_4** — R0/4 101 **DSE_5_R0_5** — R0/5 110 **DSE_6_R0_6** — R0/6 111 **DSE_7_R0_7** — R0/7
2–1 -	This field is reserved. Reserved
0 SRE	Slew Rate Field Select one out of next values for pad: GPIO1_IO01 0 **SRE_0_Slow_Slew_Rate** — Slow Slew Rate 1 **SRE_1_Fast_Slew_Rate** — Fast Slew Rate