

I	MANUALE D'ISTRUZIONE	Apparecchiatura di comando 2 Motori 12Vdc
E	ISTRUCCIONES DE USO	Cuadro electronico para dos motores 12Vdc
GB	INSTRUCTION MANUAL	Elettronic control panel for two 12Vdc motors
F	MODE D'EMPLOI	Dispositif de commande 2 moteurs 12Vdc
P	INSTRUÇÕES DE USO	Central de controle de 2 motores 12Vdc

EURO12M2

[code E109]



CE



ATTENZIONE!! Prima di effettuare l'installazione, leggere attentamente questo manuale.

La VDS declina ogni responsabilità in caso di non osservanza delle normative vigenti.

¡ATENCIÓN!! Antes de efectuar la instalación, lea atentamente el presente manual. La Empresa VDS no asumirá responsabilidad alguna en caso de inobservancia de las normas vigentes en el país donde se lleva a cabo la instalación.

WARNING!! Before installing, thoroughly read this manual that is an integral part of this Kit. VDS declines any responsibility in the event current standards in the country of installation are not complied with.

ATTENTION!! Avant d'effectuer l'installation, lire attentivement le présent manuel qui fait partie intégrante de cet emballage. La société VDS décline toute responsabilité en cas de non respect des normes en vigueur.

ATENÇÃO!! Antes de instalar, leia este manual. VDS isenta de qualquer responsabilidade pelo não cumprimento com os regulamentos.



Instruction Manual

(EURO 12 M2)

ACCESSORIES				SAFETY				SETTINGS																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																												
●	●	+	+																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																																	</

□ STANDARD • OPTIONAL + NOT AVAILABLE

WORKING

Automatic manoeuvres are carried out using the START, STOP, PED, switches and if required using the radio buttons.

The manoeuvre finishes under any of the following conditions: by activating the corresponding End of Process or due to working time finishing.

Activating STOP will immediately stop the manoeuvre and new instructions will be required to start again.

Activating the Safety Contact during the closing manoeuvre will cause the inverse, going to the opening manoeuvre.

The contact for Garage Light is activated 0,5 sec. before starting the opening manoeuvre and deactivated 3 min. after starting.

To regulate engine power selected in POWER, is applied after 2 sec. from starting the manoeuvre.

Suspension time (selected in the working time programme) is the time before finishing the manoeuvre that the engine will work in suspension mode. In POWER SLOW we can select engine speed in suspension period when I7 is ON.



After connect the alimentation, the first move must begin with the closing of the two doors until you find the closing limit switch.

TIME PROGRAMMING for working and automatic closing.

In order to programme working times and automatic lowering the control panel must be stable, closed gate position. We should choose I7 at ON if we want smooth stoppage.

Press PROG for 1,5 seconds. The red Led lights up intermittently, indicating that the equipment is ready to programme times. Now we can programme the times. To stop the programming press the PROG button again for 1,5 seconds with the gate on standby; the programming process stops automatically when the gate finalises the whole cycle.

1) Starting from the closed gate position we activate the time programme mode as indicated above, the red Led lights up intermittently.

2) Start the manoeuvre to open engine 1 pressing "GATE 1" (Located on top of the connection terminal plaque).

3) Once the required time phase has passed between the 2 engines, start the opening manoeuvre of engine 2 pressing "GATE 2".

4) **I7 OFF** -Pressing "GATE 1" again stops the manoeuvre and memorises the opening time; if the manoeuvre is finalised by activating the end of opening process for engine 1 (FCA1) the time passed plus 4 sec will be memorised. Likewise, activate "GATE 2" to stop the manoeuvre of engine 2 and memorise its opening time. If the engine 2 manoeuvre is stopped due to the end of opening process (FCA2) 4 sec will be added to the memorised time.

I7 ON – With option I7 activated, pressing "GATE 1" engine 1 will work in suspension mode and pressing "GATE 1" a second time we can stop the manoeuvre and the opening time and suspension time will be memorised; if the manoeuvre is finalised by activating the end of opening process for engine 1 (FCA1) the time passed plus 4 sec will be memorised. Once engine 1 time has been memorised repeat the process for engine 2 using "GATE 2". Likewise, if finalising opening manoeuvre with end of opening process (FCA2) 4 sec. will be added to the memorised time.

5) With the gate open, automatic lowering time is memorised until starting the closing manoeuvre. If the time between finalising the opening and starting the closure is less than 3 sec. it is considered that there is no automatic lowering.

6) Start engine 2 closure manoeuvre pressing "GATE 2".

7) Once the required time phase has passed between the 2 engines, start the closure manoeuvre of engine 1 pressing "GATE 1".

8) **I7 OFF** -Pressing "GATE 2" again stops the manoeuvre and memorises the closing time; if the closing manoeuvre is finalised by activating the end of closing process for engine 2 (FCC2) the time passed plus 4 sec will be memorised. Likewise, activate "GATE 1" to stop the manoeuvre of engine 1 and memorise its closure time. If the engine 1 manoeuvre is stopped due to the end of opening process (FCC1) 4 sec will be added to the memorised time.

I7 ON – With option I7 activated, pressing "GATE 2" engine 2 will work in suspension mode and pressing "GATE 2" a second time we can stop the manoeuvre and the closure time and suspension time will be memorised; if the manoeuvre is finalised by activating the end of closure process (FCC2) the time passed plus 4 sec will be memorised. Once engine 2 time has been memorised repeat the process for engine 1 using "GATE 1". Likewise, if finalising closure manoeuvre with end of closure process (FCC1) 4 sec. will be added to the memorised time.

9) Programming will be automatically deactivated when finalising the whole gate cycle.

OPTIONS SELECTOR

OPTION 1 - Automatic Closing

ON Door closes automatically after waiting the a.c. time.
OFF Door does not close automatically.

OPTION 2 - Disable Stop Opening

ON Opening the alternative button is disabled.
OFF If alternative button is pressed door stops.

OPTION 3 - Radio Programming

ON Not allowed.
OFF Allowed.

OPTION 4 - Inversion shut

ON Before opening the electro lock and closure relay are activated
OFF Normal opening with electro lock.

OPTION 5 - Photo electric cell opening/ Band

ON CSEG1 input works like a security band, stop and inverts the manoeuvre 2 sec. and after 3 sec. reopen.
OFF CSEG1 input works like a photo cell, stopping the gate if activated and continuing the opening manoeuvre when deactivated.

OPTION 6 - Flashing Light

ON Flashing.
OFF Fixed.

OPTION 7 - Buffer Closing

ON Drive reduce it's speed at the end of opening & closing.
OFF No buffer.

OPTION 8 - Pulse every 3 hours

ON Activated.
OFF Desactivated.

UNI
EN

I nostri prodotti se installati da personale specializzato idoneo alla valutazione dei rischi, rispondono alle normative UNI EN 12453-EN 12445

Nuestros productos tienen que ser instalados por personal cualificado capaz de evaluar los posibles riesgos, cumpliendo con la norma UNI EN 12453, EN 12445

Our products if installed by qualified personnel capable to evaluate risks, complies with UNI EN 12453, EN 12445 normative

Nos produits si installés par personnel qualifié capable d'évaluer les risques, sont conformer à la norme UNI EN 12453, EN 12445

Nossos produtos se instalado por pessoal qualificado, capaz de avaliarrisco, cumprir UNI EN 12453, EN 12445

CE

Il marchio CE è conforme alla direttiva europea CEE 89/336 + 93/68 D.L.04/12/1992 n.476

El marcaje CE indica que cumple con la directiva europea CEE 89/336 + 93/68 D.L.04/12/1992 n.476

The CE mark indicated that complies with EEC European directiva 89/336 + 93/68 D.L.04/12/1992 n.476

Le marque CE est conforme avec la CEE directiva européenne 89/336 + 93/68 D.L.04/12/1992 n.476

A marca CE em conformidade com a Directiva Europeia CEE 89/336 + 93/68 D.L.04/12/1992 n.476

I dati e le immagini sono puramente indicativi

VDS si riserva il diritto di modificare in qualsiasi momento le caratteristiche dei prodotti descritti a suo insindacabile giudizio, senza alcun preavviso.

Los datos y las imágenes son orientativos

VDS se reserva el derecho de modificar en cualquier momento las características de los productos descritos en su única discreción, sin previo aviso.

The data and images are for guidance only

VDS reserves the right to change at any time characteristics of the products described in its sole discretion, without notice.

Les données et les images sont à titre indicatif seulement

VDS réserve le droit de modifier à tout moment les caractéristiques des produits décrits à sa seule discrétion, sans préavis.

Os dados e as imagens são apenas para orientação

VDS reservas o direito de alterar, a qualquer tempo as características dos produtos descritos em seu exclusivo critério, sem aviso prévio.



Via Circolare p.i.p. sn
65010 Santa Teresa di Spoltore (PE) - Italy
Tel. 085-4971946 - Fax 085-4973849
www.vdsproduction.it - vds@vdsproduction.it