NOC DASHBOARD

Understand every card. Make sense of every number.

Detailed User Guide

A practical guide to alarms, incidents, work orders, trends, SLA results, maps, reports, and saved monitoring tools.

What this guide helps you do

Read the dashboard one card at a time, understand what each count represents, and open the right detail records.

Follow clear calculations and worked examples without needing application code or database file paths.

Check differences between source systems, saved data, and browser views before reporting an issue.

Prepared 11 November 2026. Existing PDF manuals remain unchanged.

Contents

Click a chapter title or use the PDF bookmarks to jump to a topic.

Detailed User Guide 1

Start here: read the dashboard correctly 4

Card 01 | VVIP Site: VIP and VVIP alarms 5

Card 02 | Mentor Site: selected-site monitoring 8

Card 03 | IP Ezecom 10

Card 04 | IP Telcotech/Cellcard 12

Card 05 | RAN Status: Site Down 14

Card 06 | RAN Status: Tech Down 16

Card 07 | RAN Status: Main AC and DC voltage 18

Card 08 | Incident / INC-WO by Status 20

Card 09 | All WO is Resolved: exact rules 22

Card 10 | Site Down - Open (by Age) 24

Card 11 | Incident Volume - Week over Week 26

Card 12 | Incidents Closed - Week over Week 28

Card 13 | Site-Down Duration - Weekly Trend 30

Card 14 | Top 10 Site Down - Overtime 32

Card 15 | Site-Down Root Cause and Root Cause Breakdown 34

Card 16 | SLA Compliance - Weekly Trends 36

Card 17 | Response Time - Week over Week 39

Card 18 | Resolution Time - Week over Week 41

Card 19 | Congestion and interface exclusions 43

Card 20 | Cache, refresh, Cambodia time, and verification 45

Using the Help center and dashboard 47

Getting started: a practical investigation 48

Source data and comparing records 49

Refresh, theme, layout, and fullscreen 50

Choose the right view for your question 51

Map view, colors, coordinates, and boundaries 52

Partner contacts and escalation information 54

Reports and exports 55

Prepare and export an incident report 56

Alerts, restoration replies, and delivery checks 57

Saved data and safe application updates 58

Mentor Site: adding, importing, and retaining sites 59

Troubleshooting step by step 60

Glossary: terms used throughout the guide 61

Final verification checklist 62

Start here: read the dashboard correctly

Five things to check before comparing numbers

1. What is being counted? A site, incident, work order, device alarm, and interface are different objects.

2. Which records qualify? Read the status, category, inventory, and exclusion rules for that view.

3. Which date is used? Occurred At, Created At, Resolved At, and Closed At can place the same ticket in different weeks.

4. Which filters are selected? Apply the same category, week, site, and root-cause filters before comparing.

5. Is the data current? Reloading the browser reads the saved view; source collection must complete successfully first.

Question	Start with
What needs attention now?	Live alarm cards and active incident/WO views
Why does the badge differ from the table?	The card's counting unit and distinct-site rules
Did the team meet its deadlines?	SLA Compliance and the individual incident result
How long did work take?	Response/Resolution time and outage duration charts
Why is a record missing?	Filters, inventory matching, exclusions, and update timing

A worked example

Two sites produce five alarm rows. One parent incident has three WOs. A site badge can show 2, an alarm table can show 5 rows, the incident view can show 1, and the WO view can show 3. These numbers can all be correct because they answer different questions.

For the most reliable check, choose one known identifier and follow it through the relevant card, its detail records, and the source system using the same filters.

Card 01 | VVIP Site: VIP and VVIP alarms

Live alarm cards

This card focuses on active alarms affecting VIP and VVIP sites. Although the heading says VVIP Site, the selection accepts both designations.

Where the data comes from

Streamline alarm records come from the Streamline alarm database. The the cached Streamline alarm list query keeps Opened alarms with a recorded occurrence time. It keeps the latest event for each combination of raw site, event name, and location, while retaining an occurrence count.

VIP alarm sync filters that cache using VIP/VVIP designations from the cached Streamline site inventory or the cached MSSQL VIP inventory. The MSSQL inventory uses TBL_SITE and TBL_NE for On Air, not-removed VIP/VVIP sites. Displayed alarms also require a matching the cached site inventory record.

What each badge means

Site Down uses recognized connectivity and technology-down event names. Main AC Failure matches main failure text. Low and High DC Voltage match their respective DC text. DG-On uses the event or additional information. Rectifier and door events use RECT Failure and Door Alarm. Remaining events go to Other.

High Temperature has no separate badge here. An Opened temperature event can appear under Other if the site qualifies. Open the drilldown to inspect the actual event and additional information.

How the number is counted

Each category counts distinct site codes, not alarm rows. One site can appear once in Main AC Failure and once in Low DC Voltage. Adding all category values therefore does not give a unique total of affected sites.

Example: two sites, four alarm rows

Site 0460 has three Main AC Failure rows and site 1002 has one. The badge shows 2 sites. Clicking 2 can show four alarm rows, because the table explains the alarms behind the two sites.

Clicking a badge

A badge opens that alarm category; View Alarms opens the broader list. Site inventory supplies grade and location. Ticket references are enriched from the cached VIP incident list, which can retain Resolved incident references until Closed. A resolved ticket reference does not itself prove the alarm cleared.

If a site is missing

Check that the alarm is Opened, the site code resolves, the cached site inventory contains the site, and either inventory marks it VIP/VVIP. After an inventory change, allow both inventory and alarm jobs to finish.

Site Down and power alarms in everyday use

A Site Down badge is based on recognized outage event names, not a person reading the alarm note and deciding that the site sounds down. If a source event is outside those names, it can fall into another group. Always inspect the event text when a familiar site is absent from the category you expected.

Main AC Failure means the alarm describes a mains power problem. It does not alone say that the site has stopped carrying service. A site running on batteries or a generator can have a mains alarm while remaining reachable. Low DC Voltage describes a different power condition and can appear at the same site.

High DC Voltage is kept separate from Low DC Voltage. DG-On identifies a generator-running indication using the supported event or additional-information text. RECT Failure and Door Alarm follow their event keywords. These categories explain what the source reported; they do not automatically establish a verified root cause.

Other contains remaining matched VIP/VVIP alarms. It is not an error bucket or a statement that those events are unimportant. A hardware or temperature event can be operationally important even without its own dedicated badge. Open Other and read the exact event rather than ignoring it.

Worked investigation from the badge to the incident

You receive a report that VIP site 0460 has a power problem. Open Main AC Failure and find 0460 in the table. Read its occurrence time and additional information. If three event rows share that site code, remember the category still contributes one site to the badge.

Next inspect any incident reference. That reference is added from cached ticket data, so its status can differ from the current event status. A Resolved ticket alongside an Opened alarm needs investigation; it is not sufficient to conclude the alarm is cleared. Check both source records and their update times.

Finally, compare the same site code in Mentor or RAN only if that view applies. Mentor requires a configured selection; RAN uses technology coverage and inventory. A site appearing in VIP but not Mentor is expected when it was never added to the Mentor list.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 02 | Mentor Site: selected-site monitoring

Live alarm cards

Mentor Site is your saved list of sites to watch closely. Those sites do not need to be VIP or VVIP.

Choose the sites first

Open Mentor Site and enter site inventory codes, or import a CSV using the downloadable template. Codes are validated against the site database. Unknown codes fail validation. Entering a POP identifier alone does not enable POP monitoring.

Review file validation before completing the import. Keep leading zeroes in site codes, use the template column header, and correct rejected values instead of treating a failed file as successfully imported.

Where the records come from

The service matches the saved codes against the cached Streamline alarm list and uses the cached site inventory for names and provinces. It also checks active the cached active incident list records in the Site Down category.

When a monitored site has an active Site Down incident but no Site Down alarm, the service adds an incident-based entry. This avoids showing OK solely because an alarm cleared while its active ticket remains.

What the badges count

The categories are Site Down, Main AC Failure, Low DC Voltage, High DC Voltage, DG-On, RECT Failure, Door Alarm, and Other. Each counts distinct configured sites in that category. Several alarms at one site count once in that category; a site can appear in several categories.

Example: an alarm and an incident

You monitor 0460 and 1002. Site 0460 has two Main AC Failure alarms. Site 1002 has an active Site Down incident but no current down alarm. Main AC Failure shows 1 and Site Down shows 1. The alarm table can have more rows than either site count.

Status and drilldown

View Alarms shows the configured list; the per-site View action narrows to one site. Site Down takes precedence in the configured-site status. OK means no qualifying record was found in the current matched caches, not that every external monitoring system has been checked.

What stays saved

The selected sites survive refresh and restart when instance data is retained. Removing a site removes it from Mentor monitoring, not the source inventory. Alarm and incident freshness still depends on their own background jobs.

Adding one site and importing many sites

For one site, use its exact inventory code and review the validation response before treating it as monitored. Leading zeroes are part of the identifier. A spreadsheet converting 0460 into 460 can make the imported value fail validation or refer to the wrong identifier.

For multiple sites, start from the available template rather than a file with unrelated columns. Keep the expected site-code header, remove accidental spaces, and check the file result. A completed progress bar indicates the file-processing step has finished; review whether the result says valid or failed before continuing.

An Unknown site codes result means the supplied value could not be accepted against the current site inventory. It does not prove that the physical site does not exist. Check spelling, identifier type, and the latest inventory update. POP monitoring is not enabled merely by accepting a similar-looking POP code.

Understanding the configured-site status

The configured list gives a compact status per monitored site, while the alarm drilldown explains all matched events. When several categories affect a site, the compact status cannot describe every event at once. Use the category badges and per-site View action for the full picture.

A Site Down incident can make the site remain in Site Down after its corresponding alarm is no longer present. This is deliberate: the card combines relevant incident and alarm evidence. Inspect the still-active incident before assuming the Mentor entry is stuck.

Removing a site changes only the monitoring selection. The original inventory, incident history, and alarms still exist in their own systems and can remain visible on other cards. If you later add the site again, monitoring uses the current caches rather than restoring an old snapshot of its alarms.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 03 | IP Ezecom

Live alarm cards

This card combines POP connectivity and power information with device alarms. The groups do not all use the same query or counting method.

Source and active rule

MSSQL noc.TBL_PPD supplies alarm rows. The EZE query reads alarm names beginning with EZE and keeps Status = 1 OR RestoredTime missing. Inventory joins use noc.TBL_ISPDEV and noc.TBL_POP. The local table is the Ezecom alarm cache.

POP DOWN and POP POWER use the separate the cached POP alarm list query. It requires a non-null POP name and POP code after matching device IP to inventory. A missing mapping can remove a POP record before it reaches both its badge and drilldown.

How counts work

POP DOWN/POWER count distinct POP name/code pairs. For EZE/TCT types, rows with both POP name and code are deduplicated by that pair. Rows without complete POP mapping count individually instead.

Bandwidth and congestion types feed the Congestion badge. The current implementation adds separately counted types; this is not a distinct-interface total. A POP with both types can contribute through each type.

Example: mapped sites versus rows

Three devices at the same mapped POP have one alarm type: they contribute 1 POP. Two more records without complete POP mapping contribute 2 individual records. The badge shows 3, while the drilldown can show five rows.

What to inspect

Click the badge and compare alarm type, device, IP, interface, and timestamps. A saved congestion exclusion affects the selected interface on the identified device; it does not hide all ports.

Why another system differs

Compare the same active rule, type, POP mapping, and sync time. Do not compare a mapped-site count with raw rows. Missing POP inventory is treated differently by the POP DOWN/POWER query and the general EZE/TCT type queries.

Separate POP reachability from device alarms

A POP DOWN result describes the POP-oriented alarm query, while a port or congestion result can describe a device event. They may refer to the same location but they are not interchangeable conditions. A port can be congested without the POP being unreachable.

For a missing POP record, check the relationship between device IP and POP inventory. A genuine alarm with an unmapped IP can fail the POP query requirement. The general Ezecom alarm query has different mapping rules, so the same device can still appear in another alarm group.

Example: one POP has a router alarm and several port events. A POP-based badge can count the location once, while a device drilldown lists the router and ports separately. Use the interface field to decide which event you are inspecting rather than assuming every repeated POP name is a duplicate.

Check congestion before excluding it

Read the device, IP, interface, and additional information together. Exclude only the port that has been intentionally accepted for exclusion and add a useful remark. A generic remark such as checked gives the next operator little context; describe why that interface should remain hidden.

After exclusion, another port on the same router can still generate visible congestion. This is correct. If a source event later uses a different device identity or missing interface data, review its match rather than assuming every future alarm for that site should be hidden.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 04 | IP Telcotech/Cellcard

Live alarm cards

This card combines POP connectivity and power information with device alarms. The groups do not all use the same query or counting method.

Source and active rule

MSSQL noc.TBL_PPD supplies alarm rows. The TCT query reads alarm names beginning with TCT and keeps Status = 1 OR RestoredTime missing. Inventory joins use noc.TBL_ISPDEV and noc.TBL_POP. The local table is the Telcotech alarm cache.

POP DOWN and POP POWER use the separate the cached POP alarm list query. It requires a non-null POP name and POP code after matching device IP to inventory. A missing mapping can remove a POP record before it reaches both its badge and drilldown.

How counts work

POP DOWN/POWER count distinct POP name/code pairs. For EZE/TCT types, rows with both POP name and code are deduplicated by that pair. Rows without complete POP mapping count individually instead.

Bandwidth and congestion types feed the Congestion badge. The current implementation adds separately counted types; this is not a distinct-interface total. A POP with both types can contribute through each type.

Example: mapped sites versus rows

Three devices at the same mapped POP have one alarm type: they contribute 1 POP. Two more records without complete POP mapping contribute 2 individual records. The badge shows 3, while the drilldown can show five rows.

What to inspect

Click the badge and compare alarm type, device, IP, interface, and timestamps. A saved congestion exclusion affects the selected interface on the identified device; it does not hide all ports.

Why another system differs

Compare the same active rule, type, POP mapping, and sync time. Do not compare a mapped-site count with raw rows. Missing POP inventory is treated differently by the POP DOWN/POWER query and the general EZE/TCT type queries.

Separate POP, device, and interface information

The POP badges summarize POP-oriented connectivity or power conditions. Other Telcotech/Cellcard groups come from device alarm types. One physical location can therefore contribute to several groups without representing several different POPs.

A known IP address does not guarantee a complete POP mapping. If the inventory join cannot supply both required POP fields, a POP DOWN or POWER record can be absent from that query. Other type queries can still retain unmapped device records and count them individually.

Example: a mapped POP has four device rows of one type, and a core device without POP mapping has two rows. The mapped group contributes one POP while the unmapped records contribute separately. Comparing that number to raw row totals without checking mapping gives a misleading mismatch.

Read additional information before action

A bandwidth event can identify the specific interface in its Interface field and provide utilization details in Additional Information. Read those fields before excluding a record. The device name alone does not establish which port is congested.

Excluding one interface is a local visibility decision. It is not an acknowledgment that all device problems were fixed, and it does not close an incident. Restore the exclusion when you want that qualifying port to appear again; unrelated interfaces and alarm types remain available.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 05 | RAN Status: Site Down

Live alarm cards

Site Down identifies a complete outage by comparing the recognized alarm events with the technologies known to exist at the site.

Source and classification

The service combines the cached Streamline alarm list, the cached site inventory, and the cached site technology inventory. Alarm events come from the Streamline alarm table; inventories establish which site is active and which generations must be checked.

A recognized SRAN event represents shared-baseband loss. Otherwise, the union of down 2G/3G/4G/5G generations must cover the known technology inventory. Missing inventory prevents reliable classification by this comparison.

Example: both technologies down

A site has 2G and 4G inventory. If only 4G is down, it is partially down and belongs in Tech Down. If both are down, it qualifies for Site Down even when neither source event says SRAN.

SRAN is an event classification

NE is Disconnected, NE3SWS agent not responding to requests, and the link between the server and the ME is broken are SRAN events. eNodeB is out of service is 4G; Site Abis control link broken is 2G. Complete-site classification does not rewrite their source names to SRAN.

Badges and detail rows

Hub-Site and grade badges narrow the site population. The same site can have multiple source events, so a site count is not necessarily a raw row count. Where an SRAN event exists, concurrent single-generation rows are suppressed in this complete-outage view. Without SRAN, the individual technology rows can remain visible.

Verify an unexpected site

Check its actual alarm names, site code, On Air inventory match, and technology inventory. Compare all known generations, rather than assuming two alarm rows always mean the whole site is down.

Follow the technology evidence in order

First identify the physical site and its known technologies. Then list which generations have qualifying down events. Finally compare the two sets. Counting repeated rows without this comparison can wrongly turn one failed generation into an apparent complete site outage.

For example, inventory lists 2G and 4G. Two 4G events still cover only 4G. Adding a recognized 2G down event covers both generations and establishes the complete-outage condition. The evidence can remain as separate 2G and 4G rows because that is how the source reported it.

A shared SRAN event follows the separate shared-baseband rule. Its presence can make the site completely down without needing individual events for every generation. This does not mean all future single-generation event names should be renamed SRAN.

Grades explain the grouping, not the fault cause

A Hub-Site or grade badge tells you how the affected site is grouped in inventory. It does not describe the cause of its outage. Use the event information and incident investigation for that question.

If the badge and source list differ, compare exact site codes, inventory coverage, event names, and latest update. An inventory change can alter complete-versus-partial classification even when an event row itself has not changed.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 06 | RAN Status: Tech Down

Live alarm cards

Tech Down means at least one recognized technology is down while the known inventory does not establish a complete site outage.

How it is decided

The service compares down generations in the cached Streamline alarm list with the cached site technology inventory. It shares the complete-versus-partial classification with RAN Site Down. A recognized SRAN event is a shared-baseband condition, not an extra radio generation.

Example: repeated 4G events

Inventory lists 2G, 3G, and 4G. A 4G outage alone is partial. Ten repeated 4G alarms do not prove all three generations failed. If qualifying events cover every inventoried generation, the site becomes a complete-outage case.

Using the column

Click a Hub-Site or grade badge to inspect matching partial-outage records. The technology label follows the source event. If a site appears in an unexpected group, check missing inventory or an event name outside the supported classification list.

Do not add overlapping counts blindly

One physical site can have several event rows. Compare site codes and technology coverage, not only the number of table rows or the sum of alarm types.

Partial service loss can still be important

Tech Down is not a claim that the remaining technologies are healthy in every respect. It means the recognized down events do not cover the whole known site inventory. Users of the affected generation can still experience a serious service outage.

A site with only 4G in inventory is different from a site with both 2G and 4G. A 4G down event can cover the entire first site but only part of the second. The same event text can therefore lead to different site-level classification depending on inventory.

If another generation is physically present but absent from the saved inventory, the classification may not reflect the intended real-world site configuration. Check inventory quality before changing the interpretation of an alarm name.

Worked comparison

Consider site A with 2G and 4G, and site B with 4G only. Both show eNodeB is out of service. Site A has a partial recognized outage; site B has all inventoried technology down. Comparing only the common event name misses this important distinction.

When opening the detail table, read the site and technology together. An event-level row describes one observation. The site-level column summarizes the combined evidence, which is why event counts and site counts can differ.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 07 | RAN Status: Main AC and DC voltage

Live alarm cards

These columns show power-related alarms. A power alarm does not by itself prove that all site technologies are down.

Main AC selection

Main AC Alarm reads the cached Streamline alarm list event names containing main failure, case-insensitively. A matching the cached site inventory entry supplies grade and Hub-Site metadata. Hub-Site takes precedence over the normal grade grouping.

DC Low/High selection

DC Low/High selects event names containing high dc or low dc. It also requires the corresponding site inventory match. Complete outage classification is checked separately by the Site Down service.

Example: power lost but site reachable

One site has Main AC Failure and Low DC Voltage together. It can contribute in each relevant power group while still operating on batteries. It need not appear in complete Site Down. These two alarms do not mean two different physical sites failed.

Ticket references

Power-category incident information is preferred when enriching these alarms, with Site Down as a fallback. No matching ticket reference does not erase the underlying power alarm. Check the event, occurrence time, and associated incident before deciding that records conflict.

Follow a power event through the site

When mains power fails, the site may continue operating from another supply. Later DC or generator-related events can describe the changing condition. Their presence at the same site does not establish several different sites, and their order matters when reconstructing what happened.

For example, Main AC Failure begins at 09:00 and Low DC Voltage appears at 10:00. At 10:15 the site can still be reachable. These records establish power conditions, not a complete technology outage. Check the Site Down evidence separately before stating that service was entirely lost.

Open the power badge, confirm the site code and occurrence time, and read the incident association. If the ticket category is Power, that is relevant context but not proof of a final root

cause. A source event, an incident category, and Actual Root Cause are different pieces of information.

Grade and Hub-Site values determine where a site is grouped. They do not change the meaning of High DC or Low DC. If a site is missing, verify its inventory match and supported event text before assuming the source alarm never existed.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 08 | Incident / INC-WO by Status

Incident cards

An Incident is the main ticket. An INC-WO is a linked work order. The two sides of the card count different objects.

Incident inclusion

the cached active incident list reads the Streamline incident table and keeps New or In Progress incidents. Customer Complaint is the exception: only In Progress is kept for that category. Other categories retain their normal active-status rules. Repeated site rows are not counted as extra incident IDs.

Work-order inclusion

the cached active work-order list reads the Streamline work-order table joined to its the Streamline incident table parent. It excludes closed WOs and closed parents. Customer Complaint parents must be In Progress. WO badges then use WO statuses such as New, Assigned, Acknowledged, In Progress, Resolved, Reopened, Returned, and On Hold.

Example: one ticket, three WOs

An In Progress incident has one Resolved WO and two In Progress WOs. It contributes one incident to the incident list, while the three WOs belong to their own status lists. A resolved WO does not mean its siblings are resolved or that the parent may be treated as closed.

Overdue views

Overdue uses the source overdue result. Overdue L2 and L3 further narrow by support level. Overdue Site-Down narrows to the Site Down incident category. These are overlapping filtered views, not extra independent tickets to add to a grand total.

Compare the same scope

Use the same incident category, parent status, and WO status in Streamline. All Records without those filters is a different population. Customer Complaint can remain in historical completion reporting even after leaving this active card.

Read the parent and child records separately

When reviewing a ticket, first read the parent incident status. Then inspect its work orders. Several teams may be working on different WOs under one incident, so one team finishing does not mean the entire parent ticket is finished.

For example, an incident has a field-service WO and a transmission WO. The field-service WO is Resolved, but the transmission WO remains In Progress. Both states are valid at once. The parent can remain In Progress while the individual WO badges describe each team's progress.

An overdue badge is another view of the relevant records. A WO can be both In Progress and Overdue. Adding those two badge values would count that WO twice. Likewise, a Site Down overdue subset can overlap the general overdue population.

For comparison with Streamline, decide whether you are filtering the incident table or the WO table. Apply the parent restrictions where needed and use the same statuses. A parent list of ten incidents can correctly correspond to more than ten work orders.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 09 | All WO is Resolved: exact rules

Incident cards

This badge counts qualifying incidents, not how many work orders they have. It verifies the source flag and the actual linked WO statuses.

The exact checks

The parent incident must not be Closed and the All WO is Resolved flag must be TRUE. At least one linked the Streamline work-order table WO must exist, and every linked WO must have status resolved. A New, In Progress, Closed, reopened, or missing-status sibling blocks this strict result. Customer Complaint parents must also be In Progress.

Why the extra WO check matters

The source flag can disagree with actual WO rows. Streamline filtering only All WO is Resolved = TRUE can therefore return more incidents than the dashboard. The extra verification prevents a stale flag from presenting unfinished WOs as fully resolved.

Example: all five completed

Incident A has five WOs, all Resolved. The badge counts 1 incident. Its table row shows Total WOs = 5 and Resolved WOs = 5. The badge does not become 5, because its counting unit is an incident.

Example: four of five completed

Incident B has four Resolved WOs and one In Progress WO. It is excluded even if its flag is TRUE. An incident with no linked WOs is also excluded; an empty set is not treated as a finished set.

What the table columns mean

Total WOs counts all siblings before any status filter. Resolved WOs counts strictly Resolved siblings. Latest WO Resolved At is the latest sibling resolution timestamp, not proof the parent incident closed. Multi-site codes can share one incident row without multiplying the incident count.

Refresh and drilldown

The incident job replaces the cached all-WO-resolved incident list with a complete source-verified snapshot. The drilldown uses that cache and periodically reloads its records. Browser reload alone does not re-run the source query; wait for a successful incident sync before comparing counts.

A complete verification example

Incident A has two WOs, both Resolved, and the source All WO is Resolved flag is true. Its parent is not Closed, so it can qualify. Incident B has the same true flag but one WO is In Progress. The additional sibling check excludes B rather than trusting the flag alone.

Incident C has every WO Resolved but the source flag is false. It does not qualify under the current rule because the badge requires both checks. This is important when reproducing the result: filtering only WO status is not equivalent to filtering only the incident flag, and neither alone reproduces both requirements.

Incident D has a WO with status Closed rather than Resolved. The strict check does not treat those words as interchangeable. That distinction can explain an apparently finished incident missing from the badge. Inspect the exact source statuses instead of interpreting every finished-looking state as Resolved.

When the parent later becomes Closed, it leaves this non-closed-incident badge. Its historical records are not deleted. If a total changes after an update, compare the incident IDs and sibling statuses before treating the decrease as lost data.

Worked example: check the flag and every WO

Each qualifying row contributes one incident to the badge, regardless of its number of WOs.

Example	Total WOs	Resolved WOs	Qualifies?
Flag true; all WOs Resolved	5	5	Yes, if parent conditions pass
Flag true; one WO In Progress	5	4	No
Flag false; all WOs Resolved	5	5	No
No linked WOs	0	0	No

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 10 | Site Down - Open (by Age)

Trend and performance cards

This chart measures the age of currently active Site Down incidents. It is different from the duration of already completed outages.

Source and count

The service reads the cached active incident list, narrows to Site Down, and counts each incident once rather than once for every site row. Age uses the occurrence timestamp and current Cambodia time.

How this is calculated

Incident age = current Cambodia time minus Issue Occurred At. The chart counts distinct qualifying active Site Down incidents in each age range. Count the incident once even if it appears on several site-detail rows.

Example: 13:00 minus 08:00 gives 5 hours. That incident belongs in 4-8h. If three incidents meet that range, the bar shows 3.

Bucket boundaries

Buckets are below 4 hours, 4 to below 8, 8 to below 12, 12 to below 24, and 24 hours or more. The >24h label uses the last range including its 24-hour lower boundary. An incident can move to a later bucket without a new ticket being created.

Example

An incident started at 08:00 Cambodia time. At 11:00 it belongs below 4 hours. At 13:00 it belongs in 4-8h. If it affects two sites, that does not automatically make it two incidents on this chart.

Drilldown versus worklogs

A bar or count opens incidents in that age bucket. The worklog control uses separately cached source comments and audit changes. A chart count does not promise every incident has a worklog entry; availability of worklog data is a separate question.

Verify differences

Check status, category, occurrence time, last sync, and whether the other screen counts tickets, sites, or alarm rows. Do not compare this current open-age cohort directly with the historical closed-outage duration cohort.

Use age to prioritize an investigation

The age groups help identify incidents that have remained active longer. They do not directly measure SLA breach: two incident priorities can have different deadlines. A ticket in an older group deserves review, but use its actual SLA result rather than assuming the age label alone proves a missed target.

An incident can move from 4-8h to 8-12h simply because time passed. No new source incident is required. If the incident resolves and stops matching the active query, it leaves the live chart after the source update. It can then be relevant to a historical completion report.

For example, a ticket started at 06:00 and remains active at 15:00. Its age is nine hours. If a worklog was added at 14:50, the ticket is still nine hours old; the recent comment does not reset the original incident occurrence time.

When a worklog popup contains fewer incidents than the bar, check which tickets have actual cached worklog records. Do not interpret a missing worklog entry as proof the incident itself is absent from the age cohort.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 11 | Incident Volume - Week over Week

Trend and performance cards

This chart compares incident volumes over the selected reporting weeks. Its source occurrence timestamp determines the incident cohort.

Which date is used

The incident-volume query reads the Streamline incident table and returns Issue Occurred At as the trend date. Despite the internal volume-cache name, this query is occurrence-based. It does not use the active-only New/In Progress query.

How this is calculated

Daily volume = the number of qualifying incident IDs whose occurrence date belongs to that day, after applying the category and week selections. Weekly volume = the sum of its daily incident counts.

Example: daily counts of 3, 4, 2, 5, 1, 0, and 2 produce a weekly count of 17. These are incidents, not necessarily 17 different sites.

Count and filters

The service combines cached incident IDs with details and avoids multiplying an incident by its site joins. Category and week selections narrow the population. Default category exclusions can differ from an explicitly selected category list.

Example: Sunday versus Monday

A ticket occurred Sunday at 23:30 Cambodia time but was entered Monday. An occurrence-based chart can place it in a different week from a Streamline Created At filter. Match the date field before comparing totals.

Clicking and exporting

Click a day or value to inspect the corresponding records and breakdowns. Use the same category and week selections in the export. The current week is incomplete until it ends, so a lower current-week total does not automatically mean a lower full-week volume.

Understand what a higher daily total means

Volume describes how many qualifying incidents belong to the selected period. It does not directly tell you how many are still open, how many unique sites were affected, or how long the outages lasted. Use status and duration views for those questions.

For example, Monday contains twenty qualifying incidents and Tuesday contains ten. If many Monday tickets were quickly resolved, Monday can still have the higher incident volume while Tuesday has more unresolved work. These are not contradictory results.

A category filter changes which incidents contribute. Selecting Power and Site Down includes the records in those selected categories; it does not mean an incident was classified as both. Preserve the same selection when comparing a day popup, drilldown, and exported records.

When a newly updated source record changes category or occurrence time, its placement can change after the next successful sync. Compare identifiers and date fields when explaining the change instead of assuming the chart created or deleted tickets.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 12 | Incidents Closed - Week over Week

Trend and performance cards

This historical completion view is separate from the active incident card. Its query includes specific Resolved records as well as Closed records.

Source status rules

The completed-incident query reads the Streamline incident table. Customer Complaint uses status Resolved. Other categories accept Closed or Resolved. The reporting date is Closed At if present, otherwise Resolved At.

How this is calculated

Completion date = Closed At when present, otherwise Resolved At. Daily completion count = qualifying incident IDs assigned to that date. Apply the category-specific accepted status rules before counting.

Example: four qualifying incidents have a completion date on Monday and six on Tuesday. These two days contribute 10 completions. Their original occurrence dates can be in earlier days or weeks.

Why an incident leaves one card but remains here

An incident can leave the active New/In Progress population and remain part of historical reporting. The Customer Complaint In Progress-only rule for active cards does not remove completed complaints from this historical trend.

Example

A Power incident has no Closed At but was resolved Tuesday. It can be included under that resolution date. If Closed At is later populated, the preferred completion timestamp can change its historical placement after sync.

How to verify

Match the included statuses and Closed At, falling back to Resolved At date. Streamline Status = Closed alone cannot reproduce a query that also accepts Resolved. Then apply the same categories and weeks.

Completion is different from outage start

A completion trend answers when work reached the query's accepted completed statuses. An occurrence trend answers when incidents began. An incident spanning several days can therefore contribute to different dates on these two charts.

For example, an outage begins Friday and its incident completes Monday. The completion view can show it on Monday even though the operational problem began in the previous week. Comparing Friday's volume directly with Monday's completion count does not compare the same cohort.

If both resolution and closing times exist, the preferred date rule determines the completion date. Review those fields in the source when a record moves between reporting weeks. Do not assume the time a user noticed the status change is the source completion timestamp.

This is historical reporting, so a ticket leaving the active card is expected to remain available here when it meets the completion rules. Retaining that history is different from retaining an outdated active alarm.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 13 | Site-Down Duration - Weekly Trend

Trend and performance cards

This chart groups completed Site Down incidents by outage duration. It does not measure how long the currently open tickets have existed.

Source conditions

The historical Site Down query keeps Site Down incidents with status Closed, a recorded Resolved At, and Closed At inside the reporting window. Outage duration uses occurrence to resolution; closing time scopes the historical window.

How this is calculated

Outage duration = Resolved At minus Issue Occurred At. For qualifying closed Site Down incidents, assign that duration to exactly one duration bucket and count the matching incidents for the selected closing week.

Example: 10:30 minus 08:00 is 2 hours 30 minutes, so the record belongs in the group above 15 minutes and below 4 hours. The first bucket includes exactly 15 minutes; 4 hours enters 4-8h and exactly 24 hours enters the final bucket.

Duration groups

The labels are up to 15 minutes, 16m-4h, 4-8h, 8-12h, 12-24h, and above 24h. Inspect exact timestamps in the drilldown for a record close to a boundary. Week and duration choices can also narrow related root-cause views.

Example

An incident occurred 08:00, was resolved 10:30, and closed 12:00. Its outage duration is 2 hours 30 minutes, not 4 hours. It belongs in 16m-4h. An incident still open does not qualify for this closed-incident dataset.

Comparing lines

Selected weeks determine the compared cohorts. A partial current-week line contains only data available so far. Count incident IDs rather than individual alarm occurrences when checking totals.

Duration is not closing delay

A site can be restored before administrative closing is completed. The difference between resolution and closing does not automatically extend the measured outage duration in this chart. Read the selected duration formula before comparing it with a ticket's total lifetime.

For example, service returns at 10:00 but the ticket is closed at 16:00 after verification. If the outage began at 08:00, the measured occurrence-to-resolution interval is two hours. The later closing time can affect historical eligibility without making the outage eight hours long.

Two incidents of the same duration can belong to different reporting weeks because their closing dates differ. A duration bucket is not an identifier or an independent event; it is a grouping of qualifying historical incident records.

If an apparent duration is negative or a required timestamp is missing, inspect the original times rather than treating it as a genuine fast restoration. Source timestamp quality is part of a reliable duration comparison.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 14 | Top 10 Site Down - Overtime

Trend and performance cards

This ranking highlights sites with frequent qualifying historical Site Down incidents. It does not mean every ranked site is currently down.

Source and ranking

The service uses the historical Site Down duration dataset with site details. It ranks site codes by incident participation in the selected weeks. Frequency is a different measure from the longest single outage duration.

How this is calculated

Site frequency = the number of qualifying incident associations for each site within the selected historical cohort. Sort sites by that count and show the highest-ranked ten.

Example: site A appears in 5 incidents, B in 3, and C in 2. The order is A, B, C by frequency. This formula does not rank the longest outage or calculate unique affected sites across all incidents.

Example

Site 0460 has five qualifying incidents and 1002 has two. Frequency can place 0460 higher even when 1002 had the longest individual outage. One multi-site incident may relate to more than one ranked site.

Linked root-cause view

Click a site code to filter the adjacent Root Cause Breakdown to that site. Without a selected site, that breakdown uses the top-ranked sites together. The selected Top 10 weeks also affect the related breakdown.

No data

An empty chart means there are no qualifying records in the current cached window and filters. It is not proof there are no outages anywhere. On startup, allow the relevant sync to complete before interpreting an initially empty card.

Read the ranking without confusing frequency and impact

A high position means frequent qualifying incident participation in the selected cohort. It does not establish the largest customer impact, the longest total downtime, or the highest priority. Those require their own measures and source details.

For example, site A has six short incidents and site B has one long outage. A frequency ranking can place A first, while a duration-based investigation might prioritize B. State which measure you mean when explaining the top site to another user.

Changing the selected weeks changes the ranking population and can change which sites enter the top ten. A root-cause view linked to those ranked sites can therefore change even when no cause label was edited. Its inputs changed with the ranking.

When reviewing a selected site, inspect the incident IDs and affected site codes. Several sites can be linked to one parent incident, so adding site-specific incident counts may not reproduce the number of unique incidents across the network.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 15 | Site-Down Root Cause and Root Cause Breakdown

Trend and performance cards

These views group historical records by recorded Root Cause Category. They follow different filters, so the same category can have different totals in each view.

Root Cause Breakdown

This view follows Top 10 Site Down: the ranked sites together, or one selected site, with its selected weeks. It is not a summary of every site in the source database.

How this is calculated

Category share = the category count divided by the total counted entries in that filtered breakdown, multiplied by 100. The population includes its applicable missing-cause group; multiple recorded categories can contribute separately.

Example: 4 Power entries out of 10 total entries give 40%. Selecting a site or duration bucket changes the denominator. Percentages can have rounding differences and are not percentages of all network alarms.

Site-Down Root Cause - Breakdown

This view follows the Site-Down Duration week and duration selections. Narrowing to a duration bucket changes its incident population. Check subtitles and filters before comparing it with the Top 10-linked view.

Missing and multiple causes

The root-cause lookup uses recorded Root Cause Categories. Missing causes remain an unassigned group rather than being guessed from notes. A rare incident carrying several recorded categories can contribute to each applicable category; do not assume the sum of category counts always equals unique incident IDs.

Example and percentages

A selected site has six qualifying incidents: four with recorded causes and two without. The unassigned group explains the missing classifications. Changing the selected site or duration group changes the percentage base even if category names remain the same.

Open the records

Click a category to inspect matching incidents. The chart and table provide different presentations of the same selected context. Percentages refer to that filtered breakdown, not all active alarms globally.

Keep the selected population visible in your explanation

Before reading a cause percentage, identify what the chart is summarizing: one selected site, the top-ranked sites, or a duration-filtered incident population. A percentage without that context is easy to misunderstand.

For example, Power is four of eight classifications in one filtered population and four of twenty in another. The label and count are unchanged, but the percentage differs because the denominator changed. This does not mean the system edited the cause.

An unassigned cause means the relevant category is not recorded in the matched data. It should not be silently converted into the incident note, a suspected fault, or an alarm event name. Those fields may contain useful investigation context but they do not substitute for the recorded Root Cause Category.

When a cause is assigned later, the next qualifying update can move the incident from unassigned to that category. Historical breakdowns can therefore become more complete after operational work finishes. Inspect the source category and cohort when explaining a changed slice.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 16 | SLA Compliance - Weekly Trends

Trend and performance cards

Each incident has two separate deadline results: Response SLA and Resolution SLA. Passing one does not guarantee passing the other.

Source fields

the Streamline incident table supplies the Response SLA overdue field for Response and the Resolution SLA overdue field for Resolution. FALSE means Met; TRUE means Not Met. A missing Resolution result is Not Graded, not automatically a pass or a failure. Detail targets come from saved SLA policy rules matching category, support level, and applicable priority or site grade.

How this is calculated

Response Compliance = Response Met count divided by the response cohort count, multiplied by 100. Resolution Compliance = Resolution Met count divided by the graded resolution cohort count, multiplied by 100. A missing Resolution result is excluded from the graded denominator.

Example: Response Met 90 out of 100 gives 90%. Resolution Met 30 out of 40 graded gives 75%. Combine selected categories by adding their counts first; do not take an unweighted average of category percentages.

For the root-cause table, Response Not Met = count of matching incidents with a failed Response result. Resolution Not Met = count with a failed Resolution result. An incident failing both contributes once in each column. The root-cause occurrence-week cohort is separate from the summary response-created and resolution-closed week cohorts.

Weekly percentages

Response Compliance is Response Met divided by its response cohort. Resolution Compliance uses graded Resolution records, excluding ungraded values from that denominator. The summary groups Response by Created At week and Resolution by Closed At week in Cambodia time. These are different cohorts.

Example: the rate

If 90 of 100 response records are Met, Response Compliance is 90%. If 30 of 40 graded resolution records are Met, Resolution Compliance is 75%. Ten additional ungraded resolution records must not silently become ten successful resolutions.

Root Cause table

The columns are Root Cause Category, Response Not Met, and Resolution Not Met. It uses incidents that missed either result in the occurrence-week cohort, with selected categories applied. This week anchor differs from the summary pass-rate Created At and Closed At anchors. A failed incident without a root-cause category stays under Not Assigned.

Example: why 15 and 19 are different lists

Suppose 13 incidents missed only Response, 2 missed both, and 17 missed only Resolution. Response Not Met shows 15. Resolution Not Met shows 19. Clicking 15 opens the response list; only 2 of those also show Resolution Not Met. Clicking 19 opens the separate resolution list. These are illustrative figures, not current live data.

How to verify a number

Click the specific failure count for the selected cause. Its drilldown and export apply the corresponding Response or Resolution flag, cause label, selected categories, and occurrence week. In Streamline, match that exact overdue field and date field, not just the week number.

Response and resolution measure different parts of the work

Response concerns how quickly the incident was taken up against its response requirement. Resolution concerns completing the incident against its resolution requirement. An early response can still be followed by a long repair, and a late response can still be followed by a repair that meets its separate target.

This is why the two Not Met columns are not steps in one calculation. Resolution Not Met is not supposed to equal the number of Resolution failures visible inside the Response Not Met list. Each column starts from its own failure condition within the selected root-cause cohort.

Imagine two lists of names. The Response list contains fifteen names; the Resolution list contains nineteen. Two names happen to be on both lists. Opening the first list reveals those two shared incidents, but it does not reveal the seventeen additional resolution-only incidents. Open the Resolution count to see those records.

A Not Graded resolution is a third outcome, not the same as Met. When checking an incident that appears absent from a failed-resolution list, read the recorded result before assuming the system considers it successful.

Worked example: two overlapping lists

The Response and Resolution columns count separate lists. Only the incidents that fail both appear in both lists.

Incident group	Count	Response Not Met list	Resolution Not Met list
Response failed only	13	Included	Not included
Both failed	2	Included	Included
Resolution failed only	17	Not included	Included
Total in each list		15	19

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 17 | Response Time - Week over Week

Trend and performance cards

This card measures elapsed response time, not the percentage of incidents meeting an SLA target.

Timestamp calculation

The source is the Streamline incident table. The interval ends at Taken In Progress At. When the ticket was created manually, it starts at Created At; otherwise it starts at Issue Occurred At. This avoids counting a backdated occurrence as elapsed time before the manual ticket existed.

The query groups by the chosen start timestamp's Cambodia week. Do not assume this timing chart shares the SLA summary's Created At or Closed At anchor.

How this is calculated

Response duration = Taken In Progress At minus the applicable start time. Start time is Created At for a manually created incident, otherwise Issue Occurred At. Average = total qualifying response minutes divided by the number of measured incidents. Minimum and maximum are the shortest and longest measured values.

Example: measured responses of 10, 20, and 60 minutes give an average of 30 minutes, minimum 10, and maximum 60. When combining categories, weight each category average by its measured incident count.

The displayed comparison uses the absolute change from the previous value divided by the previous value, multiplied by 100. The display rounds and caps it at 100%; a smaller duration is an improvement. A zero or missing previous value has no percentage comparison.

Average, minimum, and maximum

Average is an arithmetic mean, not a median. A few slow incidents can raise it substantially. Minimum and maximum describe the extremes of the qualifying measured records. Missing required timestamps do not establish a zero-minute response or resolution.

Example

A manual ticket was created 09:00 even though its occurrence was entered as 07:00. If its response endpoint is 10:00, the manual measured interval is 1 hour. An automatically created incident with 07:00 occurrence and 10:00 endpoint uses 3 hours.

What the result does not prove

A high average does not prove every incident breached SLA. Targets can differ by priority and support level. Inspect the individual timestamps and selected categories; compare a partial current week cautiously with completed weeks.

Use elapsed time alongside the SLA result

A measured response duration tells you how long a qualifying incident took to reach its response endpoint. It does not by itself say whether the response was acceptable: that depends on the applicable SLA target.

For example, two incidents can both take thirty minutes to respond to. If their applicable deadlines differ, one may meet its requirement while the other does not. The timing chart and compliance card answer related but different questions.

An average is sensitive to unusually slow cases. If most responses are short but one incident waited many hours, the mean rises. Use the maximum and individual detail records to understand that pattern rather than concluding that every team response was slow.

When an endpoint is missing, there is no measured completed response interval for that row. Do not substitute the current time or zero unless that particular view explicitly defines such a rule. Check the source fields and reporting cohort.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 18 | Resolution Time - Week over Week

Trend and performance cards

This card measures elapsed resolution time, not the percentage of incidents meeting an SLA target.

Timestamp calculation

The source is the Streamline incident table. The interval ends at Resolved At. When the ticket was created manually, it starts at Created At; otherwise it starts at Issue Occurred At. This avoids counting a backdated occurrence as elapsed time before the manual ticket existed.

The query groups by the chosen start timestamp's Cambodia week. Do not assume this timing chart shares the SLA summary's Created At or Closed At anchor.

How this is calculated

Resolution duration = Resolved At minus the applicable start time. Start time is Created At for a manually created incident, otherwise Issue Occurred At. Average = total qualifying resolution minutes divided by the number of measured incidents; minimum and maximum are the extremes.

Example: measured durations of 60, 120, and 180 minutes give a 120-minute average. If another category has more incidents, combine the underlying counts and duration totals, not a simple average of category averages.

The displayed comparison uses the absolute change divided by the previous value, multiplied by 100, rounded and capped at 100%. A smaller duration is better. No percentage change is calculated from a zero or missing previous value.

Average, minimum, and maximum

Average is an arithmetic mean, not a median. A few slow incidents can raise it substantially. Minimum and maximum describe the extremes of the qualifying measured records. Missing required timestamps do not establish a zero-minute response or resolution.

Example

A manual ticket was created 09:00 even though its occurrence was entered as 07:00. If its resolution endpoint is 10:00, the manual measured interval is 1 hour. An automatically created incident with 07:00 occurrence and 10:00 endpoint uses 3 hours.

What the result does not prove

A high average does not prove every incident breached SLA. Targets can differ by priority and support level. Inspect the individual timestamps and selected categories; compare a partial current week cautiously with completed weeks.

Separate repair time, closing time, and compliance

Resolution time measures the configured start-to-resolution interval. Closing can happen later for verification or administrative reasons. A closing timestamp and a resolution timestamp should not be used interchangeably when validating this chart.

For example, work begins in the morning, the incident resolves in the afternoon, and closing is completed the next day. The elapsed resolution measure ends at resolution. A completion report anchored to closing can still place that same ticket in a different daily or weekly cohort.

A long duration does not automatically prove an SLA breach without considering the applicable target. Likewise, a low overall average can coexist with several serious breaches. Review the specific incident result and target when making a compliance statement.

When investigating an extreme value, compare the creation method and start timestamp first. A manually backdated occurrence should not be mistaken for time before the ticket existed when the calculation uses the manual Created At rule.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 19 | Congestion and interface exclusions

Monitoring and data

A congestion exclusion is a saved interface-specific visibility rule. It does not resolve or delete the source alarm.

Active alarms versus history

Current EZE/TCT alarms and historical congestion charts use separate queries in the IP alarm source queries. Active queries use their current active-record condition. Historical congestion uses its reporting cutoff and can include records that later cleared. Do not expect the historical chart to be the same list as current open alarms.

Exact exclusion scope

Review device and interface before excluding. The key includes owner, device identity, and interface. It uses IP where available, otherwise device name. It does not hide the entire device or every site sharing a site code.

Example: only one port

Device A has congestion on XGigabitEthernet0/0/22 and XGigabitEthernet0/0/23. Excluding port 22 hides its congestion on Device A. Port 23 stays visible. Device B's port 22 is not automatically hidden. Other alarm types are unaffected.

Remarks, blacklist, and restore

Add a remark explaining the exclusion. Blacklist shows interface, additional information, note, remark, and other saved metadata when available. Restore removes the visibility rule. It cannot recreate an alarm that no longer qualifies in the source.

Persistence

Rules live in the instance SQLite data and survive refresh and restart. Normal source sync does not erase them. Keep the entire instance folder when upgrading. Legacy rules lacking an interface are not treated as broad device exclusions.

A remark should explain the operational reason

Before saving an exclusion, confirm that its interface matches the record you intended. Similar device names and reused port labels make it important to read the IP and owner too. A port exclusion on one device is not a rule for every similarly named port.

Write a remark that another operator can understand later, such as an approved monitoring exception and its reason. The remark documents your decision; it is not a new alarm measurement or proof that utilization returned to normal.

If the device develops a second congested interface, that other port should remain visible. Seeing it after excluding the first port is correct behavior. Do not repeatedly exclude every remaining row unless each interface has its own valid operational reason.

Restore means remove the local visibility exception. A qualifying active alarm can then reappear, while an already-cleared source record may remain absent from the current list. Historical views and current-alarm views can still show different populations.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Card 20 | Cache, refresh, Cambodia time, and verification

Monitoring and data

The dashboard reads local cached records so opening a card does not repeatedly query every source system.

From source query to card

A background job runs PostgreSQL or MSSQL SQL, normalizes fields and timestamps, and writes a local snapshot under instance. Services read the snapshot, apply counting rules, and render cards and drilldowns. Browser refresh reloads that cached view; it does not guarantee a new source query.

Not every job uses five minutes

Incident and WO sync defaults to 300 seconds. APE, VIP, and many inventory jobs also default to 300 seconds. Active MSSQL alarms default to 10 seconds; historical congestion defaults to 300 seconds. Environment settings can override these values. Source availability and query completion affect when new data actually appears.

Cache dependencies

VIP alarms depend on both alarm and inventory caches. An incident may arrive before its matching inventory or alarm update. Jobs do not all commit at the same instant. A failed source fetch can leave the last successful snapshot visible.

Cambodia date rules

The application uses Asia/Phnom_Penh, UTC+7. Convert source UTC timestamps once. Occurred At, Created At, Resolved At, and Closed At are different fields. A Sunday-night occurrence closed Monday morning can belong to different weeks in occurrence and completion reports.

Updates and saved data

Keep instance for saved exclusions, Mentor sites, reports, and alert history, and keep .env for connections and delivery settings. Live caches continue refreshing after startup. Retaining instance does not freeze source data. Run only one dashboard version to avoid overlapping jobs and delivery.

Comparison checklist

Match category, statuses, date field, timezone, week, and counting unit. Compare IDs as well as totals. Confirm whether a badge counts sites while its drilldown lists alarm rows. Then check the last successful sync before concluding a record is missing.

What five minutes means during a real update

A five-minute job interval is a schedule, not a countdown guaranteeing that every screen changes exactly five minutes after a source edit. The job must start, reach the source successfully, finish its query, save the result, and then the browser must load the relevant view.

For example, a ticket changes just after its job collected data. It can remain in the previous state until the next successful cycle. If the source query fails, the last successful snapshot can remain visible longer. Repeated browser refreshes do not make that source request succeed.

Preserving instance during an upgrade keeps saved settings and history, but it also initially carries the last cached snapshots. After startup the normal jobs replace the source-backed caches. This is expected and does not mean the upgrade froze the old records permanently.

When explaining a stale value, distinguish three times: the source record timestamp, the successful cache-update time, and the time the browser displayed the page. They describe different steps. A clean comparison checks the identifiers and relevant timestamps at each step.

Refresh and comparison

This view uses the relevant saved datasets. Allow the corresponding source and inventory jobs to finish. A browser refresh does not force every source query.

Examples in this chapter illustrate the logic and are not the current live incident, site, or alarm totals.

Using the Help center and dashboard

How to use the dashboard

Start with the current fault cards when deciding what needs attention now. Use historical charts when comparing performance over time. A live alarm list, an active ticket list, and a completed-incident report answer different questions even when they mention the same site.

Click a number to inspect its records before drawing a conclusion. Check the site or incident identifier, status, timestamp, and selected filters. An incident can affect several sites, and one site can have several alarm events, so the same number does not always represent the same unit.

A simple investigation example

If a VIP site shows a power alarm, open that badge first. Confirm the site code and event, then inspect any linked incident. Next check the relevant Site Down or SLA guide if you need to understand the outage classification or deadline result. This is more reliable than adding together counts from unrelated cards.

Where to find more detail

The card guides explain source data, included records, counting rules, examples, and refresh behavior one card at a time. General guides cover navigation, maps, reports, and troubleshooting. The original PDF documentation remains available from the Help center.

Getting started: a practical investigation

Start with one question

Decide whether you want to see a current fault, find an incident, or review historical performance. Current alarm cards describe alarms that meet their source rules. Incident cards describe tickets and work orders. Trend cards describe records inside a reporting period.

For a specific problem, begin with its site code or incident ID. Use the relevant page and then open a matching badge or chart count. This keeps your investigation focused on a known record rather than an unexplained total.

Read a card step by step

Read the title, selected dates, and category filters before the number. Open the drilldown and check whether each row is an incident, work order, site, device alarm, or interface. The count can represent unique sites while the detail table shows several alarms per site.

Example

A badge shows two affected sites. Its table contains five alarms: three at the first site and two at the second. The badge is not wrong simply because the table has five rows. It is counting different objects. The card guide explains which counting method applies.

Before reporting a mismatch

Record the page name, exact badge, selected filters, and one example identifier. Check the next successful data update and compare the same scope in Streamline or the alarm source. Screenshots of two different date filters cannot establish that one count is incorrect.

Source data and comparing records

The path from source to screen

Background jobs collect records from the source systems and save a local copy. The dashboard reads that copy to build cards, charts, and tables. A source-system change appears after the relevant job succeeds; it is not necessarily visible immediately after a browser refresh.

Site inventory gives alarms their site name, code, grade, owner, location, and technology context. An alarm can exist in its source but fail a card's inventory matching or status rule. Missing inventory and missing source alarms are different problems.

Why related cards can change at different times

Alarm, incident, VIP, and inventory data are updated by different jobs. A new source alarm may arrive before a site's inventory designation is refreshed. Wait for the relevant dependencies, not just one timer, before assuming every card should change together.

Example: one incident across a week boundary

An incident occurs Sunday night and closes Monday morning. An occurrence-based report can count it in the earlier week, while a completion report places it in the following week. Both results can be correct. The same Cambodia timezone must be used when checking the boundary.

What to compare

Match status, category, date field, counting unit, and filters. Compare incident or site IDs as well as totals. The card-by-card guides describe these rules in ordinary language so users do not need to read application code.

Refresh, theme, layout, and fullscreen

Refresh and data freshness

Refresh reloads the displayed page. It does not force every background source query to run immediately. If the saved data is unchanged, the refreshed page may show the same records. Wait for a successful source update when investigating a newly changed ticket.

Theme and readability

Light and Dark change presentation, not the selected incidents or alarm rules. Use the theme that makes labels easiest to read on your screen. Changing the theme does not resolve an alarm, change SLA results, or update the source data.

Card layout

A custom layout changes where cards are placed so your most useful information is easier to reach. It does not change what their badges count. When helping another user, refer to the card title rather than only saying the top-left card, because their layout may differ.

Fullscreen

Fullscreen gives the dashboard more space on a monitoring display. It does not change the reporting window or the source data. Exit fullscreen using the control or the browser's fullscreen shortcut when you need access to other windows.

Example

Moving the SLA card above the incident card changes only the arrangement. A Response Not Met count still uses its original SLA filter. If the count changes, investigate a filter or data update rather than assuming the new layout changed the logic.

Choose the right view for your question

Use each card for its own purpose

VIP/VVIP focuses on strategically designated sites. Mentor Site focuses on your saved monitoring list. The IP cards describe POP and device alarms. RAN Status compares the available technology alarms with inventory. Incident / INC-WO by Status describes ticket workflows rather than raw alarms.

A badge is not always an alarm-row total

Distinct-site badges count a site once per category even when it has multiple events. Incident badges count ticket IDs. WO badges count work orders. Some IP counts combine mapped POP sites and unmapped alarm records. Read the individual guide before combining values.

Current state versus historical performance

An open-age chart measures tickets still active. A duration trend uses qualifying completed outages. SLA summaries use their own response and resolution cohorts. A site can appear in several contexts without those charts being duplicates.

Example: a site with several problems

A monitored VIP site has a Main AC Failure event, Low DC Voltage, and one active Site Down incident. It can appear in both VIP and Mentor views, both power categories, and the incident view. These are different perspectives on the same site, not several additional sites.

Find the detailed card guide

Return to Help center and choose the card's exact title under Understand each dashboard card. Each guide explains its source, rules, examples, drilldown, and update timing. Use those details to reproduce the same comparison in the source system.

Alarm colors and workflow colors

The green-zero and red-nonzero example explains alarm-count badges. It does not mean every colored label throughout the system is an alarm-health indicator. Incident and WO badges use their workflow labels, such as New, In Progress, or Resolved, to explain what the number represents.

For example, a Resolved badge can show a positive count of completed work. That count is not automatically an unhealthy result. Read the badge label and card title first, then open its detail records. Map colors have their own separate status and owner meanings.

Map view, colors, coordinates, and boundaries

Read the selected layer first

A map filter determines which sites or POPs you are looking at. On Air, Planned, Other, and Site Down represent different populations. A marker missing from a selected layer does not prove the site is absent from every inventory source.

Investigate one location

Search a known code, select the matching result, and open its marker. Check its name, status, and ticket reference where available. Similar place names are not reliable identifiers; use the code to distinguish sites in the same area.

Boundary selection and export

Choose the intended province, district, or commune before exporting a scoped list. Verify the boundary and active filter first. A boundary export should be interpreted as the selected map population, not a complete list of every incident affecting that province.

Example

A site has On Air inventory and an active Site Down incident. Its outage indicator can take precedence over the ordinary inventory status color. This does not mean its inventory record was deleted or changed to Planned.

If a marker looks wrong

Check coordinates, selected layer, source inventory, active ticket match, and last update. A delayed incident cache and a missing coordinate are different causes of a map discrepancy and need different checks.

Grey site status and grey POP ownership are different

For a normal site marker, green means On Air and blue means Planned. Grey is the fallback for Other or an unrecognized inventory status. If that site matches an active Site Down condition, red takes precedence over the usual inventory color.

For a POP marker, amber identifies Telcotech and purple identifies Ezecom. Grey means its owner value is blank, unknown, or not recognized as one of those two names. Grey POP ownership does not say that the POP is down, Planned, or removed.

Example: a grey site can have an Other inventory status while a nearby grey POP has no recognized owner. The same color is used for two separate marker types. Open the popup to confirm whether it is a site or POP before interpreting the color.

An owner value can exist but still use grey

The marker color uses the recognized owner names. A different spelling or another owner value can use the fallback grey even when the owner field is not empty. Therefore the grey POP count is not necessarily the same as a database count of blank owner fields only.

Read the POP name, code, and owner information together. Missing ownership does not delete the POP from inventory. It also does not establish an outage or prove that the physical device is unmonitored.

Latitude and longitude in the popup

Latitude and Longitude show the stored coordinates for the selected site or POP, formatted to six decimal places. These are the coordinates used for its map position, not a new GPS measurement taken when you open the popup.

Latitude describes north/south position and longitude east/west position. Keep them in that order when comparing with another map. If a stored value is unavailable or invalid, the popup uses an underscore rather than inventing a coordinate.

Current map color reference

Interpret the marker type before interpreting its color. Grey has different meanings for sites and POPs.

Marker	Color	Meaning
Site	Red	Matches active Site Down; overrides normal status color
Site	Green	On Air
Site	Blue	Planned
Site	Grey	Other or unrecognized inventory status
POP	Amber	Recognized Telcotech owner
POP	Purple	Recognized Ezecom owner
POP	Grey	Blank, unknown, or unrecognized owner; not an outage conclusion

Partner contacts and escalation information

Find the correct partner

Search the partner or contact information you know, then confirm the displayed organization and escalation details. Similar names can belong to different teams. Use the full record when deciding whom to contact.

Contact data is not incident status

Partner Contact provides reference information for communication. It does not prove that a particular team accepted a ticket or that an outage is resolved. Use the linked operational workflow for incident status and work-order ownership.

Example

An incident needs partner assistance. First verify the incident's responsible team and location, then use Partner Contact to locate the matching contact or escalation record. Do not assume the first search result is responsible for every site owned by the same organization.

Missing or outdated details

The page depends on the saved source contact data and its updates. If a number or email is missing, record the exact partner and field so the source record can be checked. Repeated browser refreshes cannot supply contact information that was never entered.

Reports and exports

Choose the report population

Before exporting, decide whether you need current alarms, active tickets, completed outages, or a selected map area. These lists have different inclusion rules. A historical record can remain in a report after disappearing from a current-fault card.

Filters matter

Apply the intended category, week, status, and site selections before exporting. Compare the export with the same filtered table. A spreadsheet containing raw alarm records can have more rows than a badge counting distinct sites.

Example

Three events belong to one site and two events belong to another. The site badge shows 2, while an alarm-record export can contain 5 rows. This difference is expected when the export explains the underlying events.

Read dates carefully

Check whether the report uses Occurred At, Created At, Resolved At, or Closed At. Use Cambodia time consistently. The selected date field can move an incident across a week boundary even though its identifier stays unchanged.

Before sharing

Review the report title, selected period, total records, and a sample of identifiers. Confirm whether an empty result comes from filters or an incomplete source update. Exporting does not resolve, acknowledge, or close the source records.

Prepare and export an incident report

Prepare the report

Select the intended saved report or begin a new one. Enter the incident reference, affected service or circuits, impact, and the times required by the document. Review source details before typing a summary; a report should describe the specific incident, not assumptions based on a similar ticket.

Draft versus completed report

Save as Draft is useful while information is incomplete. Save & Complete checks required fields before marking the report final. A completed document is a reporting state; it does not by itself change the operational incident to Resolved or Closed.

Build a readable chronology

Record each event with its correct date and time. A timeline that crosses midnight must retain the next day's date. Add a missing event in its proper context, then review the sorted sequence rather than relying on entry order.

Example: an overnight incident

Detection is recorded Monday 23:40, investigation Tuesday 00:10, and recovery Tuesday 01:20. These are three ordered events across two dates. Entering every event under Monday would misrepresent the outage even if the time values look correct.

Circuit information

In the smart report, one available circuit can populate the related field automatically. With more than one circuit, choose the applicable circuit for that record. Review dependent records after deleting or renaming an inventory circuit so the report still describes the intended service.

Export and final review

Save your latest changes before exporting PDF or Word. Check the incident reference, chronology, impact statements, circuit associations, and photo captions. An exported document is a saved output; later source changes do not automatically rewrite a file you already shared.

Alerts, restoration replies, and delivery checks

This chapter explains the current delivery logic. Use configured schedules rather than treating older reference intervals as the current schedule.

A check is not always a new message

A scheduled check inspects qualifying data. It can send nothing when there are no eligible records, the alert is disabled, the destination is unavailable, or the incident was already recorded as sent. Restarting the dashboard should not be treated as a request to resend every historical incident.

Site Down threshold alerts

The threshold alert identifies qualifying outages that have lasted beyond its configured limit. It records delivery history so repeated checks can recognize an incident that was already announced. Multi-site messages can include a site sheet when the configured workflow supports that attachment process.

Restoration details

Restoration timing follows the incident source rule. NOC/manual messages use Created At for the start and Closed At for restoration. Alarm-source messages use Issue Occurred At for the start and Cleared Alarm Received At for restoration. Root Cause uses Actual Root Cause only; Action Recovery uses Resolution only. These are different fields from the original alert's suspected cause or note.

Example

An outage is announced in the morning, then restoration is confirmed later. The restoration reply refers to the earlier incident; its posted time can be later than the restoration timestamp because the source had to update and a scheduled check had to run. Those two times do not have to be identical.

If a message does not arrive

First check whether the incident qualifies in the dashboard, whether it was already sent, and whether the latest source update succeeded. Then check the configured destination and workflow result. A webhook accepting a request does not alone prove the final Teams post or attachment succeeded. Avoid repeated tests to a live group without agreeing the destination and test content.

Saved data and safe application updates

Why local saved data is used

The application separates collecting source data from displaying it. Background jobs collect records, while page requests read saved copies and calculate the view. This reduces repeated source requests when several users open the same card.

Different types of saved information

Live caches are replaceable snapshots of alarms, incidents, inventory, and other source records. Saved user selections and delivery history are different: they preserve Mentor sites, congestion exclusions, reports, and previously sent alerts. A routine source refresh should not erase those saved choices.

Browser settings versus shared data

Presentation choices such as the saved theme can belong to the browser. The server's instance data holds shared application information. Copying only browser settings does not transfer the server's saved exclusions or alert history.

Updates

Keep both the instance folder and the connection settings when moving to a new application folder. Stop the old version before copying its database, and run only the intended version afterward. Keeping old instance data does not prevent incident and alarm caches from refreshing.

Performance expectations

A fast page can still show the last successful snapshot when a source is slow or unavailable. Page loading speed and source freshness are separate checks. Investigate a stale record using source update status and filters, not only how quickly the page opened.

Mentor Site: adding, importing, and retaining sites

What Mentor monitoring changes

Mentor Site narrows monitoring to the site codes you deliberately saved. It does not change the site's grade, make it VIP, close its tickets, or delete its alarms from other cards.

Adding codes safely

Use site inventory codes and preserve leading zeroes. For bulk import, download the template and keep its expected header. Read validation results before completing the add operation. An unknown code should be checked against inventory instead of repeatedly uploading the same invalid file.

Example

You save sites 0460 and 1002. Only alarms and qualifying Site Down incidents matched to those codes contribute to Mentor monitoring. If 0460 has three Main AC Failure events, it still counts as one site in that category. The detail list can show all three events.

Why a site can remain Site Down

An active Site Down incident can keep the site in the down group even when no corresponding down alarm is currently matched. This reflects the combined alarm-and-incident rule, not necessarily a stale alarm row.

Removing and retaining sites

Removing a configured site ends its Mentor selection but does not delete the source site or its incidents. Keep instance data during upgrades to preserve the monitoring list. For the full badge definitions and source rules, open the dedicated Mentor Site card guide.

Troubleshooting step by step

Start with the exact record

Record a site code, incident ID, or device and interface. Include the page, badge, selected dates, and category. A total without filters is difficult to verify because several correct views can count different populations.

A missing record

Check status, category, time window, source occurrence or completion date, and inventory matching. For congestion, check whether its interface is excluded. For Mentor, verify the saved site code. For VIP/VVIP, verify the strategic designation and active site inventory.

A different number

Determine the counting unit first. Sites, alarm rows, incidents, and WOs are not interchangeable. Then compare the same filters and allow the relevant source jobs to finish. If the mismatch remains, compare the actual identifiers in both lists.

SLA example

Response Not Met and Resolution Not Met are independent filters. An incident can fail both. Seeing two Resolution failures inside a list of fifteen Response failures does not mean the separate Resolution total must be two. Open each count to inspect its own matching population.

An empty page after startup

The application can open before its first successful background sync completes. Wait for the relevant data update, then refresh. If the page remains empty, check source availability and the selected filters rather than clearing all saved instance data.

What to report

Provide the exact expected identifier, where you saw it in the source, the filters and time used, and what the dashboard shows. For delivery issues, include the destination and expected alert type without sharing bot tokens or signed webhook links in the report.

Glossary: terms used throughout the guide

Alarm

An event reported by a monitoring source. It is not the same object as an incident ticket.

Incident

A parent ticket describing an operational issue; it can affect more than one site.

INC-WO

A work order linked to an incident. One incident can have several WOs.

Cache

The saved local copy used by the dashboard after a background source update.

Drilldown

The detailed records behind a selected badge, chart value, or table count.

Inventory

The reference data for sites, POPs, technologies, ownership, grades, and location.

Response SLA

The recorded result for meeting the applicable response deadline.

Resolution SLA

The recorded result for meeting the applicable resolution deadline.

Not Graded

No recorded resolution SLA result; it must not be assumed to mean Met.

Cohort

The set of records matching a specific date field, reporting window, and filters.

SRAN

The supported shared-baseband/connectivity event classification, not a new name for every full-site outage.

Exclusion

A saved interface-specific congestion visibility rule; it does not delete the source alarm.

Final verification checklist

The expected record

Keep one exact site, incident, WO, or device/interface identifier.

Matching filters

Use the same status, category, week, site, and cause selections.

Matching dates

Check the actual date field and Cambodia timezone.

Matching unit

Compare incidents with incidents, sites with sites, and alarm rows with alarm rows.

Source freshness

Confirm the relevant background jobs completed, including inventory dependencies.

Preserved settings

Check Mentor selection and interface exclusions before concluding data is missing.

Useful issue report

Record what you expected, what you saw, exact filters, and one example identifier. Do not include credentials or signed webhook URLs.