

sonos4lox - relevant MQTT/UDP inputs (Room)

Focus on actually useful Sonos status and media fields. Pure metadata fields (ip, model, room, rincon, service, ts, type, health) are removed. Text/URI fields remain included, but their generic Loxone command recognition is intentionally left blank.

Colours Legend: Usable via MQTT or UDP		Usable only via MQTT				
Loxone MQTT Command Recognition (copy/paste from MQTT client into Loxone Input)	value examples	Loxone Input	Template Title (in XML Templates included)	Loxone UDP Command Recognition (usage of XML template)	Loxone MQTT UDP Command Recognition (usage of XML template)	possible values
STATE						
s4lox_sonos_ROOM_state_state	PLAYING	VTI				PLAYING PAUSED STOPPED TRANSITIONING
s4lox_sonos_ROOM_state_state##_code	1	VI	State_code ROOM	\is4lox: ROOM_state_code@\i\v	MQTT:\is4lox/sonos/ROOM/state/state_code=\i\v	1 PLAYING 2 PAUSED 3 STOPPED 4 TRANSITIONING 0 unknown
s4lox_sonos_ROOM_state_playback##_storage	NETWORK	VTI				NETWORK TV ...
s4lox_sonos_ROOM_state_transport##_status	OK	VTI				OK ...
VOLUME						
s4lox_sonos_ROOM_volume_volume	0	VI	Volume ROOM	\is4lox: ROOM_volume@\i\v	MQTT:\is4lox/sonos/ROOM/volume/volume=\i\v	0..100
MUTE						
s4lox_sonos_ROOM_mute_mute	0	VI	Mute ROOM	\is4lox: ROOM_mute@\i\v	MQTT:\is4lox/sonos/ROOM/mute/mute=\i\v	0 1
EQ						
s4lox_sonos_ROOM_eq_balance	0	VI	EQ balance ROOM	\is4lox: ROOM_balance@\i\v	MQTT:\is4lox/sonos/ROOM/eq/balance=\i\v	Integer
s4lox_sonos_ROOM_eq_bass	4	VI	EQ bass ROOM	\is4lox: ROOM_bass@\i\v	MQTT:\is4lox/sonos/ROOM/eq/bass=\i\v	Integer
s4lox_sonos_ROOM_eq_treble	4	VI	EQ treble ROOM	\is4lox: ROOM_treble@\i\v	MQTT:\is4lox/sonos/ROOM/eq/treble=\i\v	Integer
s4lox_sonos_ROOM_eq_loudness	1	VI	EQ loudness ROOM	\is4lox: ROOM_loudness@\i\v	MQTT:\is4lox/sonos/ROOM/eq/loudness=\i\v	0 1
s4lox_sonos_ROOM_eq_nightmode	0	VI		\is4lox: ROOM_nightmode@\i\v	MQTT:\is4lox/sonos/ROOM/eq/nightmode=\i\v	0 1
s4lox_sonos_ROOM_eq_subgain	3	VI	EQ subgain ROOM	\is4lox: ROOM_subgain@\i\v	MQTT:\is4lox/sonos/ROOM/eq/subgain=\i\v	Integer
s4lox_sonos_ROOM_eq_dialoglevel	1	VI		\is4lox: ROOM_dialoglevel@\i\v	MQTT:\is4lox/sonos/ROOM/eq/dialoglevel=\i\v	Integer
GROUP						
s4lox_sonos_ROOM_group_is##_coordinator	1	VI		\is4lox: ROOM_group_is_coordinator@\i\v	MQTT:\is4lox/sonos/ROOM/group/is_coordinator=\i\v	0 1
s4lox_sonos_ROOM_group_role##_code	1	VI		\is4lox: ROOM_group_role@\i\v	MQTT:\is4lox/sonos/ROOM/group/role_code=\i\v	1 single 2 master 3 member
s4lox_sonos_ROOM_group_role##_name	single	VTI				single master member
s4lox_sonos_ROOM_group_coordinator##_room	ROOM	VTI				Room name
PLAYMODE						
s4lox_sonos_ROOM_playmode_mode##_raw	NORMAL	VTI				NORMAL REPEAT_ALL REPEAT_ONE SHUFFLE_*
s4lox_sonos_ROOM_playmode_code	0	VI	Playmode_code ROOM	\is4lox: ROOM_playmode_code@\i\v	MQTT:\is4lox/sonos/ROOM/playmode/code=\i\v	0 NORMAL 1 REPEAT_ALL 2 REPEAT_ONE 3 SHUFFLE_NOREPEAT 4 SHUFFLE_REPEAT_ALL 5 SHUFFLE_REPEAT_ONE 99 unknown
s4lox_sonos_ROOM_playmode_shuffle	0	VI	Shuffle ROOM	\is4lox: ROOM_shuffle@\i\v	MQTT:\is4lox/sonos/ROOM/playmode/shuffle=\i\v	0 1
s4lox_sonos_ROOM_playmode_repeat	0	VI	Repeat ROOM	\is4lox: ROOM_repeat@\i\v	MQTT:\is4lox/sonos/ROOM/playmode/repeat=\i\v	0 1
s4lox_sonos_ROOM_playmode_repeat##_one	0	VI	Repeat one ROOM	\is4lox: ROOM_repeat_one@\i\v	MQTT:\is4lox/sonos/ROOM/playmode/repeat_one=\i\v	0 1
s4lox_sonos_ROOM_playmode_crossfade	0	VI		\is4lox: ROOM_crossfade@\i\v	MQTT:\is4lox/sonos/ROOM/playmode/crossfade=\i\v	0 1
POSITION						
s4lox_sonos_ROOM_position_position##_sec	34	VI		\is4lox: ROOM_position_sec@\i\v	MQTT:\is4lox/sonos/ROOM/position/position_sec=\i\v	Seconds
s4lox_sonos_ROOM_position_duration##_sec	121	VI		\is4lox: ROOM_duration_sec@\i\v	MQTT:\is4lox/sonos/ROOM/position/duration_sec=\i\v	Seconds
s4lox_sonos_ROOM_position_progress##_pct	80	VI		\is4lox: ROOM_progress_pct@\i\v	MQTT:\is4lox/sonos/ROOM/position/progress_pct=\i\v	0..100
s4lox_sonos_ROOM_position_track##_no	2	VI	Pos track_no ROOM	\is4lox: ROOM_track_no@\i\v	MQTT:\is4lox/sonos/ROOM/position/track_no=\i\v	Integer
s4lox_sonos_ROOM_position_track##_count	5	VI	Pos track_count ROOM	\is4lox: ROOM_track_count@\i\v	MQTT:\is4lox/sonos/ROOM/position/track_count=\i\v	Integer
s4lox_sonos_ROOM_position_av##_uri						URI / may be empty
TRACK						
s4lox_sonos_ROOM_track_title	Let it be	VTI				Text / may be empty
s4lox_sonos_ROOM_track_artist	Beatles	VTI				Text / may be empty
s4lox_sonos_ROOM_track_album	Let it be	VTI				Text / may be empty
s4lox_sonos_ROOM_track_tit	Let it be	VTI				Text / may be empty
s4lox_sonos_ROOM_track_int	Beatles	VTI				Text / may be empty
s4lox_sonos_ROOM_track_titint	Let it be - Beatles	VTI				Text / may be empty
s4lox_sonos_ROOM_track_radio	FFH Die 80er	VTI				Text / may be empty
s4lox_sonos_ROOM_track_radioStationName	FFH Die 80er	VTI				Text / may be empty
s4lox_sonos_ROOM_track_streamContent	Indeep - Last Night A DJ Saved My Life	VTI				Text / may be empty
s4lox_sonos_ROOM_track_source	2	VI		\is4lox: ROOM_current_source@\i\v	MQTT:\is4lox/sonos/ROOM/track/source=\i\v	0 Nothing 1 Radio 2 Track 3 TV 4 LineIn
s4lox_sonos_ROOM_track_source##_text	Track	VTI				Nothing Radio Track TV LineIn

sonos4lox - relevant MQTT/UDP inputs (Room)

Focus on actually useful Sonos status and media fields. Pure metadata fields (ip, model, room, rincon, service, ts, type, health) are removed. Text/URI fields remain included, but their generic Loxone command recognition is intentionally left blank.

Colours Legend:		Usable via MQTT or UDP				
		Usable only via MQTT				
Loxone MQTT Command Recognition (copy/paste from MQTT client into Loxone Input)	value examples	Loxone Input	Template Title (in XML Templates included)	Loxone UDP Command Recognition (usage of XML template)	Loxone MQTT UDP Command Recognition (usage of XML template)	possible values
s4lox_sonos_ROOM_track_sid	Music	VTI				TV Radio Music
s4lox_sonos_ROOM_track_cover	http://192.168.50.65:1400/getaa?s=1&u=x-sonosapi-stream%3as84481%3fsid%3d333%26flags%3d8232%26sn%3d30	VTI				URL / may be empty
s4lox_sonos_ROOM_track_albumArtUri	http://192.168.50.65:1400/getaa?s=1&u=x-sonosapi-stream%3as84481%3fsid%3d333%26flags%3d8232%26sn%3d30	VTI				URL / may be empty
s4lox_sonos_ROOM_track_tvstate	0	VI		\is4lox: ROOM_tvstate@\i\v	MQTT:\is4lox/sonos/ROOM/track/tvstate=\i\v	0 1 (currently placeholder)
NEXTTRACK						
s4lox_sonos_ROOM_nexttrack_title	Radioname or Nexttitle (Playlist)	VTI				Text / may be empty
s4lox_sonos_ROOM_nexttrack_artist	Beatles	VTI				Text / may be empty
s4lox_sonos_ROOM_nexttrack_album	Let it be	VTI				Text / may be empty
s4lox_sonos_ROOM_nexttrack_streamContent		VTI				Text / may be empty
s4lox_sonos_ROOM_nexttrack_radioStationName		VTI				Text / may be empty
s4lox_sonos_ROOM_nexttrack_albumArtUri	https://cdn-profiles.tunein.com/s84481/images/logoq.jpg	VTI				URL / may be empty
s4lox_sonos_ROOM_nexttrack_uri	https://cdn-profiles.tunein.com/s84481/images/logoq.jpg	VTI				URI / may be empty