

干扰范围：
全向： 500-1000m
定线： 1000-2000m

Frequencies & Powers:

Version IV: 6 频：全向+定向天线

频段MHz	功率 (W)±1.5dB
428-438	46dBm (40W)
902 - 928	46dBm (40W)
1559- 1610	46dBm (40W)
2400 - 2500	46dBm (40W)
5725 - 5875	46dBm (30W)
1170-1280	46dBm (40W)
2400-2500	46dBm (40W)
5150-5250	46dBm (30W)



背包式无人机屏蔽器

Version II. 参数：

外接天线：8 根全向 (6-8 dBi) 天线.	
手持式定向天线：1 套定向高增益天线	
VSWR – 天线断开/短路保护	
内置锂电池 -使用 1 小时 / 待机 48 小时 / 充电时间 5 小时	
电源 90-260 V AC / 24-30 VDC	
重量:35kg (一套)	
频段	输出功率
1. 1575-1610 MHz	40 W / 46±1.5dbm
2. 2400-2500 MHz	40 W / 46±1.5dbm
3. 5725-5850 MHz	30 W / 45±1.5dbm
4.433MHz	40 W / 46 ±1.5dbm
5. 860-930 MHz	40 W / 46±1.5dbm
6.1170-1280MHz	40 W / 46±1.5dbm
7.2400-2500MHz	40 W / 46±1.5dbm
8.5150-5250MHz	30 W / 45±1.5dbm
Total amount:300W Power consumption:600W	
保护措施	VSWR 保护 过热保护： 70°切断操作 65°恢复运行
散热	风扇散热

控制装置/指示器	On/Off 开关指示灯 外接有线遥控器，可选择频段（每个频段1个按钮）
电池	Li Ion 25AH
外壳	背包式
Environmental	
工作温度	-20°c to +65°c
防护	IP52
相对湿度	5%-95%

遥控盒要有对应的频段开关:

- Each button should select if the band will be jammed or not
- Each button should be labeled:
- CH1 5.8 (Light on = selected. Light off = not selected)
- CH2 915 (Light on = selected. Light off = not selected)
- CH3 GPSL1 (Light on = selected. Light off = not selected)
- CH4 GPSL1 (Light on = selected. Light off = not selected)
- CH5 2.4 (Light on = selected. Light off = not selected)
- CH6 433MHz (Light on = selected. Light off = not selected)
- CH7 2.4GHz (Light on = selected. Light off = not selected)
- CH8 5.8GHz (Light on = selected. Light off = not selected)

遥控盒



套装:

- 背包: 1 个
- 电源: 1 个
- 全向天线: 8 根
- 定向天线: 1 个



背包屏蔽器



遥控盒



馈线





电池

Transportability

发货套装如下：



发货套装



Warranty

12 months