



US 20190334221A1

(19) **United States**(12) **Patent Application Publication****Henry et al.**(10) **Pub. No.: US 2019/0334221 A1**(43) **Pub. Date: Oct. 31, 2019**

(54) **GUIDED WAVE COUPLERS FOR COUPLING ELECTROMAGNETIC WAVES BETWEEN A WAVEGUIDE SURFACE AND A SURFACE OF A WIRE**

(71) Applicant: **AT&T Intellectual Property I, L.P.**,
Atlanta, GA (US)

(72) Inventors: **Paul Shala Henry**, Holmdel, NJ (US);
Donald J. Barnickel, Flemington, NJ (US);
Farhad Barzegar, Branchburg, NJ (US);
Robert Bennett, Southold, NY (US);
Irwin Gerszberg, Kendall Park, NJ (US);
Thomas M. Willis, III, Tinton Falls, NJ (US)

(73) Assignee: **AT&T Intellectual Property I, L.P.**,
Atlanta, GA (US)

(21) Appl. No.: **16/507,485**

(22) Filed: **Jul. 10, 2019**

Related U.S. Application Data

(63) Continuation of application No. 15/602,944, filed on May 23, 2017, now Pat. No. 10,396,424, which is a continuation of application No. 14/469,287, filed on Aug. 26, 2014, now Pat. No. 9,692,101.

Publication Classification(51) **Int. Cl.****H01P 5/08** (2006.01)**H04B 3/52** (2006.01)**H01P 5/103** (2006.01)**H01P 3/10** (2006.01)**H01P 3/16** (2006.01)**H04B 3/56** (2006.01)**H04B 3/38** (2006.01)**H04B 3/58** (2006.01)(52) **U.S. Cl.**CPC **H01P 5/087** (2013.01); **H04B 3/52**(2013.01); **H01P 5/103** (2013.01); **H04B 3/58**(2013.01); **H01P 3/16** (2013.01); **H04B 3/56**(2013.01); **H04B 3/38** (2013.01); **H01P 3/10**


(2013.01)

(57)

ABSTRACT

A dielectric waveguide coupling system for launching and extracting guided wave communication transmissions from a wire. At millimeter-wave frequencies, wherein the wavelength is small compared to the macroscopic size of the equipment, transmissions can propagate as guided waves guided by a strip of dielectric material. Unlike conventional waveguides, the electromagnetic field associated with the dielectric waveguide is primarily outside of the waveguide. When this dielectric waveguide strip is brought into close proximity to a wire, the guided waves decouple from the dielectric waveguide and couple to the wire, and continue to propagate as guided waves about the surface of the wire.

200






FIG. 1




FIG. 2




FIG. 3




FIG. 4




FIG. 5




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13a




FIG. 13b




FIG. 13c




FIG. 14




FIG. 15




FIG. 16

GUIDED WAVE COUPLERS FOR COUPLING ELECTROMAGNETIC WAVES BETWEEN A WAVEGUIDE SURFACE AND A SURFACE OF A WIRE

CROSS-REFERENCE TO RELATED APPLICATION(S)

[0001] This application is a continuation of U.S. patent application Ser. No. 15/602,944 filed May 23, 2017, pending, which is a continuation of U.S. patent application Ser. No. 14/469,287 filed Aug. 26, 2014 (now U.S. Pat. No. 9,692,101, issued Jun. 27, 2017). All sections of the aforementioned application(s) are incorporated herein by reference in their entirety.

TECHNICAL FIELD

[0002] The subject disclosure relates to guided wave couplers and methods thereof.

BACKGROUND

[0003] As smart phones and other portable devices increasingly become ubiquitous, and data usage increases, macrocell base station devices and existing wireless infrastructure in turn require higher bandwidth capability in order to address the increased demand. To provide additional mobile bandwidth, small cell deployment is being pursued, with microcells and picocells providing coverage for much smaller areas than traditional macrocells.

BRIEF DESCRIPTION OF THE DRAWINGS

[0004] FIG. 1 is a block diagram illustrating an example, non-limiting embodiment of a guided wave communications system in accordance with various aspects described herein.

[0005] FIG. 2 is a block diagram illustrating an example, non-limiting embodiment of a dielectric waveguide coupler in accordance with various aspects described herein.

[0006] FIG. 3 is a block diagram illustrating an example, non-limiting embodiment of a dielectric waveguide coupler in accordance with various aspects described herein.

[0007] FIG. 4 is a block diagram illustrating an example, non-limiting embodiment of a dielectric waveguide coupler in accordance with various aspects described herein.

[0008] FIG. 5 is a block diagram illustrating an example, non-limiting embodiment of a dielectric waveguide coupler and transceiver in accordance with various aspects described herein.

[0009] FIG. 6 is a block diagram illustrating an example, non-limiting embodiment of a dual dielectric waveguide coupler in accordance with various aspects described herein.

[0010] FIG. 7 is a block diagram illustrating an example, non-limiting embodiment of a bidirectional dielectric waveguide coupler in accordance with various aspects described herein.

[0011] FIG. 8 illustrates a block diagram illustrating an example, non-limiting embodiment of a bidirectional dielectric waveguide coupler in accordance with various aspects described herein.

[0012] FIG. 9 illustrates a block diagram illustrating an example, non-limiting embodiment of a bidirectional repeater system in accordance with various aspects described herein.

[0013] FIG. 10 illustrates a flow diagram of an example, non-limiting embodiment of a method for transmitting a transmission with a dielectric waveguide coupler as described herein.

[0014] FIG. 11 is a block diagram of an example, non-limiting embodiment of a computing environment in accordance with various aspects described herein.

[0015] FIG. 12 is a block diagram of an example, non-limiting embodiment of a mobile network platform in accordance with various aspects described herein.

[0016] FIGS. 13a, 13b, and 13c are block diagrams illustrating example, non-limiting embodiments of a slotted waveguide coupler in accordance with various aspects described herein.

[0017] FIG. 14 is a block diagram illustrating an example, non-limiting embodiment of a waveguide coupling system in accordance with various aspects described herein.

[0018] FIG. 15 is a block diagram illustrating an example, non-limiting embodiment of a waveguide coupling system in accordance with various aspects described herein.

[0019] FIG. 16 illustrates a flow diagram of an example, non-limiting embodiment of a method for transmitting an electromagnetic wave with use of a waveguide as described herein.

DETAILED DESCRIPTION OF THE PRESENT EMBODIMENTS

[0020] One or more embodiments are now described with reference to the drawings, wherein like reference numerals are used to refer to like elements throughout the drawings. In the following description, for purposes of explanation, numerous details are set forth in order to provide a thorough understanding of the various embodiments. It is evident, however, that the various embodiments can be practiced without these details (and without applying to any particular networked environment or standard).

[0021] To provide network connectivity to additional base station devices, the backhaul network that links the communication cells (e.g., microcells and macrocells) to network devices of the core network correspondingly expands. Similarly, to provide network connectivity to a distributed antenna system, an extended communication system that links base station devices and their distributed antennas is desirable. A guided wave communication system can be provided to enable alternative, increased or additional network connectivity and a waveguide coupling system can be provided to transmit and/or receive guided wave (e.g., surface wave) communications on a wire, such as a wire that operates as a single-wire transmission line (e.g., a utility line), that operates as a waveguide and/or that otherwise operates to guide the transmission of an electromagnetic wave. In an embodiment, a waveguide coupler that is utilized in a waveguide coupling system can be made of a dielectric material, or other low-loss insulator (e.g., TEF-LON®, e.g., synthetic resin, polyethylene and etc.), or even be made of a conducting (e.g., metallic, non-conducting, etc.) material, or any combination of the foregoing materials. Reference throughout the detailed description to “dielectric waveguide” is for illustration purposes and does not limit embodiments to being constructed solely of dielectric materials. In other embodiments, other dielectric or insulating materials are possible. It will be appreciated that a variety of wires, whether insulated or not, and whether single-stranded

or multi-stranded, can be utilized with guided wave communications without departing from example embodiments.

[0022] For these and/or other considerations, in one or more embodiments, an apparatus comprises a waveguide that facilitates propagation of a first electromagnetic wave at least in part on a waveguide surface, wherein the waveguide surface does not surround in whole or in substantial part a wire surface of a wire, and, in response to the waveguide being positioned with respect to the wire, the first electromagnetic wave couples at least in part to the wire surface and travels at least partially around the wire surface as a second electromagnetic wave, and wherein the second electromagnetic wave has a wave propagation mode.

[0023] In another embodiment, an apparatus comprises a waveguide that has a waveguide surface that defines a cross sectional area of the waveguide wherein a wire is positioned outside of the cross-sectional area of the waveguide such that a first electromagnetic wave, traveling along the wire in part on the wire surface, couples at least in part to the waveguide surface and travels at least partially around the waveguide surface as a second electromagnetic wave.

[0024] In an embodiment, a method comprises emitting, by a transmission device, a first electromagnetic wave that propagates at least in part on a waveguide surface of a waveguide, wherein the waveguide is not coaxially aligned with a wire. The method can also include configuring the waveguide in proximity of the wire to facilitate coupling of at least a part of the first electromagnetic wave to a wire surface, forming a second electromagnetic wave that propagates at least partially around the wire surface.

[0025] In another embodiment, an apparatus comprises, in one or more embodiments, a waveguide having a slot formed by opposing slot surfaces that are non-parallel, wherein the opposing slot surfaces are separated by a distance that enables insertion of a wire in the slot, wherein the waveguide facilitates propagation of a first electromagnetic wave at least in part on a waveguide surface, and, in response to the waveguide being positioned with respect to the wire, the first electromagnetic wave couples at least in part to a wire surface of the wire and travels at least partially around the wire surface as a second electromagnetic wave, and wherein the second electromagnetic wave has a wave propagation mode.

[0026] In another embodiment, an apparatus comprises, in one or more embodiments, a waveguide, wherein the waveguide comprises a material that is not electrically conductive and is suitable for propagating electromagnetic waves on a waveguide surface of the waveguide, wherein the waveguide facilitates propagation of a first electromagnetic wave at least in part on the waveguide surface, and, in response to the waveguide being positioned with respect to a wire, the first electromagnetic wave couples at least in part to a wire surface of the wire and travels at least partially around the wire surface as a second electromagnetic wave, and wherein the second electromagnetic wave has a wave propagation mode.

[0027] In another embodiment, a method of transmitting electromagnetic waves with use of a waveguide disposed in proximity to but not coaxially aligned with a wire can include emitting, by a transmission device, a first electromagnetic wave that propagates at least in part on the surface of the waveguide. The method can also include delivering at least a part of the first electromagnetic wave to the surface of the wire via the non-coaxially aligned waveguide, thereby

forming a second electromagnetic wave that propagates along the wire, at least partially around the wire surface.

[0028] Various embodiments described herein relate to a dielectric waveguide coupling system for launching and extracting guided wave (e.g., surface wave communications that are electromagnetic waves) transmissions from a wire. At millimeter-wave frequencies, wherein the wavelength is small compared to the size of the equipment, transmissions can propagate as waves guided by a strip or length of dielectric material. The electromagnetic field structure of the guided wave can be both inside and outside of the waveguide. However, in alternate embodiments, the electromagnetic structure of the guided wave can also be primarily inside or primarily outside of the waveguide as well. When this dielectric waveguide strip is brought into close proximity to a wire (e.g., a utility line or other transmission line), at least a portion of the guided waves decouples from the dielectric waveguide and couples to the wire, and continue to propagate as guided waves, such as surface waves about the surface of the wire. According to an example embodiment, a surface wave is a type of guided wave that is guided by a surface of the wire, which can include an exterior or outer surface of the wire, or another surface of the wire that is adjacent to or exposed to another type of medium having different properties (e.g., dielectric properties). Indeed, in an example embodiment, a surface of the wire that guides a surface wave can represent a transitional surface between two different types of media. For example, in the case of a bare or uninsulated wire, the surface of the wire can be the outer or exterior conductive surface of the bare or uninsulated wire that is exposed to air or free space. As another example, in the case of insulated wire, the surface of the wire can be the conductive portion of the wire that meets the insulator portion of the wire, or can otherwise be the insulator surface of the wire that is exposed to air or free space, or can otherwise be any material region between the insulator surface of the wire and the conductive portion of the wire that meets the insulator portion of the wire, depending upon the relative differences in the properties (e.g., dielectric properties) of the insulator, air, and/or the conductor. As described herein, insulated wire can refer to any metallic wire or cable with a dielectric coating or sheathing, regardless of the intended function of such dielectric coating. Such insulated wires can include in some embodiments, tree guard insulation and Hendrix insulation, among other varieties of insulation.

[0029] According to an example embodiment, guided waves such as surface waves can be contrasted with radio transmissions over free space/air or conventional propagation of electrical power or signals through the conductor of the wire. Indeed, with surface wave or guided wave systems described herein, conventional electrical power or signals can still propagate or be transmitted through the conductor of the wire, while guided waves (including surface waves and other electromagnetic waves) can propagate or be transmitted about the surface of the wire, according to an example embodiment. In an embodiment, a surface wave can have a field structure (e.g., an electromagnetic field structure) that lies primarily or substantially outside of the line or wire that serves to guide the surface wave.

[0030] According to an example embodiment, the electromagnetic waves traveling along the wire and around the outer surface of the wire are induced by other electromagnetic waves traveling along a waveguide in proximity to the

wire. The inducement of the electromagnetic waves can be independent of any electrical potential, charge or current that is injected or otherwise transmitted through the wires as part of an electrical circuit. It is to be appreciated that while a small current in the wire may be formed in response to the propagation of the electromagnetic wave through the wire, this can be due to the propagation of the electromagnetic wave along the wire surface, and is not formed in response to electrical potential, charge or current that is injected into the wire as part of an electrical circuit. The electromagnetic waves traveling on the wire therefore do not require a return path (i.e., circuit) to propagate along the wire surface. The wire therefore is a single wire transmission line that is not part of a circuit. Also, in some embodiments, a wire is not necessary, and the electromagnetic waves can propagate along a single line transmission medium that is not a wire.

[0031] According to an example embodiment, the term “about” a wire used in conjunction with a guided wave (e.g., surface wave) can include fundamental wave propagation modes and other guided waves having a circular or substantially circular field distribution (e.g., electric field, magnetic field, electromagnetic field, etc.) at least partially around a wire. In addition, when a guided wave propagates “about” a wire, it can do so according to a wave propagation mode that includes not only the fundamental wave propagation modes (e.g., zero order modes), but additionally or alternatively other non-fundamental wave propagation modes such as higher-order guided wave modes (e.g., 1st order modes, 2nd order modes, etc.), asymmetrical modes and/or other guided (e.g., surface) waves that have non-circular field distributions around a wire. For example, such non-circular field distributions can be unilateral or multi-lateral with one or more axial lobes characterized by relatively higher field strength and/or one or more nulls or null regions characterized by relatively low-field strength, zero-field strength or substantially zero field strength. Further, the field distribution can otherwise vary as a function of a longitudinal axial orientation around the wire such that one or more regions of axial orientation around the wire have an electric or magnetic field strength (or combination thereof) that is higher than one or more other regions of axial orientation, according to an example embodiment. It will be appreciated that the relative positions of the wave higher order modes or asymmetrical modes can vary as the guided wave travels along the wire.

[0032] Referring now to FIG. 1, a block diagram illustrating an example, non-limiting embodiment of a guided wave communication system 100 is shown. Guided wave communication system 100 depicts an exemplary environment in which a dielectric waveguide coupling system can be used.

[0033] Guided wave communication system 100 can be a distributed antenna system that includes one or more base station devices (e.g., base station device 104) that are communicably coupled to a macrocell site 102 or other network connection. Base station device 104 can be connected by a wired (e.g., fiber and/or cable), or by a wireless (e.g., microwave wireless) connection to macrocell site 102. Macrocells such as macrocell site 102 can have dedicated connections to the mobile network and base station device 104 can share and/or otherwise use macrocell site 102's connection. Base station device 104 can be mounted on, or attached to, utility pole 116. In other embodiments, base station device 104 can be near transformers and/or other locations situated nearby a power line.

[0034] Base station device 104 can facilitate connectivity to a mobile network for mobile devices 122 and 124. Antennas 112 and 114, mounted on or near utility poles 118 and 120, respectively, can receive signals from base station device 104 and transmit those signals to mobile devices 122 and 124 over a much wider area than if the antennas 112 and 114 were located at or near base station device 104.

[0035] It is noted that FIG. 1 displays three utility poles, with one base station device, for purposes of simplicity. In other embodiments, utility pole 116 can have more base station devices, and one or more utility poles with distributed antennas are possible.

[0036] A dielectric waveguide coupling device 106 can transmit the signal from base station device 104 to antennas 112 and 114 via utility or power line(s) that connect the utility poles 116, 118, and 120. To transmit the signal, radio source and/or coupler 106 upconverts the signal (e.g., via frequency mixing) from base station device 104 to a millimeter-wave band signal and the dielectric waveguide coupling device 106 launches a millimeter-wave band wave that propagates as a guided wave (e.g., surface wave or other electromagnetic wave) traveling along the utility line or other wire. At utility pole 118, another dielectric waveguide coupling device 108 receives the guided wave (and optionally can amplify it as needed or desired) and sends it forward as a guided wave (e.g., surface wave or other electromagnetic wave) on the utility line or other wire. The dielectric waveguide coupling device 108 can also extract a signal from the millimeter-wave band guided wave and shift it down in frequency to its original cellular band frequency (e.g., 1.9 GHz or other defined cellular frequency) or another cellular (or non-cellular) band frequency. An antenna 112 can transmit (e.g., wirelessly transmit) the downshifted signal to mobile device 122. The process can be repeated by dielectric waveguide coupling device 110, antenna 114 and mobile device 124, as necessary or desirable.

[0037] Transmissions from mobile devices 122 and 124 can also be received by antennas 112 and 114 respectively. Repeaters on dielectric waveguide coupling devices 108 and 110 can upshift or otherwise convert the cellular band signals to millimeter-wave band and transmit the signals as guided wave (e.g., surface wave or other electromagnetic wave) transmissions over the power line(s) to base station device 104.

[0038] In an example embodiment, system 100 can employ diversity paths, where two or more utility lines or other wires are strung between the utility poles 116, 118, and 120 (e.g., for example, two or more wires between poles 116 and 120) and redundant transmissions from base station 104 are transmitted as guided waves down the surface of the utility lines or other wires. The utility lines or other wires can be either insulated or uninsulated, and depending on the environmental conditions that cause transmission losses, the coupling devices can selectively receive signals from the insulated or uninsulated utility lines or other wires. The selection can be based on measurements of the signal-to-noise ratio of the wires, or based on determined weather/environmental conditions (e.g., moisture detectors, weather forecasts, etc.). The use of diversity paths with system 100 can enable alternate routing capabilities, load balancing, increased load handling, concurrent bi-directional or synchronous communications, spread spectrum communications, etc. (See FIG. 8 for more illustrative details).

[0039] It is noted that the use of the dielectric waveguide coupling devices **106**, **108**, and **110** in FIG. **1** are by way of example only, and that in other embodiments, other uses are possible. For instance, dielectric waveguide coupling devices can be used in a backhaul communication system, providing network connectivity to base station devices. Dielectric waveguide coupling devices can be used in many circumstances where it is desirable to transmit guided wave communications over a wire, whether insulated or not insulated. Dielectric waveguide coupling devices are improvements over other coupling devices due to no contact or limited physical and/or electrical contact with the wires. With dielectric waveguide coupling devices, the apparatus can be located away from the wire (e.g., spaced apart from the wire) and/or located on the wire so long as it is not electrically in contact with the wire, as the dielectric acts as an insulator, allowing for cheap, easy, and/or less complex installation.

[0040] It is further noted, that while base station device **104** and macrocell site **102** are illustrated in an embodiment, other network configurations are likewise possible. For example, devices such as access points or other wireless gateways can be employed in a similar fashion to extend the reach of other networks such as a wireless local area network, a wireless personal area network or other wireless network that operates in accordance with a communication protocol such as a 802.11 protocol, WIMAX protocol, UltraWideband protocol, BLUETOOTH® protocol, ZIGBEE® protocol or other wireless protocol.

[0041] Turning now to FIG. **2**, illustrated is a block diagram of an example, non-limiting embodiment of a dielectric waveguide coupling system **200** in accordance with various aspects described herein. System **200** comprises a dielectric waveguide **204** that has a wave **206** propagating as a guided wave about a waveguide surface of the dielectric waveguide **204**. In an embodiment, the dielectric waveguide **204** is curved, and at least a portion of the waveguide **204** can be placed near a wire **202** in order to facilitate coupling between the waveguide **204** and the wire **202**, as described herein. The dielectric waveguide **204** can be placed such that a portion of the curved dielectric waveguide **204** is parallel or substantially parallel to the wire **202**. The portion of the dielectric waveguide **204** that is parallel to the wire can be an apex of the curve, or any point where a tangent of the curve is parallel to the wire **202**. When the dielectric waveguide **204** is positioned or placed thusly, the wave **206** travelling along the dielectric waveguide **204** couples, at least in part, to the wire **202**, and propagates as guided wave **208** around or about the wire surface of the wire **202**. The guided wave **208** can be characterized as a surface wave or other electromagnetic wave, although other types of guided waves **208** can be supported as well without departing from example embodiments. A portion of the wave **206** that does not couple to the wire **202** propagates as wave **210** along the dielectric waveguide **204**. It will be appreciated that the dielectric waveguide **204** can be configured and arranged in a variety of positions in relation to the wire **202** to achieve a desired level of coupling or non-coupling of the wave **206** to the wire **202**. For example, the curvature and/or length of the dielectric waveguide **204** that is parallel or substantially parallel, as well as its separation distance (which can include zero separation distance in an embodiment), to the wire **202** can be varied without departing from example embodiments.

Likewise, the arrangement of dielectric waveguide **204** in relation to the wire **202** may be varied based upon considerations of the respective intrinsic characteristics (e.g., thickness, composition, electromagnetic properties, etc.) of the wire **202** and the dielectric waveguide **204**, as well as the characteristics (e.g., frequency, energy level, etc.) of the waves **206** and **208**.

[0042] The guided wave **208** stays parallel or substantially parallel to the wire **202**, even as the wire **202** bends and flexes. Bends in the wire **202** can increase transmission losses, which are also dependent on wire diameters, frequency, and materials. If the dimensions of the dielectric waveguide **204** are chosen for efficient power transfer, most of the power in the wave **206** is transferred to the wire **202**, with little power remaining in wave **210**. It will be appreciated that the guided wave **208** can still be multi-modal in nature (discussed herein), including having modes that are non-fundamental or asymmetric, while traveling along a path that is parallel or substantially parallel to the wire **202**. In an embodiment, non-fundamental or asymmetric modes can be utilized to minimize transmission losses and/or obtain increased propagation distances.

[0043] It is noted that the term “parallel” is generally a geometric construct which often is not exactly achievable in real systems. Accordingly, the term “parallel” as utilized in the subject disclosure represents an approximation rather than an exact configuration when used to describe embodiments disclosed in the subject disclosure. In an embodiment, “substantially parallel” can include approximations that are within 30 degrees of true parallel in all dimensions.

[0044] In an embodiment, the wave **206** can exhibit one or more wave propagation modes. The dielectric waveguide modes can be dependent on the shape and/or design of the waveguide **204**. The one or more dielectric waveguide modes of wave **206** can generate, influence, or impact one or more wave propagation modes of the guided wave **208** propagating along wire **202**. In an embodiment, the wave propagation modes on the wire **202** can be similar to the dielectric waveguide modes since both waves **206** and **208** propagate about the outside of the dielectric waveguide **204** and wire **202** respectively. In some embodiments, as the dielectric waveguide mode couple to the wire **202**, the modes can change form due to differences in size, material, and/or impedances of the dielectric waveguide **204** and wire **202**. The wave propagation modes can comprise the fundamental transverse electromagnetic mode (Quasi-TEM₀₀), where only small electric and/or magnetic fields extend in the direction of propagation, and the electric and magnetic fields extend radially outwards while the guided wave propagates along the wire. This guided wave mode can be donut shaped, where few of the electromagnetic fields exist within the dielectric waveguide **204** or wire **202**. Waves **206** and **208** can comprise a fundamental TEM mode where the fields extend radially outwards, and also comprise other, non-fundamental (e.g., asymmetric, higher-level, etc.) modes. While particular wave propagation modes are discussed above, other wave propagation modes are likewise possible such as transverse electric (TE) and transverse magnetic (TM) modes, based on the frequencies employed, the design of the dielectric waveguide **204**, the dimensions and composition of the wire **202**, as well as its surface characteristics, its optional insulation, the electromagnetic properties of the surrounding environment, etc. It should be noted that, depending on the frequency, the electrical and

physical characteristics of the wire **202** and the particular wave propagation modes that are generated, guided wave **208** can travel along the conductive surface of an oxidized uninsulated wire, an unoxidized uninsulated wire, an insulated wire and/or along the insulating surface of an insulated wire.

[0045] In an embodiment, a diameter of the dielectric waveguide **204** is smaller than the diameter of the wire **202**. For the millimeter-band wavelength being used, the dielectric waveguide **204** supports a single waveguide mode that makes up wave **206**. This single waveguide mode can change as it couples to the wire **202** as guided wave **208**. If the dielectric waveguide **204** were larger, more than one waveguide mode can be supported, but these additional waveguide modes may not couple to the wire **202** as efficiently, and higher coupling losses can result. However, in some alternative embodiments, the diameter of the dielectric waveguide **204** can be equal to or larger than the diameter of the wire **202**, for example, where higher coupling losses are desirable or when used in conjunction with other techniques to otherwise reduce coupling losses (e.g., impedance matching with tapering, etc.).

[0046] In an embodiment, the wavelength of the waves **206** and **208** are comparable in size, or smaller than a circumference of the dielectric waveguide **204** and the wire **202** respectively. In an example, if the wire **202** has a diameter of 0.5 cm, and a corresponding circumference of around 1.5 cm, the wavelength of the transmission is around 1.5 cm or less, corresponding to a frequency of 20 GHz or greater. In another embodiment, a suitable frequency of the transmission and the carrier-wave signal is in the range of 30-100 GHz, perhaps around 30-60 GHz, and around 38 GHz in one example. In an embodiment, when the circumference of the dielectric waveguide **204** and wire **202** is comparable in size to, or greater, than a wavelength of the transmission, the waves **206** and **208** can exhibit multiple wave propagation modes including fundamental and/or non-fundamental (symmetric and/or asymmetric) modes that propagate over sufficient distances to support various communication systems described herein. The waves **206** and **208** can therefore comprise more than one type of electric and magnetic field configuration. In an embodiment, as the guided wave **208** propagates down the wire **202**, the electrical and magnetic field configurations will remain the same from end to end of the wire **202**. In other embodiments, as the guided wave **208** encounters interference or loses energy due to transmission losses, the electric and magnetic field configurations can change as the guided wave **208** propagates down wire **202**.

[0047] In an embodiment, the dielectric waveguide **204** can be composed of nylon, TEFLON® (e.g., synthetic resin), polyethylene, a polyamide, or other plastics. In other embodiments, other dielectric materials are possible. The wire surface of wire **202** can be metallic with either a bare metallic surface, or can be insulated using plastic, dielectric, insulator or other sheathing. In an embodiment, a dielectric or otherwise non-conducting/insulated waveguide can be paired with either a bare/metallic wire or insulated wire. In other embodiments, a metallic and/or conductive waveguide can be paired with a bare/metallic wire or insulated wire. In an embodiment, an oxidation layer on the bare metallic surface of the wire **202** (e.g., resulting from exposure of the bare metallic surface to oxygen/air) can also provide insu-

lating or dielectric properties similar to those provided by some insulators or sheathings.

[0048] It is noted that the graphical representations of waves **206**, **208** and **210** are presented merely to illustrate the principles that wave **206** induces or otherwise launches a guided wave **208** on a wire **202** that operates, for example, as a single wire transmission line. Wave **210** represents the portion of wave **206** that remains on the dielectric waveguide **204** after the generation of guided wave **208**. The actual electric and magnetic fields generated as a result of such wave propagation may vary depending on the frequencies employed, the particular wave propagation mode or modes, the design of the dielectric waveguide **204**, the dimensions and composition of the wire **202**, as well as its surface characteristics, its optional insulation, the electro-magnetic properties of the surrounding environment, etc.

[0049] It is noted that dielectric waveguide **204** can include a termination circuit or damper **214** at the end of the dielectric waveguide **204** that can absorb leftover radiation or energy from wave **210**. The termination circuit or damper **214** can prevent and/or minimize the leftover radiation from wave **210** reflecting back toward transmitter circuit **212**. In an embodiment, the termination circuit or damper **214** can include termination resistors, and/or other components that perform impedance matching to attenuate reflection. In some embodiments, if the coupling efficiencies are high enough, and/or wave **210** is sufficiently small, it may not be necessary to use a termination circuit or damper **214**. For the sake of simplicity, these transmitter and termination circuits or dampers **212** and **214** are not depicted in the other figures, but in those embodiments, transmitter and termination circuits or dampers may possibly be used.

[0050] Further, while a single dielectric waveguide **204** is presented that generates a single guided wave **208**, multiple dielectric waveguides **204** placed at different points along the wire **202** and/or at different axial orientations about the wire can be employed to generate multiple guided waves **208** at the same or different frequencies, at the same or different phases, at the same or different wave propagation modes. The guided wave or waves **208** can be modulated to convey data via a modulation technique such as phase shift keying, frequency shift keying, quadrature amplitude modulation, amplitude modulation, multi-carrier modulation and via multiple access techniques such as frequency division multiplexing, time division multiplexing, code division multiplexing, multiplexing via differing wave propagation modes and via other modulation and access strategies.

[0051] Turning now to FIG. 3, illustrated is a block diagram of an example, non-limiting embodiment of a dielectric waveguide coupling system **300** in accordance with various aspects described herein. System **300** comprises a dielectric waveguide **304** and a wire **302** that has a wave **306** propagating as a guided wave about a wire surface of the wire **302**. In an example embodiment, the wave **306** can be characterized as a surface wave or other electromagnetic wave.

[0052] In an example embodiment, the dielectric waveguide **304** is curved or otherwise has a curvature, and can be placed near a wire **302** such that a portion of the curved dielectric waveguide **304** is parallel or substantially parallel to the wire **302**. The portion of the dielectric waveguide **204** that is parallel to the wire can be an apex of the curve, or any point where a tangent of the curve is parallel to the wire **302**. When the dielectric waveguide **304** is near the wire, the

guided wave 306 travelling along the wire 302 can couple to the dielectric waveguide 304 and propagate as guided wave 308 about the dielectric waveguide 304. A portion of the guided wave 306 that does not couple to the dielectric waveguide 304 propagates as guided wave 310 (e.g., surface wave or other electromagnetic wave) along the wire 302.

[0053] The guided waves 306 and 308 stay parallel to the wire 302 and dielectric waveguide 304, respectively, even as the wire 302 and dielectric waveguide 304 bend and flex. Bends can increase transmission losses, which are also dependent on wire diameters, frequency, and materials. If the dimensions of the dielectric waveguide 304 are chosen for efficient power transfer, most of the energy in the guided wave 306 is coupled to the dielectric waveguide 304 and little remains in guided wave 310.

[0054] In an embodiment, a receiver circuit (not shown) can be placed on the end of waveguide 304 in order to receive wave 308. A termination circuit (not shown) can be placed on the opposite end of the waveguide 304 in order to receive guided waves traveling in the opposite direction to guided wave 306 that couple to the waveguide 304. The termination circuit would thus prevent and/or minimize reflections being received by the receiver circuit. If the reflections are small, the termination circuit may not be necessary.

[0055] It is noted that the dielectric waveguide 304 can be configured such that selected polarizations of the guided wave 306 are coupled to the dielectric waveguide 304 as guided wave 308. For instance, if guided wave 306 is made up of guided waves or wave propagation modes with respective polarizations, dielectric waveguide 304 can be configured to receive one or more guided waves of selected polarization(s). Guided wave 308 that couples to the dielectric waveguide 304 is thus the set of guided waves that correspond to one or more of the selected polarization(s), and further guided wave 310 can comprise the guided waves that do not match the selected polarization(s).

[0056] The dielectric waveguide 304 can be configured to receive guided waves of a particular polarization based on an angle/rotation around the wire 302 that the dielectric waveguide 304 is placed. For instance, if the guided wave 306 is polarized horizontally, most of the guided wave 306 transfers to the dielectric waveguide as wave 308. As the dielectric waveguide 304 is rotated 90 degrees around the wire 302, though, most of the energy from guided wave 306 would remain coupled to the wire as guided wave 310, and only a small portion would couple to the wire 302 as wave 308.

[0057] It is noted that waves 306, 308, and 310 are shown using three circular symbols in FIG. 3 and in other figures in the specification. These symbols are used to represent a general guided wave, but do not imply that the waves 306, 308, and 310 are circularly polarized or otherwise circularly oriented. In fact, waves 306, 308, and 310 can comprise a fundamental TEM mode where the fields extend radially outwards, and also comprise other, non-fundamental (e.g. higher-level, etc.) modes. These modes can be asymmetric (e.g., radial, bilateral, trilateral, quadrilateral, etc.) in nature as well.

[0058] It is noted also that guided wave communications over wires can be full duplex, allowing simultaneous communications in both directions. Waves traveling one direction can pass through waves traveling in an opposite direction. Electromagnetic fields may cancel out at certain points

and for short times due to the superposition principle as applied to waves. The waves traveling in opposite directions propagate as if the other waves weren't there, but the composite effect to an observer may be a stationary standing wave pattern. As the guided waves pass through each other and are no longer in a state of superposition, the interference subsides. As a guided wave (e.g., surface wave or other electromagnetic wave) couples to a waveguide and move away from the wire, any interference due to other guided waves (e.g., surface waves or other electromagnetic waves) decreases. In an embodiment, as guided wave 306 (e.g., surface wave or other electromagnetic wave) approaches dielectric waveguide 304, another guided wave (e.g., surface wave or other electromagnetic wave) (not shown) traveling from left to right on the wire 302 passes by causing local interference. As guided wave 306 couples to dielectric waveguide 304 as wave 308, and moves away from the wire 302, any interference due to the passing guided wave subsides.

[0059] It is noted that the graphical representations of waves 306, 308 and 310 are presented merely to illustrate the principles that guided wave 306 induces or otherwise launches a wave 308 on a dielectric waveguide 304. Guided wave 310 represents the portion of guided wave 306 that remains on the wire 302 after the generation of wave 308. The actual electric and magnetic fields generated as a result of such guided wave propagation may vary depending on one or more of the shape and/or design of the dielectric waveguide, the relative position of the dielectric waveguide to the wire, the frequencies employed, the design of the dielectric waveguide 304, the dimensions and composition of the wire 302, as well as its surface characteristics, its optional insulation, the electromagnetic properties of the surrounding environment, etc.

[0060] Turning now to FIG. 4, illustrated is a block diagram of an example, non-limiting embodiment of a dielectric waveguide coupling system 400 in accordance with various aspects described herein. System 400 comprises a dielectric waveguide 404 that has a wave 406 propagating as a guided wave about a waveguide surface of the dielectric waveguide 404. In an embodiment, the dielectric waveguide 404 is curved, and an end of the dielectric waveguide 404 can be tied, fastened, or otherwise mechanically coupled to a wire 402. When the end of the dielectric waveguide 404 is fastened to the wire 402, the end of the dielectric waveguide 404 is parallel or substantially parallel to the wire 402. Alternatively, another portion of the dielectric waveguide beyond an end can be fastened or coupled to wire 402 such that the fastened or coupled portion is parallel or substantially parallel to the wire 402. The coupling device 410 can be a nylon cable tie or other type of non-conducting/dielectric material. The dielectric waveguide 404 can be adjacent to the wire 402 without surrounding the wire 402.

[0061] When the dielectric waveguide 404 is placed with the end parallel to the wire 402, the guided wave 406 travelling along the dielectric waveguide 404 couples to the wire 402, and propagates as guided wave 408 about the wire surface of the wire 402. In an example embodiment, the guided wave 408 can be characterized as a surface wave or other electromagnetic wave.

[0062] It is noted that the graphical representations of waves 406 and 408 are presented merely to illustrate the principles that wave 406 induces or otherwise launches a guided wave 408 on a wire 402 that operates, for example,

as a single wire transmission line. The actual electric and magnetic fields generated as a result of such wave propagation may vary depending on one or more of the shape and/or design of the dielectric waveguide, the relative position of the dielectric waveguide to the wire, the frequencies employed, the design of the dielectric waveguide **404**, the dimensions and composition of the wire **402**, as well as its surface characteristics, its optional insulation, the electromagnetic properties of the surrounding environment, etc.

[0063] In an embodiment (not shown), an end of dielectric waveguide **404** can taper towards the wire **402** in order to increase coupling efficiencies. Indeed, the tapering of the end of the dielectric waveguide **404** can provide impedance matching to the wire **402**, according to an example embodiment of the subject disclosure. For example, an end of the dielectric waveguide **404** can be gradually tapered in order to obtain a desired level of coupling between waves **406** and **408** as illustrated in FIG. 4.

[0064] In an embodiment (not shown), the coupling device **410** can be placed such that there is a short length of the dielectric waveguide **404** between the coupling device **410** and an end of the dielectric waveguide **404**. Increased coupling efficiencies are realized when the length of the end of the dielectric waveguide **404** that is beyond the coupling device **410** is one or more wavelengths long for whatever frequency is being transmitted.

[0065] Turning now to FIG. 5, illustrated is a block diagram of an example, non-limiting embodiment of a dielectric waveguide coupler and transceiver system **500** in accordance with various aspects described herein. System **500** comprises a transmitter/receiver device **506** that launches and receives waves (e.g., guided wave **504** onto dielectric waveguide **502**) based on signals received from and sent to a base station device **508**.

[0066] The output of the base station device **508** can be combined with a millimeter-wave carrier wave generated by a local oscillator **512** at frequency mixer **510**. Frequency mixer **510** can use heterodyning techniques or other frequency shifting techniques to frequency shift the transmission (Tx) signals from base station device **508**. For example, signals sent to and from the base station **508** can be modulated signals such as orthogonal frequency division multiplexed (OFDM) signals formatted in accordance with a Long-Term Evolution (LTE) wireless protocol or other wireless 3G, 4G or higher voice and data protocol, a ZIGBEE®, WIMAX, UltraWideband or IEEE 802.11 wireless protocol or other wireless protocol. In an example embodiment, this frequency conversion can be done in the analog domain, and as a result, the frequency shifting can be done without regard to the type of communications protocol that base station devices **508** use. According to embodiment, as new communications technologies are developed, the base station device **508** can be upgraded or replaced and the frequency shifting and transmission apparatus can remain, simplifying upgrades. The carrier wave can then be sent to a power amplifier (“PA”) **514** and can be transmitted by the transmitter receiver device **506** by the diplexer **516**.

[0067] Signals received from the transmitter/receiver device **506** that are directed towards the base station device **508** can be separated from other signals via diplexer **516**. The transmission can then be sent to low noise amplifier (“LNA”) **518** for amplification. A frequency mixer **520**, with help from local oscillator **512** can downshift the transmission (which is in the millimeter-wave band or around 38

GHz in some embodiments) to the native frequency. The base station device **508** can then receive (Rx) the transmission.

[0068] In an embodiment, transmitter/receiver device **506** can be a cylindrical (which, for example, can be hollow in an embodiment) metal or conducting waveguide and an end of the dielectric waveguide **502** can be placed in or in proximity to the transmitter/receiver device **506** such that when the transmitter/receiver device **506** generates a transmission, the guided wave couples to dielectric waveguide **502** and propagates as a guided wave **504** about the waveguide surface of the dielectric waveguide **502**. Similarly, if guided wave **504** is incoming (coupled to the dielectric waveguide **502** from a wire), guided wave **504** then enters the transmitter/receiver device **506** and become coupled to the cylindrical waveguide or conducting waveguide.

[0069] In an embodiment, dielectric waveguide **502** can be wholly constructed of a dielectric material, without any metallic or otherwise conducting materials therein. Dielectric waveguide **502** can be composed of nylon, TEFLON® (e.g., synthetic resin), polyethylene, a polyamide, other plastics, or other materials that are non-conducting and suitable for facilitating transmission of electromagnetic waves on an outer surface of such materials. In another embodiment, dielectric waveguide **502** can include a core that is conducting/metallic, and have an exterior dielectric surface. Similarly, a transmission medium that couples to the dielectric waveguide **502** for propagating electromagnetic waves induced by the dielectric waveguide **502** or for supplying electromagnetic waves to the dielectric waveguide **502** can be wholly constructed of a dielectric material, without any metallic or otherwise conducting materials therein.

[0070] It is noted that although FIG. 5 shows that the opening of transmitter receiver device **506** is much wider than the dielectric waveguide **502**, this is not to scale, and that in other embodiments the width of the dielectric waveguide **502** is comparable or slightly smaller than the opening of the hollow waveguide. It is also not shown, but in an embodiment, an end of the waveguide **502** that is inserted into the transmitter/receiver device **506** tapers down in order to reduce reflection and increase coupling efficiencies.

[0071] The transmitter/receiver device **506** can be communicably coupled to a base station device **508**, and alternatively, transmitter/receiver device **506** can also be communicably coupled to the one or more distributed antennas **112** and **114** shown in FIG. 1. In other embodiments, transmitter receiver device **506** can comprise part of a repeater system for a backhaul network.

[0072] Before coupling to the dielectric waveguide **502**, the one or more waveguide modes of the guided wave generated by the transmitter/receiver device **506** can couple to one or more wave propagation modes of the guided wave **504**. The wave propagation modes can be different than the hollow metal waveguide modes due to the different characteristics of the hollow metal waveguide and the dielectric waveguide. For instance, wave propagation modes can comprise the fundamental transverse electromagnetic mode (Quasi-TEM₀₀), where only small electrical and/or magnetic fields extend in the direction of propagation, and the electric and magnetic fields extend radially outwards from the dielectric waveguide **502** while the guided waves propagate along the dielectric waveguide **502**. The fundamental transverse electromagnetic mode wave propagation mode does

not exist inside a waveguide that is hollow. Therefore, the hollow metal waveguide modes that are used by transmitter/receiver device 506 are waveguide modes that can couple effectively and efficiently to wave propagation modes of dielectric waveguide 502.

[0073] Turning now to FIG. 6, illustrated is a block diagram illustrating an example, non-limiting embodiment of a dual dielectric waveguide coupling system 600 in accordance with various aspects described herein. In an embodiment, two or more dielectric waveguides (e.g., 604 and 606) can be positioned around a wire 602 in order to receive guided wave 608. In an embodiment, the guided wave 608 can be characterized as a surface wave or other electromagnetic wave. In an embodiment, one dielectric waveguide is enough to receive the guided wave 608. In that case, guided wave 608 couples to dielectric waveguide 604 and propagates as guided wave 610. If the field structure of the guided wave 608 oscillates or undulates around the wire 602 due to various outside factors, then dielectric waveguide 606 can be placed such that guided wave 608 couples to dielectric waveguide 606. In some embodiments, as many as four dielectric waveguides can be placed around a portion of the wire 602, e.g., at 90 degrees or another spacing with respect to each other, in order to receive guided waves that may oscillate or rotate around the wire 602, that have been induced at different axial orientations or that have non-fundamental or higher order modes that, for example, have lobes and/or nulls or other asymmetries that are orientation dependent. However, it will be appreciated that there may be less than or more than four dielectric waveguides placed around a portion of the wire 602 without departing from example embodiments. It will also be appreciated that while some example embodiments have presented a plurality of dielectric waveguides around at least a portion of a wire 602, this plurality of dielectric waveguides can also be considered as part of a single dielectric waveguide system having multiple dielectric waveguide subcomponents. For example, two or more dielectric waveguides can be manufactured as single system that can be installed around a wire in a single installation such that the dielectric waveguides are either pre-positioned or adjustable relative to each other (either manually or automatically) in accordance with the single system. Receivers coupled to dielectric waveguides 606 and 604 can use diversity combining to combine signals received from both dielectric waveguides 606 and 604 in order to maximize the signal quality. In other embodiments, if one or the other of a dielectric waveguides 604 and 606 receive a transmission that is above a predetermined threshold, receivers can use selection diversity when deciding which signal to use.

[0074] It is noted that the graphical representations of waves 608 and 610 are presented merely to illustrate the principles that guided wave 608 induces or otherwise launches a wave 610 on a dielectric waveguide 604. The actual electric and magnetic fields generated as a result of such wave propagation may vary depending on the frequencies employed, the design of the dielectric waveguide 604, the dimensions and composition of the wire 602, as well as its surface characteristics, its optional insulation, the electromagnetic properties of the surrounding environment, etc.

[0075] Turning now to FIG. 7, illustrated is a block diagram of an example, non-limiting embodiment of a bidirectional dielectric waveguide coupling system 700 in accordance with various aspects described herein. In system

700, two dielectric waveguides 704 and 714 can be placed near a wire 702 such that guided waves (e.g., surface waves or other electromagnetic waves) propagating along the wire 702 are coupled to dielectric waveguide 704 as wave 706, and then are boosted or repeated by repeater device 710 and launched as a guided wave 716 onto dielectric waveguide 714. The guided wave 716 can then couple to wire 702 and continue to propagate along the wire 702. In an embodiment, the repeater device 710 can receive at least a portion of the power utilized for boosting or repeating through magnetic coupling with the wire 702, which can be a power line.

[0076] In some embodiments, repeater device 710 can repeat the transmission associated with wave 706, and in other embodiments, repeater device 710 can be associated with a distributed antenna system and/or base station device located near the repeater device 710. Receiver waveguide 708 can receive the wave 706 from the dielectric waveguide 704 and transmitter waveguide 712 can launch guided wave 716 onto dielectric waveguide 714. Between receiver waveguide 708 and transmitter waveguide 712, the signal can be amplified to correct for signal loss and other inefficiencies associated with guided wave communications. In an embodiment, a signal can be extracted from the transmission and processed and otherwise emitted to mobile devices nearby via distributed antennas communicably coupled to the repeater device 710. Similarly, signals and/or communications received by the distributed antennas can be inserted into the transmission that is generated and launched onto dielectric waveguide 714 by transmitter waveguide 712. Accordingly, the repeater system 700 depicted in FIG. 7 can be comparable in function to the dielectric waveguide coupling device 108 and 110 in FIG. 1.

[0077] It is noted that although FIG. 7 shows guided wave transmissions 706 and 716 entering from the left and exiting to the right respectively, this is merely a simplification and is not intended to be limiting. In other embodiments, receiver waveguide 708 and transmitter waveguide 712 can also function as transmitters and receivers respectively, allowing the repeater device 710 to be bi-directional.

[0078] In an embodiment (not shown), repeater device 710 can be placed at locations where there are discontinuities or obstacles (not shown) on the wire 702. These obstacles can include transformers, connections, utility poles, and other such power line devices. The repeater device 710 can help the guided (e.g., surface) waves jump over these obstacles on the line and boost the transmission power at the same time. In other embodiments (not shown), a dielectric waveguide can be used to jump over the obstacle without the use of a repeater device. In that embodiment, both ends of the dielectric waveguide can be tied or fastened to the wire, thus providing a path for the guided wave to travel without being blocked by the obstacle.

[0079] Turning now to FIG. 8, illustrated is a block diagram of an example, non-limiting embodiment of a bidirectional dielectric waveguide coupler 800 in accordance with various aspects described herein. The bidirectional dielectric waveguide coupler 800 can employ diversity paths in the case of when two or more wires are strung between utility poles. Since guided wave transmissions have different transmission efficiencies and coupling efficiencies for insulated wires and un-insulated wires based on weather, precipitation and atmospheric conditions, it can be advantageous to selectively transmit on either an insulated wire or un-insulated wire at certain times.

[0080] In the embodiment shown in FIG. 8, repeater device uses a receiver waveguide 808 to receive a guided wave traveling along uninsulated wire 802 and repeats the transmission using transmitter waveguide 810 as a guided wave along insulated wire 804. In other embodiments, repeater device can switch from the insulated wire 804 to the un-insulated wire 802, or can repeat the transmissions along the same paths. Repeater device 806 can include sensors, or be in communication with sensors that indicate conditions that can affect the transmission. Based on the feedback received from the sensors, the repeater device 806 can make the determination about whether to keep the transmission along the same wire, or transfer the transmission to the other wire.

[0081] Turning now to FIG. 9, illustrated is a block diagram illustrating an example, non-limiting embodiment of a bidirectional repeater system 900. Bidirectional repeater system 900 includes waveguide coupling devices 902 and 904 that receive and transmit transmissions from other coupling devices located in a distributed antenna system or backhaul system.

[0082] In various embodiments, waveguide coupling device 902 can receive a transmission from another waveguide coupling device, wherein the transmission has a plurality of subcarriers. Diplexer 906 can separate the transmission from other transmissions, and direct the transmission to low-noise amplifier (“LNA”) 908. A frequency mixer 928, with help from a local oscillator 912, can downshift the transmission (which is in the millimeter-wave band or around 38 GHz in some embodiments) to a lower frequency, whether it is a cellular band (~1.9 GHz) for a distributed antenna system, a native frequency, or other frequency for a backhaul system. An extractor 932 can extract the signal on the subcarrier that corresponds to antenna or other output component 922 and direct the signal to the output component 922. For the signals that are not being extracted at this antenna location, extractor 932 can redirect them to another frequency mixer 936, where the signals are used to modulate a carrier wave generated by local oscillator 914. The carrier wave, with its subcarriers, is directed to a power amplifier (“PA”) 916 and is retransmitted by waveguide coupling device 904 to another repeater system, via diplexer 920.

[0083] At the output device 922 (antenna in a distributed antenna system), a PA 924 can boost the signal (Tx) for transmission to the mobile device. An LNA 926 can be used to amplify weak signals that are received (Rx) from the mobile device and then send the signal to a multiplexer 934 which merges the signal with signals that have been received from waveguide coupling device 904. The signals received from coupling device 904 have been split by diplexer 920, and then passed through LNA 918, and downshifted in frequency by frequency mixer 938. When the signals are combined by multiplexer 934, they are upshifted in frequency by frequency mixer 930, and then boosted by PA 910, and transmitted back to the launcher or on to another repeater by waveguide coupling device 902. In an embodiment bidirectional repeater system 900 can be just a repeater without the antenna/output device 922. It will be appreciated that in some embodiments, a bidirectional repeater system 900 could also be implemented using two distinct and separate uni-directional repeaters. In an alternative embodiment, a bidirectional repeater system 900 could also be a booster or otherwise perform retransmissions without downshifting and upshifting. Indeed in example embodiment, the

retransmissions can be based upon receiving a signal or guided wave and performing some signal or guided wave processing or reshaping, filtering, and/or amplification, prior to retransmission of the signal or guided wave.

[0084] FIG. 10 illustrates a process in connection with the aforementioned systems. The process in FIG. 10 can be implemented for example by systems 100, 200, 300, 400, 500, 600, 700, 800, and 900 illustrated in FIGS. 1-9 respectively. While for purposes of simplicity of explanation, the methods are shown and described as a series of blocks, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described hereinafter.

[0085] FIG. 10 illustrates a flow diagram of an example, non-limiting embodiment of a method for transmitting a transmission with a dielectric waveguide coupler as described herein. Method 1000 can begin or start at 1002 where a first electromagnetic wave is emitted by a transmission device that propagates at least in part on a waveguide surface of a waveguide, wherein the waveguide surface of the waveguide does not surround in whole or in substantial part a wire surface of a wire. The transmission that is generated by a transmitter can be based on a signal received from a base station device, access point, network or a mobile device.

[0086] At 1004, based upon configuring the waveguide in proximity of the wire, the guided wave then couples at least a part of the first electromagnetic wave to a wire surface, forming a second electromagnetic wave (e.g., a surface wave) that propagates at least partially around the wire surface, wherein the wire is in proximity to the waveguide. This can be done in response to positioning a portion of the dielectric waveguide (e.g., a tangent of a curve of the dielectric waveguide) near and parallel to the wire, wherein a wavelength of the electromagnetic wave is smaller than a circumference of the wire and the dielectric waveguide. The guided wave, or surface wave, stays parallel to the wire even as the wire bends and flexes. Bends can increase transmission losses, which are also dependent on wire diameters, frequency, and materials. The coupling interface between the wire and the waveguide can also be configured to achieve the desired level of coupling, as described herein, which can include tapering an end of the waveguide to improve impedance matching between the waveguide and the wire.

[0087] The transmission that is emitted by the transmitter can exhibit one or more waveguide modes. The waveguide modes can be dependent on the shape and/or design of the waveguide. The propagation modes on the wire can be different than the waveguide modes due to the different characteristics of the waveguide and the wire. When the circumference of the wire is comparable in size to, or greater, than a wavelength of the transmission, the guided wave exhibits multiple wave propagation modes. The guided wave can therefore comprise more than one type of electric and magnetic field configuration. As the guided wave (e.g., surface wave) propagates down the wire, the electrical and magnetic field configurations may remain substantially the same from end to end of the wire or vary

as the transmission traverses the wave by rotation, dispersion, attenuation or other effects. The process ends at step 1004.

[0088] Referring now to FIG. 11, there is illustrated a block diagram of a computing environment in accordance with various aspects described herein. In order to provide additional context for various embodiments of the embodiments described herein, FIG. 11 and the following discussion are intended to provide a brief, general description of a suitable computing environment 1100 in which the various embodiments of the embodiment described herein can be implemented. While the embodiments have been described above in the general context of computer-executable instructions that can run on one or more computers, those skilled in the art will recognize that the embodiments can be also implemented in combination with other program modules and/or as a combination of hardware and software.

[0089] Generally, program modules comprise routines, programs, components, data structures, etc., that perform particular tasks or implement particular abstract data types. Moreover, those skilled in the art will appreciate that the inventive methods can be practiced with other computer system configurations, comprising single-processor or multiprocessor computer systems, minicomputers, mainframe computers, as well as personal computers, hand-held computing devices, microprocessor-based or programmable consumer electronics, and the like, each of which can be operatively coupled to one or more associated devices.

[0090] The terms “first,” “second,” “third,” and so forth, as used in the claims, unless otherwise clear by context, is for clarity only and doesn’t otherwise indicate or imply any order in time. For instance, “a first determination,” “a second determination,” and “a third determination,” does not indicate or imply that the first determination is to be made before the second determination, or vice versa, etc.

[0091] The illustrated embodiments of the embodiments herein can be also practiced in distributed computing environments where certain tasks are performed by remote processing devices that are linked through a communications network. In a distributed computing environment, program modules can be located in both local and remote memory storage devices.

[0092] Computing devices typically comprise a variety of media, which can comprise computer-readable storage media and/or communications media, which two terms are used herein differently from one another as follows. Computer-readable storage media can be any available storage media that can be accessed by the computer and comprises both volatile and nonvolatile media, removable and non-removable media. By way of example, and not limitation, computer-readable storage media can be implemented in connection with any method or technology for storage of information such as computer-readable instructions, program modules, structured data or unstructured data.

[0093] Computer-readable storage media can comprise, but are not limited to, random access memory (RAM), read only memory (ROM), electrically erasable programmable read only memory (EEPROM), flash memory or other memory technology, compact disk read only memory (CD-ROM), digital versatile disk (DVD) or other optical disk storage, magnetic cassettes, magnetic tape, magnetic disk storage or other magnetic storage devices or other tangible and/or non-transitory media which can be used to store desired information. In this regard, the terms “tangible” or

“non-transitory” herein as applied to storage, memory or computer-readable media, are to be understood to exclude only propagating transitory signals per se as modifiers and do not relinquish rights to all standard storage, memory or computer-readable media that are not only propagating transitory signals per se.

[0094] Computer-readable storage media can be accessed by one or more local or remote computing devices, e.g., via access requests, queries or other data retrieval protocols, for a variety of operations with respect to the information stored by the medium.

[0095] Communications media typically embody computer-readable instructions, data structures, program modules or other structured or unstructured data in a data signal such as a modulated data signal, e.g., a carrier wave or other transport mechanism, and comprises any information delivery or transport media. The term “modulated data signal” or “signals” refers to a signal that has one or more of its characteristics set or changed in such a manner as to encode information in one or more signals. By way of example, and not limitation, communication media comprise wired media, such as a wired network or direct-wired connection, and wireless media such as acoustic, RF, infrared and other wireless media.

[0096] With reference again to FIG. 11, the example environment 1100 for transmitting and receiving signals via base station (e.g., base station devices 104 and 508) and repeater devices (e.g., repeater devices 710, 806, and 900) comprises a computer 1102, the computer 1102 comprising a processing unit 1104, a system memory 1106 and a system bus 1108. The system bus 1108 couples system components including, but not limited to, the system memory 1106 to the processing unit 1104. The processing unit 1104 can be any of various commercially available processors. Dual microprocessors and other multi-processor architectures can also be employed as the processing unit 1104.

[0097] The system bus 1108 can be any of several types of bus structure that can further interconnect to a memory bus (with or without a memory controller), a peripheral bus, and a local bus using any of a variety of commercially available bus architectures. The system memory 1106 comprises ROM 1110 and RAM 1112. A basic input/output system (BIOS) can be stored in a non-volatile memory such as ROM, erasable programmable read only memory (EPROM), EEPROM, which BIOS contains the basic routines that help to transfer information between elements within the computer 1102, such as during startup. The RAM 1112 can also comprise a high-speed RAM such as static RAM for caching data.

[0098] The computer 1102 further comprises an internal hard disk drive (HDD) 1114 (e.g., Enhanced Integrated Drive Electronics (EIDE), Serial Advanced Technology Attachment (SATA)), which internal hard disk drive 1114 can also be configured for external use in a suitable chassis (not shown), a magnetic floppy disk drive (FDD) 1116, (e.g., to read from or write to a removable diskette 1118) and an optical disk drive 1120, (e.g., reading a CD-ROM disk 1122 or, to read from or write to other high capacity optical media such as the DVD). The hard disk drive 1114, magnetic disk drive 1116 and optical disk drive 1120 can be connected to the system bus 1108 by a hard disk drive interface 1124, a magnetic disk drive interface 1126 and an optical drive interface 1128, respectively. The interface 1124 for external drive implementations comprises at least one or both of

Universal Serial Bus (USB) and Institute of Electrical and Electronics Engineers (IEEE) 1394 interface technologies. Other external drive connection technologies are within contemplation of the embodiments described herein.

[0099] The drives and their associated computer-readable storage media provide nonvolatile storage of data, data structures, computer-executable instructions, and so forth. For the computer **1102**, the drives and storage media accommodate the storage of any data in a suitable digital format. Although the description of computer-readable storage media above refers to a hard disk drive (HDD), a removable magnetic diskette, and a removable optical media such as a CD or DVD, it should be appreciated by those skilled in the art that other types of storage media which are readable by a computer, such as zip drives, magnetic cassettes, flash memory cards, cartridges, and the like, can also be used in the example operating environment, and further, that any such storage media can contain computer-executable instructions for performing the methods described herein.

[0100] A number of program modules can be stored in the drives and RAM **1112**, comprising an operating system **1130**, one or more application programs **1132**, other program modules **1134** and program data **1136**. All or portions of the operating system, applications, modules, and/or data can also be cached in the RAM **1112**. The systems and methods described herein can be implemented utilizing various commercially available operating systems or combinations of operating systems. Examples of application programs **1132** that can be implemented and otherwise executed by processing unit **1104** include the diversity selection determining performed by repeater device **806**. Base station device **508** shown in FIG. 5, also has stored on memory many applications and programs that can be executed by processing unit **1104** in this exemplary computing environment **1100**.

[0101] A user can enter commands and information into the computer **1102** through one or more wired/wireless input devices, e.g., a keyboard **1138** and a pointing device, such as a mouse **1140**. Other input devices (not shown) can comprise a microphone, an infrared (IR) remote control, a joystick, a game pad, a stylus pen, touch screen or the like. These and other input devices are often connected to the processing unit **1104** through an input device interface **1142** that can be coupled to the system bus **1108**, but can be connected by other interfaces, such as a parallel port, an IEEE 1394 serial port, a game port, a universal serial bus (USB) port, an IR interface, etc.

[0102] A monitor **1144** or other type of display device can be also connected to the system bus **1108** via an interface, such as a video adapter **1146**. It will also be appreciated that in alternative embodiments, a monitor **1144** can also be any display device (e.g., another computer having a display, a smart phone, a tablet computer, etc.) for receiving display information associated with computer **1102** via any communication means, including via the Internet and cloud-based networks. In addition to the monitor **1144**, a computer typically comprises other peripheral output devices (not shown), such as speakers, printers, etc.

[0103] The computer **1102** can operate in a networked environment using logical connections via wired and/or wireless communications to one or more remote computers, such as a remote computer(s) **1148**. The remote computer(s) **1148** can be a workstation, a server computer, a router, a personal computer, portable computer, microprocessor-based entertainment appliance, a peer device or other com-

mon network node, and typically comprises many or all of the elements described relative to the computer **1102**, although, for purposes of brevity, only a memory/storage device **1150** is illustrated. The logical connections depicted comprise wired/wireless connectivity to a local area network (LAN) **1152** and/or larger networks, e.g., a wide area network (WAN) **1154**. Such LAN and WAN networking environments are commonplace in offices and companies, and facilitate enterprise-wide computer networks, such as intranets, all of which can connect to a global communications network, e.g., the Internet.

[0104] When used in a LAN networking environment, the computer **1102** can be connected to the local network **1152** through a wired and/or wireless communication network interface or adapter **1156**. The adapter **1156** can facilitate wired or wireless communication to the LAN **1152**, which can also comprise a wireless AP (Access Point) disposed thereon for communicating with the wireless adapter **1156**.

[0105] When used in a WAN networking environment, the computer **1102** can comprise a modem **1158** or can be connected to a communications server on the WAN **1154** or has other means for establishing communications over the WAN **1154**, such as by way of the Internet. The modem **1158**, which can be internal or external and a wired or wireless device, can be connected to the system bus **1108** via the input device interface **1142**. In a networked environment, program modules depicted relative to the computer **1102** or portions thereof, can be stored in the remote memory/storage device **1150**. It will be appreciated that the network connections shown are example and other means of establishing a communications link between the computers can be used.

[0106] The computer **1102** can be operable to communicate with any wireless devices or entities operatively disposed in wireless communication, e.g., a printer, scanner, desktop and/or portable computer, portable data assistant, communications satellite, any piece of equipment or location associated with a wirelessly detectable tag (e.g., a kiosk, news stand, restroom), and telephone. This can comprise Wireless Fidelity (Wi-Fi) and BLUETOOTH® wireless technologies. Thus, the communication can be a predefined structure as with a conventional network or simply an ad hoc communication between at least two devices.

[0107] Wi-Fi can allow connection to the Internet from a couch at home, a bed in a hotel room or a conference room at work, without wires. Wi-Fi is a wireless technology similar to that used in a cell phone that enables such devices, e.g., computers, to send and receive data indoors and out; anywhere within the range of a base station. Wi-Fi networks use radio technologies called IEEE 802.11 (a, b, g, n, ac, etc.) to provide secure, reliable, fast wireless connectivity. A Wi-Fi network can be used to connect computers to each other, to the Internet, and to wired networks (which can use IEEE 802.3 or Ethernet). Wi-Fi networks operate in the unlicensed 2.4 and 5 GHz radio bands for example or with products that contain both bands (dual band), so the networks can provide real-world performance similar to the basic 10BaseT wired Ethernet networks used in many offices.

[0108] FIG. 12 presents an example embodiment **1200** of a mobile network platform **1210** that can implement and exploit one or more aspects of the disclosed subject matter described herein. In one or more embodiments, the mobile network platform **1210** can generate and receive signals

transmitted and received by base stations (e.g., base station devices **104** and **508**) and repeater devices (e.g., repeater devices **710**, **806**, and **900**) associated with the disclosed subject matter. Generally, wireless network platform **1210** can comprise components, e.g., nodes, gateways, interfaces, servers, or disparate platforms, that facilitate both packet-switched (PS) (e.g., internet protocol (IP), frame relay, asynchronous transfer mode (ATM)) and circuit-switched (CS) traffic (e.g., voice and data), as well as control generation for networked wireless telecommunication over a radio access network (RAN). As a non-limiting example, wireless network platform **1210** can be included in telecommunications carrier networks, and can be considered carrier-side components as discussed elsewhere herein. Mobile network platform **1210** comprises CS gateway node(s) **1212** which can interface CS traffic received from legacy networks like telephony network(s) **1240** (e.g., public switched telephone network (PSTN), or public land mobile network (PLMN)) or a signaling system #7 (SS7) network **1260**. Circuit switched gateway node(s) **1212** can authorize and authenticate traffic (e.g., voice) arising from such networks. Additionally, CS gateway node(s) **1212** can access mobility, or roaming, data generated through SS7 network **1260**; for instance, mobility data stored in a visited location register (VLR), which can reside in memory **1230**. Moreover, CS gateway node(s) **1212** interfaces CS-based traffic and signaling and PS gateway node(s) **1218**. As an example, in a 3GPP UMTS network, CS gateway node(s) **1212** can be realized at least in part in gateway GPRS support node(s) (GGSN). It should be appreciated that functionality and specific operation of CS gateway node(s) **1212**, PS gateway node(s) **1218**, and serving node(s) **1216**, is provided and dictated by radio technology(ies) utilized by mobile network platform **1210** for telecommunication.

[0109] In addition to receiving and processing CS-switched traffic and signaling, PS gateway node(s) **1218** can authorize and authenticate PS-based data sessions with served mobile devices. Data sessions can comprise traffic, or content(s), exchanged with networks external to the wireless network platform **1210**, like wide area network(s) (WANs) **1250**, enterprise network(s) **1270**, and service network(s) **1280**, which can be embodied in local area network(s) (LANs), can also be interfaced with mobile network platform **1210** through PS gateway node(s) **1218**. It is to be noted that WANs **1250** and enterprise network(s) **1260** can embody, at least in part, a service network(s) like IP multimedia subsystem (IMS). Based on radio technology layer(s) available in technology resource(s), packet-switched gateway node(s) **1218** can generate packet data protocol contexts when a data session is established; other data structures that facilitate routing of packetized data also can be generated. To that end, in an aspect, PS gateway node(s) **1218** can comprise a tunnel interface (e.g., tunnel termination gateway (TTG) in 3GPP UMTS network(s) (not shown)) which can facilitate packetized communication with disparate wireless network(s), such as Wi-Fi networks.

[0110] In embodiment **1200**, wireless network platform **1210** also comprises serving node(s) **1216** that, based upon available radio technology layer(s) within technology resource(s), convey the various packetized flows of data streams received through PS gateway node(s) **1218**. It is to be noted that for technology resource(s) that rely primarily on CS communication, server node(s) can deliver traffic without reliance on PS gateway node(s) **1218**; for example,

server node(s) can embody at least in part a mobile switching center. As an example, in a 3GPP UMTS network, serving node(s) **1216** can be embodied in serving GPRS support node(s) (SGSN).

[0111] For radio technologies that exploit packetized communication, server(s) **1214** in wireless network platform **1210** can execute numerous applications that can generate multiple disparate packetized data streams or flows, and manage (e.g., schedule, queue, format . . .) such flows. Such application(s) can comprise add-on features to standard services (for example, provisioning, billing, customer support . . .) provided by wireless network platform **1210**. Data streams (e.g., content(s) that are part of a voice call or data session) can be conveyed to PS gateway node(s) **1218** for authorization/authentication and initiation of a data session, and to serving node(s) **1216** for communication thereafter. In addition to application server, server(s) **1214** can comprise utility server(s), a utility server can comprise a provisioning server, an operations and maintenance server, a security server that can implement at least in part a certificate authority and firewalls as well as other security mechanisms, and the like. In an aspect, security server(s) secure communication served through wireless network platform **1210** to ensure network's operation and data integrity in addition to authorization and authentication procedures that CS gateway node(s) **1212** and PS gateway node(s) **1218** can enact. Moreover, provisioning server(s) can provision services from external network(s) like networks operated by a disparate service provider; for instance, WAN **1250** or Global Positioning System (GPS) network(s) (not shown). Provisioning server(s) can also provision coverage through networks associated to wireless network platform **1210** (e.g., deployed and operated by the same service provider), such as the distributed antennas networks shown in FIG. 1(s) that enhance wireless service coverage by providing more network coverage. Repeater devices such as those shown in FIGS. 7, 8, and 9 also improve network coverage in order to enhance subscriber service experience by way of UE (User Equipment) **1275**.

[0112] It is to be noted that server(s) **1214** can comprise one or more processors configured to confer at least in part the functionality of macro network platform **1210**. To that end, the one or more processor can execute code instructions stored in memory **1230**, for example. It is should be appreciated that server(s) **1214** can comprise a content manager.

[0113] In example embodiment **1200**, memory **1230** can store information related to operation of wireless network platform **1210**. Other operational information can comprise provisioning information of mobile devices served through wireless platform network **1210**, subscriber databases; application intelligence, pricing schemes, e.g., promotional rates, flat-rate programs, couponing campaigns; technical specification(s) consistent with telecommunication protocols for operation of disparate radio, or wireless, technology layers; and so forth. Memory **1230** can also store information from at least one of telephony network(s) **1240**, WAN **1250**, enterprise network(s) **1270**, or SS7 network **1260**. In an aspect, memory **1230** can be, for example, accessed as part of a data store component or as a remotely connected memory store.

[0114] In order to provide a context for the various aspects of the disclosed subject matter, FIG. 12, and the following discussion, are intended to provide a brief, general description of a suitable environment in which the various aspects

of the disclosed subject matter can be implemented. While the subject matter has been described above in the general context of computer-executable instructions of a computer program that runs on a computer and/or computers, those skilled in the art will recognize that the disclosed subject matter also can be implemented in combination with other program modules. Generally, program modules comprise routines, programs, components, data structures, etc. that perform particular tasks and/or implement particular abstract data types.

[0115] Turning now to FIGS. 13a, 13b, and 13c, illustrated are block diagrams of example, non-limiting embodiments of a slotted waveguide coupler system 1300 in accordance with various aspects described herein. In FIG. 13a, the waveguide coupler system comprises a wire 1306 that is positioned with respect to a waveguide 1302, such that the wire 1306 fits within or near a slot formed in the waveguide 1302 that runs longitudinally with respect to the wire 1304. The opposing ends 1304a and 1304b of the waveguide 1302, and the waveguide 1302 itself, surrounds less than 180 degrees of the wire surface of the wire 1306.

[0116] In FIG. 13b the waveguide coupler system comprises a wire 1314 that is positioned with respect to a waveguide 1308, such that the wire 1314 fits within or near a slot formed in the waveguide 1308 that runs longitudinally with respect to the wire 1304. The slot surfaces of the waveguide 1308 can be non-parallel, and two different exemplary embodiments are shown in FIG. 13b. In the first, slot surfaces 1310a and 1310b can be non-parallel and aim outwards, slightly wider than the width of the wire 1314. In the other embodiment, the slots surfaces 1312a and 1312b can still be non-parallel, but narrow to form a slot opening smaller than a width of the wire 1314. Any range of angles of the non-parallel slot surfaces are possible, of which these are two exemplary embodiments.

[0117] In FIG. 13c, the waveguide coupler system shows a wire 1320 that fits within a slot formed in waveguide 1316. The slot surfaces 1318a and 1318b in this exemplary embodiment can be parallel, but the axis 1326 of the wire 1320 is not aligned with the axis 1324 of the waveguide 1316. The waveguide 1316 and the wire 1320 are therefore not coaxially aligned. In another embodiment, shown, a possible position of the wire at 1322 also has an axis 1328 that is not aligned with the axis 1324 of the waveguide 1316.

[0118] It is to be appreciated that while three different embodiments showing a) waveguide surfaces that surround less than 180 degrees of the wire, b) non parallel slot surfaces, and c) coaxially unaligned wires and waveguide were shown separately in FIGS. 13a, 13b, and 13c, in various embodiments, diverse combinations of the listed features are possible.

[0119] Turning now to FIG. 14, illustrated is an example, non-limiting embodiment of a waveguide coupling system 1400 in accordance with various aspects described herein. FIG. 14 depicts a cross sectional representation of the waveguide and wire embodiments shown in FIGS. 2, 3, 4, and etc. As can be seen in 1400, the wire 1404 can be positioned directly next to and touching waveguide 1402. In other embodiments, as shown in waveguide coupling system 1500 in FIG. 15, the wire 1504 can still be placed near, but not actually touching waveguide strip 1502. In both cases, electromagnetic waves traveling along the waveguides can induce other electromagnetic waves on to the wires and vice versa. Also, in both embodiments, the wires 1404 and 1504

are placed outside the cross-sectional area defined by the outer surfaces of waveguides 1402 and 1502.

[0120] For the purposes of this disclosure, a waveguide does not surround, in substantial part, a wire surface of a wire when the waveguide does not surround an axial region of the surface, when viewed in cross-section, of more than 180 degrees. For avoidance of doubt, a waveguide does not surround, in substantial part a surface of a wire when the waveguide surrounds an axial region of the surface, when viewed in cross-section, of 180 degrees or less.

[0121] It is to be appreciated that while FIGS. 14 and 15 show wires 1404 and 1504 having a circular shape and waveguides 1402 and 1502 having rectangular shapes, this is not meant to be limiting. In other embodiments (not shown), wires and waveguides can have a variety of shapes, sizes, and configurations. The shapes can include, but not be limited to: ovals or other ellipsoid shapes, octagons, quadrilaterals or other polygons with either sharp or rounded edges, or other shapes. Additionally, in some embodiments, the wires 1404 and 1504 can be stranded wires comprising smaller gauge wires, such as a helical strand, braid or other coupling of individual strands into a single wire. Any of wires and waveguides shown in the figures and described throughout this disclosure can include one or more of these embodiments.

[0122] FIG. 16 illustrates a process in connection with the aforementioned systems. The process in FIG. 16 can be implemented for example by systems 100, 200, 300, 400, 500, 600, 700, 800, 900, 1300, 1400, and 1500 illustrated in FIGS. 1-9, 13a, 13b, 13c, 14, and 15 respectively. While for purposes of simplicity of explanation, the methods are shown and described as a series of blocks, it is to be understood and appreciated that the claimed subject matter is not limited by the order of the blocks, as some blocks may occur in different orders and/or concurrently with other blocks from what is depicted and described herein. Moreover, not all illustrated blocks may be required to implement the methods described hereinafter.

[0123] FIG. 16 illustrates a flow diagram of an example, non-limiting embodiment of a method 1600 for transmitting an electromagnetic wave with use of a waveguide as described herein. The method 1600 can begin or start at 1602, where a transmission device emits a first electromagnetic wave that propagates at least in part on the surface of the waveguide. The method can continue at 1604 where at least a part of the first electromagnetic wave is delivered to the surface of the wire via the non-coaxially aligned waveguide, thereby forming a second electromagnetic wave that propagates along the wire, at least partially around the wire surface. The process ends at step 1604.

[0124] In the subject specification, terms such as “store,” “storage,” “data store,” data storage,” “database,” and substantially any other information storage component relevant to operation and functionality of a component, refer to “memory components,” or entities embodied in a “memory” or components comprising the memory. It will be appreciated that the memory components described herein can be either volatile memory or nonvolatile memory, or can comprise both volatile and nonvolatile memory, by way of illustration, and not limitation, volatile memory, non-volatile memory, disk storage, and memory storage. Further, non-volatile memory can be included in read only memory (ROM), programmable ROM (PROM), electrically programmable ROM (EPROM), electrically erasable ROM

(EEPROM), or flash memory. Volatile memory can comprise random access memory (RAM), which acts as external cache memory. By way of illustration and not limitation, RAM is available in many forms such as synchronous RAM (SRAM), dynamic RAM (DRAM), synchronous DRAM (SDRAM), double data rate SDRAM (DDR SDRAM), enhanced SDRAM (ESDRAM), Synchlink DRAM (SLDRAM), and direct Rambus RAM (DRRAM). Additionally, the disclosed memory components of systems or methods herein are intended to comprise, without being limited to comprising, these and any other suitable types of memory.

[0125] Moreover, it will be noted that the disclosed subject matter can be practiced with other computer system configurations, comprising single-processor or multiprocessor computer systems, mini-computing devices, mainframe computers, as well as personal computers, hand-held computing devices (e.g., PDA, phone, watch, tablet computers, netbook computers, etc.), microprocessor-based or programmable consumer or industrial electronics, and the like. The illustrated aspects can also be practiced in distributed computing environments where tasks are performed by remote processing devices that are linked through a communications network; however, some if not all aspects of the subject disclosure can be practiced on stand-alone computers. In a distributed computing environment, program modules can be located in both local and remote memory storage devices.

[0126] Some of the embodiments described herein can also employ artificial intelligence (AI) to facilitate automating one or more features described herein. For example, artificial intelligence can be used to determine positions around a wire that dielectric waveguides **604** and **606** should be placed in order to maximize transfer efficiency. The embodiments (e.g., in connection with automatically identifying acquired cell sites that provide a maximum value/benefit after addition to an existing communication network) can employ various AI-based schemes for carrying out various embodiments thereof. Moreover, the classifier can be employed to determine a ranking or priority of the each cell site of the acquired network. A classifier is a function that maps an input attribute vector, $x=(x_1, x_2, x_3, x_4, \dots, x_n)$, to a confidence that the input belongs to a class, that is, $f(x)=\text{confidence (class)}$. Such classification can employ a probabilistic and/or statistical-based analysis (e.g., factoring into the analysis utilities and costs) to prognose or infer an action that a user desires to be automatically performed. A support vector machine (SVM) is an example of a classifier that can be employed. The SVM operates by finding a hypersurface in the space of possible inputs, which the hypersurface attempts to split the triggering criteria from the non-triggering events. Intuitively, this makes the classification correct for testing data that is near, but not identical to training data. Other directed and undirected model classification approaches comprise, e.g., naïve Bayes, Bayesian networks, decision trees, neural networks, fuzzy logic models, and probabilistic classification models providing different patterns of independence can be employed. Classification as used herein also is inclusive of statistical regression that is utilized to develop models of priority.

[0127] As will be readily appreciated, one or more of the embodiments can employ classifiers that are explicitly trained (e.g., via a generic training data) as well as implicitly trained (e.g., via observing UE behavior, operator preferences, historical information, receiving extrinsic informa-

tion). For example, SVMs can be configured via a learning or training phase within a classifier constructor and feature selection module. Thus, the classifier(s) can be used to automatically learn and perform a number of functions, including but not limited to determining according to a predetermined criteria which of the acquired cell sites will benefit a maximum number of subscribers and/or which of the acquired cell sites will add minimum value to the existing communication network coverage, etc.

[0128] As used in some contexts in this application, in some embodiments, the terms “component,” “system” and the like are intended to refer to, or comprise, a computer-related entity or an entity related to an operational apparatus with one or more specific functionalities, wherein the entity can be either hardware, a combination of hardware and software, software, or software in execution. As an example, a component may be, but is not limited to being, a process running on a processor, a processor, an object, an executable, a thread of execution, computer-executable instructions, a program, and/or a computer. By way of illustration and not limitation, both an application running on a server and the server can be a component. One or more components may reside within a process and/or thread of execution and a component may be localized on one computer and/or distributed between two or more computers. In addition, these components can execute from various computer readable media having various data structures stored thereon. The components may communicate via local and/or remote processes such as in accordance with a signal having one or more data packets (e.g., data from one component interacting with another component in a local system, distributed system, and/or across a network such as the Internet with other systems via the signal). As another example, a component can be an apparatus with specific functionality provided by mechanical parts operated by electric or electronic circuitry, which is operated by a software or firmware application executed by a processor, wherein the processor can be internal or external to the apparatus and executes at least a part of the software or firmware application. As yet another example, a component can be an apparatus that provides specific functionality through electronic components without mechanical parts, the electronic components can comprise a processor therein to execute software or firmware that confers at least in part the functionality of the electronic components. While various components have been illustrated as separate components, it will be appreciated that multiple components can be implemented as a single component, or a single component can be implemented as multiple components, without departing from example embodiments.

[0129] Further, the various embodiments can be implemented as a method, apparatus or article of manufacture using standard programming and/or engineering techniques to produce software, firmware, hardware or any combination thereof to control a computer to implement the disclosed subject matter. The term “article of manufacture” as used herein is intended to encompass a computer program accessible from any computer-readable device or computer-readable storage/communications media. For example, computer readable storage media can include, but are not limited to, magnetic storage devices (e.g., hard disk, floppy disk, magnetic strips), optical disks (e.g., compact disk (CD), digital versatile disk (DVD)), smart cards, and flash memory devices (e.g., card, stick, key drive). Of course, those skilled

in the art will recognize many modifications can be made to this configuration without departing from the scope or spirit of the various embodiments.

[0130] In addition, the words “example” and “exemplary” are used herein to mean serving as an instance or illustration. Any embodiment or design described herein as “example” or “exemplary” is not necessarily to be construed as preferred or advantageous over other embodiments or designs. Rather, use of the word example or exemplary is intended to present concepts in a concrete fashion. As used in this application, the term “or” is intended to mean an inclusive “or” rather than an exclusive “or”. That is, unless specified otherwise or clear from context, “X employs A or B” is intended to mean any of the natural inclusive permutations. That is, if X employs A; X employs B; or X employs both A and B, then “X employs A or B” is satisfied under any of the foregoing instances. In addition, the articles “a” and “an” as used in this application and the appended claims should generally be construed to mean “one or more” unless specified otherwise or clear from context to be directed to a singular form.

[0131] Moreover, terms such as “user equipment,” “mobile station,” “mobile,” “subscriber station,” “access terminal,” “terminal,” “handset,” “mobile device” (and/or terms representing similar terminology) can refer to a wireless device utilized by a subscriber or user of a wireless communication service to receive or convey data, control, voice, video, sound, gaming or substantially any data-stream or signaling-stream. The foregoing terms are utilized interchangeably herein and with reference to the related drawings.

[0132] Furthermore, the terms “user,” “subscriber,” “customer,” “consumer” and the like are employed interchangeably throughout, unless context warrants particular distinctions among the terms. It should be appreciated that such terms can refer to human entities or automated components supported through artificial intelligence (e.g., a capacity to make inference based, at least, on complex mathematical formalisms), which can provide simulated vision, sound recognition and so forth.

[0133] As employed herein, the term “processor” can refer to substantially any computing processing unit or device comprising, but not limited to comprising, single-core processors; single-processors with software multithread execution capability; multi-core processors; multi-core processors with software multithread execution capability; multi-core processors with hardware multithread technology; parallel platforms; and parallel platforms with distributed shared memory. Additionally, a processor can refer to an integrated circuit, an application specific integrated circuit (ASIC), a digital signal processor (DSP), a field programmable gate array (FPGA), a programmable logic controller (PLC), a complex programmable logic device (CPLD), a discrete gate or transistor logic, discrete hardware components or any combination thereof designed to perform the functions described herein. Processors can exploit nano-scale architectures such as, but not limited to, molecular and quantum-dot based transistors, switches and gates, in order to optimize space usage or enhance performance of user equipment. A processor can also be implemented as a combination of computing processing units.

[0134] As used herein, terms such as “data storage,” “data storage,” “database,” and substantially any other information storage component relevant to operation and function-

ality of a component, refer to “memory components,” or entities embodied in a “memory” or components comprising the memory. It will be appreciated that the memory components or computer-readable storage media, described herein can be either volatile memory or nonvolatile memory or can include both volatile and nonvolatile memory.

[0135] What has been described above includes mere examples of various embodiments. It is, of course, not possible to describe every conceivable combination of components or methodologies for purposes of describing these examples, but one of ordinary skill in the art can recognize that many further combinations and permutations of the present embodiments are possible. Accordingly, the embodiments disclosed and/or claimed herein are intended to embrace all such alterations, modifications and variations that fall within the spirit and scope of the appended claims. Furthermore, to the extent that the term “includes” is used in either the detailed description or the claims, such term is intended to be inclusive in a manner similar to the term “comprising” as “comprising” is interpreted when employed as a transitional word in a claim.

What is claimed is:

1. An apparatus, comprising:

a coupler that facilitates propagation of a first electromagnetic wave along the coupler, the coupler being mechanically coupled to a transmission medium, the first electromagnetic wave coupling to the transmission medium, thereby forming a second electromagnetic wave, the second electromagnetic wave having a wave propagation mode that enables the second electromagnetic wave to propagate along the transmission medium.

2. The apparatus of claim 1, wherein a portion of the coupler is positioned parallel to the transmission medium such that the first electromagnetic wave couples to the transmission medium.

3. The apparatus of claim 2, wherein the portion of the coupler that is positioned parallel to the transmission medium comprises an end of the coupler.

4. The apparatus of claim 3, wherein the coupler comprises a dielectric coupler mechanically coupled to the transmission medium.

5. The apparatus of claim 1, wherein the coupler includes a first end and a second end opposite the first end, wherein the coupler includes a curve between the first end and the second end, and wherein a part of the curve is a portion of the coupler that is positioned parallel to the transmission medium.

6. The apparatus of claim 1, wherein an outer surface of the transmission medium is insulated.

7. The apparatus of claim 1, wherein a first portion of an electromagnetic field of the first electromagnetic wave is located inside the coupler, and wherein a second portion of the electromagnetic field of the first electromagnetic wave is located outside the coupler.

8. The apparatus of claim 1, wherein an outer surface of the coupler does not surround in substantial part the outer surface of the transmission medium by more than 180 degrees.

9. The apparatus of claim 1, wherein the second electromagnetic wave travels along the transmission medium without requiring an electrical return path.

- 10.** An apparatus, comprising:
a first coupler that has an outer surface defining a cross-sectional area of the first coupler, wherein a transmission medium is positioned outside of the cross-sectional area of the first coupler such that a first electromagnetic wave propagating along the transmission medium couples at least in part to the first coupler and travels along the first coupler as a second electromagnetic wave.
- 11.** The apparatus of claim **10**, wherein the first coupler comprises a dielectric material.
- 12.** The apparatus of claim **11**, wherein the first coupler comprises a low-loss insulator material.
- 13.** The apparatus of claim **10**, wherein an end of the first coupler is positioned in proximity to the transmission medium.
- 14.** The apparatus of claim **13**, wherein the end of the first coupler comprises at least a portion of the first coupler mechanically coupled to the transmission medium by using a non-conductive fastener.
- 15.** The apparatus of claim **14**, wherein the end of the first coupler tapers towards the transmission medium.
- 16.** The apparatus of claim **10**, wherein the first coupler is curved, and the transmission medium is in proximity to and parallel to a tangent of a curve of the first coupler.
- 17.** The apparatus of claim **10**, further comprising a second coupler, wherein the first electromagnetic wave

couples to one or both of the first coupler and the second coupler based on a position of a field of the first electromagnetic wave.

- 18.** A method, comprising:
generating, by a transmission device, a first electromagnetic wave that propagates along a coupler; and
mechanically coupling at least a portion of the coupler to a transmission medium to facilitate coupling of at least a portion of the first electromagnetic wave to the transmission medium, thereby forming a second electromagnetic wave that propagates along the transmission medium, and wherein the second electromagnetic wave has a wave propagation mode that enables the second electromagnetic wave to travel along the transmission medium without requiring an electrical return path.
- 19.** The method of claim **18**, wherein the generating comprises generating the first electromagnetic wave with a wavelength smaller than a circumference of the coupler.
- 20.** The method of claim **18**, further comprising coupling an incoming electromagnetic wave from the transmission medium onto the coupler and providing the incoming electromagnetic wave to a receiver, wherein first characteristics of the incoming electromagnetic wave differ from second characteristics of the second electromagnetic wave.

* * * * *