




	1	2	3	4	5	6	7	8																																									
A	PARTS LIST <table><tr><th>REF</th><th>QTY</th><th>DESCRIPTION</th><th>KEY RATINGS / NOTES</th></tr><tr><td>BT1</td><td>1</td><td>12 V LiFePO4 battery, 200 Ah, internal BMS</td><td>10-14.6 V working range</td></tr><tr><td>F1</td><td>1</td><td>Fuse + holder, 10 A</td><td>within 15 cm of BT1 +</td></tr><tr><td>SW1</td><td>1</td><td>Battery master switch</td><td>disconnects the whole system</td></tr><tr><td>TB1</td><td>1</td><td>Fused distribution block, 2 ways</td><td>F2 5 A -> PS1, F3 2 A -> PS2</td></tr><tr><td>TB2</td><td>1</td><td>Negative bus bar</td><td>single return point</td></tr><tr><td>PS1</td><td>1</td><td>Buck converter 12 V -> 5.1 V, 5 A or more</td><td>set off-load before connecting A2</td></tr><tr><td>PS2</td><td>1</td><td>Buck converter 12 V -> 5 V USB</td><td>1 A or more; size by note 5, sheet 1</td></tr><tr><td>A1</td><td>1</td><td>ESP32-WROOM-32 DevKitC, 38-pin</td><td>I2C on IO21/IO22; BLE to A2</td></tr><tr><td>A2</td><td>1</td><td>Raspberry Pi 5</td><td>USB-C power only; Wi-Fi off</td></tr></table>								REF	QTY	DESCRIPTION	KEY RATINGS / NOTES	BT1	1	12 V LiFePO4 battery, 200 Ah, internal BMS	10-14.6 V working range	F1	1	Fuse + holder, 10 A	within 15 cm of BT1 +	SW1	1	Battery master switch	disconnects the whole system	TB1	1	Fused distribution block, 2 ways	F2 5 A -> PS1, F3 2 A -> PS2	TB2	1	Negative bus bar	single return point	PS1	1	Buck converter 12 V -> 5.1 V, 5 A or more	set off-load before connecting A2	PS2	1	Buck converter 12 V -> 5 V USB	1 A or more; size by note 5, sheet 1	A1	1	ESP32-WROOM-32 DevKitC, 38-pin	I2C on IO21/IO22; BLE to A2	A2	1	Raspberry Pi 5	USB-C power only; Wi-Fi off	A
	REF	QTY	DESCRIPTION	KEY RATINGS / NOTES																																													
	BT1	1	12 V LiFePO4 battery, 200 Ah, internal BMS	10-14.6 V working range																																													
	F1	1	Fuse + holder, 10 A	within 15 cm of BT1 +																																													
	SW1	1	Battery master switch	disconnects the whole system																																													
	TB1	1	Fused distribution block, 2 ways	F2 5 A -> PS1, F3 2 A -> PS2																																													
	TB2	1	Negative bus bar	single return point																																													
	PS1	1	Buck converter 12 V -> 5.1 V, 5 A or more	set off-load before connecting A2																																													
	PS2	1	Buck converter 12 V -> 5 V USB	1 A or more; size by note 5, sheet 1																																													
	A1	1	ESP32-WROOM-32 DevKitC, 38-pin	I2C on IO21/IO22; BLE to A2																																													
A2	1	Raspberry Pi 5	USB-C power only; Wi-Fi off																																														
B	<table><tr><td>U1, U2</td><td>2</td><td>TCA9548A 8-channel I2C switch module</td><td>0x70 / 0x71; VCC 1.65-5.5 V; 400 kHz</td></tr><tr><td>MOD01-16</td><td>16</td><td>MAX30102 pulse-oximetry module</td><td>0x57; module VIN, onboard regulator</td></tr><tr><td>U3</td><td>1</td><td>IMU module (optional)</td><td>on the main bus; address must not clash</td></tr><tr><td>R1-R4</td><td>a/r</td><td>Pull-up resistors 4.7 k</td><td>one pair per enabled segment (note 5)</td></tr><tr><td>R5, R6</td><td>2</td><td>Pull-up resistors 10 k</td><td>RESET of U1/U2 to +3V3 (note 3)</td></tr><tr><td>-</td><td>a/r</td><td>Harness wire, sleeving, strain relief</td><td>size from the measured current (note 7)</td></tr></table>								U1, U2	2	TCA9548A 8-channel I2C switch module	0x70 / 0x71; VCC 1.65-5.5 V; 400 kHz	MOD01-16	16	MAX30102 pulse-oximetry module	0x57; module VIN, onboard regulator	U3	1	IMU module (optional)	on the main bus; address must not clash	R1-R4	a/r	Pull-up resistors 4.7 k	one pair per enabled segment (note 5)	R5, R6	2	Pull-up resistors 10 k	RESET of U1/U2 to +3V3 (note 3)	-	a/r	Harness wire, sleeving, strain relief	size from the measured current (note 7)	B																
	U1, U2	2	TCA9548A 8-channel I2C switch module	0x70 / 0x71; VCC 1.65-5.5 V; 400 kHz																																													
	MOD01-16	16	MAX30102 pulse-oximetry module	0x57; module VIN, onboard regulator																																													
	U3	1	IMU module (optional)	on the main bus; address must not clash																																													
	R1-R4	a/r	Pull-up resistors 4.7 k	one pair per enabled segment (note 5)																																													
	R5, R6	2	Pull-up resistors 10 k	RESET of U1/U2 to +3V3 (note 3)																																													
-	a/r	Harness wire, sleeving, strain relief	size from the measured current (note 7)																																														
C	WIRE LIST <table><tr><th>FROM</th><th>TO</th><th>NET</th><th>WIRE</th></tr><tr><td>BT1 +</td><td>F1 in</td><td>+12V_RAW</td><td>red</td></tr><tr><td>F1 out</td><td>SW1 1</td><td>+12V_FUSED</td><td>red</td></tr><tr><td>SW1 2</td><td>TB1 in</td><td>+12V_SW</td><td>red</td></tr><tr><td>TB1 F2 out</td><td>PS1 IN+</td><td>+12V_PI</td><td>red</td></tr><tr><td>TB1 F3 out</td><td>PS2 IN+</td><td>+12V_ESP</td><td>red</td></tr><tr><td>BT1 -</td><td>TB2</td><td>GND</td><td>black</td></tr><tr><td>TB2</td><td>PS1 IN- , PS2 IN-</td><td>GND</td><td>black</td></tr><tr><td>PS1 OUT+ / OUT-</td><td>A2 USB-C</td><td>+5V_PI</td><td>USB cable</td></tr><tr><td>PS2 OUT</td><td>A1 micro-USB</td><td>+5V_ESP</td><td>USB cable</td></tr></table>								FROM	TO	NET	WIRE	BT1 +	F1 in	+12V_RAW	red	F1 out	SW1 1	+12V_FUSED	red	SW1 2	TB1 in	+12V_SW	red	TB1 F2 out	PS1 IN+	+12V_PI	red	TB1 F3 out	PS2 IN+	+12V_ESP	red	BT1 -	TB2	GND	black	TB2	PS1 IN- , PS2 IN-	GND	black	PS1 OUT+ / OUT-	A2 USB-C	+5V_PI	USB cable	PS2 OUT	A1 micro-USB	+5V_ESP	USB cable	C
	FROM	TO	NET	WIRE																																													
	BT1 +	F1 in	+12V_RAW	red																																													
	F1 out	SW1 1	+12V_FUSED	red																																													
	SW1 2	TB1 in	+12V_SW	red																																													
	TB1 F2 out	PS1 IN+	+12V_PI	red																																													
	TB1 F3 out	PS2 IN+	+12V_ESP	red																																													
	BT1 -	TB2	GND	black																																													
	TB2	PS1 IN- , PS2 IN-	GND	black																																													
	PS1 OUT+ / OUT-	A2 USB-C	+5V_PI	USB cable																																													
PS2 OUT	A1 micro-USB	+5V_ESP	USB cable																																														
D	<table><tr><td>A1 3V3</td><td>U1 VIN, U2 VIN</td><td>+3V3</td><td>pink</td></tr><tr><td>A1 5V</td><td>MOD01-16 VIN</td><td>+5V_PAD</td><td>orange</td></tr><tr><td>A1 GND</td><td>U1/U2 GND, MOD01-16 GND, U3 GND</td><td>GND</td><td>black</td></tr><tr><td>A1 IO21</td><td>U1 SDA, U2 SDA, U3 SDA</td><td>SDA_MAIN</td><td>blue</td></tr><tr><td>A1 IO22</td><td>U1 SCL, U2 SCL, U3 SCL</td><td>SCL_MAIN</td><td>yellow</td></tr><tr><td>U1 SD0..SD7</td><td>MOD01..MOD08 SDA</td><td>SDA_A0..A7</td><td>blue</td></tr><tr><td>U1 SC0..SC7</td><td>MOD01..MOD08 SCL</td><td>SCL_A0..A7</td><td>yellow</td></tr><tr><td>U2 SD0..SD7</td><td>MOD09..MOD16 SDA</td><td>SDA_B0..B7</td><td>blue</td></tr><tr><td>U2 SC0..SC7</td><td>MOD09..MOD16 SCL</td><td>SCL_B0..B7</td><td>yellow</td></tr><tr><td>U1 A0, A1, A2</td><td>GND</td><td>ADDR_U1 = 0x70</td><td>-</td></tr></table>								A1 3V3	U1 VIN, U2 VIN	+3V3	pink	A1 5V	MOD01-16 VIN	+5V_PAD	orange	A1 GND	U1/U2 GND, MOD01-16 GND, U3 GND	GND	black	A1 IO21	U1 SDA, U2 SDA, U3 SDA	SDA_MAIN	blue	A1 IO22	U1 SCL, U2 SCL, U3 SCL	SCL_MAIN	yellow	U1 SD0..SD7	MOD01..MOD08 SDA	SDA_A0..A7	blue	U1 SC0..SC7	MOD01..MOD08 SCL	SCL_A0..A7	yellow	U2 SD0..SD7	MOD09..MOD16 SDA	SDA_B0..B7	blue	U2 SC0..SC7	MOD09..MOD16 SCL	SCL_B0..B7	yellow	U1 A0, A1, A2	GND	ADDR_U1 = 0x70	-	D
	A1 3V3	U1 VIN, U2 VIN	+3V3	pink																																													
	A1 5V	MOD01-16 VIN	+5V_PAD	orange																																													
	A1 GND	U1/U2 GND, MOD01-16 GND, U3 GND	GND	black																																													
	A1 IO21	U1 SDA, U2 SDA, U3 SDA	SDA_MAIN	blue																																													
	A1 IO22	U1 SCL, U2 SCL, U3 SCL	SCL_MAIN	yellow																																													
	U1 SD0..SD7	MOD01..MOD08 SDA	SDA_A0..A7	blue																																													
	U1 SC0..SC7	MOD01..MOD08 SCL	SCL_A0..A7	yellow																																													
	U2 SD0..SD7	MOD09..MOD16 SDA	SDA_B0..B7	blue																																													
	U2 SC0..SC7	MOD09..MOD16 SCL	SCL_B0..B7	yellow																																													
U1 A0, A1, A2	GND	ADDR_U1 = 0x70	-																																														
E	<table><tr><td>U2 A0</td><td>+3V3 (A1, A2 to GND)</td><td>ADDR_U2 = 0x71</td><td>-</td></tr><tr><td>U1 RESET, U2 RESET</td><td>+3V3 through 10 k</td><td>RST_MUX</td><td>-</td></tr></table>								U2 A0	+3V3 (A1, A2 to GND)	ADDR_U2 = 0x71	-	U1 RESET, U2 RESET	+3V3 through 10 k	RST_MUX	-	E																																
	U2 A0	+3V3 (A1, A2 to GND)	ADDR_U2 = 0x71	-																																													
U1 RESET, U2 RESET	+3V3 through 10 k	RST_MUX	-																																														
F	NOT A MEDICAL DEVICE - student prototype. Interconnect drawing: not to scale, not a PCB layout.								F																																								
	<table><tr><td>REV</td><td>DESCRIPTION</td><td>DATE</td><td>BY</td></tr><tr><td>A</td><td>Initial release - 16 pads, two multiplexers</td><td>2026-09-22</td><td>Team 18</td></tr></table>								REV	DESCRIPTION	DATE	BY	A	Initial release - 16 pads, two multiplexers	2026-09-22	Team 18																																	
	REV	DESCRIPTION	DATE	BY																																													
	A	Initial release - 16 pads, two multiplexers	2026-09-22	Team 18																																													
<table><tr><td colspan="4">Team 18 - FIU Senior Design Biometric Steering Wheel - 16 PPG pad harness</td></tr><tr><td colspan="2">SUBTITLE Sheet 2 - parts list and wire list</td><td>DRAWING No. TD18-HW-002</td><td>REV A</td><td>SHEET 2 of 2</td></tr><tr><td colspan="2">DRAWN Team 18</td><td>DATE 2026-09-22</td><td>SCALE NTS</td><td>SIZE B</td></tr></table>								Team 18 - FIU Senior Design Biometric Steering Wheel - 16 PPG pad harness				SUBTITLE Sheet 2 - parts list and wire list		DRAWING No. TD18-HW-002	REV A	SHEET 2 of 2	DRAWN Team 18		DATE 2026-09-22	SCALE NTS	SIZE B																												
Team 18 - FIU Senior Design Biometric Steering Wheel - 16 PPG pad harness																																																	
SUBTITLE Sheet 2 - parts list and wire list		DRAWING No. TD18-HW-002	REV A	SHEET 2 of 2																																													
DRAWN Team 18		DATE 2026-09-22	SCALE NTS	SIZE B																																													
1	2	3	4	5	6	7	8																																										