Emergency card · Example Electrical Ltd

Business: Example Electrical Ltd Printed: 23 October 2026

Hangs next to the fire extinguisher; one copy in the drawer of the responsible person, one with the deputy at home. Nothing on this card is in the computer that may be encrypted.

The first hour

1. Disconnect. Pull the network cable, switch Wi-Fi off; if it is unclear which device is affected, disconnect the router from the internet. Do not switch off if help arrives shortly, because traces are lost; switch off if nobody comes and the encryption spreads visibly.
2. Do not delete, do not reinstall, do not plug in the backup. A backup connected to an infected device is the next encrypted backup.
3. Call. The responsible person, the IT provider, the hotline. The numbers are on this card, not in the encrypted computer.
4. Write down. Time, device, what was on the screen, who did what; a photo of the screen with the phone. The authority and the insurer will ask.

No ransom without talking to the police and the insurer first: experts advise against paying, and payment guarantees nothing.

Who to call

Responsible	Owner or managing director, mobile phone and the office email address
Deputy	office management
IT provider	Example IT Services Ltd, emergency line in the service contract
Hotline	Cyber-Security-Hotline of the Austrian Economic Chambers: 0800 888 133, around the clock, free for members
Computer emergency team	CERT.at: reports@cert.at, +43 1 5056416 78
Police	Emergency 133 (Euro emergency 112); report at the nearest police station; tips to the cybercrime desk of the Bundeskriminalamt: against-cybercrime@bmi.gv.at
Data protection authority	Datenschutzbehörde, Vienna: online form or dsb@dsb.gv.at, +43 1 52 152-0
Cyber insurer	no policy; decide with the management
Bank	[blocking number from the card or online banking]
Email and cloud provider	[customer portal and support number]

Deadlines

Customers that may be affected	Within 24 hours of becoming aware, by phone, through the management or the deputy
Personal data affected?	Owner or managing director checks; report to the data protection authority without undue delay and within 72 hours of becoming aware.
Business covered by NIS 2?	Early warning to the authority within 24 hours of becoming aware; see the NIS2 memo on scutoria.com.

Where things are

Backup	daily to the NAS in the office, no offline copy
Recovery codes and account list	[place, outside the computers]
Evidence folder	Folder "Security" on the office server and the paper folder in the office
We can bridge	About a day

Afterwards

Change the passwords of email, bank and cloud from a clean device, check the second factor, write one page about what happened and what was changed.

Model: the IT-Notfallkarte of the BSI and the Alliance for Cyber Security; first-hour steps after onlinesicherheit.gv.at and the BSI. Numbers as of 19 October 2026; check them before printing. Generated with the Scutoria Security Evidence Toolkit. No legal advice.