Emergency card · Example Electrical Ltd

Business: Example Electrical Ltd Printed: 3 November 2026

Who to call

Responsible
+43 660 000 00 01 (example)
Owner or managing director, office@example.at

Deputy
[phone number]
office management

IT provider
+43 1 000 00 00 (example)
Example IT Services Ltd

Hotline
0800 888 133
Cyber-Security-Hotline of the Austrian Economic Chambers, around the clock, free for members; IT security experts Mon to Fri 8:00 to 18:00

Computer emergency team
+43 1 5056416 78
CERT.at, reports@cert.at

Police
133 · 112
Emergency 133 (Euro emergency 112); report at the nearest police station; tips to the cybercrime desk of the Bundeskriminalamt: against-cybercrime@bmi.gv.at

Data protection authority
+43 1 52 152-0
Datenschutzbehörde, Vienna: online form or dsb@dsb.gv.at

Cyber insurer
no policy; decide with the management

Bank
[blocking number from the card or online banking]

Email and cloud provider
[customer portal and support number]

The first hour

1. Disconnect.
Pull the network cable, switch Wi-Fi off; if it is unclear which device is affected, disconnect the router from the internet. Do not switch off if help arrives shortly, because traces are lost; switch off if nobody comes and the encryption spreads visibly.

2. Do not delete, do not reinstall.
Stop the backup jobs and disconnect the NAS or backup disk from the network; never connect a backup to an infected device.

3. Call.
The responsible person, the IT provider, the hotline. The numbers are on this card, not in the encrypted computer.

4. Write down.
Time, device, what was on the screen, who did what; a photo of the screen with the phone. The authority and the insurer will ask.

No ransom without talking to the police and the insurer first: experts advise against paying, and payment guarantees nothing.

Deadlines

Inform customers who may be affected
Within 24 hours of becoming aware, by phone, through the management or the deputy
List of customer contacts: [place]

Personal data affected?
Owner or managing director checks. Report to the data protection authority without undue delay and where possible within 72 hours of becoming aware, unless there is unlikely to be a risk to people; if you process the data for a customer, inform the customer at once instead. Record every breach (GDPR Art. 33).

Business covered by NIS 2?
Only for a significant incident: early warning to CERT.at or your sector CSIRT via the USP reporting platform within 24 hours of becoming aware, notification within 72 hours, final report within one month of the notification (§ 34 NISG 2026).

Where things are

Backup	daily to the NAS in the office, no offline copy
Recovery codes and account list	[place, outside the computers]
Evidence folder	Folder “Security” on the office server and the paper folder in the office
We can bridge	About a day

Afterwards

Change the passwords of email, bank and cloud from a clean device, check the second factor, write one page about what happened and what was changed.

Hangs next to the fire extinguisher; one copy in the drawer of the responsible person, one with the deputy at home. Nothing on this card is in the computer that may be encrypted.

Model: the IT-Notfallkarte of the BSI and the Alliance for Cyber Security; first-hour steps after onlinesicherheit.gv.at and the BSI. On switching off, the sources differ; the card follows our weighing (handbook, section 4). Numbers and deadlines as of 23 October 2026; check them before printing. Sources, retrieved 23 October 2026: GDPR Art. 33; NISG 2026 § 34; cert.at, Vorfall melden; wko.at, Cyber-Security-Hotline; dsb.gv.at; bmi.gv.at, Meldestellen. Generated with the Scutoria Security Evidence Toolkit. No legal advice.

Example Electrical Ltd

Sample · page 1 of 1 · The complete document comes from the toolkit.