

Clock MQTT Messages

Type	Topic	Package	Description
subscription	Paradox/Houdini/Mirror/Clock/Commands	{"time":"MM:SS"}	Sets the clock to the designated time.
subscription	Paradox/Houdini/Mirror/Clock/Commands	{"command":"start"}	Starts the clock to counting down.
subscription	Paradox/Houdini/Mirror/Clock/Commands	{"command":"pause"}	Pauses the clock countdown.
			Use alpha to transition to a solid back screen over the milliseconds specified in duration. Once alpha is=0 the animation can stop but the time continues to need to be tracked.
subscription	Paradox/Houdini/Mirror/Clock/Commands	{"command":"fadeout", "duration":"2000"}	If the animation has been paused, update it to the current time and then transition the alpha back to showing the clock over the specified duration in milliseconds.
subscription	Paradox/Houdini/Mirror/Clock/Commands	{"command":"fadein", "duration":"2000"}	Display the user entered text centered on the screen in the 90 orientation that matches the clock numbers. The text should fade in over 2 seconds, hold for the specified duration in seconds, then fade out over 2 seconds. If a null or spaces (e.g. " ") are sent then simply clear out the previous message. If no duration is not supplied then default to 25 seconds.
subscription	Paradox/Houdini/Mirror/Clock/Commands	{"hint":"<User entered text.>","duration":"<seconds>"}	