

MagicCode Super-Resolution Software Getting Started v1.1.0

Document

Version:

v1.1.0

Release Date: July 4, 2026

1. Purpose

This guide is the entry document for customers receiving the MagicCode Super-Resolution Software v1.1.0 release package. It explains the release package layout, supported platforms, quick-start workflow, and where to find detailed documents.

2. Release Package Overview

A typical v1.1.0 release package contains native headers, native libraries, model files, demo projects, engine plugins, and documentation.

Path	Description
------	-------------

header/	
---------	--

Public C API header, including mc_interface.h.	
--	--

lib/	
------	--

Platform-specific static or dynamic libraries for Android, iOS/iPadOS, macOS, Windows, or other enabled targets.	
--	--

model/	
--------	--

MagicSR model parameter files. The selected model must match the backend and mode.	
--	--

demo/	
-------	--

Reference demo projects, including Android and iOS/iPadOS examples where provided.	
--	--

plugin/unity/	
---------------	--

Unity wrapper, C# API, native bridge, sample project, and validation materials.	
---	--

plugin/ue/

Unreal Engine plugin, Blueprint/C++ bridge, sample project, and validation materials.

doc/

Product specification, EULA, privacy policy, error code manual, release notes, API reference, integration guide, and supporting release documents.

3. Supported Capabilities

- Scaling factor range: 1.0x to 8.0x, subject to backend and model capability.
- Public modes: HIGH_SPEED_MODE and SPEED_MODE.
- Input resolution range: 64 x 64 to 4032 x 4032.
- CPU backends: x86 and NEON.
- GPU backends: Metal, OpenGL, OpenGLES, and Vulkan where supported by platform and build.
- Engine plugins: Unity integration and Unreal Engine integration for supported Android and iOS workflows.

4. Quick Start - Native API

- 1 Include mc_interface.h in your native project.
- 2 Link the matching libmagic_sr library for your platform and architecture.
- 3 Place the matching model file in a runtime-accessible path.
- 4 Fill input_param_t with input type, model path, width, height, scale, mode, thread count, log level, and backend.

- 5 Call MC_Init to create a handle.
- 6 Call MC_Process for each input frame or image.
- 7 Use MC_Control to query status or change supported runtime parameters.
- 8 Call MC_Uninit before shutdown.

5. Quick Start - Unity

- 1 Build or obtain libmagic_sr_unity.so for Android and libmagic_sr_unity_ios.a for iOS.
- 2 Copy Android plugin files to Assets/Plugins/Android/arm64-v8a/ and iOS files to Assets/Plugins/iOS/.
- 3 Copy MagicSRNative.cs and MagicSRRealtimeDemo.cs into your Unity project.
- 4 Place model files in StreamingAssets or another runtime-accessible location.
- 5 Run on a physical target device and validate output dimensions and non-zero output content.

6. Quick Start - Unreal Engine

- 1 Copy plugin/ue/MagicSR into <YourUEProject>/Plugins/MagicSR.
- 2 Ensure platform libraries exist at the paths expected by the plugin module rules.
- 3 Enable the plugin, regenerate project files if needed, and reopen the editor.

4 Use Blueprint nodes such as CreateSession, ProcessY8, SetParam, QueryStatus, and DestroySession.

5 Package and run on a physical Android or iOS device for validation.

7. Related Documents

- Software Specification v1.1.0
- End User License Agreement v1.1.0
- Privacy Policy v1.1.0
- Error Code Manual
- API Reference v1.1.0
- Integration Guide v1.1.0
- Release Notes v1.1.0
- FAQ and Troubleshooting v1.1.0