

Overview





Overview

These GPS uses multi-constellation GNSS powered by u-blox M10, M9N, and M8N series, a concurrent GNSS receiver that can receive and track multiple GNSS systems. Owing to the multi-band RF front-end architecture, all four major GNSS constellations, GPS, Galileo, GLONASS, and BeiDou, can be received concurrently.

It also comes with the IST8310 compass, tricolored LED indicator, buzzer, and a safety switch. The high-gain 25 × 25 mm² patch antenna provides excellent performance, and the omnidirectional antenna radiation pattern increases flexibility for device installation.

There are 3 different connector options for different purposes. Please Pinout page for more details.

 M10 and M9N GPS modules now come with an IP67 rating.

 **Firmware Support for M10 GPS:** PX4 1.14, ArduPilot 4.3, INAV 5.0.0, Betaflight 4.3.0 or newer is required.

Specification

	Holybro M10 GPS	Holybro M9N GPS
GNSS Receiver	Ublox M10	Ublox M9N
Number of Concurrent GNSS	Up to 4 GNSS - BeiDou - Galileo - GLONASS - GPS - QZSS	Up to 4 GNSS - BeiDou - Galileo - GLONASS - GPS - QZSS
Frequency Band	- GPS L1 - Galileo E1 - GLONASS L1 - BeiDou B1 - SBAS L1 - QZSS L1	- GPS L1 - Galileo E1 - GLONASS L1 - BeiDou B1 - SBAS L1 - QZSS L1
Compass	IST8310	IST8310
Output Protocol	- UBX (U-blox) - NMEA	- UBX (U-blox) - NMEA
Accuracy	2.0m CEP	1.5m CEP
Nav. Update Rate	Up to 25 Hz (single GNSS), Up to 10 Hz (4 concurrent GNSS)	Up to 25 Hz (4 concurrent GNSS)
GNSS Augmentation System	EGNOS, GAGAN, MSAS and WAAS QZSS: L1S	EGNOS, GAGAN, MSAS and WAAS QZSS: L1S
Default Baud Rate	115200	115200
Input Voltage	4.7-5.2V	4.7-5.2V
Port Type	JST-GH-10P	JST-GH-10P
Antenna	25 × 25 × 4 mm ceramic patch antenna	25 × 25 × 4 mm ceramic patch antenna
Power consumption	Less than 200mA @ 5V	Less than 200mA @ 5V

Water Resistance Rating	IP67	IP67
Operating Temperature	-40~80C	-40~80C
Dimension	φ50 x14.4 mm	φ50 x14.4 mm
Weight	32g	32g
Cable Length	26cm (42cm cable purchase separately)	26cm (42cm cable purchase separately)
Other	<ul style="list-style-type: none"> - Tri-color LED - Onboard Buzzer - Safety Switch - LNA MAX2659ELT+ RF Amplifier - Rechargeable Farah capacitance - Low noise 3.3V regulator 	<ul style="list-style-type: none"> - Tri-color LED - Onboard Buzzer - Safety Switch - LNA MAX2659ELT+ RF Amplifier - Rechargeable Farah capacitance - Low noise 3.3V regulator

- **M8N:** Concurrent reception of up to 3 GNSS (GPS, Galileo, GLONASS, BeiDou)