

FAN COILS ACCESSORY ELECTRIC HEATERS

WIRING DIAGRAMS

FIG.	FIELD INSTALLED HEATER MODEL	FB4C	FE4A FE5A	FH4C	FV4C	FX4D	FY5B	PF4MA	PF4MB	LABEL
1	KFCEH0401N03	18,24		001		19,25	18,24	18,19,24,25		328613-101
1	KFCEH0501N05	18-60	002-006	001-002	002-006	19-61	18-60	18-61	19-61	328613-101
1	KFCEH0801N08	18-60	002-006	001-003	002-006	19-61	18-60	18-61	19-61	328613-101
1	KFCEH0901N10	18-60	002-006	001-004	002-006	19-61	18-60	18-61	19-61	328613-101
5	KFCEH1601315	42-60	002-006	001-004	002-006	43-61	18-60	18-61	19-61	328614-101
6	KFCEH2001318	42-60	003-006	001-004	002-006	43-61	42-60	42-61	37-61	328615-101
1	KFCEH2401C05	18-60	002-006	001-002	002-006	19-61	18-60	18-61	19-61	328613-101
1	KFCEH2501C08	18-60	002-006	001-003	002-006	19-61	18-60	18-61	19-61	328613-101
1	KFCEH2601C10	18-60	002-006	001-004	002-006	19-61	18-60	18-61	19-61	328613-101
2	KFCEH2901N09	36-60	002-006	003-004	002-006	37-61	36-60	36-60	31-61	328606-101
3	KFCEH3001F15	24-60	002-006	001-004	002-006	25-61	24-60	24-61	19-61	328605-101
3	KFCEH3101C15	24-60	002-006	001-004	002-006	25-61	24-60	24-61	19-61	328605-101
4	KFCEH3201F20	30-60	002-006	002-004	002-006	31-61	30-60	30-61	19-61	328604-101
4	KFCEH3301C20	30-60	002-006	002-004	002-006	31-61	30-60	30-61	19-61	328604-101
7,8	KFCEH3401F24	48,60	004-006	003-004	005-006	49-61	48-60	48-61	49-61	328602-101, 328603-101
7,8	KFCEH3501F30	48,60	004-006	003-004	005-006	49-61	48-60	48-61	49-61	328602-101, 328603-101

FIG.	FIELD INSTALLED HEATER MODEL	FY5B	LABEL
9	MKFCEH0501N05	18,24	328205-101
9	MKFCEH0801N08	18,30	328205-101
9	MKFCEH0901N10	24-48	328205-101
10	MKFCEH3001F15	36-60	328206-101

FAN COIL WITH RBC X-13 MOTOR

FIG.	FIELD INSTALLED HEATER MODEL	FB4C	FX4D	LABEL
11	MKFCEH0501N05	18,24	19,25	335975-101
11	MKFCEH0801N08	18,30	31	335975-101
11	MKFCEH0901N10	24-48	37-61	335975-101
12	MKFCEH3001F15	36-60	61	336923-101

FAN COIL WITH BROAD OCEAN DIGI – MOTOR

FIG.	FIELD INSTALLED HEATER MODEL	FB4C	FX4D	LABEL
13	MKFCEH0501N05	24	–	337518 – 101
13	MKFCEH0801N08	18,30	31	337518 – 101
13	MKFCEH0901N10	24 – 36	37 – 49	337518 – 101
14	MKFCEH3001F15	36	–	338001 – 101

FAN COIL WITH COOLING ONLY CONTROL

FIG.	MODEL	SIZE	LABEL
15	FV4C	002 – 006	326014 – 101
16	FE4A/FE5A	002 – 006	333107 – 101
17	FY5B/PF4MNA	18 – 60	328964 – 101
17	FH4C	001 – 004	328964 – 101
18	FB4C/FX4D (RBC)	18 – 61	336228 – 101
18	PF4MNA/B	19,25,31,37,43,49,61	336228 – 101
19	FB4C/FX4D (BOM)	18 – 61	337519 – 101

FIG.	HEATER MODEL	FF1E	LABEL
20	KFDEH0801D05	18,24,30,36	324494 – 101
20	KFDEH0901D75	18,24,30,36	324494 – 101
20	KFDEH1001D11	18,24,30,36	324494 – 101
20	MKFDEH0801D05	18,24,30,36	324494 – 101
20	MKFDEH0901D75	18,24,30,36	324494 – 101
20	MKFDEH1001D11	18,24,30,36	324494 – 101
21	KFEEH0101D05	19,25,31,37	335826 – 101
21	KFEEH0201D75	19,25,31,37	335826 – 101
21	KFEEH0301D11	19,25,31,37	335826 – 101




Fig. 1 - 328613-101

A07001




Fig. 2 - 328606-101

A07002




Fig. 3 - 328605-101

A07003




Fig. 4 - 328604-101

A07004




Fig. 5 - 328614-101

A07005




Fig. 6 - 328615-101

A07006




Fig. 7 - 328603-101

A07007




Fig. 8 - 328602-101

A07038





Fig. 11 - 335975-101

**THIS COMPARTMENT MUST BE
CLOSED EXCEPT FOR SERVICING**

**BLOWER MOTOR
ROTATION**


COOLING ONLY SCHEMATIC DIAGRAM



LEGEND

---	FIELD POWER WIRING
⬢	MARKED TERMINAL
⌋⌋	PLUG AND RECEPTACLE
COM	COMMON
F1	LOW VOLTAGE FUSE
GND	EQUIPMENT GROUND
ICM	FAN MOTOR
PCB	PRINTED CIRCUIT BOARD
RECP	RECEPTACLE
TRAN	TRANSFORMER

COMPONENT ARRANGEMENT



NOTES:

1. USE COPPER WIRE (75°C MIN) ONLY BETWEEN DISCONNECT SWITCH AND UNIT.
2. TO BE WIRED IN ACCORDANCE WITH N.E.C. AND LOCAL CODES.
3. TRANSFORMER PRIMARY LEADS, BLUE 208V, RED 230V.
4. IF ANY OF THE ORIGINAL WIRE, AS SUPPLIED, MUST BE REPLACED, USE THE SAME OR EQUIVALENT TYPE WIRE.
5. REPLACE LOW VOLTAGE FUSE WITH NO GREATER THAN 5 AMP FUSE.
7. USE 60 AMP CLASS K FUSES ONLY, FOR REPLACEMENT.
8. CONNECT R TO R, G TO G, ETC., SEE OUTDOOR INSTRUCTION FOR DETAILS.

326014-101 REV. D

Fig. 15 - 326014-101

A07029





Fig. 16 - 333107-101

A12363

BLOWER MOTOR ROTATION



CAP	CAPACITOR
COM	COMMON
F	LOW VOLTAGE FUSE
FR	PCB FAN RELAY
FM	FAN MOTOR
GND	EQUIPMENT GROUND
PCB	PRINTED CIRCUIT BOARD
RECP	RECEPTACLE
SPT	FAN SPEED TAP LOCATION
TRAN	TRANSFORMER



328964-101 REV.A


MODEL SIZE	HEATER SIZE KW						
	3,5,8	9	10	15	18	20	24, 30
18	MED *	----	HI	----	----	----	----
24	MED ‡	----	MED ‡	MED ‡	----	---	----
30	----	----	LO	LO	----	MED *	---
36, 42, 48, 60	----	LO	LO	LO	LO	LO	LO
70	----	MED	MED	MED	MED	MED	MED

- * - MED speed on 3 speed motors
and HI speed on 2 speed motors.
- ‡ - MED speed on 3 speed motors
and LO speed on 2 speed motors.

1. Use Copper Wire (75°C Min) Only Between Disconnect Switch And Unit.
2. To Be Wired In Accordance With NEC And Local Codes.
3. If Any Of The Original Wire, As Supplied, Must Be Replaced, Use The Same Or Equivalent Type Wire.
4. Replace Low Voltage Fuse With No Greater Than 5 Amp Fuse.
5. (3) Speed Motor Shown Optional (2) Speed Motor Uses HI (BLK) And LOW (BLUE or RED).
6. Connect R To R, G To G, Etc. See Outdoor Instruction For Details.

THIS COMPARTMENT MUST BE CLOSED EXCEPT FOR SERVICING

BLOWER MOTOR
ROTATION



NOTES



1. Use Copper Wire (75°C Min) Only Between Disconnect Switch And Unit.
2. To Be Wired In Accordance With NEC And Local Codes.
3. If Any Of The Original Wire, As Supplied, Must Be Replaced. Use The Same Or Equivalent Type Wire.
4. Replace Low Voltage Fuse With No Greater Than 5 Amp Fuse.
5. Connect R To R, G To G, Etc. See Outdoor Instruction For Details.
6. To change speed tap, move blue wire to desired terminal.
7. See airflow tables for tap usage.

336228-101 REV. A

Fig. 18 - 336228-101

A12364

BLOWER MOTOR ROTATION



C	COMMON
F	LOW VOLTAGE FUSE
FM	FAN MOTOR
GND	EQUIPMENT GROUND
RECP	RECEPTACLE
SPT	FAN SPEED TAP LOCATION
TRAN	TRANSFORMER
	UNMARKED TERMINAL
	FIELD POWER WIRING
	MARKED TERMINAL
	PLUG AND RECEPTACLE

1. Use Copper Wire (75°C Min) Only Between Disconnect Switch And Unit.
2. To Be Wired In Accordance With NEC And Local Codes.
3. If Any Of The Original Wire, As Supplied, Must Be Replaced. Use The Same Or Equivalent Type Wire.
4. Replace Low Voltage Fuse With No Greater Than 5 Amp Fuse.
5. Connect R To R, G To G, Etc. See Outdoor Instruction For Details.
6. To Change Speed Tap, Move Blue Wire To Desired Terminal.
7. See Airflow Tables For Tap Usage.
8. Factory wires may be present. DO NOT USE

337519-101 REV. B



A12365




Fig. 21 - 335826-101

A09212

