

Supplement "Operating time of the PS500 power supply unit"

This supplement applies only to the listed medical devices and updates the information of the respective instructions for use and the supplement to the instructions for use in the following chapters.

Medical device	Instructions for use		Supplement to instructions for use
	Part number	Edition	
Infinity Acute Care System Evita Infinity V500	9052161	7 – 2012-11	9054353
Infinity Acute Care System Babylog VN500	9038982	6 – 2012-11	
Evita V300	9052995	1 – 2012-11	

Keep this supplement with the current instructions for use of the respective medical device and the current supplement to the instructions for use.

WARNING

To properly use this medical device, read and comply with the instructions for use and the supplements.

The operating time of the PS500 power supply unit has been changed.

The information in the online help files and the table "Alarm – Cause – Remedy" on the device have not been updated.

Alarm – Cause – Remedy

Alarm priority	Alarm message	Cause	Remedy
!!! 160	Battery activated	The ventilation unit is powered by the battery as there is no mains power supply. – If PS500 is not connected, the maximum operating time is 30 minutes. – If PS500 is connected, the maximum operating time is 240 minutes.	Connect device to the mains power supply.
!! 200	Battery activated	The ventilation unit is powered by the battery as there is no mains power supply. – If PS500 is not connected, the maximum operating time is 30 minutes. – If PS500 is connected, the maximum operating time is 240 minutes.	Connect device to the mains power supply.
! 201	Battery activated	The ventilation unit is powered by the battery as there is no mains power supply. – If PS500 is not connected, the maximum operating time is 30 minutes. – If PS500 is connected, the maximum operating time is 240 minutes.	Connect device to the mains power supply.
!!! 254	Battery discharged	The remaining operating time of the battery is less than 5 minutes.	Connect device immediately to the mains power supply.
!!! 250	Battery low	The battery is almost discharged.	Connect device to the mains power supply.
!! 251	Battery low	The battery is almost discharged.	Connect device to the mains power supply.

Technical data, operating data

Batteries of power supply unit PS500

Type	VRLA batteries, maintenance-free (VRLA = Valve Regulated Lead Acid)
Fuse	Two F15A 80V UL248
Capacity	24 Ah
Voltage	24 V
Current	0 to 15 A
Operating time if mains power supply is not available	
without GS500	240 minutes
with GS500	120 minutes
Charging	
Charging time (to charge battery completely)	<24 hours (<20 hours for 80 % charge)

Operation, mains power supply / DC power supply

Battery operation

Alarm messages during battery operation

Switch-over to the batteries is indicated with the alarm message **Battery activated**. The alarm priority can be configured.

Alarm messages are displayed corresponding to the remaining battery capacity in order to warn against the complete discharge of the battery. Alarm messages, see chapter "Alarm – Cause – Remedy."

- Reestablish the mains power supply immediately to avoid an interruption of the ventilation functions.

If power was supplied from the batteries, recharge the batteries, see accompanying instructions for use.