

BOM monotropa v4d 2025 (v4f) Reverselandfill 2025**Resistors**

r1, r8, r10, r15	1.8k	4	feedback amp
r7	10k*	1	feedback amount
r4, r5, r6, r12, r13	10k	5	Mixers & opamps
r18	100k	1	Neg CV block
r17, r19, r21	1k	3	output resistors
r3	15k*	1	CV feedback mix
r16	15k*	1	Direct feedback mix
r20	2.2nf	1	Filter freq MOD option, see below

Band combinations* see below for more info and mods

band1	low		
c1	1uf	1	5mm film
c6	22nF	1	5mm film
r2	130k	1	
band2	low-mid		
c7	470n	1	5mm film
c9	10n	1	5mm film
r9	110k	1	
band3	mid		
c8	82nf / 100nF	1	5mm film
c10	2.2nf	1	5mm film
r11	82k	1	
band4	mid-high		
c11	33nf	1	5mm film
c12	1nf	1	5mm film
r14	68k	1	

Diode

d1, d2	1n4001	1	
d3	1n914	1	Neg CV block

Capacitors

c2, c3	10uF	2	electrolythic
c27	1uf	1	electrolythic
Unlabeled 2.54mm footprints	100nF	6	2.54mm

Vactrol

LED	3mm yellow	1	DIY Vactrol
LDR	3mm	1	DIY vactrol
shrink tube		1	DIY vactrol

IC

u1, u4	14pin socket	2	
--------	--------------	---	--

Blad1			
u2	8pin socket	1	
u1, u4	TL074	2	alt: TL064, TL084
u2	TL072	1	

Power

10 pin connector	shrouded	1
power cable	10pin to 16pin	1
mount screws	m3 6mm	4

Place the panel on the PCB before soldering the pots and jacks

Pots + nuts

band1, band2, band3, band4, FB1, FB2	b10k	6	vertical 9mm
--------------------------------------	------	---	--------------

Jacks + nuts

thonkiconn	5	vertical
------------	---	----------

Knobs

5

MOD options:

*Alternative frequency bands: (you can use parts that are near these values)

63Hz (band 1)	1270nF, 22nF, 130k
160Hz (band 2)	503nF, 10nF, 110k
410Hz	200nF, 4.7nF, 91k
1KHz (band 3)	80nF, 2.2nF, 82k
2.5KHz (band 4)	33nF, 1nF, 68k
7.7KHz	12.2nF, 470pF, 62k
16KHz	4.7nF, 220pF, 51k

LPG MOD

r20 (with 10k resistor instead of capacitor)
(this needs testing!!)

Feedback amount MOD

r7 sets the feedback amount. Recommended values from 5.1k to 24k (lower is more feedback)
With low values the feedback settings at fully CW can overblow.

Feedback mixer MOD

r3 and r16 form the feedback mixer.
Change these values to increase or decrease the 2 feedback mixes.
Recommended values from 10k to 20k, un-even mixes could be interesting

CC-BY-SA

credits: part of the EQ was inspired by the Boss GE7 and MTM Graphic EQ

www.reverselandfill.org
martijn@reverselandfill.org