

On the ZTE ZXA10 C600, the SNMP OID used to enable or disable an ONU (setting the admin-state) is **different** from the one used in the legacy C300/C320 MIB structure.

The C600 SNMP OID

As part of the transition to the modern **1.3.6.1.4.1.3902.1082** (zxAccessNode) subtree for the Titan platform, the management OID for an ONU's administrative status is:

- **OID:** 1.3.6.1.4.1.3902.1082.500.10.2.8.1.1 (zxAnGponSrvOnuAdminStatus) 1.
- **Legacy Comparison:** You are correct that the C300 uses the legacy 1.3.6.1.4.1.3902.1012 subtree (associated with the ZTE-GPON-MIB), but for the C600, all GPON service and status management has moved to the .1082 tree 2, 3.

Integer Values for Admin State

The administrative status OID uses the following integer values to control the registration state of the ONU:

Integer Value, Administrative State, Description

1, Active, The ONU is authorized and allowed to register with the PON port.

2, Inactive / Disabled, The ONU is blocked from registering and will remain in an offline/unauthorized state.

Indexing Note

To target a specific ONU, you must append the ifIndex and the OnuIndex to the end of the OID.

- **ifIndex:** The Type 1 physical interface index of the PON port (e.g., 285278465 for Slot 1, Port 1).
- **OnuIndex:** The local numerical ID assigned to the ONU on that port.

Example: To set ONU 1 on Slot 1, Port 1 to "Active," you would perform an SNMP SET on: 1.3.6.1.4.1.3902.1082.500.10.2.8.1.1.285278465.1 with a value of 1.

Would you like the OIDs for configuring other administrative parameters, such as the registration mode (SN, Password, or LOID)?