GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Matrix Mixer Crosspoint
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls the gain and mute of one crosspoint of a Q-SYS Matrix Mixer and reports its gain and mute state.
GENERAL NOTES:	Gain and GainValue use the crosspoint gain control's position (0 to 1 in Q-SYS) scaled to 0–65535. Position follows the control's taper as configured in Q-SYS, so a given percentage may not correspond to a fixed dB value. GainUp/GainDown step from the last gain reported by Q-SYS: one step on press, then one step every GainRepeatTime until release. Gain is clamped to 0–65535. Use one instance of this module per crosspoint.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	Works with a Q-SYS Matrix Mixer; Script Access must be External or All. The mixer must have at least as many inputs and outputs as the Input and Output numbers used.
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

[MuteOn]	D	Pulse to mute the crosspoint.
[MuteOff]	D	Pulse to unmute the crosspoint.
[GainUp]	D	Hold to raise the crosspoint gain by GainStep, repeating while held.
[GainDown]	D	Hold to lower the crosspoint gain by GainStep, repeating while held.
[Gain]	A	Sets the crosspoint gain position, 0–65535.

FEEDBACK:

[MuteIsOn]	D	High while the crosspoint is muted.
[MuteIsOff]	D	High while the crosspoint is not muted.
[GainValue]	A	Crosspoint gain position, 0–65535. Pairs with the Gain input.

PARAMETERS:

CoreID	S	Used to address this module to a Qsys Core module. Must match the CoreID of the Qsys Core module. Default: 1
ComponentName	S	Code Name of the Matrix Mixer component in the Q-SYS design.
Input	Dec	Matrix Mixer input number of the crosspoint.
Output	Dec	Matrix Mixer output number of the crosspoint.
GainStep	Dec	Amount (in 0–65535 position units) to change the gain per GainUp/GainDown step.
GainRepeatTime	Time	Time between repeated steps while GainUp/GainDown is held.

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	