GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Router
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls one output of a Q-SYS Router component: input selection and output mute, with feedback for both.
GENERAL NOTES:	Input values are passed straight through to the select_N control; no scaling is applied. OutputMuteToggle uses OutputMuteIsOn to decide the new state. Use one instance of this module per router output. See Qsys Router AutoMute for a version that uses input 0 to mute the output.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	Works with a Q-SYS Router; Script Access must be External or All. The Router must have at least as many outputs as OutputNumber.
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

[OutputMuteOn]	D	Pulse to mute the router output.
[OutputMuteOff]	D	Pulse to unmute the router output.
[OutputMuteToggle]	D	Pulse to toggle the router output mute.
Input	A	Router input number to route to the output. Sent each time the value changes.

FEEDBACK:

[OutputMuteIsOn]	D	High when the router output is muted.
[OutputMuteIsOff]	D	High when the router output is unmuted.
[InputValue]	A	Router input currently routed to the output, as reported by Q-SYS.

PARAMETERS:

CoreID	S	Used to address this module to a Qsys Core module. Must match the CoreID of the Qsys Core module. Default: 1
ComponentName	S	Code Name of the Router component in the Q-SYS design.
OutputNumber	Dec	Router output to control (1 = first output).

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	