GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Router AutoMute
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls one output of a Q-SYS Router component using a single analog value, where 0 un-routes (mutes) the output and any other value selects that input and unmutes the output.
GENERAL NOTES:	Setting InputSet to 0 sets the output mute on and leaves the router's input selection unchanged. Setting InputSet to a value above 0 selects that input and then sets the output mute off. InputValue reports 0 while the output is muted, and the selected input while unmuted. This applies to changes made from Q-SYS as well. Otherwise operates the same as the Qsys Router module.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	Works with a Q-SYS Router; Script Access must be External or All. The Router must have at least as many outputs as OutputNumber.
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

InputSet	A	Router input to route to the output. 0 mutes the output; any other value selects that input and unmutes the output. Acts each time the value changes.

FEEDBACK:

[InputValue]	A	Router input currently routed to the output, or 0 if the output is muted.

PARAMETERS:

CoreID	S	Used to address this module to a Qsys Core module. Must match the CoreID of the Qsys Core module. Default: 1
ComponentName	S	Code Name of the Router component in the Q-SYS design.
OutputNumber	Dec	Router output to control (1 = first output).

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	