GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Camera
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls a Q-SYS PTZ camera component: pan, tilt, zoom, focus, home preset, privacy, auto-framing and image settings (brightness, saturation, sharpness, contrast, exposure and white balance), with feedback for each setting. The camera is addressed as a Named Component by its Code Name (ComponentName parameter).
GENERAL NOTES:	Pan/tilt, zoom and focus near/far inputs move while held and stop on release. Brightness, Saturation, Sharpness, Contrast, Gain, WhiteBalanceHue, WhiteBalanceRedGain and WhiteBalanceBlueGain use the Q-SYS control's position (0 to 1) scaled to 0–65535. Their matching feedback outputs use the same scaling. ExposureMode, Iris, Shutter, AutoWhiteBalanceMode and AutoWhiteBalanceSensitivity take an index that the module converts to the text value Q-SYS expects (see each input). Values outside the listed range are ignored. The matching feedback outputs report the text value from Q-SYS. Only settings supported by the camera model have an effect (e.g. AutoFrame on cameras with auto-framing). All feedback follows the Q-SYS controls, so it also updates when changes are made from Q-SYS or another control system.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	In Q-SYS Designer, set the camera component's Code Name to match the ComponentName parameter and set its Script Access to External (or All).
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

[TiltUp]	D	Hold to tilt up.
[TiltDown]	D	Hold to tilt down.
[PanLeft]	D	Hold to pan left.
[PanRight]	D	Hold to pan right.
[PanLeftUp]	D	Hold to pan left and tilt up.
[PanLeftDown]	D	Hold to pan left and tilt down.
[PanRightUp]	D	Hold to pan right and tilt up.

[PanRightDown]	D	Hold to pan right and tilt down.
[ZoomIn]	D	Hold to zoom in.
[ZoomOut]	D	Hold to zoom out.
[AutoFocus]	D	Pulse to turn auto focus on.
[FocusNear]	D	Hold to focus near.
[FocusFar]	D	Hold to focus far.
[RecallHome]	D	Pulse to recall the camera's home preset.
[SaveHome]	D	Pulse to save the current position as the camera's home preset.
[PrivacyOn]	D	Pulse to turn privacy on.
[PrivacyOff]	D	Pulse to turn privacy off.
[PrivacyToggle]	D	Pulse to toggle privacy, based on PrivacyIsOn.
[AutoFrameOn]	D	Pulse to turn auto-framing on.
[AutoFrameOff]	D	Pulse to turn auto-framing off.
[AutoFrameToggle]	D	Pulse to toggle auto-framing, based on AutoFrameIsOn.
[Brightness]	A	Sets image brightness, 0–65535.
[Saturation]	A	Sets image saturation, 0–65535.
[Sharpness]	A	Sets image sharpness, 0–65535.
[Contrast]	A	Sets image contrast, 0–65535.
[ExposureMode]	A	Sets exposure mode: 0 = Auto, 1 = Manual.
[Iris]	A	Sets iris: 0 = Close, 1 = f/1.8, 2 = f/2.0, 3 = f/2.4, 4 = f/2.8, 5 = f/3.4, 6 = f/4.0, 7 = f/4.8, 8 = f/5.6, 9 = f/6.8, 10 = f/8.0, 11 = f/9.6, 12 = f/11.0.
[Shutter]	A	Sets shutter speed: 0 = 1/30, 1 = 1/60, 2 = 1/90, 3 = 1/100, 4 = 1/125, 5 = 1/180, 6 = 1/250, 7 = 1/350, 8 = 1/500, 9 = 1/725, 10 = 1/1000, 11 = 1/1500, 12 = 1/2000, 13 = 1/3000, 14 = 1/4000, 15 = 1/6000, 16 = 1/10000.
[Gain]	A	Sets exposure gain, 0–65535.
[AutoWhiteBalanceMode]	A	Sets white balance mode: 0 = Auto, 1 = Indoor/3000K, 2 = Outdoor/5000K, 3 = Manual, 4 = One Push.
[AutoWhiteBalanceSensitivity]	A	Sets auto white balance sensitivity: 0 = Low, 1 = Mid, 2 = High.
[WhiteBalanceHue]	A	Sets white balance hue, 0–65535.
[WhiteBalanceRedGain]	A	Sets white balance red gain, 0–65535.
[WhiteBalanceBlueGain]	A	Sets white balance blue gain, 0–65535.

FEEDBACK:

[AutoFocusIsOn]	D	High while auto focus is on.
[PrivacyIsOn]	D	High while privacy is on.
[AutoFrameIsOn]	D	High while auto-framing is on.
[BrightnessValue]	A	Image brightness, 0–65535.
[SaturationValue]	A	Image saturation, 0–65535.
[SharpnessValue]	A	Image sharpness, 0–65535.
[ContrastValue]	A	Image contrast, 0–65535.
[ExposureModeValue]	S	Exposure mode as text from Q-SYS (e.g. Auto).
[IrisValue]	S	Iris setting as text from Q-SYS (e.g. f/2.8).
[ShutterValue]	S	Shutter speed as text from Q-SYS (e.g. 1/60).
[GainValue]	A	Exposure gain, 0–65535.
[AutoWhiteBalnceModeValue]	S	White balance mode as text from Q-SYS (e.g. Auto). Note the signal name is spelled AutoWhiteBalnceModeValue.
[AutoWhiteBalanceSensitivityValue]	S	Auto white balance sensitivity as text from Q-SYS (e.g. Mid).
[WhiteBalanceHueValue]	A	White balance hue, 0–65535.
[WhiteBalanceRedGainValue]	A	White balance red gain, 0–65535.
[WhiteBalanceBlueGainValue]	A	White balance blue gain, 0–65535.

PARAMETERS:

CoreID	S	Used to address this module to a Qsys Core module. Must match the CoreID of the Qsys Core module. Default: 1
ComponentName	S	Code Name of the camera component in the Q-SYS design.

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	