GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Generic Boolean Component Control
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls and monitors a single boolean (on/off) control of any Q-SYS component (e.g. a mute, bypass or invert button). The control is identified by the component's Code Name and the control's name within that component.
GENERAL NOTES:	Inputs act on the rising edge only. BooleanState is high when the control's value is non-zero (greater than 0.1 in magnitude). ToggleBooleanState relies on BooleanState, so toggling will not work correctly until feedback has been received from the Q-SYS Core.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	The Q-SYS component that owns the control must have a Code Name set in its Properties, and Script Access set to External (or All). Enter that Code Name in the ComponentName parameter. ComponentControlName is the control's name inside that component as Q-SYS exposes it to external control (the name shown in the control's tooltip / Control Info in Q-SYS Designer, e.g. "gain", "mute"). It is case sensitive.
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

[SetBooleanStateOn]	D	Pulse to set the control's value to On (1).
[SetBooleanStateOff]	D	Pulse to set the control's value to Off (0).
[ToggleBooleanState]	D	Pulse to toggle the control. The new state is the opposite of the current BooleanState feedback.

FEEDBACK:

[BooleanState]	D	High when the control is On in Q-SYS, low when Off.

PARAMETERS:

CoreID	S	Used to address this module to the Qsys Core module with the same CoreID. Default: 1
ComponentName	S	Code Name of the Q-SYS component that contains the control.
ComponentControlName	S	Name of the control within the component to be controlled.

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	