GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Generic Boolean Named Control
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls and monitors a single boolean (on/off) Q-SYS Named Control (e.g. a mute, bypass or invert button). The control is identified by its name in the design's Named Controls list.
GENERAL NOTES:	Inputs act on the rising edge only. BooleanState follows the control's value truncated to a whole number: high for 1 (On), low for 0 (Off). ToggleBooleanState relies on BooleanState, so toggling will not work correctly until feedback has been received from the Q-SYS Core.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	The control must be added to the Named Controls list in Q-SYS Designer (drag the control into the Named Controls pane) and the design saved to the Core. Enter that name in the NamedControlName parameter; it is case sensitive.
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

[SetBooleanStateOn]	D	Pulse to set the control's value to On (1).
[SetBooleanStateOff]	D	Pulse to set the control's value to Off (0).
[ToggleBooleanState]	D	Pulse to toggle the control. The new state is the opposite of the current BooleanState feedback.

FEEDBACK:

[BooleanState]	D	High when the control is On in Q-SYS, low when Off.

PARAMETERS:

CoreID	S	Used to address this module to the Qsys Core module with the same CoreID. Default: 1
NamedControlName	S	Name of the control as entered in Q-SYS Designer's Named Controls.

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	