GENERAL INFORMATION:

SIMPLWINDOWS NAME:	Qsys Matrix Mixer Output Fader
CATEGORY:	Qsys
VERSION:	5.0.0
SUMMARY:	Controls the gain and mute of one output of a Q-SYS Matrix Mixer and reports its gain and mute state. The mixer is addressed as a Named Component by its Code Name (ComponentName parameter). The Output parameter selects the output_X_gain and output_X_mute controls.
GENERAL NOTES:	Gain and GainValue use the output gain control's position (0 to 1 in Q-SYS) scaled to 0–65535. Position follows the control's taper in Q-SYS, so it is not linear in dB. GainUp/GainDown step from the last gain reported by Q-SYS: one step on press, then one step every GainRepeatTime until release. Gain is clamped to 0–65535. All feedback follows the Q-SYS controls, so it also updates when changes are made from Q-SYS or another control system. Use one instance of this module per mixer output.
CRESTRON HARDWARE REQUIRED:	3 Series Processor or 4 Series Processor
SETUP OF CRESTRON HARDWARE:	Requires a Qsys Core module in the same program with a matching CoreID.
VENDOR FIRMWARE:	N/A
VENDOR SETUP:	In Q-SYS Designer, set the Matrix Mixer component's Code Name to match the ComponentName parameter and set its Script Access to External (or All).
GENERATION:	Generated by Claude Code from SIMPL+ and SIMPL# source files

CONTROL:

[MuteOn]	D	Pulse to mute the output.
[MuteOff]	D	Pulse to unmute the output.
[GainUp]	D	Hold to raise the output gain by GainStep, repeating while held.
[GainDown]	D	Hold to lower the output gain by GainStep, repeating while held.
[Gain]	A	Sets the output gain position, 0–65535.

FEEDBACK:

[MuteIsOn]	D	High while the output is muted.
[MuteIsOff]	D	High while the output is not muted.
[GainValue]	A	Output gain position, 0–65535. Pairs with the Gain input.

PARAMETERS:

CoreID	S	Used to address this module to a Qsys Core module. Must match the CoreID of the Qsys Core module. Default: 1
ComponentName	S	Code Name of the Matrix Mixer component in the Q-SYS design.
Output	Dec	Matrix Mixer output number to control.
GainStep	Dec	Amount (in 0–65535 position units) to change the gain per GainUp/GainDown step.
GainRepeatTime	Time	Time between repeated steps while GainUp/GainDown is held.

TESTING:

SAMPLE PROGRAM:	3-Series: 3 Series Test.smw 4-Series: 4 Series Test.smw
REVISION HISTORY:	