

REDE CORPORATIVA

show ip inter brief
show standby brief
show ip interface brief
show ip ospf neighbor

Prédio 1:

Configuração swicths de camada 3:

Switch Multilayer 0,1:

```
configure terminal
interface range fa0/1-3
switchport trunk encapsulation dot1q
switchport mode trunk
switchport trunk allowed vlan 10,20,30
```

```
vlan 10
name HR
```

```
vlan 20
name SALES
```

```
vlan 30
name FINANCE
```

Switch Multilayer 0:

```
inter vlan 10
ip address 192.168.10.2 255.255.255.0
no shutdown
ex
```

```
inter vlan 20
ip address 192.168.20.2 255.255.255.0
no shutdown
ex
```

```
inter vlan 30
ip address 192.168.30.2 255.255.255.0
no shutdown
ex
```

```
inter vlan 10
standby 10 ip 192.168.10.1
standby 10 priority 110
```

standby preempt

inter vlan 20
standby 20 ip 192.168.20.1
standby 20 priority 110
standby preempt

inter vlan 30
standby 30 ip 192.168.30.1
standby 30 priority 110
standby preempt

inter g0/1
no switchport
ip address 10.10.1.2 255.255.255.252
no shut

ip routing

router ospf 1
network 10.10.1.0 0.0.0.3 area 0
network 10.10.1.4 0.0.0.3 area 0
network 192.168.10.0 0.0.0.255 area 0
network 192.168.20.0 0.0.0.255 area 0
network 192.168.30.0 0.0.0.255 area 0
passive-interface vlan 10
passive-interface vlan 20
passive-interface vlan 30

Switch Multilayer 1:

inter vlan 10
ip address 192.168.10.3 255.255.255.0
no shutdown
ex

inter vlan 20
ip address 192.168.20.3 255.255.255.0
no shutdown
ex

inter vlan 30
ip address 192.168.30.3 255.255.255.0
no shutdown
ex

inter vlan 10
standby 10 ip 192.168.10.1

```
standby 10 priority 100
standby preempt
```

```
inter vlan 20
standby 20 ip 192.168.20.1
standby 20 priority 100
standby preempt
```

```
inter vlan 30
standby 30 ip 192.168.30.1
standby 30 priority 100
standby preempt
```

```
inter g0/1
no switchport
ip address 10.10.1.6 255.255.255.252
no shut
```

```
ip routing
```

```
router ospf 1
network 10.10.1.0 0.0.0.3 area 0
network 10.10.1.4 0.0.0.3 area 0
network 192.168.10.0 0.0.0.255 area 0
network 192.168.20.0 0.0.0.255 area 0
network 192.168.30.0 0.0.0.255 area 0
passive-interface vlan 10
passive-interface vlan 20
passive-interface vlan 30
```

Configuração swicths de camada 2:

Swicth 0,1,2:

```
configure terminal
interface range fa0/1-2
switchport mode trunk
switchport trunk allowed vlan 10,20,30
```

Swicth 0:

```
configure terminal
vlan 10
name HR
ex
```

```
interface range f0/3-24
switchport mode access
switchport access vlan 10
```

```
Swicth 1:
configure terminal
vlan 20
name SALES
ex
interface range f0/3-24
switchport mode access
switchport access vlan 20
```

```
Swicth 2:
configure terminal
vlan 30
name FINANCE
ex
interface range f0/3-24
switchport mode access
switchport access vlan 30
```

Router:

```
interface g0/1
ip address 10.10.1.1 255.255.255.252
no shut
```

```
interface g0/0
ip address 10.10.1.5 255.255.255.252
no shut
```

```
interface s0/0/0
ip address 10.10.10.1 255.255.255.252
clock rate 64000
no shut
```

```
router ospf 1
network 10.10.1.0 0.0.0.3 area 0
network 10.10.1.4 0.0.0.3 area 0
network 10.10.10.0 0.0.0.3 area 0
```

Prédio 2:

Configuração swicths de camada 3:

Switch Multilayer 2,3:

```
configure terminal
interface range fa0/1-3
switchport trunk encapsulation dot1q
switchport mode trunk
switchport trunk allowed vlan 40,50,60
```

```
vlan 40
name HR
```

```
vlan 50
name SALES
```

```
vlan 60
name FINANCE
```

Switch Multilayer 2:

```
inter vlan 40
ip address 192.168.40.2 255.255.255.0
no shutdown
ex
```

```
inter vlan 50
ip address 192.168.50.2 255.255.255.0
no shutdown
ex
```

```
inter vlan 60
ip address 192.168.60.2 255.255.255.0
no shutdown
ex
```

```
inter vlan 40
standby 40 ip 192.168.40.1
standby 40 priority 210
standby preempt
```

```
inter vlan 50
standby 50 ip 192.168.50.1
standby 50 priority 210
standby preempt
```

```
inter vlan 60
standby 60 ip 192.168.60.1
standby 60 priority 210
standby preempt
```

```
inter g0/1
no switchport
ip address 10.10.2.2 255.255.255.252
no shut
```

```
ip routing
```

```
router ospf 1
network 10.10.2.0 0.0.0.3 area 0
network 10.10.2.4 0.0.0.3 area 0
network 192.168.40.0 0.0.0.255 area 0
network 192.168.50.0 0.0.0.255 area 0
network 192.168.60.0 0.0.0.255 area 0
passive-interface vlan 40
passive-interface vlan 50
passive-interface vlan 60
```

Switch Multilayer 3:

```
inter vlan 40
ip address 192.168.40.3 255.255.255.0
no shutdown
ex
```

```
inter vlan 50
ip address 192.168.50.3 255.255.255.0
no shutdown
ex
```

```
inter vlan 60
ip address 192.168.60.3 255.255.255.0
no shutdown
ex
```

```
inter vlan 40
standby 40 ip 192.168.40.1
standby 40 priority 200
```

```
standby preempt
```

```
inter vlan 50  
standby 50 ip 192.168.50.1  
standby 50 priority 200  
standby preempt
```

```
inter vlan 60  
standby 60 ip 192.168.60.1  
standby 60 priority 200  
standby preempt
```

```
inter g0/1  
no switchport  
ip address 10.10.2.6 255.255.255.252  
no shut
```

```
ip routing
```

```
router ospf 1  
network 10.10.2.0 0.0.0.3 area 0  
network 10.10.2.4 0.0.0.3 area 0  
network 192.168.40.0 0.0.0.255 area 0  
network 192.168.50.0 0.0.0.255 area 0  
network 192.168.60.0 0.0.0.255 area 0  
passive-interface vlan 40  
passive-interface vlan 50  
passive-interface vlan 60
```

Configuração swicths de camada 2:

Swicth 3,4,5

```
configure terminal  
interface range fa0/1-2  
switchport mode trunk  
switchport trunk allowed vlan 40,50,60
```

Swicth 3:
configure terminal
vlan 40
name HR

Swicth 4:
configure terminal
vlan 50
name SALES

Swicth 5:
configure terminal
vlan 60
name FINANCE

Router:

interface g0/1
ip address 10.10.2.1 255.255.255.252
no shut

interface g0/0
ip address 10.10.2.5 255.255.255.252
no shut

interface s0/0/0
ip address 10.10.10.2 255.255.255.252
no shut

router ospf 1
network 10.10.2.0 0.0.0.3 area 0
network 10.10.2.4 0.0.0.3 area 0
network 10.10.10.0 0.0.0.3 area 0