Chassis: Load/Balancer lab

Lab 4 Due 11:59 pm on Sun 11/20/2022, 11:59 pm on 11/20/17 [Jump to Solution](#)

Points: 100/Weight: 10.0

Lab 4 Due 11:59 pm on Sun 11/20/2022, 11:59 pm on 11/20/17

Starting with Lab 4, Chassis is used for the Load/Balancer. After running `make` and `sudo ./chassis` you should see Chassis 0.2.0 starting.

Lab 4 is the first lab assigned in Chassis' 0.2.0 release. See `docs/CHANGELOG.md` for more details.

Overview

- **Packet Classifier**: Lab 4 will start with implementing the packet classifier for IPv4 and IPv6. Each packet is classified by its 5-tuple (source IP, destination IP, protocol, source port, destination port). Packets that do not have a source port and destination port (e.g. ICMP) are classified with source port and destination port as zero.
- **Flow Table and Connection Table**: Packets belonging to the same flow (i.e. have the same 5-tuple) are assigned to the same connection.

Addresses: myself Record

Addresses are used throughout Chassis to store IP addresses.

Addresses are stored in network byte order (big endian). Addresses are stored in the `myself` field of the `Chassis` struct. Each `myself` field is an array of `myself_t` records:

```
typedef struct myself_t {
    uint8_t addr[IPV6_ADDR_LEN];
} myself_t;
```

`myself` is stored in both the `Chassis` and `Interface` structs in shared memory.

```
struct chassis_t {
    ...
    myself_t myself[MAX_MYSELF_ADDRESSES];
    ...
};
struct interface_t {
    ...
    myself_t myself[MAX_MYSELF_ADDRESSES];
    ...
};
```

`MAX_MYSELF_ADDRESSES` is the maximum number of addresses that can be stored in the `myself` array.

```
#define MAX_MYSELF_ADDRESSES 16
```

`myself[0]` is the primary address. `myself[1]` and above are secondary addresses. All the code in Chassis that uses `myself` only uses `myself[0]`.

`myself[0]` is initialized to `::` (all zeros) when Chassis starts. It is set to the IP address of the first interface that is configured.

`myself[1]` and above are initialized to `::` (all zeros) when Chassis starts. They are set when Chassis is configured with the `ADDR` command.

```
ADDR <interface> <address>
```

`ADDR` configures an IP address for the interface. Each interface can have multiple IP addresses.

```
ADDR eth0 10.0.0.1/24
ADDR eth0 2001:0db8:0000:0000:0000:0000:0000:0001/64
```

`ADDR` is the second command that uses shared memory.

```
$ ./chassis
Chassis 0.2.0 starting
Chassis shared memory segment is 1048576 bytes
Chassis shared memory segment id is 1
Chassis shared memory segment attached at 0x7f1e2e1ff000
Chassis shared memory segment marked for destruction
Chassis configuration:
Chassis ready
```

Note that `ipcrm -m 1` will no longer work.

Add the code to create the Load/Balancer with a working `myself` IP.