



This site ▾



[Home](#)

[About us](#)

[Products](#)

[Download](#)

[FAQ](#)

[Contact us](#)

[Technical articles](#)

[Online store](#)

[Tue Nov 4, 2025](#)

Products List

[Products](#) >> [Sensors](#) >> [Cylinder proximity sensors](#) >> [LJ8A3-2](#)

[Back](#)

◀ [LJ8A3-1 series cylinder inductive proximity sensor](#)

[LJ12A3-2 series cylinder inductive proximity sensor](#) ▶

LJ8A3-2 series cylinder inductive proximity sensors - M8 and 2m detection distance

■ Operating form and model number

Current type	Operating form	Contact form	Connection form	Model number	Remark	Online store:	This site ▾
DC	NPN	NO	Wire lead	LJ8A3-2-Z/BX	6-36Vdc	US \$2 / piece	Order
DC	NPN	NO	Wire lead	LJ8A3-2-Z/BX-5V	5Vdc	US \$2.3 / piece	Order
DC	NPN	NO	Wire lead	LJ8A3-2-Z/BX-5V-4	5Vdc, 4m cable	US \$2.83 / piece	Order
DC	NPN	NC	Wire lead	LJ8A3-2-Z/AX	6-36Vdc	US \$2 / piece	Order
DC	NPN	NC	Wire lead	LJ8A3-2-Z/AX-5V	5Vdc	US \$2.5 / piece	Order
DC	PNP	NO	Wire lead	LJ8A3-2-Z/BY	6-36Vdc	US \$2 / piece	Order
DC	PNP	NC	Wire lead	LJ8A3-2-Z/AY	6-36Vdc	US \$2.14 / piece	Order
DC	Two wires	NO	Wire lead	LJ8A3-2-Z/EX	6-36Vdc	US \$2.17 / piece	Order
DC	Two wires	NC	Wire lead	LJ8A3-2-Z/DX	6-36Vdc	US \$2.17 / piece	Order
AC	Two wires	NO	Wire lead	LJ8A3-2-J/EZ	90-250Vac	US \$2.17 / piece	Order
AC	Two wires	NC	Wire lead	LJ8A3-2-J/DZ	90-250Vac	US \$2.17 / piece	Order

■ General

Model number	LJ8A3-2 series
External dimensions	M8x50
Installation type	Non-shielded
Detection distance	2mm
Setting distance	0-1.6 mm
Supply voltage	6-36Vdc, 5Vdc; 90-250Vac, 50/60Hz
Output current	DC type: 300mA max; AC Type: 400mA
Standard detected object	Mild steel (8x8x1mm)
Sensing object	Magnetic metals (if it is not magnetic metals, the sensing distance would decrease)
Response frequency	500Hz
Matched mounting bracket	M8 mounting bracket
Output indication	Red LED
Short-circuit protection	No
Reverse connection protection	Yes
Insulation resistance	50MΩ min (between charging part and housing)
Dielectric strength	1000Vac, 1min (between charging part and housing)
IP Rating	IP65
Operating temperature	-25 to 70 °C (13 to 158 °F)
Cable length	1.2m, PVC cable
Material	Case: Brass-nickel plated; Sensing surface: ABS
Alias name	LJ8A3-2 series cylinder inductive proximity switches



Mouse over to zoom in



[LJ8A3-2-Z/BX M8 2mm sensing DC 6-36V NPN NO cylinder inductive proximity switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-Z/BX-5V M8 2mm sensing DC 5V NPN NO cylinder inductive proximity switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-Z/AX M8 2mm sensing DC 6-36V NPN NC cylinder inductive proximity switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-Z/AX-5V M8 2mm sensing DC 5V NPN NC cylinder inductive proximity switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-Z/BY M8 2mm sensing DC 6-36V PNP NO cylinder inductive proximity switch sensor](#)



[Instruments](#)

[Relays](#)

[Switches](#)

[Sensors](#)

[Cylinder proximity sensors](#)

[LJ6A3-1](#)

[LJ6A3-2](#)

[LJ8A3-1](#)

[LJ8A3-2](#)

[LJ12A3-2](#)

[LJ12A3-4](#)

[LJ18A3-5](#)

[LJ18A3-8](#)

[LJ30A3-10](#)

[LJ30A3-15](#)

[Full screw proximity sensors](#)

[General proximity sensors](#)

[Panel mounting inductive pro...](#)

[Limit position proximity sensors](#)

[Trough shape proximity sensors](#)

[Signal output proximity sensors](#)

[Full view proximity sensors](#)

[Prism shape proximity sensors](#)

[Flat shape proximity sensors](#)

[Capacitive proximity sensors](#)

[Magnetic proximity sensors](#)

[Cylinder amplifier photoelectri...](#)

[Prism relay photoelectric sens...](#)

[Prism amplifier photoelectric s...](#)

[Color sensors](#)

[Sensor connectors](#)

[Photoelectric sensor reflectors](#)

[Sensor mounting brackets](#)

[Contactors](#)

[Drivers](#)

[Switching power supplies](#)

[Industrial plugs and sockets](#)

[Axial flow fans](#)

[Fasteners](#)

[Fuses](#)

[Transformers](#)

[Terminals](#)

[Tools](#)

Mouse over to zoom in



[LJ8A3-2-Z/AY M8 2mm](#)
[sensing DC 6-36V PNP](#)
[NC cylinder inductive](#)
[proximity switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-Z/EX M8 2mm](#)
[sensing DC 6-36V 2](#)
[wires NO cylinder](#)
[inductive proximity](#)
[switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-Z/DX M8 2mm](#)
[sensing DC 6-36V 2](#)
[wires NC cylinder](#)
[inductive proximity](#)
[switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-J/EZ M8 2mm](#)
[sensing AC 90-250V 2](#)
[wires NO cylinder](#)
[inductive proximity](#)
[switch sensor](#)



Mouse over to zoom in



[LJ8A3-2-J/DZ M8 2mm](#)
[sensing AC 90-250V 2](#)
[wires NC cylinder](#)
[inductive proximity](#)
[switch sensor](#)

◀ [LJ8A3-1 series cylinder inductive proximity sensor](#)

[LJ12A3-2 series cylinder inductive proximity sensor](#) ▶