Plasma Battery Pack - User Manual

Official Technical Specification, Operating Instructions & Support Policy

Category:	Electronics	**Retail Price:**	$45.99
Model Number:	PBP-25K-65W	**Warranty Term:**	1 Month Limited

1. Product Overview & Technical Specifications

The Plasma Battery Pack is a high-density, ultra-durable 25,000mAh external power station built for power users, field technicians, and demanding multi-device workflows. Constructed with solid-state plasma-ion pouch cells and encased in an anodized flame-retardant aluminum alloy housing, it provides industry-leading thermal stability and resilience against thermal runaway. The battery pack boasts 65W bidirectional Power Delivery 3.0 via its primary USB-C port, supplemented by a secondary 30W USB-C port and an 18W USB-A QuickCharge output. An integrated monochromatic OLED display provides real-time readouts of remaining capacity percentage, operational output wattage, incoming charging voltage, and estimated time to full discharge under current load conditions.

2. Setup & Operating Instructions

To operate the Plasma Battery Pack efficiently, begin by fully charging the pack using a certified 65W USB-PD wall adapter. Plug the charger into the primary 'USB-C1 In/Out' port; the OLED display will illuminate showing input wattage and an incrementing percentage indicator until reaching 100%. To charge mobile workstations, tablets, or phones, simply connect your device's high-wattage charging cable to USB-C1 or USB-C2. The internal intelligent power-negotiation chip automatically identifies the connected device and supplies optimal voltage. For low-current peripherals like wireless earbuds or smart bands, double-tap the side control button to engage 'Trickle Charge Mode', preventing the power bank from auto-shutting off during trickle cycles. Single-click the power button at any time to inspect remaining cell capacity.

3. Troubleshooting & Diagnostics Guide

In case of unexpected power behavior, follow these diagnostic procedures. Issue 1: Battery pack does not accept incoming charge or remains at 0%. Resolution: Inspect the USB-C cable for bent pins, verify the wall adapter delivers at least 15W of USB-PD power, and perform a master controller reset by holding the side power button down for 12 seconds. Issue 2: Output wattage is lower than device manufacturer rating. Resolution: Confirm you are plugged into the primary USB-C1 port and that your charging cable is rated for 5A/100W throughput. Issue 3: The OLED screen displays an 'OVERTEMP' error icon. Resolution: Immediately disconnect all connected devices, place the unit on a cool flat surface out of direct sunlight, and wait 20 minutes for temperatures to normalize.

4. Warranty Terms & Customer Support Information

Warranty Summary: 1 Month (30 Days) Limited Manufacturer Protection

The Plasma Battery Pack is warranted against manufacturing flaws, internal cell degradation exceeding 20% capacity drop, and short-circuit protection board failures for a period of 1 month (30 calendar days) from retail delivery. The 1-month warranty does not cover damages incurred through deep water submersion, structural crushing, disassembly of the aluminum casing, exposure to open flame, or use of substandard third-party chargers. For warranty service within the 1-month period, contact our technical support division at support@agentichelpdesk.com with your original receipt and proof of device failure. Approved RMA requests qualify for direct replacement with an identical or superior capacity unit. For technical.