

E-008 TERMINAL STRIP (X1) + WIRE LIST

Conv_Simple / CV-101 (garage conveyor) — Generated wire list — every conductor across E-003..E-007 (this sheet carries no wires of its own)

WIRE LIST (all sheets, generated)

Wire	From	To	Signal	Sheet	Status
W300	SUPPLY (source — see E-002)	CB1.1	L1 230V 1ph supply	E-003	field_verify
W301	SUPPLY (source — see E-002)	CB1.3	L2 230V 1ph supply	E-003	field_verify
W303	CB1.2	Q1.13	L1 protected -> MLC	E-003	field_verify
W304	CB1.4	Q1.43	L2 protected -> MLC	E-003	field_verify
W305	Q1.14	VFD1.R/L1	L1 switched -> drive	E-003	field_verify
W306	Q1.44	VFD1.S/L2	L2 switched -> drive	E-003	field_verify
W310	VFD1.U/T1	M1.T1	motor phase U	E-003	field_verify
W311	VFD1.V/T2	M1.T2	motor phase V	E-003	field_verify
W312	VFD1.W/T3	M1.T3	motor phase W	E-003	field_verify
W315	VFD1.GND	PE bus	drive PE (≤0.1Ω)	E-003	field_verify
W316	M1.PE	PE bus	motor frame PE	E-003	field_verify
W317	PE bus	SUPPLY (source — see E-002)	PE to source	E-003	field_verify
W400	230 V 1φ (E-002)	PS1.L	AC line in	E-004	field_verify
W401	230 V 1φ (E-002)	PS1.N	AC neutral in	E-004	field_verify
W402	PS1.+V	DB1.+24V-bus	+24 VDC distribution feed	E-004	field_verify
W403	PS1.-V	DB1.0V-bus	0V distribution return	E-004	field_verify
W404	DB1.+24V-bus	control loads (E-005/E-006)	+24V to E-005/E-006 loads	E-004	field_verify
W405	DB1.0V-bus	control loads (E-005/E-006)	0V to E-005/E-006 loads	E-004	field_verify
W0V	PLC1.COM0	PS1.0V	0V / input common	E-005	field_verify
W24	PS1.+24V	+24V rail (this sheet)	+24 VDC	E-005	field_verify
W500	SS1.FWD	PLC1.I-00	dir_fwd	E-005	field_verify
W501	SS1.REV	PLC1.I-01	dir_rev	E-005	field_verify
W502	S0.11-12	PLC1.I-02	e_stop_nc (healthy=1)	E-005	field_verify
W503	S0.23-24	PLC1.I-03	e_stop_no (healthy=0)	E-005	field_verify
W504	S2.3-4	PLC1.I-04	run_pb	E-005	field_verify
W505	B1.BK	PLC1.I-05	photo_eye	E-005	field_verify
W600	PS1.+24V	PLC1.+CM0	output bank 0 feed	E-006	field_verify
W601	PLC1.O-00	PL1.X1	LightGreen (run light)	E-006	field_verify
W602	PLC1.O-01	PL2.X1	LightRed (fault/e-stop light)	E-006	field_verify
W603	PLC1.O-02	Q1.A1	ContactorQ1 coil (safety power)	E-006	field_verify
W604	PLC1.O-03	S2.X1	PBRunLED (run button lamp)	E-006	field_verify
W605	PL1.X2	output return rail (E-006)	run light return	E-006	field_verify
W606	PL2.X2	output return rail (E-006)	fault light return	E-006	field_verify
W607	Q1.A2	output return rail (E-006)	contactor coil return	E-006	field_verify
W608	S2.X2	output return rail (E-006)	PB lamp return	E-006	field_verify
W609	PLC1.-CM0	PS1.0V	output bank 0 return	E-006	field_verify
485+	PLC1.D+ (A)	VFD1.RJ45 pin 5 / SG+	RS-485 inverting (D+ = SG+)	E-007	verified
485-	PLC1.D- (B)	VFD1.RJ45 pin 4 / SG-	RS-485 non-inverting (D- = SG-)	E-007	verified
SGND	PLC1.SG	VFD1.RJ45 pin 3 / SGND	signal ground / common reference	E-007	verified
SH	PLC1.shield / chassis	VFD1.(floated)	cable shield	E-007	field_verify

NOTES

- X1 (field terminal strip, devices.yaml) is where field devices land before the PLC. Its physical terminal-strip layout and numbering are NOT documented in any recovered source — FIELD VERIFY. This table lists the conductors on each side of it, indexed by their owning sheet — it is not X1's internal terminal map.
- Rows are sorted by sheet, then wire number/label. VERIFIED (black) vs FIELD VERIFY (red) mirrors each conductor's status on its owning sheet — see that sheet for the drawn circuit and evidence.

SOURCES:

model/wires.yaml · model/e007_rs485.yaml (generated — do not hand-edit this table; re-run emit after any model change)

LEGEND

- VERIFIED (solid)
- FIELD VERIFY (dashed)
- Wxxx

proposed wire number (red = unverified)

TERMINAL STRIP (X1) + WIRE LIST

Conv_Simple / CV-101 (garage conveyor)

Drawn: MIRA / FactoryLM

SHEET

E-008

REV A

2026-07-11

8 of 9