

DURAPULSE GS10 AC Drive — Fault Codes (excerpt)

Section 6.2 Fault and Warning Codes

oC Overcurrent

The drive output current exceeded 200% of the rated current.

Common causes: short acceleration time, shorted output / motor winding, mechanical jam on the driven load, or a ground fault.

Action: increase the acceleration time (P0.10), check the motor leads and load for shorts/jams, then reset the fault.

oC1 Overcurrent during acceleration

oC2 Overcurrent during deceleration

oC3 Overcurrent at constant speed

oL Drive overload (150% for 60 s).

oH1 Heat-sink over-temperature.

GFF Ground fault detected at the drive output.

MIRA beta-gate TEST FIXTURE — synthetic excerpt, not a licensed manual.