

# NEXEDGE

One Radio with Multi-Protocol Support





















VHF/UHF/700-800 MHz TRANSCEIVERS

NX-5200/5300/5400



#### FEATURE HIGHLIGHTS

- Multi-Digital operation in NXDN, DMR, and P25 (Phase 1 & 2) protocols
- · Any combination of two digital protocols can be selected from NXDN. DMR. and P25
- Mixed Digital & FM Analog Operation allows intelligent migration in mixed sites and easy migration with digital radios in other sites
- · Large, Color 1.74" (240 x 180 pixels) Transflective TFT Display for better interface even in direct sunlight and with use of polarized sunglasses
- Easy to follow GUI for at-a-glance operational status checking and Multi-line Text to convey more information
- · 4-way Directional-pad (D-pad) and 2-Position Lever Switch for intuitive control and operation
- · Built-In GPS Receiver/Antenna for effective fleet management
- Bluetooth® Module built-in for hands-free operation
- Renowned KENWOOD Audio Quality can be achieved with Active Noise Reduction (ANR) that utilizes built-in DSP with two microphones for suppression of ambient
- · Built-in 56-bit DES Encryption
- Optional 256-bit AES Encryption
- · Built-in Motion Sensor for life-critical man down detection
- microSD/SDHC (up to 2GB/32GB) Memory Card Slot
- IP67/68 and MIL-STD-810 C/D/E/F/G



- 6 W (136-174 MHz) Models
- 5 W (380-470, 450-520 MHz) Models
- 3 W (700/800 MHz) Models
- Full Key Models (w/ numeric keypad) and Standard Key Models (w/o numeric keypad)
- · Maximum of 4,000 CH/Radio capacity, 512 CH/Zone, 128 Zones
- AMBE+2™ Enhanced Vocoder
- 1 W Loud Speaker Audio

### DIGITAL – NXDN MODE

- Gen2 & NXDN Type-C Trunked Operation
- NXDN Conventional Operation
- 6.25 & 12.5 kHz Channels
- Over-the-Air Alias
- Over-the-Air Programming
- Paging Call
- Emergency Call
- All Group Call
- Status Messaging
- Remote Stun/Kill
- Remote Check
- Short & Long Data Messages
- NXDN Digital Scrambler

# DIGITAL – DMR MODE

- S-Trunking
- DMR Tier III Trunking
- · DMR Tier II Conventional
- DMR Auto Slot Select
- Site Roaming
- Two-slot TDMA in 12.5kHz channels
- Call Interruption
- Dual-slot Direct Mode
- · Energy Efficient

### DIGITAL – P25 MODE

- P25 Phase 1 Conventional/Trunked Operation
- P25 Phase 2 Trunked Operation
- · Talk Group ID Lists
- Individual ID Lists
- Caller ID Display
- · Remote Monitor/Remote Check
- · Radio Inhibit
- · Encryption Key Zeroize & Retention
- P25 Over-the-Air Re-keving
- · P25 Over-the-Air Programming

# FM MODES – GENERAL

- Conventional & LTR Zones
- NPSPAC (USA only) Channels (±4.0 Modulation)
- FleetSync®/II: PTT ID ANI / Caller ID Display, Selective Group Call, Emergency Status / Text Messages
- MDC-1200: PTT ID ANI / Caller ID Display, Emergency, Radio Check / Inhibit
- QT / DQT & Two-Tone
- Built-in Voice Inversion Scrambler

# INTELLIGENT BATTERY SYSTEM

- · System consists of a Li-ion or Ni-MH rechargeable
- (KNB-L1/L2/L3/N4), Rapid Charger (KSC-Y32), and Battery Reader (KAS-12/12PRO) software
- · Up to 60 Rapid Chargers can be chain-connected to a PC
- · KAS-12 Battery Reader software can display and manage information
- Up to 5,000 batteries can be managed at a time with the addition of optional KAS-12PRO license upgrade











# OPTIONAL ACCESSORIES



All accessories and options may not be available in all markets. Contact an authorized KENWOOD dealer for details and complete list of all accessories and options.

## SPECIFICATIONS

| GENERAL                              |                              | NX-5200  | NX-5300                                    | NX-5400   |  |  |  |
|--------------------------------------|------------------------------|--|--|---|--|--|--|
| Frequency Range                      |                              | 136-174 MHz                                      | Type 1: 450-520 MHz<br>Type 2: 380-470 MHz | RX: 763-776, 851-870 MHz<br>TX: 763-776, 793-806,<br>806-825, 851-870 MHz |  |  |  |
| Max. Channels Per Radio              |                              | 1024 (Up to 4000 channels with option)           |  |   |  |  |  |
| Number of Zones                      |                              | 128  |  |   |  |  |  |
| Max. Channels Per Zone               |                              | 512  |  |   |  |  |  |
| Channel Spacing                      | Analog                       | 12.5 / 15 / 20 / 25*1 / 30*1 kHz 12.5 / 25*1 kHz |  | 12.5 / 25 kHz   |  |  |  |
|                                      | Digital                      | 6.25 / 12.5 kHz                                  | 6.25 / 12.5 kHz                            | 12.5 kHz (6.25 kHz)   |  |  |  |
| Power Supply                         |                              | 7.5 V DC ±20 %                                   |  |   |  |  |  |
| Battery Life<br>(5-5-90/10-10-80     | KNB-L1<br>(2,000 mAh)        | 10 hours / 6.5 hours                             |  |   |  |  |  |
|                                      | KNB-L2<br>(2,600 mAh)        | 12.5 hours / 8.5 hours                           |  |   |  |  |  |
|                                      | KNB-L3<br>(3,400 mAh)        | 17 hours / 11 hours                              |  |   |  |  |  |
| duty cycle)                          | KNB-N4<br>(2,500 mAh)        | 12 hours / 8.5 hours                             |  |   |  |  |  |
|                                      | KBP-8                        | High Power: 11 hours / 8 hours                   |  |   |  |  |  |
|                                      | (w/ AA x12)                  | Low Power: 26 hours / 18.5 hours                 |  |   |  |  |  |
| Operating Temperature (Radio only)*2 |                              | -22 °F to +140 °F (-30 °C to +60 °C)             |  |   |  |  |  |
| Frequency Stability                  | (-30°C to +60°C; +25°C Ref.) | ±0.5 ppm   |  |   |  |  |  |
| Dimensions<br>(W x H x D)            | KNB-L1<br>(2,000 mAh)        | 2.28 x 5.47 x 1.44 in (58.0 x 138.9 x 36.5 mm)   |  |   |  |  |  |
|                                      | KNB-L2<br>(2,600 mAh)        | 2.28 x 5.47 x 1.56 in (58.0 x 138.9 x 39.5 mm)   |  |   |  |  |  |
| Radio w/ Battery,<br>Projections Not | KNB-L3<br>(3,400 mAh)        | 2.28 x 5.47 x 1.77 in (58.0 x 138.9 x 44.9 mm)   |  |   |  |  |  |
| Included                             | KNB-N4<br>(2,500 mAh)        | 2.28 x 6.55 x 1.78 in (58.0 x 166.4 x 45.2 mm)   |  |   |  |  |  |
|                                      | KBP-8<br>(w/ AA x 12)        | 2.64 x 8.59 x 2.12 in (67.0 x 218.3 x 53.9 mm)   |  |   |  |  |  |
|                                      | KNB-L1<br>(2,000 mAh)        | 13.5 oz (382 g)                                  |  |   |  |  |  |
|                                      | KNB-L2<br>(2,600 mAh)        | 14.3 oz (406 g)                                  |  |   |  |  |  |
| Weight                               | KNB-L3<br>(3,400 mAh)        | 15.8 oz (449 g)                                  |  |   |  |  |  |
|                                      | KNB-N4<br>(2,500 mAh)        | 20.4 oz (579 g)                                  |  |   |  |  |  |
|                                      | KBP-8<br>(w/ AA x 12)        | 25.1 oz (712 g)                                  |  |   |  |  |  |
| ECC ID                               | Type 1                       | K44431400  | K44431500                                  | ALH442000   |  |  |  |
| FUU ID                               | Type 2                       | -  | K44431501                                  | _   |  |  |  |
| IC Certification                     | Type 1                       | 282F-431400                                      | -  | 282D-442000   |  |  |  |
|                                      | Type 2                       | _  | 282F-431501                                | _   |  |  |  |

| RECEIVER            |                                    | NX-5200  | NX-5300  | NX-5400  |  |  |  |
|---------------------|------------------------------------|--|--|----------|--|--|--|
| Sensitivity         | NXDN 6.25 kHz<br>Digital (3 % BER) | 0.20 μV  |  |          |  |  |  |
|                     | NXDN 12.5 kHz<br>Digital (3 % BER) | 0.25 μV  |  |          |  |  |  |
|                     | DMR Digital<br>(5 % BER)           | 0.25 μV  |  |          |  |  |  |
|                     | DMR Digital<br>(1 % BER)           | 0.40 μV  |  |          |  |  |  |
|                     | P25 Digital<br>(5 % BER)           | 0.25 μV  |  |          |  |  |  |
|                     | P25 Digital<br>(1 % BER)           | 0.40 µV  |  |          |  |  |  |
|                     | Analog<br>(12 dB SINAD)            | 0.25 μV  |  |          |  |  |  |
| Selectivity         | Analog @ 12.5 kHz                  | 67   | 64 dB  |          |  |  |  |
| Selectivity         | Analog @ 25 kHz                    | 73 dB  |  |          |  |  |  |
| Intermodulation     |                                    | 73 dB 75 dB  |  |          |  |  |  |
| Spurious Rejection  |                                    | 80 dB 75 dB  |  |          |  |  |  |
| Audio Distortion    |                                    | 3 %  |  |          |  |  |  |
| Audio Output Power  |                                    | 500 mW (3 % Distortion)/1,000 mW (5 % Distortion)                        |  |          |  |  |  |
| TRANSMITTER         |                                    | NX-5200  | NX-5300  | NX-5400  |  |  |  |
| RF Power Output Po  | ower                               | 6 to 1 W   | 5 to 1 W   | 3 to 1 W |  |  |  |
| Spurious Emission   |                                    | -70 dB   |  |          |  |  |  |
| FM Hum & Noise      | Analog @ 12.5 kHz                  | 40 dB  |  |          |  |  |  |
| rivi rium & Noise   | Analog @ 25 kHz                    | 45 dB  |  |          |  |  |  |
| Audio Distortion    |                                    | 2 %  |  |          |  |  |  |
| Emission Designator |                                    | 16K0F3E, 11K0F3E,<br>8K10F1W, 8K30F1E,<br>7K60FXE, 7K60FXD, 4K00<br>4K00 | 16K0F3E, 14K0F3E,<br>11K0F3E, 8K10F1E,<br>8K10F1D, 8K10F1W,<br>8K30F1E, 8K30F1D,<br>8K30F7W, 7K60FXE,<br>7K60FXD, 4K00F1E,<br>4K00F1D, 4K00F7W,<br>4K00F2D |          |  |  |  |

- \*1 25 and 30 kHz are not included in the models sold in the USA or US territories.
  \*2 Operating temperature specification for a Li-ion battery is 14°F to +140°F (-10°C to +60°C).
- P25 Digital measurements made per TIA 102CAAA, analog measurements made per EN Standards or TIA 603 and Specifications are subject change without notice, due to advancements in technology.

### APPLICABLE MIL-STD & IP\*3

| MIL Standards                      | 810C Methods/ Procedures | 810D Methods/ Procedures | 810E Methods/ Procedures | 810F Methods/ Procedures | 810G Methods/ Procedures |  |  |
|------------------------------------|--------------------------|--------------------------|--------------------------|--------------------------|--------------------------|--|--|
| Low Pressure                       | 500.1/ I                 | 500.2/ I, II             | 500.3/ I, II             | 500.4/ I, II             | 500.5/ I, II             |  |  |
| High Temperature                   | 501.1/ I, II             | 501.2/ I, II             | 501.3/ I, II             | 501.4/ I, II             | 501.5/ I, II             |  |  |
| Low Temperature                    | 502.1/ I                 | 502.2/ I, II             | 502.3/ I, II             | 502.4/ I, II             | 502.5/ I, II             |  |  |
| Temp. Shock                        | 503.1/ I                 | 503.2/1                  | 503.3/ I                 | 503.4/ I, II             | 503.5/ I                 |  |  |
| Solar Radiation                    | 505.1/ I                 | 505.2/1                  | 505.3/ I                 | 505.4/ I                 | 505.5/ I                 |  |  |
| Rain                               | 506.1/ I, II             | 506.2/ I, II             | 506.3/ I, II             | 506.4/ I, III            | 506.5/ I, III            |  |  |
| Humidity                           | 507.1/ I, II             | 507.2/ II, III           | 507.3/ II, III           | 507.4                    | 507.5/ II                |  |  |
| Salt Fog                           | 509.1/ I                 | 509.2/1                  | 509.3/ I                 | 509.4                    | 509.5                    |  |  |
| Dust                               | 510.1/ I                 | 510.2/ I                 | 510.3/ I                 | 510.4/ I, III            | 510.5/ I                 |  |  |
| Vibration                          | 514.2/ VIII, X           | 514.3/ I                 | 514.4/ I                 | 514.5/ I                 | 514.6/ I                 |  |  |
| Shock                              | 516.2/ I, II, V          | 516.3/ I, IV             | 516.4/ I, IV             | 516.5/ I, IV             | 516.6/ I, IV             |  |  |
| Immersion                          | _                        | _                        | _                        | 512.4/I                  | 512.5/I                  |  |  |
| International Protection Standards |                          |                          |                          |                          |                          |  |  |
| Dust & Water                       | IP54, IP55               |                          |                          |                          |                          |  |  |
| Immersion                          | IP67, IP68               |                          |                          |                          |                          |  |  |

- \*3 All interfaces must be fully sealed with appropriate covers or by designated genuine accessories.
- The Bluetooth word mark and logos are registered trademarks owned by the Bluetooth SIG, Inc. SD and microSD are trademarks of SD-3C, LLC in the United States, and/or other countries AMBE+2™ is a trademark of Digital Voice Systems Inc.
   Windows® is a registered trademark of Microsoft Corporation. NXDN™ is a trademark of JVCKENWOOD Corporation and Icom Inc. NEXEDGE® is a registered trademark of JVCKENWOOD Corporation. FleetSync® is a registered trademark of JVCKENWOOD Corporation.
- JVCKENWOOD Corporation.





