## Procedure 1: Inverter fault inspection

Record the inverter model and displayed alarm code before troubleshooting. Consult the manufacturer's service instructions and site isolation procedure. Only qualified personnel may inspect an enclosure; isolate all required sources and verify the safe state before access. Never work on exposed energized conductors.

Safety note: Manufacturer instructions and approved site procedures take precedence.

## Procedure 2: Photovoltaic module cleaning

Plan cleaning for cool modules and follow the module manufacturer's instructions and the site's electrical isolation procedure. Use clean water and a soft, non-abrasive brush or cloth to remove loose dirt. Do not use abrasive cleaners or high-pressure jets. Avoid stepping on modules, and stop if cables or glass appear damaged; report defects to the site supervisor.

Safety note: Manufacturer instructions and approved site procedures take precedence.

## Procedure 3: Thermal anomaly survey

Use a suitable infrared camera from a safe, approved position and follow the site's electrical safety rules. Record the inspection time, weather, irradiance and operating conditions. Compare suspect modules with nearby modules under similar conditions, photograph anomalies, and report findings for qualified review. Do not touch or open electrical equipment during the survey.

Safety note: Manufacturer instructions and approved site procedures take precedence.