

AI Engineering Summer Training

Daily Task Submission

Topic: Fix 3 bugs (Week 2 - Day 4)

Submitted by: [Molham waleed]

Student ID: [2338908]

Supervisor: Eng. Abdullah Barghash

Date: July 15, 2026

Bug 1: Invalid Model Name Call

Symptom : The application runs, but clicking "Generate Assessment" instantly returns an Ollama Model Error in the UI, and no questions are generated.

Diagnosis : The AI assistant analyzed the error traceback and identified that the API call requested 'llama-3', which does not exist in the local Ollama registry. The correct tag format is required to establish a connection.

Fix : Corrected the model parameter in the API call back to the exact local tag: `model='llama3'`.

Bug 2: Malformed JSON Prompt Injection

Symptom : The app successfully connects to Llama 3, but always returns the fallback UI error: ✖ Error: Llama3 did not return valid JSON.

Diagnosis : The AI assistant reviewed the prompt instructions and found a syntax error in the requested JSON structure. The prompt asked for "correct_answer": Option A without string quotes. The LLM followed this flawed instruction, generating invalid JSON that the `json.loads()` function could not parse.

Fix : Added the missing quotes in the prompt template to enforce valid JSON generation: "correct_answer": "Option A".

Bug 3: Gradio Component Output Mismatch

Symptom : Clicking the generate button crashes the application internally. The terminal shows a `ValueError` stating that the number of returned elements from the function does not match the expected outputs in Gradio.

Diagnosis : The AI assistant compared the function's return statement with the Gradio button mapping. It diagnosed that the hidden `gr.State()` components (used for storing correct answers) were missing from the output array, breaking the UI state management.

Fix : Re-added the missing line `gen_outputs.append(state_components[i])` to the output configuration loop to sync the backend data with the frontend layout.