

Exp No: 10

PIR SENSOR IN PROTEUS USING ARDUINO

AIM:

To write an Embedded C program for interfacing PIR Sensor using Arduino Uno and Proteus

PROGRAM:

```
int Status = 13; // Digital pin D6

int sensor = 12; // Digital pin D7

void setup() {

  Serial.begin(9600);

  pinMode(sensor, INPUT); // declare sensor as input

  pinMode(Status, OUTPUT); // declare LED as output

}

void loop() {

  long state = digitalRead(sensor);

  Serial.println(state) ;

  if(state == HIGH) {

    digitalWrite (Status, HIGH);

    Serial.println("Motion detected!");

    delay(1000);

  }

  else {

    digitalWrite (Status, LOW);

    Serial.println("Motion absent!");

    delay(1000);

  }

}
```

