# What to Expect in this Module

- To facilitate learning, the following features within the GUI may be included in this module:

| Feature | Description |
|---|---|
| Animations | Expose learners to new skills and concepts. |
| Videos | Expose learners to new skills and concepts. |
| Check Your Understanding(CYU) | Per topic online quiz to help learners gauge content understanding. |
| Interactive Activities | A variety of formats to help learners gauge content understanding. |
| Syntax Checker | Small simulations that expose learners to Cisco command line to practice configuration skills. |
| PT Activity | Simulation and modeling activities designed to explore, acquire, reinforce, and expand skills. |


© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# What to Expect in this Module (Cont.)

- To facilitate learning, the following features may be included in this module:

| Feature | Description |
|---|---|
| Hands-On Labs | Labs designed for working with physical equipment. |
| Class Activities | These are found on the Instructor Resources page. Class Activities are designed to facilitate learning, class discussion, and collaboration. |
| Module Quizzes | Self-assessments that integrate concepts and skills learned throughout the series of topics presented in the module. |
| Module Summary | Briefly recaps module content. |

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential



# Module 12: IPv6 Addressing



Introduction to Networks v7.0 (ITN)

# Module Objectives

**Module Title:** IPv6 Addressing

**Module Objective**: Implement an IPv6 Addressing scheme.

| Topic Title | Topic Objective |
|---|---|
| IPv4 Issues | Explain the need for IPv6 addressing. |
| IPv6 Address Representation | Explain how IPv6 addresses are represented. |
| IPv6 Address Types | Compare types of IPv6 network addresses. |
| GUA and LLA Static Configuration | Explain how to Configure static global unicast and link-local IPv6 network addresses. |
| Dynamic Addressing for IPv6 GUAs | Explain how to configure global unicast addresses dynamically. |

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Module Objectives (Cont.)

**Module Title:** IPv6 Addressing

**Module Objective**: Implement an IPv6 Addressing scheme.

| Topic Title | Topic Objective |
|---|---|
| Dynamic Addressing for IPv6 LLAs | Configure link-local addresses dynamically. |
| IPv6 Multicast Addresses | Identify IPv6 addresses. |
| Subnet an IPv6 Network | Implement a subnetted IPv6 addressing scheme. |

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# 12.1 IPv4 Issues

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Need for IPv6

- IPv4 is running out of addresses.
- IPv6 is the successor to IPv4.
- IPv6 has a much larger 128-bit address space.
- The development of IPv6 also included fixes for IPv4 limitations and other enhancements.
- With an increasing internet population, a limited IPv4 address space, issues with NAT and the IoT, the time has come to begin the transition to IPv6.
- IPv6 has a larger 128-bit address space, providing **340 undecillion (i.e., 340 followed by 36 zeroes) possible addresses**




| Number Of Zeros | What You Call It |
|---|---|
| 3 | thousand |
| 6 | million |
| 9 | billion |
| 12 | trillion |
| 15 | quadrillion |
| 18 | quintillion |
| 21 | sextillion |
| 24 | septillion |
| 27 | octillion |
| 30 | nonillion |
| 33 | decillion |
| 36 | undecillion |
| 39 | duodecillion |
| 42 | tredecillion |
| 45 | quattuordecillion |
| 48 | quindecillion |
| 51 | sexdecillion |
| 54 | septendecillion |
| 57 | octodecillion |
| 60 | novemdecillion |
| 63 | vigintillion |

# IPv4 and IPv6 Coexistence

Both IPv4 and IPv6 will coexist in the near future and the transition will take several years.

The IETF has created various protocols and tools to help network administrators migrate their networks to IPv6.

These migration techniques can be divided into three categories:


- **Dual stack** -The devices run both IPv4 and IPv6 protocol stacks simultaneously.
- **Tunneling** – A method of transporting an IPv6 packet over an IPv4 network. The IPv6 packet is encapsulated inside an IPv4 packet.
- **Translation** - Network Address Translation 64 (NAT64) allows IPv6-enabled devices to communicate with IPv4-enabled devices using a translation technique similar to NAT for IPv4.

**Note:** Tunneling and translation are for transitioning to native IPv6 and should only be used where needed. The goal should be native IPv6 communications from source to destination.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Dual stack

- **Native IPv6**



# 12.2 IPv6 Address Representation

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# IPv6 Addressing Formats

- IPv6 addresses are 128 bits in length and written in hexadecimal.
- IPv6 addresses are not case-sensitive and can be written in either lowercase or uppercase.
- The preferred format for writing an IPv6 address is x:x:x:x:x:x:x:x, with each “x” consisting of four hexadecimal values.
- In IPv6, a hextet is the unofficial term used to refer to a segment of 16 bits, or four hexadecimal values.
- Examples of IPv6 addresses in the preferred format:

```
2001:0db8:0000:1111:0000:0000:0000:0200
2001:0db8:0000:00a3:abcd:0000:0000:1234
FE80::123:4567:89AB:CDEF
```


| Decimal | Binary | Hexadecimal |
|---|---|---|
| 0 | 0000 | 0 |
| 1 | 0001 | 1 |
| 2 | 0010 | 2 |
| 3 | 0011 | 3 |
| 4 | 0100 | 4 |
| 5 | 0101 | 5 |
| 6 | 0110 | 6 |
| 7 | 0111 | 7 |
| 8 | 1000 | 8 |
| 9 | 1001 | 9 |
| 10 | 1010 | A |
| 11 | 1011 | B |
| 12 | 1100 | C |
| 13 | 1101 | D |
| 14 | 1110 | E |
| 15 | 1111 | F |

©Elprocus.com

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

IPv6 Address Representation

# 16-bit Segments or Hextets



# IPV6 address examples

```
2001 : 0db8 : 0000 : 1111 : 0000 : 0000 : 0000: 0200
2001 : 0db8 : 0000 : 00a3 : abcd : 0000 : 0000: 1234
2001 : 0db8 : 000a : 0001 : c012 : 9aff : fe9a: 19ac
2001 : 0db8 : aaaa : 0001 : 0000 : 0000 : 0000: 0000
fe80 : 0000 : 0000 : 0000 : 0123 : 4567 : 89ab: cdef
fe80 : 0000 : 0000 : 0000 : 0000 : 0000 : 0000: 0001
fe80 : 0000 : 0000 : 0000 : c012 : 9aff : fe9a: 19ac
fe80 : 0000 : 0000 : 0000 : 0123 : 4567 : 89ab: cdef
0000 : 0000 : 0000 : 0000 : 0000 : 0000 : 0000: 0001
0000 : 0000 : 0000 : 0000 : 0000 : 0000 : 0000: 0000
```

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Rule 1 – Omit Leading Zero

The first rule to help reduce the notation of IPv6 addresses is to omit any leading 0s (zeros).

**Examples:**

- 01ab can be represented as 1ab
- 09f0 can be represented as 9f0
- 0a00 can be represented as a00
- 00ab can be represented as ab
- 000d can be represented as d

**Note**: This rule only applies to leading 0s, NOT to trailing 0s, otherwise the address would be ambiguous.

| Type | Format |
|---|---|
| Preferred | 2001 : **0**db8 : **000**0 : 1111 : **000**0 : **000**0 : **000**0 : **0**200 |
| No leading zeros | 2001 : db8 : 0 : 1111 : 0 : 0 : 0 : 200 |

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Rule 2 – Double Colon

A double colon (::) can replace any single, contiguous string of one or more 16-bit hextets consisting of all zeros.

**Example:**

- 2001:db8:cafe:1:0:0:0:1 (leading 0s omitted) could be represented as 2001:db8:cafe:1::1

**Note**: The double colon (::) can only be used once within an address, otherwise there would be more than one possible resulting address.

| Type | Format |
|---|---|
| Preferred | 2001 : **0**db8 : **000**0 : 1111 : **0000** : **0000** : **0000** : **0**200 |
| Compressed | 2001:db8:0:1111::200 |

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Incorrect use Double Colon

Here is an example of the incorrect use of the double colon: 2001:db8::abcd::1234.

The double colon is used twice in the example above. Here are the possible expansions of this incorrect compressed format address:

- 2001:db8::abcd:0000:0000:1234
- 2001:db8::abcd:0000:0000:0000:1234
- 2001:db8:0000:abcd::1234
- 2001:db8:0000:0000:abcd::1234

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

IPv6 Address Representation

# Omitting leading zeros and All zero segments

| Type | Format |
|---|---|
| Preferred | 2001 : 0db8 : 0000 : 1111 : 0000 : 0000 : 0000 : 0200 |
| Compressed/spaces | 2001 : db8 : 0 : 1111 : : 200 |
| Compressed | 2001:db8:0:1111::200 |
| | |
| Preferred | 2001 : 0db8 : 0000 : 0000 : ab00 : 0000 : 0000 : 0000 |
| Compressed/spaces | 2001 : db8 : 0 : 0 : ab00 :: |
| Compressed | 2001:db8:0:0:ab00:: |
| | |
| Preferred | 2001 : 0db8 : aaaa : 0001 : 0000 : 0000 : 0000 : 0000 |
| Compressed/spaces | 2001 : db8 : aaaa : 1 :: |
| Compressed | 2001:db8:aaaa:1:: |
| | |
| Preferred | fe80 : 0000 : 0000 : 0000 : 0123 : 4567 : 89ab : cdef |
| Compressed/spaces | fe80 : : 123 : 4567 : 89ab : cdef |
| Compressed | fe80::123:4567:89ab:cdef |

cisco
es. All rights reserved. Cisco Confidential

# 12.3 IPv6 Address Types

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Unicast, Multicast, Anycast

There are three broad categories of IPv6 addresses:

- **Unicast** – Unicast uniquely identifies an interface on an IPv6-enabled device.
- **Multicast** – Multicast is used to send a single IPv6 packet to multiple destinations.
- **Anycast** – This is any IPv6 unicast address that can be assigned to multiple devices. A packet sent to an anycast address is routed to the nearest device having that address.


**Note**: Unlike IPv4, IPv6 does not have a broadcast address. However, there is an IPv6 all-nodes multicast address that essentially gives the same result.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# IPv6 Prefix Length

Prefix length is represented in slash notation and is used to indicate the network portion of an IPv6 address.

The IPv6 prefix length can range from 0 to 128. The recommended IPv6 prefix length for LANs and most other types of networks is /64.





**Note**: It is strongly recommended to use a 64-bit Interface ID for most networks. This is because stateless address autoconfiguration (SLAAC) uses 64 bits for the Interface ID. It also makes subnetting easier to create and manage.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Types of IPv6 Unicast Addresses

Unlike IPv4 devices that have only a single address, IPv6 addresses typically have two unicast addresses:

- **Global Unicast Address (GUA)** – This is similar to a public IPv4 address. These are globally unique, internet-routable addresses.
- **Link-local Address (LLA)** - Required for every IPv6-enabled device and used to communicate with other devices on the same local link. LLAs are not routable and are confined to a single link.
- With IPv6, the term link refers to a subnet.




© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential


# IPv6 GUA

IPv6 global unicast addresses (GUAs) are globally unique and routable on the IPv6 internet.

- Currently, only GUAs with the first three bits of 001 or 2000::/3 are being assigned.
- Currently available GUAs begins with a decimal 2 or a 3 (This is only 1/8th of the total available IPv6 address space).

| Decimal | Binary | Hexadecimal |
|---|---|---|
| 0 | 0000 | 0 |
| 1 | 0001 | 1 |
| 2 | 0010 | 2 |
| 3 | 0011 | 3 |
| 4 | 0100 | 4 |
| 5 | 0101 | 5 |
| 6 | 0110 | 6 |
| 7 | 0111 | 7 |
| 8 | 1000 | 8 |
| 9 | 1001 | 9 |
| 10 | 1010 | A |
| 11 | 1011 | B |
| 12 | 1100 | C |
| 13 | 1101 | D |
| 14 | 1110 | E |
| 15 | 1111 | F |

©Elprocus.com




© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# IPv6 GUA Structure

**Global Routing Prefix:**

- The global routing prefix is the prefix, or network portion of the address that is assigned by the provider, such as an ISP, to a customer or site. The global routing prefix will vary depending on ISP policies.

**Subnet ID:**

- The Subnet ID field is the area between the Global Routing Prefix and the Interface ID.
- The Subnet ID is used by an organization to identify subnets within its site.

**Interface ID:**

- The IPv6 interface ID is equivalent to the host portion of an IPv4 address. It is strongly recommended that in most cases /64 subnets should be used, which creates a 64-bit interface ID.


**Note**: IPv6 allows the all-0s and all-1s host addresses can be assigned to a device. The all-0s address is reserved as a Subnet-Router anycast address, and should be assigned only to routers.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# IPv6 LLA

An IPv6 link-local address (LLA) enables a device to communicate with other IPv6-enabled devices on the same link and only on that link (subnet).

- Packets with a source or destination LLA cannot be routed.
- Every IPv6-enabled network interface must have an LLA.
- If an LLA is not configured manually on an interface, the device will automatically create one.
- IPv6 LLAs are in the fe80::/10 range.





1. Routers use the LLA of neighbor routers to send routing updates.
2. Hosts use the LLA of a local router as the default-gateway.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Two ways of getting IPv6 LLA for devices

**There are two ways that a device can obtain an LLA:**

- **Statically** - This means the device has been manually configured.
- **Dynamically** - This means the device creates its own interface ID by using randomly generated values or using the **Extended Unique Identifier (EUI) method**, which uses the client MAC address along with additional bits.




1. Routers use the LLA of neighbor routers to send routing updates.
2. Hosts use the LLA of a local router as the default-gateway.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# 12.4 GUA and LLA Static Configuration

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Static GUA Configuration on a Router

Most IPv6 configuration and verification commands in the Cisco IOS are similar to their IPv4 counterparts. In many cases, the only difference is the use of **ipv6** in place of **ip** within the commands.

- The command to configure an IPv6 GUA on an interface is: **ipv6 address** *ipv6-address/prefix-length.*
- The example shows commands to configure a GUA on the G0/0/0 interface on R1:


```
R1(config)# interface gigabitethernet 0/0/0
R1(config-if)# ipv6 address 2001:db8:acad:1::1/64
R1(config-if)# no shutdown
R1(config-if)# exit
```

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Static GUA Configuration on a Windows Host

- Manually configuring the IPv6 address on a host is similar to configuring an IPv4 address.
- The GUA or LLA of the router interface can be used as the default gateway. Best practice is to use the LLA.

**Note**: When DHCPv6 or SLAAC is used, the LLA of the router will automatically be specified as the default gateway address.




© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Static GUA Configuration of a Link-Local Unicast Address

Configuring the LLA manually lets you create an address that is recognizable and easier to remember.

- LLAs can be configured manually using the **ipv6 address** *ipv6-link-local-address* **link-local** command.
- The example shows commands to configure a LLA on the G0/0/0 interface on R1

```
R1(config)# interface gigabitethernet 0/0/0
R1(config-if)# ipv6 address fe80::1:1 link-local
R1(config-if)# no shutdown
R1(config-if)# exit
```

**Note**: The same LLA can be configured on each link as long as it is unique on that link. Common practice is to create a different LLA on each interface of the router to make it easy to identify the router and the specific interface.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# 12.5 Dynamic Addressing for IPv6 GUAs

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# RS and RA Messages


Devices obtain GUA addresses dynamically through Internet Control Message Protocol version 6 (ICMPv6) messages.

- **Router Solicitation (RS)** messages are sent by host devices to discover IPv6 routers
- **Router Advertisement (RA)** messages are sent by routers to inform hosts on how to obtain an IPv6 GUA and provide useful network information such as:
  - Network prefix and prefix length
  - Default gateway address
  - DNS addresses and domain name
- The RA provides three methods for configuring an IPv6 GUA :
  - SLAAC – Stateless Address Autoconfiguration
  - SLAAC with stateless DHCPv6 server
  - Stateful DHCPv6 (no SLAAC)

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# RS and RA Messages


## ICMPv6 RS and RA Messages




1. RS messages are sent to all IPv6 routers by hosts requesting addressing information.
2. RA messages are sent to all IPv6 nodes. If Method 1 (SLAAC only) is used, the RA includes network prefix, prefix-length, and default-gateway information.

# Method 1: SLAAC

- SLAAC allows a device to configure a GUA without the services of DHCPv6.
- Devices obtain the necessary information to configure a GUA from the ICMPv6 RA messages of the local router.
- The prefix is provided by the RA and the device uses either the EUI-64 or random generation method to create an interface ID.




1. The router sends an RA message with the prefix for the local link.
2. The PC uses SLAAC to obtain a prefix from the RA message and creates its own Interface ID.


© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Method 2: SLAAC and Stateless DHCP

An RA can instruct a device to use both SLAAC and stateless DHCPv6.

The RA message suggests devices use the following:

- SLAAC to create its own IPv6 GUA
- The router LLA, which is the RA source IPv6 address, as the default gateway address
- A stateless DHCPv6 server to obtain other information such as a DNS server address and a domain name




016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential


# Method 3: Stateful DHCPv6

An RA can instruct a device to use stateful DHCPv6 only.

Stateful DHCPv6 is similar to DHCP for IPv4. A device can automatically receive a GUA, prefix length, and the addresses of DNS servers from a stateful DHCPv6 server.


The RA message suggests devices use the following:

- The router LLA, which is the RA source IPv6 address, for the default gateway address.
- A stateful DHCPv6 server to obtain a GUA, DNS server address, domain name and other necessary information.



# EUI-64 Process vs. Randomly Generated

- When the RA message is either SLAAC or SLAAC with stateless DHCPv6, the client must generate its own interface ID.
- The interface ID can be created using the **(1) EUI-64 process or a (2) randomly generated 64-bit number.**




© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# EUI-64 Process


The IEEE defined the Extended Unique Identifier (EUI) or modified EUI-64 process which performs the following:

- A 16 bit value of **fffe** (in hexadecimal) is inserted into the middle of the 48-bit Ethernet MAC address of the client.
- The 7th bit of the client MAC address is reversed from binary 0 to 1.
- Example:

| | |
|---|---|
| 48-bit MAC | fc:99:47:75:ce:e0 |
| EUI-64 Interface ID | fe:99:47:ff:fe:75:ce:e0 |

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# EUI-64 Process




## Observations

### Advantages of EUI-64 process

- Ethernet MAC address can be used to determine the interface ID, and that helps maintain the uniqueness of the resulting IPv6 addresses.
- It also allows network administrators to easily track an IPv6 address to an end device using the unique MAC address.

### Disadvantage of the EUI-64 process

- This has caused privacy concerns among many users who are worried that their packets could be traced to the actual physical computer by **hackers**.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Randomly Generated Interface IDs

Depending upon the operating system, a device may use a randomly generated interface ID instead of using the MAC address and the EUI-64 process.

Beginning with Windows Vista, Windows uses a randomly generated interface ID instead of one created with EUI-64.

```
C:\> ipconfig
Windows IP Configuration
Ethernet adapter Local Area Connection:
   Connection-specific DNS Suffix  . :
   IPv6 Address. . . . . . . . . . . : 2001:db8:acad:1:50a5:8a35:a5bb:66e1
   Link-local IPv6 Address . . . . . : fe80::50a5:8a35:a5bb:66e1
   Default Gateway . . . . . . . . . : fe80::1
C:\>
```

**Note**: To ensure the uniqueness of any IPv6 unicast address, the client may use a process known as **Duplicate Address Detection (DAD).** This is similar to an ARP request for its own address. If there is no reply, then the address is unique.


© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# 12.6 Dynamic Addressing for IPv6 LLAs

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Dynamic LLAs

- All IPv6 interfaces must have an IPv6 LLA.
- Like IPv6 GUAs, LLAs can be configured dynamically.
- The figure shows the LLA is dynamically created using the fe80::/10 prefix and the interface ID using the EUI-64 process, or a randomly generated 64-bit number.




© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Dynamic LLAs on Windows

Operating systems, such as Windows, will typically use the same method for both a SLAAC-created GUA and a dynamically assigned LLA.

**EUI-64 Generated Interface ID:**

```
C:\> ipconfig
Windows IP Configuration
Ethernet adapter Local Area Connection:
Connection-specific DNS Suffix . :
IPv6 Address. . . . . . . . . . . : 2001:db8:acad:1:fc99:47ff:fe75:cee0
Link-local IPv6 Address . . . . . : fe80::fc99:47ff:fe75:cee0
Default Gateway . . . . . . . . . : fe80::1
C:\>
```

**Random 64-bit Generated Interface ID:**

```
C:\> ipconfig
Windows IP Configuration
Ethernet adapter Local Area Connection:
   Connection-specific DNS Suffix  . :
   IPv6 Address. . . . . . . . . . . : 2001:db8:acad:1:50a5:8a35:a5bb:66e1
   Link-local IPv6 Address . . . . . : fe80::50a5:8a35:a5bb:66e1
   Default Gateway . . . . . . . . . : fe80::1
C:\>
```

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Dynamic LLAs on Cisco Routers

Cisco routers automatically create an IPv6 LLA whenever a GUA is assigned to the interface. By default, Cisco IOS routers use EUI-64 to generate the interface ID for all LLAs on IPv6 interfaces.

Here is an example of a LLA dynamically configured on the G0/0/0 interface of R1:

```
R1# show interface gigabitEthernet 0/0/0
GigabitEthernet0/0/0 is up, line protocol is up
Hardware is ISR4221-2x1GE, address is 7079.b392.3640 (bia 7079.b392.3640)
(Output omitted)
R1# show ipv6 interface brief
GigabitEthernet0/0/0 [up/up]
FE80::7279:B3FF:FE92:3640
2001:DB8:ACAD:1::1
```

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Verify IPv6 Address Configuration

- **show ipv6 interface brief** command

Cisco routers automatically create an IPv6 LLA whenever a GUA is assigned to the interface. By default, Cisco IOS routers use EUI-64 to generate the interface ID for all LLAs on IPv6 interfaces.

Here is an example of a LLA dynamically configured on the G0/0/0 interface of R1:

```
R1# show interface gigabitEthernet 0/0/0
GigabitEthernet0/0/0 is up, line protocol is up
Hardware is ISR4221-2x1GE, address is 7079.b392.3640
(bia 7079.b392.3640)
(Output omitted)
R1# show ipv6 interface brief
GigabitEthernet0/0/0 [up/up]
FE80::7279:B3FF:FE92:3640
2001:DB8:ACAD:1::1
```

```
R1# show ipv6 interface brief
GigabitEthernet0/0/0    [up/up]
    FE80::7279:b3ff:fe92:3640
    2001:DB8:ACAD:1::1
GigabitEthernet0/0/1    [up/up]
    FE80::8320:e4ff:fe79:2830
    2001:DB8:ACAD:2::1
Serial0/1/0             [up/up]
    FE80::7279:b3ff:fe92:3640
    2001:DB8:ACAD:3::1
Serial0/1/1             [down/down]
    unassigned
R1#
```

# Verify IPv6 Address Configuration

- **show ipv6 route** command
- **show ipv6 route** command can be used to verify that IPv6 networks and specific IPv6 interface addresses have been installed in the IPv6 routing table.
- The **show ipv6 route** command will only display IPv6 networks, not IPv4 networks.

```
R1# show ipv6 route
IPv6 Routing Table - default - 7 entries
Codes: C - Connected, L - Local, S - Static, U - Per-user Static route

C   2001:DB8:ACAD:1::/64 [0/0]
     via GigabitEthernet0/0/0, directly connected
L   2001:DB8:ACAD:1::1/128 [0/0]
     via GigabitEthernet0/0/0, receive
C   2001:DB8:ACAD:2::/64 [0/0]
     via GigabitEthernet0/0/1, directly connected
L   2001:DB8:ACAD:2::1/128 [0/0]
     via GigabitEthernet0/0/1, receive
C   2001:DB8:ACAD:3::/64 [0/0]
     via Serial0/1/0, directly connected
L   2001:DB8:ACAD:3::1/128 [0/0]
     via Serial0/1/0, receive
L   FF00::/8 [0/0]
     via Null0, receive
R1#
```

ts reserved. Cisco Confidential

# Verify IPv6 Address Configuration

- **ping** command
- The **ping** command for IPv6 is identical to the command used with IPv4, except that an IPv6 address is used.

```
R1# ping 2001:db8:acad:1::10
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:DB8:ACAD:1::10, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/1/1 ms
R1#
```


© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Exercises

1. Enter the show command that will display a brief summary of the IPv6 interface status.

2. Verify connectivity from R1 to PC2 at 2001:db8:acad:1::10.

Use **show** commands to verify IPv6 address configuration on router R1 interfaces.




## Answers:

```
R1# show ipv6 interface brief
GigabitEthernet0/0/0   [up/up]
    FE80::1:1
    2001:DB8:ACAD:1::1
GigabitEthernet0/0/1   [up/up]
    FE80::2:1
    2001:DB8:ACAD:2::1
Serial0/1/0            [up/up]
    FE80::3:1
    2001:DB8:ACAD:3::1
Serial0/1/1            [down/down]
    unassigned
GigabitEthernet0       [administratively down/down]
    unassigned
```

```
R1# ping 2001:db8:acad:1::10
Type escape sequence to abort.
Sending 5, 100-byte ICMP Echos to 2001:DB8:ACAD:1::10, timeout is 2 seconds:
!!!!!
Success rate is 100 percent (5/5), round-trip min/avg/max = 1/1/1 ms

You successfully verified IPv6 address configuration.
```

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# 12.7 IPv6 Multicast Addresses

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Assigned IPv6 Multicast Addresses

IPv6 multicast addresses have the prefix ff00::/8. There are two types of IPv6 multicast addresses:

- Well-Known multicast addresses
- Solicited node multicast addresses

**Note**: Multicast addresses can only be destination addresses and not source addresses.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Well-Known IPv6 Multicast Addresses

Well-known IPv6 multicast addresses are assigned and are reserved for predefined groups of devices.


There are two common IPv6 Assigned multicast groups:

- **ff02::1 All-nodes multicast group** - This is a multicast group that all IPv6-enabled devices join. A packet sent to this group is received and processed by all IPv6 interfaces on the link or network.
- **ff02::2 All-routers multicast group** - This is a multicast group that all IPv6 routers join. A router becomes a member of this group when it is enabled as an IPv6 router with the **ipv6 unicast-routing** global configuration command.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Solicited-Node IPv6 Multicast

- A solicited-node multicast address is similar to the all-nodes multicast address.
- A solicited-node multicast address is mapped to a special Ethernet multicast address.
- The Ethernet NIC can filter the frame by examining the destination MAC address without sending it to the IPv6 process to see if the device is the intended target of the IPv6 packet.




© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential


# 12.8 Subnet an IPv6 Network

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Subnet Using the Subnet ID

IPv6 was designed with subnetting in mind.

- A separate subnet ID field in the IPv6 GUA is used to create subnets.
- The subnet ID field is the area between the Global Routing Prefix and the interface ID.





© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# IPv6 Subnetting Example

Given the 2001:db8:acad::/48 global r
prefix with a 16 bit subnet ID.

- Allows 65,536 /64 subnets
- The global routing prefix is the san
  all subnets.
- Only the subnet ID hextet is increment
  hexadecimal for each subnet.






© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# IPv6 Subnet Allocation

The example topology requires five subnets, one for each LAN as well as for the serial link between R1 and R2.

The five IPv6 subnets were allocated, with the subnet ID field 0001 through 0005. Each /64 subnet will provide more addresses than will ever be needed.




© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# Router Configured with IPv6 Subnets

The example shows that each of the router interfaces on R1 has been configured to be on a different IPv6 subnet.

```
R1(config)# interface gigabitethernet 0/0/0
R1(config-if)# ipv6 address 2001:db8:acad:1::1/64
R1(config-if)# no shutdown
R1(config-if)# exit
R1(config)# interface gigabitethernet 0/0/1
R1(config-if)# ipv6 address 2001:db8:acad:2::1/64
R1(config-if)# no shutdown
R1(config-if)# exit
R1(config)# interface serial 0/1/0
R1(config-if)# ipv6 address 2001:db8:acad:3::1/64
R1(config-if)# no shutdown
```

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# What did I learn in this module?

- IPv4 has a theoretical maximum of 4.3 billion addresses.
- The IETF has created various protocols and tools to help network administrators migrate their networks to IPv6. The migration techniques can be divided into three categories: dual stack, tunneling, and translation.
- IPv6 addresses are 128 bits in length and written as a string of hexadecimal values.
- The preferred format for writing an IPv6 address is x:x:x:x:x:x:x:x, with each “x” consisting of four hexadecimal values.
- There are three types of IPv6 addresses: unicast, multicast, and anycast.
- An IPv6 unicast address uniquely identifies an interface on an IPv6-enabled device.
- IPv6 global unicast addresses (GUAs) are globally unique and routable on the IPv6 internet.
- An IPv6 link-local address (LLA) enables a device to communicate with other IPv6-enabled devices on the same link and only on that link (subnet).
- The command to configure an IPv6 GUA on an interface is **ipv6 address** *ipv6-address/prefix-length*.
- A device obtains a GUA dynamically through ICMPv6 messages. IPv6 routers periodically send out ICMPv6 RA messages, every 200 seconds, to all IPv6-enabled devices on the network.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# What did I learn in this module? (Cont.)

- RA messages have three methods: SLAAC, SLAAC with a stateless DHCPv6 server, and stateful DHCPv6 (no SLAAC).
- The interface ID can be created using the EUI-64 process or a randomly generated 64-bit number.
- The EUIs process uses the 48-bit Ethernet MAC address of the client and inserts another 16 bits in the middle of MAC address to create a 64-bit interface ID.
- Depending upon the operating system, a device may use a randomly generated interface ID.
- All IPv6 devices must have an IPv6 LLA. An LLA can be configured manually or created dynamically.
- Cisco routers automatically create an IPv6 LLA whenever a GUA is assigned to the interface.
- There are two types of IPv6 multicast addresses: well-known multicast addresses and solicited node multicast addresses.
- Two commonIPv6 assigned multicast groups are: ff02::1 All-nodes multicast group and ff02::2 All-routers multicast group.
- A solicited-node multicast address is similar to the all-nodes multicast address. The advantage of a solicited-node multicast address is that it is mapped to a special Ethernet multicast address.
- IPv6 was designed with subnetting in mind. A separate subnet ID field in the IPv6 GUA is used to create subnets.

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential

# New Terms and Commands

- Hextet
- Link-local address (LLA)
- ipv6 address
- show ipv6 interface brief
- SLAAC
- Router advertisement
- Router solicitation
- EUI-64
- Solicited node multicast

© 2016 Cisco and/or its affiliates. All rights reserved. Cisco Confidential


CISCO